TECHNICAL MANUAL OPERATORS, AVIATION UNIT. AND AVIATION INTERMEDIATE MAINTENANCE

BATTLEFIELD DAMAGE ASSESSMENT AND REPAIR



FOR

HELICOPTER, UTILITY, UH-1H (1520-00-087-7637) AND UH-1V (1520-01-043-4949)

CHAPTER 1 GENERAL INFORMATION
CHAPTER 2 ASSESSING BATTLEFIELD DAMAGE
CHAPTER 3 GENERAL REPAIRS
CHAPTER 4 AIRFRAME
CHAPTER 5 ALIGHTING GEAR
CHAPTER 6 POWER PLANT INSTALLATION
CHAPTER 7 ROTORS
CHAPTER 8 DRIVE TRAIN SYSTEMS
CHAPTER 9 HYDRAULIC & PNEUMATIC SYSTEMS
CHAPTER 10 INSTRUMENTS
CHAPTER 11 ELECTRICAL & AVIONICS SYSTEMS
CHAPTER 12 FUEL SYSTEM
CHAPTER 13 FLIGHT CONTROLS
CHAPTER 14 UTILITY SYSTEM
CHAPTER 15 ENVIRONMENTAL CONTROL SYSTEM (ECS)
CHAPTER 16 HOLST & WINCHES
CHAPTER 17 AUXILIARY POWER PLANT - N/A_
CHAPTER 18 MISSION EQUIPMENT
APPENDIX A REFERENCES
APPENDIX B SPECIAL TOOLS .AND REPAIR KLTS
APPENDIX C EXPENDABLE/DURABLE SUPPLIES & MATERIALS
APPENDIX D SUBSTITUTE MATERIALS/PARTS
APPENDIX E BDAR FIXES AUTHORIZED FOR TRAINING
APPENDIX F AVIONICS CONFIGURATIONS

HEADQUARTERS, DEPARTMENT OF THE ARMY
19 FEBRUARY 1991

CHANGE NO. 1 HEADQUARTERS
DEPARTMENT OF THE ARMY
WASHINGTON, D.C., 02 September 1994

TECHNICAL MANUAL OPERATOR'S, AVIATION UNIT, AND AVIATION INTERMEDIATE MAINTENANCE

BATTLEFIELD DAMAGE ASSESSMENT AND REPAIR

FOR

HELICOPTER, UTILITY, UH-1H (1520-00-084-7637) AND UH-1V (1520-01-043-4049)

DISTRIBUTION STATEMENT A: Approved for public release; distribution is unlimited

TM 55-1 5200-210-BD, 19 February 1991, is changed as follows:

1. Remove and insert pages as indicated below. New or changed text material is indicated by a vertical bar in the margin. An illustration change is indicated by a miniature pointing hand.

Remove pages Insert pages

3-19 and 3-20 3-19 and 3-20

2. Retain this sheet in front of manual for reference purposes.

By Order of the Secretary of the Army:

GORDON R. SULLIVAN General, United States Army Chief of Staff

Official:

MILTON H. HAMILTON
Administrative Assistant to the
Secretary of the Army
07653

DISTRIBUTION:

To be distributed in accordance with DA Form 12-31-E, block no. 3068, requirements for TM 55-1520-210-BD.

WARNING AND PRECAUTIONARY DATA

Personnel performing operations, procedures, and practices which are included or implied in this technical manual shall observe the following warnings. Disregard of these warnings and precautionary information can cause serious injury or death.

The standards contained herein allow aircraft to be flown with battle damage substantially in excess of peacetime limits. Under no circumstances shall this manual be used wholly or in part for peacetime maintenance of the aircraft. Assessment of aircraft battlefield damage requires extreme care and diligence and strict adherence to the instructions and standards contained in this manual. If at any stage of damage assessment the assessor believes that oversights or errors have been made, the assessment shall be stopped at that point and repeated from the beginning. Under no circumstances shall the requirements of this manual be waived or circumvented without the express approval of the commander or his designated representative.

WARNINGS

Battle damaged areas should be inspected for unexploded ordnance before attempting repairs. Disposal of unexploded ordnance should be accomplished by qualified EOD personnel.

Substitute or repair hoses must meet system pressure and fluid requirements.

Adhesives and materials must be compatible with the system fluid.

AIRCRAFT FIRE EXTINGUISHER

Exposure to high concentrations of fire extinguishing agent or decomposition products should be avoided. The liquid should not be allowed to come into contact with the skin, as it may cause frost bite or low temperature burns.

ARMAMENT

Loaded weapons, or weapons being loaded or unloaded, shall be pointed in a direction which offers the least exposure to personnel or property in the event of accidental firing. Personnel shall remain clear of hazardous area of all loaded weapons.

CLEANING SOLVENTS


Cleaning solvents may be flammable and toxic. Use only in well-ventilated areas. Avoid inhalation of vapor and skin contact. Do not use solvents near open flame or in areas where very high temperatures prevail. Solvent flash point must not be less than 100°F.

ELECTROLYTE

Battery Electrolyte (Potassium Hydroxide) is corrosive. Wear rubber gloves, apron, and eye protection when handling leaking batteries. If potassium hydroxide is spilled on clothing or other material, wash immediately with clean water. If spilled on personnel, immediately start flushing the affected area with clean water. Continue washing until medical assistance arrives.

TOXIC POISONS

Turbine fuels and lubricating oils contain additives which are poisonous and readily absorbed through the skin. Do not allow them to remain on skin longer than necessary.



RADIOACTIVE MATERIALS

Self-luminous dials and ignition units may contain radioactive materials. If such an instrument or unit is broken or becomes unsealed, avoid personal contact. Use forceps or gloves made of rubber or polyethylene to pick up contaminated material. Place materials and gloves in a plastic bag. Seal bag and dispose of it as radioactive waste in accordance with AR 755-15 and TM 3-261 (refer to TB 43-0108). Repair shall conform to requirements in AR 700-52.

CAUTION

Dynamic components which have experienced sudden stoppage, overtemperature, overtorque, or overspeed shall be evaluated prior to reuse.

LIST OF EFFECTIVE PAGES

Insert latest changed pages; dispose of superseded pages in accordance with applicable regulations.

NOTE: On a changed page, the portion of the text affected by the latest change is indicated by a vertical line or other symbol in the outer margin of the page. Changes to illustrations are indicated by miniature pointing hands. Changes to wiring diagrams are indicated by shaded areas.

Dates of issue for original and changed pages are:

Original. 19 February 1991

Page	*Change
No.	No.
Cover. a thru b A/(B Bl ank) i thru viii 1-1 thru 1-9/(1-10 Bl ank) 2-1 thru2-8 3-1 thru 3-21/(3-22 Bl ank 4-1 thru 4-84 5-1 thru 5-7/(5-8 Bl ank) 6-1 thru 6-9/(6-10 Bl ank) 7-1 thru 7-4 8-1 thru 9-25/(9-26 Bl ank 9-1 thru 9-25/(9-26 Bl ank 10-1 thru 10-7/(10-8 Bl ark 10-1 thru 11-39/(11-40 Bl 12-1 thru 12-23/(12-24 Bl 13-1 thru 13-30 14-1/(14-2 Bl ank) 15-1/(15-2 Bl ank) 15-1/(16-2 Bl ank) 17-1/(17-2 Bl ank) 18-1/(18-2 Bl ank) 18-1/(18-2 Bl ank) 1-1 thru B-9/(B-10 Bl ank) C-1 thru C-9/(C-10 Bl ank) D-1 thru D-22 E-1 thru E-2 F-1 thru F-37/(F-38 Bl ank GLOS-1 thru GLOS-8 INDEX-1 thru INDEX-4	0 0 0 0 0 0 0 ank) 0 ank) 0 ank) 0 0 0 0

^{*}Zero in this column indicates an original page.

Techni cal Manual

No. 55-1520-210-BD

HEADQUARTERS DEPARTMENT OF THE ARMY WASHINGTON, D.C., 19 February 1991

TECHNICAL MANUAL

OPERATORS, AVIATION UNIT, AND AVIATION INTERMEDIATE MAINTENANCE BATTLEFIELD DAMAGE ASSESSMENT AND REPAIR FOR HELICOPTER, UTILITY, UH-1H (1520-00-087-7637) AND UH-1V (1520-01-043-4949)

REPORTING ERRORS AND RECOMMENDING IMPROVEMENTS

You can help improve this manual. If you find any mistake or if you know of a way to improve the procedure, please let us know. Mail your letter or DA Form 2028 (Recommended Changes to Publications and Blank Forms) direct to: Commander, U.S. Army Aviation Systems Command, ATTN: AMSAV-MC, 4300 Goodfellow Blvd., St. Louis, MO 63120-1798. A reply will be furnished to you.

TABLE OF CONTENTS

		Page
ŀ	HOW TO USE THIS MANUAL	vii
CHAPTER 1 - (GENERAL INFORMATION	
Section II.	Introduction	
CHAPTER 2- A	ASSESSING BATTLEFIELD DAMAGE	
Section I. Section II.	Introduction	2-1 2-1
CHAPTER 3- (GENERAL REPAIRS	
Section I. Section II. Section III. Section IV. Section V. Section VI. Section VII.	Introduction. Skin Structure	3-2 3-6 3-7
CHAPTER 4- A	AI RFRAME	
Section II.	Introduction	4-1 4-25

TABLE OF CONTENTS (Cont)

	Page
CHAPTER 5 - ALIGHTING GEAR	
Section I. Introduction	
CHAPTER 6 - POWER PLANT INSTALLATION	
Section I. Introduction	6-1 6-1 6-7
CHAPTER 7 - ROTORS	
Section I. Introduction	
CHAPTER 8 - DRIVE TRAIN SYSTEMS	
Section I. Introduction	8-1 8-10
CHAPTER 9 - HYDRAULIC AND PNEUMATIC SYSTEMS	
Section I. Introduction Section II. Hydraulic Reservoir. Section III. Hydraulic Filter. Section IV. Relief Valve. Section V. Solenoid Valve. Section VI. Pressure Switch Section VII. Check Valves Section VIII. Armament Hydraulic System Section IX. Hydraulic High Pressure Metal Tubing Section XI. Bleed Air System Tubes and Hoses Section XII. Bleed Air Fitting.	9-1 9-7 9-9 9-10 9-12 9-14 9-16 9-16 9-16 9-18
CHAPTER 10- INSTRUMENTS	
Section I. Introduction	10-1 10-1 10-4 10-6

TABLE OF CONTENTS (Cont)

		Page
CHAPTER 11-	ELECTRICAL AND AVIONICS SYSTEMS	
Section I. Section II. Section IV. Section V. Section VI. Section VII.	Introduction	11-1 11-7 11-23 11-25 11-29 11-32
CHAPTER 12-	FUEL SYSTEM	
	Introduction	12-1 12-5 12-12
CHAPTER 13-	FLI GHT CONTROLS	
Section I. Section II. Section IV. Section V. Section VI.	Introduction Connecting Links Lever Assemblies Bell cranks El evator Control Cables	13-1 13-1 13-22 13-23 13-23 13-27
CHAPTER 14-	UTILITY SYSTEM	14-1
CHAPTER 15-	ENVIRONMENTAL CONTROL SYSTEM (ECS)	15-1
CHAPTER 16-	HOIST AND WINCHES	16-1
CHAPTER 17-	AUXILIARY POWER PLANT	17-1
CHAPTER 18-	MISSION EQUIPMENT	18-1
APPENDIX D - APPENDIX E - APPENDIX F - GLOSSARY	REFERENCES SPECIAL TOOLS AND REPAIR KITS EXPENDABLE/DURABLE SUPPLIES AND MATERIALS LIST. SUBSTITUTE MATERIALS/PARTS. BDAR FIXES AUTHORIZED FOR TRAINING. AVIONICS CONFIGURATIONS GIANT	A-1 B-1 C-1 D-1 E-1 F-1 LOS-1

TM 55-1520-210-BD

LIST OF ILLUSTRATIONS

Fi gure	Ti tl e	Page
3-1	External Stiffener/Stringer Patch	3-4
3-2	Patch Plate Repair	3-5
3-3	Patch Plate Repair	3-8
3 - 4	Bulkhead and FormerDamage	3-9
3-5	Bulkhead and FormerDamage	3-10
3-6	Repair of Damaged Bulkhead Flange (Sheet 1 of 2)	3-14
3-7	Honovcomb Danal Danair	3-14
3-8	Honeycomb Panel Repair	3-10
3-0	Inches - Both Skins and Core	3-19
4-1	Fuselage Structure, Station, Water, and Butt Lines	4-2
4-2	(Sheet 1 of 15)	4-17
4-3	Damage Limits Measurement for Tables 4-1 thru 4-10	4-26
5-1	Landing Gear and Support Installation	5-2
5-2	Ckid Tuho Damago Increction	5-5
5-3	Skid Tübe Damage Inspection	
5-3 5-4	Skid Tube Splint Repair	5-6
	Skid Tube - Splint and Clamp Repair	5-7
6-1	Oil Tank	6-3
6-2	Screw, washer, and Gasket	6-4
6-3	Sheet Metal with Sealant or Blind Rivets	6-6
6-4	Fuel Control and Accessory Gearbox Assemblies	6-8
6-5	Tach Generator Removal	6-9
7 – 1	Blade Repair by Application of Tape	7 – 4
8-1	Drive Irain System, Major Components (Sheet 1 of 2)	8-4
8-2	Pressure Switch and Transmitter	8-7
8-3	Iransmission External Oil Filter Bypass	8-9
8-4	Damage Passing Through Center of Shaft	8-12
8-5	Balance Restoring Repair for Damage Not Passing Through the Center of Shaft	8-13
8-6	Y vs. s	8-15
8-7	Area vs. Diameter	8-15
8-8	Renai red Shaft	8-16
8-9	Repaired Shaft	8-18
9-1	Hydraulic System (Sheet 1 of 2)	9-3
9-2	Hydraulic System (Sheet 1 of 2)	9-5
9-3	Patch Repair for Leaks	9-8
9-4	Filter Bypass Hose Installation.	9-10
3-5	Relief Valve, Removal	9-10
9-6		
9-0 9-7	Solenoid Valve Replacement	9-13
	Bypass of Solenoid Valve	9-13
9-8	Check Valve Substitution	9-15
9-9	Rubber Pressure Patch	9-17
9-10	UH-1 Bleed Air System	9-19
9-11	Bleed Air Hose Repair.	9-20
9-12	Rigid Bleed Air Tube Splice Repair	9-22
9-13	Rigid Bleed Air Tube Patch Repair	9-23
9-14	Bypassing Damaged Bleed Air Fittings	9-25
10-1	Oil Pressure Transmitter	10-5
10-2	Bypassing Damaged Plenum	10-7

LIST OF ILLUSTRATIONS (Cont)

Fi gure	Ti tl e	Page
11-1	Circuit Identification	11-2
11-2	Splicing with Terminal Lug Barrel	11-8
11-3	lwist Wire Splice	11-10
11-4	Replacement Section; Twist Wire Splice	11-10
11-5	Metal Casting Splice Repair	11-11
11-6 11-7	Bolted Terminal Lug Repair of Large Wires.	11-12 11-12
11-7	Replacement Section; Terminal Lug Repair	11-12
11-9	Ram Wire Repair	11-15
11-10	Shi el ded Cable Repair Preparation.	11-13
11-11	Pigtail Method Repair.	11-18
11-12	Substitute Shiel ded Braid Repair	11-19
11-13	Component Bypass	11-23
11-14	Component Bypass	11-24
11-15	Damaged Connector and Pigtail	11-25
11-16	Construction of Fuse Link	11-27
11-17	Fabricated Fuse, Type A	11-28
11-18	Fabricated Fuse, Type B	11-29
11-19	Splicing Bus Bars	11-30
11-20	Lengthening Bus Bars	11-30
11-21	Battery, Storage BB-433/A Cell Layout	11-32
11-22	UH-1H/V Relay Location (Sheet 1 of 4)	11-34
11-23	Block Diagram, Typical Power Relays	11-34
11-24	Frequency vs. Wave length Fabrication of Emergency Antenna	11-36
11-25	Fabrication of Emergency Antenna	11-36
11-26 11-27	Installation of Field Expedient Antenna	11-37
12-1	Pigtail Termination for Shielded Wire	11-38 12-2
12-1	Fuel System Schematic	12-2
12-3	Fuel System Hose/Tube Installation (Sheet 1 of 4)	12-3
12-4	Hose and Clamp Fuel Tubing Repair	12-10
12-5	Damaged Hose Repair.	12-11
12-6	Fuel Cell Location and Approximate Arm as Compared with	12 11
	Center of Gravity	12-13
12-7	Isolation of Cell Ä	12-15
12-8	Isolation of Cell B	12-16
12-9	Isolation of Cell D or E	12-18
12-10	Inlet Line to Fuel Control	12-19
12-11	Emergency Mechanical Clamp Repair	12-21
12-12	Fuel Cell Patch Repair	12-22
12-13	Filter Bypass Detail	12-23
13-1	Cyclic Control System	13-2
13-2	Collective Control System	13-3
13-3	Elevator Control System	13-4
13-4	Power Control System	13-5
13-5	Tail Rotor Control System	13-6
13-6	Control Connecting Link Splices	13-13
13-7	Fabrication of Link End (Sheet 1 of 2)	13-14
13-8	Fabrication of Links from Tube	13-17

TM 55-1520-210-BD

LIST OF ILLUSTRATIONS (Cont)

Fi gure	Title	Page
13-9 13-10 13-11 13-12 13-13	Fabrication of Connecting Link (Sheet 1 of 3)	13-19 13-22 13-24 13-26 13-29
	LIST OF TABLES	
Table No.	Ti tl e	Page
1-1 2-1 2-2 4-1 4-2 4-3 4-4 4-5 4-6 4-7 4-8 4-9 4-10 5-1 6-1 7-1 8-1 8-2 9-1 10-1 10-2 10-3 11-1 11-2 11-3 12-1 12-2 13-1 13-2 13-3 13-4	Damage Assessment Markings General Decision Logic Helicopter Flight Assessment Damage Limits Cabin Roof - Condition I Damage Limits Fuselage, Forward (FS 23 to 129) - Condition I Damage Limits Fuselage, Midsection (FS 129 to 178) - Condition I Damage Limits Fuselage, Aft (FS 178 to 243) - Condition I Damage Limits Tail Boom - Condition I Damage Limits Tail Boom - Condition II Damage Limits Fuselage, Forward (FS 23 to 129) - Condition II Damage Limits Fuselage, Forward (FS 23 to 129) - Condition II Damage Limits Fuselage, Midsection (FS 129 to 178) - Condition II Damage Limits Fuselage, Aft (FS 178 to 243) - Condition II Damage Limits Fuselage, Aft (FS 178 to 243) - Condition II Damage Limits Tall Boom - Condition II Assessment Procedures Assessment Procedures Assessment Procedures Assessment Procedures Instruments Assessment System Evaluation Functional List and Flight Essential Instruments Function and Designation Letters Electrical and Avionics System Assessment Fuse Link Assessment Procedures Weight & Balance Computation Data for Fuel Cells Assessment Procedures Connecting Link Dimensions Bolt/Drill Sizes for Splice Repairs. Fabricated Link End Dimensions	1-6 2-2 2-3 4-27 4-32 4-38 4-44 4-47 4-55 4-59 4-65 4-75 5-3 6-2 7-2 8-18 9-2 10-3 10-5 11-2 11-5 11-26 12-4 12-13 13-7 13-10 13-12

HOW TO USE THIS MANUAL

This manual is developed to assist the soldier in a battlefield environment make assessment and repair of damage to the UH-1H/V utility helicopter which cannot, due to asset availability or environmental factors, be repaired in the normal prescribed manner. Within this technical manual, the word shall is used to indicate a mandatory requirement. The word should is used to indicate an acceptable method of accomplishment. The word <a href="mailto:ma

- 1. Organization of the Manual. This manual contains a general information chapter (chapter 1), a general assessment chapter (chapter 2), a general repair chapter (chapter 3), and specific repair chapters (chapters 4 thru 18). It also contains five appendixes, A through F.
- 2. Chapter 2 is used to assess the helicopter in general and references specific chapters for detailed repair procedures of the major functional groups. The major functional groups correspond with the functional groups of the -23 series manuals that are employed in routine repairs to the helicopter.
- 3. Chapter 3 contains repairs for equipment which does not fall under one of the standard helicopter functional groups.
- 4. Each chapter is organized as follows:
 - a. Section I Introduction.
 - (1) Scope. Purpose of the chapter.
- (2) Assessment Procedures. General assessment Information for the repairs covered therein.
 - (3) Repair Procedure Index.
- b. Section II Repair Item. A subsection is included for each repair item covered in that functional group. It contains the following:
 - (1) General. About the nature and cause of damage and repair.
 - (2) I tem and trouble statement with:
 - (a) Limits given.
 - (b) Personnel and time required to effect repairs.
 - (c) Materials and tools needed.
 - (d) Procedural steps to accomplish the repair.
- (3) If more than one method of repair can be used, the various options will be included next.

NOTE

The first option is the preferred choice, the second option is the next preferred, etc. Selection of the option should be the most preferred method possible under the circumstances and with the available materials and manpower.

HOW TO USE THIS MANUAL (Cont)

- 5. Finding Repairs in this Manual.
- a. When the damage is obvious and known, find the functional group chapter of which the damaged item is a part. Turn to the repair procedure index, section I, subparagraph 3, of each chapter to locate the item being repaired. Then turn to the repair section and review each option to find an appropriate fix. Read the entire section for all the options. Select a repair and follow the procedures given to fix the helicopter.
- b. When the damage is hidden or unknown, follow the overall assessment procedures provided in chapter 2, and follow the procedures and directions provided.
- 6. Preparation.
- a. Each mechanic/technician shall have read chapters 1 and 2 and become familiar with the repairs and layout of the manual prior to attempting to accomplish BDAR repairs.
- b. All warnings, cautions, and safety precautions shall be followed at all times during BDAR procedures so as not to further damage and/or jeopardize either personnel or the equipment during or subsequent to the BDAR action. Ensure all documentation is completed as directed in this manual and by local command.
- 7. Expendable/Durable Supplies and Materials.
- a. Each fix or repair option contains a short listing of materials and tools considered basic to the repair. It is important to note that the expendable materials listed usually cover a wide range for any one item.

Example: MATERIALS/TOOLS REQUIRED:

- •Drill with Bit
- •Sheet Metal (Items 129-141, App C)
- •Rivets (items 94-114, App C)

In this example, sheet metal covers the range of items 129 thru 141 listed in Appendix C. This means that, depending on the circumstances and location of the fix, any one of these metals could be used. Likewise any one of the rivets, items 94 thru 114, may be used to attach the patch plate depending on the application.

b. One of the key points concerning successful BDAR repairs is flexibility. The users of this manual should strive to use the items on hand, provided a safe repair is made. The stringent requirements of normal maintenance may be lifted.

CHAPTER 1

GENERAL INFORMATION

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

1-1. PURPOSE. The purpose of Battle-field Damage Assessment and Repair (BDAR) is to quickly return the disabled helicopter to duty by expediently fixing, bypassing, or jury-rigging components to restore the minimum essential systems required for the support of the specific combat mission, or self-recovery. These repairs will be temporary and may not restore full performance capability. Standard repair will be completed as soon as practicable.

1-2. SCOPE.

- a. This technical manual (TM) describes BDAR procedures and fixes applicable to UH-1 utility helicopter. These procedures are to be used by crew, operators, aviation unit maintenance (AVUM) teams, and aviation intermediate maintenance (AVIM) support teams.
- b. Standard repair techniques for the UH-1 helicopter are included in other technical manuals which are referenced in Appendix A of this TM. If the repairs are more than one page in length, the repairs may only be referenced to the appropriate TM.
- c. All possible types of combat damage and failure cannot be predicted, nor are all effective field expedient repairs known. This TM provides guide-

- lines for assessing and repairing battlefield failures of UH-1 helicopters and is not intended to be a complete catalog of all possible emergency repairs. The repairs described here will serve as guidelines and will stimulate the experienced mechanic or operator to devise repairs as needed to quickly return equipment to operation in a combat situation.
- d. The direct replacement of a piece of equipment by its spare, even under battlefield conditions, is not a BDAR fix and is not covered in this TM. A standard procedure should be performed in preference to a BDAR fix when time and spares are available.

1-3. APPLICATION.

- a. The procedures in this manual are designed for battlefield environments. BOAR procedures are only authorized for use in a battlefield environment, and only at the direction of the commander. These fixes are only temporary and are not to be continued after the equipment is out of the battle environment.
- b. BDAR techniques are not limited to simple restoration of minimum functional combat capability. If full functional capability can be restored expediently with a limited expenditure of time and assets, it should be accomplished.

TM 55-1520-210-BD GENERAL INFORMATION

c. Some of the special techniques in this manual, if applied, may result in shortened life or in further damage to major components of the helicopter. The commander must decide whether the risk of having one less helicopter available for combat outweighs the risk of applying the potentially destructive expedient repair technique. Each technique gives appropriate warnings, cautions, and lists systems limitations caused by this action.

1-4. DEFINITIONS.

- a. <u>Battlefield Damage.</u> Any incident such as combat damage, random failures, operator errors, accidents, and wear out failures which occur on the battlefield and which prevent the helicopter from accomplishing its mission.
- b. <u>Repair</u> or <u>Fix.</u> Any expedient action that returns a damaged part or assembly to a full or an acceptably degraded operating condition, including:
- (1) Short cuts in parts removal or installation.
- (2) Installation of components from other equipment that can be modified to fit or interchange with components on the damaged equipment.
- (3) Repair using parts that serve a noncritical function elsewhere on the same equipment for the purpose of restoring a critical function.
- (4) Bypassing of noncritical components in order to restore basic functional capability.
- (5) Expeditious cannibalization procedures.
- (6) Fabrication of parts from kits or readily available materials.
 - (7) Jury-rigging.

- (8) Use of substitute materials.
- c. <u>Damage Assessment</u>. A procedure to rapidly determine what is damaged, whether it is repairable, what-assets are required to make the repair, who can do the repair (e.g., crew, maintenance team or maintenance support team), and where the repair should be made. The assessment procedure includes the following steps:
- (1) Determine which components must be fixed.
- (2) Determine if the repair can be deferred, or if it must be done.
- (3) Determine if isolating and/or bypassing can be done to damaged areas and components.
 - (4) Select and prescribes fix.
- (5) Determine if parts or components, materials, and tools are available for selected fix.
- (6) Estimate the manpower and skill required.
- (7) Estimate the total time (clock hours) required to make the repair.
- (8) If more than one damage exists, establish the priority of the fix.
- (9) Decide where the fix shall be performed.
- (10) Decide if recovery or evacuation is necessary and to what location.
- d. Fully Mission Capable (FMC). The helicopter can perform all its combat missions. To be FMC, the helicopter must be complete and fully operable with no faults listed in the aircraft inspection and maintenance record as prescribed in DA PAM 738-751.

- e. <u>Combat Capable.</u> Equipment meets the minimum functional combat capability requirements. (See paragraph 1-7.)
- f. <u>Combat Emergency Capable.</u> The equipment meets the needs for specific tactical missions; however, all systems are not functional. Also, additional damage due to the nature of an expedient repair may occur to the equipment if it is used. The commander must decide if these limitations are acceptable for that specific emergency situation.
- g. Cannibalization or Controlled Exchange. Throughout this manual, cannibalization and-controlled exchange are used interchangeably meaning the removal of an item of materiel from one piece of equipment for immediate use in another. Generally, the rules for cannibalization/controlled exchange provided in TM 1-1500-328-25, as modified by local authority, will prevail.
- h. <u>Evacuation</u>. A combat service support function which involves the movement of recovered helicopters from a main supply route, maintenance collection point, or maintenance activity to higher categories of maintenance. The materiel may be returned to the user, to the supply system for reissue, or to property disposal activities.

- i. <u>Recovery.</u> The retrieval of immobile, inoperative, or abandoned helicopter from the battlefield or immediate vicinity, and its movement to a maintenance collection point, the main supply route, or a maintenance activity for disposition, repair, or evacuation.
- j. <u>Self-Recovery.</u> The ability of a battle damaged helicopter to retrieve itself (fly-out) from-a battlefield environment. It usually will involve flying with degraded aircraft status and with restrictions and limitations placed on performance characteristics such as limitations placed on weight, airspeed, engine torque, and other characteristics. In BDAR repairs, the limitations recommended should be followed. Emergency flight procedure in TM 55-1520-210-10 should furthur be consulted.
- k. <u>Maintenance Collection Point.</u> A point operated by AVIM unit for the collection of equipment for repair.
- I. <u>Maintenance Support Team (MST).</u> A team of AVIM mechanics and technical specialists who are trained in assessing battlefield damage and field repair procedures.
- m. <u>Maintenance Team (MT)</u>. Helicopter crew chief or AVUM mechanics/technicians who are trained in assessing battlefield damage and field repair procedures.

Section II. STANDARDS AND PRACTICES

- 1-5. BDAR CHARACTERISTICS. BDAR capability requires simplicity, speed, and effectiveness. Some BDAR procedures include repair techniques that violate standard peacetime maintenance practices. In a combat emergency situation, greater risks are sometimes necessary and acceptable.
- 1-6. WAIVER OF PRECAUTIONS. Under combat conditions, BDAR may be performed on helicopters which are in flight or which are under power while on the ground. While some of these BDAR actions may require waiving of safety precautions, the cautions to protect personnel life should not be overlooked. Other similar precautions may be waived at the discretion of the commander. BDAR fixes may be required in a Nuclear Biological Chemical (NBC) environment or under other adverse battlefield conditions with severe limitations in personnel, facilities, equipment, and materials. Performance of repair tasks may be necessary while wearing protective gear. In the case of NBC environment, decontamination procedures are described in FM 3-5, NBC Decontaminati on.
- 1-7. OPERATING CHARACTERISTICS. This manual covers expedient repairs for the UH-1 helicopter and its components. It is entirely possible that in a combat situation the helicopter, having undergone one or more repairs, may suffer degradation of its normal operating characteristics (e.g., reduced speed, reduced load capability, reduced range, etc.), and still be able to carry out all or parts of an assigned mission. The minimum functional combat capability (MFCC) criteria for the UH-1 areas follows:

WARNING

Careful consideration shall be given to the operation of the Identify Friend or FOE (IFF), Mode 4, avionics system. Failure of the IFF or failure to properly communicate with area air defense command prior to liftoff could result in an attack from friendly forces due to mistaken identity.

NOTE

Criteria may be waived for recovery or if the tactical situation demands otherwise.

- a. Flight Capability for Mission Completion. Helicopter's flight characteristics degraded to a minimum of combat capable (CC).
- (1) Sufficient power for safe flight for intended mission capability for helicopter crew and cargo.
- (2) No fuel leaks which will curtail the intended length of flight.
- (3) No degradation of any component/system which will end in failure and curtailment of intended mission.
- (4) Communications. Must have intercom communications within aircraft and at least two tactical receiver-transmitter (R-T) units operating at full capability.
- b. Flight Capability for Self-Recovery Capability (SRC).
- (1) Must have power torque delivered to the main rotor and tail rotot at acceptable limits.

- (2) Lift capability for a minimum size crew. Unload unnecessary weight (cargo). Dump excess fuel if necessary.
- (3) Flight controls at minimum function level acceptable for flight.
 - (4) Maximum speed of 50 kts.
- (5) Maximum flight duration of 1/2 hours. Consideration will be given to minimize flight duration and inspection of damage or nonfunctional area causing downgrading of flight status.
- (6) Be prepared for emergency landing procedures. See TM 55-1520-210-10.
- (7) Instruments/avionics as required to meet needs.

1-8. TRAINING.

- a. BDAR by its nature involves fixes, bypasses, and/or jury-rigging which is outside authorized standard repairs, and may degrade the inherent safety of the helicopter. BDAR actions are not intended to supplement or replace standard maintenance practices during peacetime. They should not be employed indiscriminately to facilitate training.
- b. BDAR fixes authorized for sustainment training are listed in Appendix E. In addition, repair procedures which are authorized for training will be boxed in the chapter repair procedures index.

Section III. TASKS AND RESPONSIBILITIES

1-9. TAGGING/IDENTIFYING BDAR REPAIRS.

- a. All damage will be identified on aircraft inspection and maintenance record, DA Form 2408-13, DA Form 2408-14, and DA PAM 2408-18, as per DA PAM 738-751.
- b. Recording of BDAR repairs and the use of status symbols, as defined in DA PAM 738-751, will be completed as soon as practical to indicate any limitations and restrictions or required standard repairs.
- c. In addition to recording all damage, the area damaged will be marked on aircraft or component part using damage assessment markings as shown in Table 1-1.

- d. Maintenance of Forms. Instructions for the maintenance of forms, records, and reports are listed in DA PAM 738-751. When BDAR becomes necessary, the procedures in DA PAM 738-751 will apply.
- e. Temporary Repair. If the repair is temporary, take the following additional action:
- (1) In block 18 of DA Form 2408-13, enter the corrective action and a statement that the repair is temporary. Then make an entry in DA Form 2408-14, block b. The entry will be a duplicate of the entry in block 17 of DA Form 2408-13 to include a statement that a temporary repair has been made.

Table 1-1. Damage Assessing Markings

MEANI NGS MARKI NGS

TO INDICATE DAMAGE HAS BEEN ASSESSED AND EVALUATED:

Draw a circle around the damage.

DRAWN CIRCLE DAMAGE

TO INDICATE NO BDAR REPAIR REQUIRED:

Write "OK" inside the circle.



TO INDICATE STRUCTURAL SKIN REPAIRS ARE REQUIRED:

Draw a second line about 1/4 to 1/2 way around the initial circle then draw slashes or crosshatch between the two circular lines.



STRINGER/LONGERON REPAIR: Place an X to the left and right of the circle.



FRAME REPAIR: Place an X above and below the circle.



TO INDICATE DAMAGE TO SYSTEMS REQUIRING REPAIRS:

Draw a series of "curly cue" lines about 1/4 to 1/2 way around the initial circle.



TO INDICATE REPAIR INSTRUCTIONS:

For internal damage - draw a dashed circle around the repair instructions.



For external damage - write repair instructions but do NOT enclose with a circle.

REPAIR INSTRUCTIONS

PARTIAL

Table 1-1. Damage Assessment Markings (Cont)

WRITTEN INSTRUCTIONS	<u>MEANI NG</u>
See me - print name & rank. (Signature)	See assessor or whoever has signed written instructions for additional information.
Names of parts to be repaired (item, skin, stringer).	Where compound damage occurs, the names or abbreviations of specific items can be written adjacent to the damage to clarify repair instructions.
Full	A full strength repair is required.
Partial	Partial strength repair required in accordance with specific aircraft BDAR manual.
OK	No repairs required - damage is within acceptable limits for battle conditions.
?	Continual assessment or reinspection is required after each sortie.

Instruction markings for system are in two parts:

- (1) Repair instruction markings and meanings are shown on this sheet and are used to indicate repair actions required.
- (2) System Identification When known, identify the system using markings shown in this Table.

MARKI NGS	<u>MEANI NG</u>
Fi x	Repair the damaged system in accordance with approved standard BDAR techniques for type of system, item, high pressure, low pressure, etc.
Сар	Terminate or block the system to prevent leakage.
Repl	Replace damaged part - repairs not acceptable.
OK	No repairs required.
Tag	Repair instructions are written on tags tied to indivi- dual damaged lines/components.

Table 1-1. Damage Assessment Markings (Cont)

System identification markings are primarily abbreviations of the system.

MARKI NGS	SYSTEM/MEANI NG			
Sys	Damage to unknown system.			
Fuel	Fuel			
Hyd	Hydraul i c			
HP	High Pressure			
LP	Low Pressure			
El ec	El ectri cal			
AV	Avi oni cs			
Flt Cont	Flight Control			
Main Rotor	Main Rotor Group			
Tail Rotor	Tail Rotor Group			
Air	Pneumati c			
Air Cond	Air Conditioning			
BL Air	Bleed Air System			
BLC	Boundary Layer Control			
N_2	Ni trogen			
0,	0xygen			
Eng Contr	Engine Control			
Pow Tr	Power Train			
EJ	Ej ecti on			

NOTE

More than one identification marking may be used to describe the system (e.g., HP, Hyd).

- (2) If the temporary repair limits the capability of the aircraft, the following entry will be made on DA Form 2408-13:
- (a) Place a circled red "X" in block 16.
- (b) State the limitation in block 17.
- (3) If the temporary repair requires an inspection at intervals, list the required inspection on DA Form 2408-18.

- (a) Enter item to be inspected in block 5.
- (b) List the applicable TM in block 6.
- (c) State the frequency of the inspection in block 7.

CHAPTER 2

ASSESSING BATTLEFIELD DAMAGE

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

2-1 SCOPF.

- a. This chapter provides guidelines for use in assessing battlefield damage to the UH-1 utility helicopter. It directs you to a BDAR fix or to the standard system fix of TM 55-1520-210-23 if a BDAR repair does not exist. General decision logic chart, Table 2-1, assists in BDAR discussions.
- b. Each chapter will have a specific fault assessment table for each functional group, and this flow chart will direct you to specific BDAR fixes for and within the functional group.
- c. Use the following guidelines to find and fix sustained damage or suspected damage to your helicopter.

Keep in mind that damage can be sustained while on the ground or in flight. The helicopter location can have a considerable effect on the assessment. The following appraisal shall be accomplished.

- d. If possible and time permits, inspect and check the helicopter using operator's checklist (CL), operator's manual (-10), and other records and forms kept in aircraft log book. At the same time be looking for obvious damage to aircraft.
- e. After repairing the damage, replace all lost fluids/lubricants. If one specified by aircraft TM is not available, refer to Appendix D for alternative materials/parts.

Section II. FAULT ASSESSMENT

2-2. HELICOPTER FLIGHT ASSESSMENT. The helicopter flight assessment table, Table 2-2, guides you through the aircraft's systems so that all the necessary capabilities are evaluated. If a fault is found, Table 2-2 directs you to the chapter for the functional group which contains the fault. The BDAR assessment procedure will refer you

to a chapter in this manual, a standard TM 55-1520-210-23 repair if it is feasible, or a higher level of repair if extent of damage, time constraint, tooling requirements, repair part or material, and any other necessary requirements are only available at a higher level of maintenance.

Table 2-1. General Decision Logic




Table 2-2. Helicopter Flight Assessment

I TEM/ACTION

FAULT ISOLATION NOTE

BDAR REF.

Helicopters inspected by this table must operate to provide a minimum functional combat capability (MFCC). Even if all systems work, the helicopter may be unsafe to fly and may not provide or satisfy normal required operating capabilities. Flight status may be degraded and this may lessen the mission support the helicopter can contribute.




Table 2-2. Helicopter Flight Assessment (Cont)




Table 2-2. Helicopter Flight Assessment (Cont)




Table 2-2. Helicopter Flight Assessment (Cont)




Table 2-2. Helicopter Flight Assessment (Cont)





Table 2-2. Helicopter Flight Assessment (Cont)



CHAPTER 3

GENERAL REPAIRS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

3-1. SCOPE. This chapter provides information for BDAR of items that are not necessarily associated with a specific component or specific subsystem of the helicopter and which are not available in other manuals. It provides general repair procedures to use in more than one area of the helicopter. These fixes are designed to be expedient repairs using minimum amount of tools and standard common materials. The experienced technician/mechanic will easily be able to find equivalent substitute materials and tools. materials listed in text and in Appendix C are only recommendations. Any equivalent substitute is acceptable. 3-2. ASSESSMENT PROCEDURES. Use the planned steps defined in Chapter 1, paragraph 1-4.c, and the helicopter flight assessment.

3-3. REPAIR PROCEDURE INDEX.

	PARA.
	3-5 3-7 3-9
Bulkhead and Former Frames, Major Damage	3-11
	3-12
Honeycomb Panels, Damaged 2 inch Max Dia Honeycomb Panels, Damaged	3-14
2 to 8 Inches in Dia	3-15
Honeycomb Panels, Damaged 12 by 12 Inches	3-16

Section II. SKIN STRUCTURE

3-4. GENERAL.

- a. Helicopter structure is specified as primary structure which holds the helicopter together and secondary structure which mounts on primary structure.
- b. Skin damage or damage to secondary structure which occur by itself with no damage to primary structure is normally confined to a very small area (e.g., between longerons and stringers). This type of damage is deferrable if it poses no other problems.
- c. Skin damage, which in itself does not degrade structure but which can cause other problems, must be removed.
- d. Structural and skin metal substitution is allowed per Appendix D, Section V.
- 3-5. SKIN DAMAGE. Skin damage of less than 1-1/2 inches in diameter can be deferred and repaired later per TM 55-1520-210-23. Repair as follows:

TM 55-1520-210-BD GENERAL REPAIRS

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- Sol di er
- 15 Minutes

MATERI ALS/TOOLS REQUIRED:

- Adhesive Tape (items 153, 156, App C)
- Tools (App B)
- Aluminum Sheets (item 135, App C)
- Cherrymax Rivets (items 94-114, App C)

PROCEDURAL STEPS:

1. If the damage is less than 1-1/2 inches in diameter, apply adhesive tape to hole. Overlap tape 2 inches minimum around the hole.

- 2. If the damage is 1-1/2 Inches or larger, repair the hole as follows:
 - a. Trim and cut out all cracks.
 - b. Smooth edges with file.
- c. Apply a metal overlay patch using standard rivet pattern.
 - d. Use cherrymax rivets.
- 3. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section III. STIFFENER AND STRINGERS

3-6. GENERAL.

- a. Stiffeners and stringers are similar to longerons structural members. Their damage will range from either complete failure as in total separation and break to just deformation by over stress loading. In most cases, the skin over the stringers member will also be damaged. The damage causes will be varied, but the general causes can be as impact damage (i.e., by projectiles) concussion from explosions and over stress loading damage. Damage will be evident as breaks, cracks, holes, tears, buckling, bending, wrinkled, twisted, and stretched metal skin or stringer.
- b. Fixes in this section are designed to be expedient repairs to restore as much of original structure strength as possible without regards to weight or appearance. Over stress damage can cause internal damage to stringers without rupturing the skin.

- c. Fixes to stiffeners/stringers are listed in order of optional preference. Consideration to time, materials and tools available should be given.
- 3-7. STIFFENERS AND STRINGERS, DAMAGED.

GENERAL INFORMATION: These repairs are applicable to any skin stiffener structure on the helicopter. Two options are provided for repair. Option one is adding an external skin stiffener; option two is combining both external stiffener and skin patch.

OPTION 1: Reinforcing External Stiffener/Stringer.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- 2 Soldiers
- 30 Minutes

MATERIALS/TOOLS REQUIRED:

- Extrusion Angle, Aluminum or Steel (item 59, App C)
- Drill Bit (item 67, Sec II, App B)
- Drill Motor (item 69, Sec II, App B)
- Rivets (items 94-114, App C)
- Hand Rivet Puller (items 147-150, Sec II, App B)
- Locating & Drill Fixture (items 90-91, Sec II, App B)

PROCEDURAL STEPS:

- 1. If the damaged stiffener/stringer is lightweight and the bordering stringer and former are not damaged, apply an external bridging stiffener/stringer patch without regards to skin damage. Defer the skin damage until later.
- 2. Stop drill all cracks, but do not remove all damage. See Figure 3-1.
- 3. Use an angle or other suitable extrusion to bridge the damage. Metal size and thickness should be equal to or greater than original stiffener/stringer.
- Remove a minimum of eight existing rivets in undamaged area on both ends of damage. Using a rivet hole drill and locating fixture, locate, drill and rivet the repair piece of bridging extrusion in place as shown in Figure 3-1.
- Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Sheet Metal Patch and External Stiffener/Stringer.

LIMITATIONS: None.


PERSONNEL/TIME REQUIRED:

- 2 Soldiers
- 60 Minutes

MATERI ALS/TOOLS REQUIRED:

- Angle Extrusion (items 47-61, App C)
- Drill Bit (item 67, Sec II, App B)
 Drill Motor (item 69, App B)
- Hand Rivet Puller (items 147-150, Sec II, App B)
- Rivet Hole Drill and Locating Fixture (items 90-91, Sec II, App B)
- Sheet Metal (items 129-141, App C)

- Cut out the damaged skin and stiffener/stringer. Smooth and round the cutout. Clean up the ends of the stringer, Figure 3-2. If it is not possible to remove all the cracks, stop drill cracks.
- 2. Cut and fit a skin patch of the same material or one gage thicker than original. Steel sheet metal substitution per Table D-8, Appx D. Allow for an overlap for a minimum of two rows of cherry rivets as shown in Figure 3-2.
- 3. Cut a piece of substitute stringer to extend a minimum of eight inches or eight rivets beyond the damage on each end. Use an angle, channel, or tee extrusion with a cross section and strength equal to or greater than the original existing stiffener/stringer. If damage area is next to another damage area on the same stringer, extend the stringer to cover the damage of both areas.






Figure 3-1. External Stiffener/Stringer Patch




Figure 3-2. Patch Plate

TM 55-1520-210-BD GENERAL REPAIRS

- Remove rivets in the existing stiffener/stringer and back drill rivet holes in the substitute stiffener/ stringer. If the area is unaccessible for back drilling, use a rivet locating and drilling fixture to locate and drill new holes to match old rivet hole pattern.
- Rivet the skin patch and stiffener in place using the same size rivets as the originals, or one size larger di ameter.

NOTE

The placement of stiffener/stringer on the outside of the skin is strictly for expediency. If time permits and accessibility of damaged area permit, stiffener/ stringer can be installed internally.

Record BDAR action taken, When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section IV. LONGERONS AND CAPS

3-8. GENERAL.

- a. Longerons and caps are normally primary structures which hold the helicopter airframe together. Longerons and caps damaged will invariably result in damage to the skin at the same time. Longeron/cap damage which is severe to complete failure such as complete separation and missing sections will require reinforcement repairs.
- Repairs listed in this section are expedient temporary repairs. For permanent repairs, consult TM 55-1520-210-
- 3-9. LONGERONS AND CAPS, SEVERED. (Complete failure/separation.) See Figure 3-3.

LIMITATIONS: This temporary repair will be inspected after every flight, and permanent repair will be completed as soon as practical.

PERSONNEL/TIME REQUIRED:

- 2 Soldiers
- 2 Hours

MATERI ALS/TOOLS REQUIRED:

- Angle Extrusion (items 47-61, App C)
- Cherrymax Rivets (items 96-114, App C) Drill Bit Set (item 67, Sec II, App B)
- Drill Motor (item 69, App B)
- Hand Rivet Puller (item 147-150, Sec II, App B)
- Drill & Locating Fixture (items 90-91, Sec II, App B)

PROCEDURAL STEPS: Repair the damaged area with material of the same cross section as damaged member if available, or use a substitute material such as angle or channel extrusion, or corrugated sheet metal. For expediency, the longeron/cap used in this repair will be riveted on external side of skin using cherrymax rivets.

- Remove sections of the helicopter skin containing the damage. This will allow access to the inside for inspection and repair steps. Do not remove any more skin than is necessary to remove all cracks. Do not shorten the longeron/cap, but only remove the damaged ends.
- If time and material availability permit, patch the skin with a sheet metal patch of same material but one gage thicker, or a stronger material. Patch per basic instructions in TM 55-1500-204-25/1.

- 3. Cut substitute longerons/cap from angle or channel extrusion. The cross section of substitute longeron should be greater and stronger than the original metal. Cut the repair piece length to bridge the damage and to extend a minimum of 18 inches on both sides, overlapping the existing longeron. If space permits, install two angle extrusions as shown in Figure 3-3.
- 4. In the area where the substitute longeron/cap will overlap the damaged longeron section, remove the old rivets which attach the longeron to the skin. Remove rivets for a minimum of 18 inches.
- 5. Place the substitute longeron in place on the outside of the skin surface. Back drill or mark for rivet holes through the existing holes on the damaged and trimmed longeron/cap, or use a rivet hole drill and locating fixture.
- 6. Rivet the substitute longeron/cap in place using the cherrymax rivets.
- 7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equiment/system using standard maintenance procedures.

Section V. BULKHEAD AND FORMER FRAMES

3-10. GENERAL.

- a. Bulkheads and former frames are primary load carrying structures. Severe damage which reduces the cross section from 1/2 to complete separation will require substantial work to repair. Consideration should be given to using a permanent repair as authorized in TM 55-1520-210-23. If this is not possible, use the following expedient temporary repairs.
- b. Severe damage (Figure 3-4) which destroys 50 to 100 percent of the cross section of a bulkhead or former frame will be repaired per paragraph 3-11.
- c. Minor damage (Figure 3-4) which destroys 50 percent or less of the cross section of a bulkhead or former frame will be repaired per paragraph 3-12.

3-11. BULKHEAD AND FORMER FRAMES, MAJOR DAMAGE.

GENERAL INFORMATION: Damage which completely destroys one side of the bulkhead or former to where it is considered separated will be reinforced on both the inside and outside per this

paragraph and Figure 3-5. For more repair procedures on formers, consult TM 55-1520-210-23 and TM 55-1500-204-25/1.

LIMITATIONS: Inspect after every flight.

PERSONNEL/TIME REQUIRED:

- 2 Soldiers
- 3 Hours

MATERIALS/TOOLS REQUIRED:

- Aluminum Tape, Pressure Sensitive (item 153, App C)
- Cherrymax Rivets (items 96-114, App C)
- Sheet Metal (items 129-141, App C)
- Rivet Hand Pulling Tool (item 147-150, Sec II, App B)
- Drill & Locating Fixture (item 90-91, Sec II, Appx B)

- 1. Refer to Figure 3-5 for this procedure.
- 2. Remove sections of the skin and bulkhead/frame containing the damage. Smooth and round the cutout as shown.




Figure 3-3. Expedient Longeron/Cap Repair





Figure 3-4. Bulkhead and Former Damage







Figure 3-5. Typical Bulkhead and Former Repair (Sheet 1 of 2)



SECTION B-B

THRU REPAIRED SUBSTRUCTURE




Figure 3-5. Typical Bulkhead and Former Repair (Sheet 2 of 2)

TM 55-1520-210-BD GENERAL REPAIRS

- 3. Cut and fit repair doubler to inside flange of bulkhead/frame. Cut repair skin patch allowing overlap for at least four rows of rivets. Skin patch and inside doubler should be of the same material and one gage thicker than the original material. The filler doubler must be of the same thickness of original material.
- 4. Remove existing rivets where the repair parts will overlap existing rivets. If the area is not accessible for back drilling, use rivet hole drill and locating fixture to locate rivet holes in the repair pieces. As an alternate method, it may be possible to install repair rivets interspaced between existing rivets.
- 5. Rivet the repair pieces in place with cherrymax rivets of same diameter as original or one size larger if necessary.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 3-12. BULKHEAD AND FORMER FRAMES, MINOR DAMAGE.

GENERAL INFORMATION: A damaged outside flange on a bulkhead or frame which does not exceed 50 percent of cross section of bulkhead can be repaired with an external reinforcement skin patch plate or extrusion, Figure 3-6.

OPTION 1: Patch plate repair for minor damage to bulkhead and frames where skin contour is from flat to single place curved.

LIMITATIONS: Inspect the repair area after every flight.

PERSONNEL/TIME REQUIRED:

- 2 Sol di ers
- 3 Hours

MATERIALS/TOOLS REQUIRED:

- Aluminum Tape, Pressure Sensitive (item 153, App C)
- Cherrymax Rivets (items 96-114, App C)
- Drill Bit Set (item 67, Sec II, App B)
- Drill Motor (item 69, Sec II, App B)
- Rivet Hand Pulling Tool (items 147-150, Sec II, App B)
- Drill and Locating Fixture (items 90-91, Sec II, App B)
- Sheet Metal Strap Patch, Aluminum or Steel (items 129-141, App C)

- 1. Refer to Figure 3-6, sheet 1 of 2, for this procedure.
- 2. Stop drill all cracks, but do not remove the damage metal unless time permits.
- 3. Cover the damage hole with aluminum tape.
- 4. Fabricate repair strap using sheet metal twice as thick as the combined thickness of skin; flange and stringer (if any are present).
- Form the repair strap to fit the contour of the skin. The strap should be wide enough to cover damaged area and to allow at least two rows of rivets spaced at six rivet diameters on the skin, and a minimum of six rivet in the undamaged portion of damaged stringers if any present. The strap length should be enough to overlap both ends of the damaged bulkhead or frame flange by six rivets at each end. In the area where repair strap will overlap on the damaged bulkhead flange and stringer, remove rivets and backdrill. If the area is not accessible, backdrilling is not feasible. Locate new holes by using rivet hole drill and locating fixture.

- 6. Rivet the repair strap to the bulkhead or frame flange and stringer using the same size rivets or one size larger cherrymax rivets. Rivet the strap to the skin using two rows of rivets around the perimeter using the same size rivets or one size larger.
- 7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- OPTION 2: Channel or angle extrusion repair for minor damage to bulkhead and frames where the damage area is in a fairly straight contour.

LIMITATIONS: Inspect the repair area after every flight.

PERSONNEL/TIME REQUIRED:

- . 2 Soldiers
- . 2 Hours

MATERI ALS/TOOLS REQUIRED:

- Aluminum Tape, Pressure Sensitive (Item 153, App C)
- Channel or Angle Extrusion Strap Patch, Aluminum or Steel (Items 47-61, App C)
- Cherrymax Rivets (item 112, App C)
- Drill Bit Set (item 67, Sec II, App B)
- Drill Motor (item 69, Sec II, App B)
- Rivet Hand Pulling Tool (items 147-150, Sec II, App B)
- Drill & Locating Fixture (items 90-91, Sec II, App B)

- 1. Refer to Figure 3-6, sheet 2 of 2, for this procedure.
- 2. Stop drill all cracks, but do not remove the damage metal unless time permits.
- 3. Cover the damage hole with aluminum tape.
- 4. Select channel or L shaped angle extrusion that is wide enough for three rows of rivets spaced at four to six rivet diameters apart. The length of strap should cover the damage in center; plus an overlap on each end to allow for six rows of rivets spaced at six rivet diameters. In the area where the repair strap will overlap on the damaged bulkhead flange and stringers, remove rivets and drills. If the area is not accessible for backdrilling, use a rivet hole drill and locating fixture to drill rivet holes in the new repair piece and match the old rivet hole pattern. Interpitching new rivets between existing rivets is also possible if space allows.
- 5. Rivet the repair strap to the bulkhead or frame flange and stringer using the same size rivets or one size larger cherrymax rivets.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 3-6. Repair of Damaged Bulkhead Flange (Sheet 1 of 2




Figure 3-6. Repair of Damaged Bulkhead Flange (Sheet 2 of 2)

Section VI. HONEYCOMB PANEL

3-13. GENERAL.

- a. The UH-1 helicopter uses laminated honeycomb panels in numerous places. The cabin floor, the engine service deck, the main beams, and various other areas are constructed of bonded and laminated structures. These laminated panels are usually made up of a lightweight core sandwiched between two skins. The core material is normally a honeycomb metal or honeycomb material. The two outside skins can be either metal or composite fiberglass. Generally speaking, honeycomb panels stiffness comes from the external skin being held rigidly in one plane and fixed parallel to each other, resembling a solid element. Normally, they avoid any stiffness element within their boundaries, but require structural support around the edges.
- b. This section will give various repairs and options depending on size of the damage, and in order of optional preference. Fixes in this section are designed to be expedient repairs to restore as much of original structure strength as possible without regards of weight or appearance.
- c. Some of the repairs that follow are for damage to one side of skin. However, some of the repair procedures can be applied to both sides. The decision to repair both sides should be based on strength to be replaced and the time required to remove panel. The assessor will make this determination.
- d. For permanent repairs on honeycomb panel, consult TM 55-1520-210-23.
- 3-14. HONEYCOMB PANELS, DAMAGED 2 INCH MAX DIA (THRU HOLE).

LIMITATIONS: Repair of both skins is optional.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 10 Mi nutes

MATERI ALS/TOOLS REQUIRED:

- •Abrasive Grit Cloth (item 121, App C)
- Acetone Cleaner (item 1, App C)
- Aluminum Adhesive Tape (item 153, App C)
- Aluminum Sheet Metal 0.012/0.020 in. (item 130, App C)
- Epoxy, Five Minute (item 4, App C)
- Green Cotton Tape (item 156, App C)
- Chemical Conversion Coating (item 36, App C)

- 1. The following repair procedure will apply to one or both sides of panel as needed. Remove ragged edges using files and abrasive grit cloth, or push skin into void. Remove any paint, or at minimum roughen up the surface of the skin with 180 grit abrasive cloth around the damaged area. This bonding area around hole should be two to three inches wide.
- 2. Clean the reworked area with acetone or any equivalent fast drying cleaner. To improve adhesion, treat aluminum with chemical conversion coating (alodine).
- 3. Prepare a thin piece of aluminum (0.012 to 0.020 inch thick) to cover the damage in the skin and to extend 1-1/2 inches past the damage. Treat aluminum with chemical conversion coating.
- 4. Coat the aluminum patch and the skin in the area around the damage in skin with quick five minute drying epoxy. If no epoxy is available, cover the damaged area with either green cotton tape or aluminum adhesive tape.
- 5. Repeat steps 1 thru 4 for the other side of panel if accessible or needed.

- Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 3-15. HONEYCOMB PANELS, DAMAGED 2 TO 8 INCHES IN DIAMETER.

OPTION 1: One Skin and Core Damaged.

LIMITATIONS: This repair is limited to damaged panels with metal skins.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 45 Minutes

- MATERIALS/TOOLS REQUIRED:
 Abrasi ve Grit (item 121, App C)
- Acetone Cleaner (item 1, App C)
- Aluminum Sheet Mètal 0.012/0.020 in. (item 130, App C)
- Cherry Rivets (items 94-114, App C)
- Epoxy, Five Minute (item 4, App C)
- Hand Rivet Puller (items 147-150,
- Sec II, App B)
 Chemical Conversion Coating (item 36, App C)

PROCEDURAL STEPS:

- Remove damaged skin if it is loose; otherwise, push damaged skin into the void, Figure 3-7. The maximum damage that may be cutout or damaged is 8 inches in diameter. Use abrasive grit cloth to roughen up the surface of metal in a 3 inch wide band around the damage/hol e.
- 2. Make a patch plate from aluminum sheet metal twice as thick as the original external skin metal. Plate dimensions are to be the same size of the hole plus a 2-1/2 inch rivet and adhesive border around the damage.
- Lay out and drill a rivet pattern on patch and on the damaged panel. Rivet spacing to be 1 to 1-1/2 Inches. Bolts

may be used in place of rivets. When bolt, washer, and nuts are used, drilling all the way through panel's both skins will be required. Care should be used when tightening the bolts, so as not to crush the panel.

4. Clean the patch plate, the void, and the repair area on skin with acetone. Treat bare alumimum with chemical conversion coating to improve adhesion.

NOTE

Epoxy hardens in five minutes. Be prepared, work fast, and line up rivet holes with at least four Cleco clamps or rivets.

- 5. Coat the patch plate and the damage panel repair area with adhesive. Place the patch in place, lining up the rivet holes with rivets or bolts.
- 6. Immediately rivet the patch plate in place with cherry rivets or install bolts.
- Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 3-16. HONEYCOMB PANELS, DAMAGED UP TO 12 BY 12 INCHES THROUGH PANEL.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 1-1/2 Hour

MATERI ALS/TOOLS REQUIRED:

- Abrasive Grit (item 121, App C)
- Acetone Cleaner (item 1, App C)
- •Aluminum Patch Plates (items 129-141, App C)
- Cherry Rivets (item 112, App C)
- Hand Rivet Puller (items 147-150, Sec II, App B)




Figure 3-7. Honeycomb Panel Repair




Figure 3-8. Repair of Honeycomb Core Panel - Damage up to 12 X 12 Inches - Both Skins and Core

TM 55-1520-210-BD GENERAL REPAIRS

PROCEDURAL STEPS:

- 1. Remove damaged skin if it is loose; otherwise, push damaged skin into the core/void, Figure 3-8. The maximum damage allowed is 144 square inches. Use abrasive grit cloth and a file to remove burrs.
- 2. Make two patch plates from aluminum sheet metal twice as thick as the original metal. Plate dimensions are to be as shown in Figure 3-8. If time is available and panel can be unbolted, remove panel to repair if damage is inaccessible on interior skin. If panel cannot be removed, then consider installing a single patch plate on the accessible side, making the patch plate of metal three times the thickness of original metal thickness.
- 3. Lay out and drill a double row rivet pattern on patch and on the damaged panel. Rivet spacing to be as shown in Figure 3-8. Bolts (No. 10) may be used in place of rivets if backside area is accessible for wrenches. When bolt, washer, and nuts are used, drilling all the way through panel's both skins will be required. Care should be used when tightening the bolts so as not to crush the panel.
- 4. Rivet the patch plate in place with cherry rivets or install bolts.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section VII. LOW PRESSURE HOSES AND METAL TUBING

3-17. GENERAL. The UH-1 helicopter has four low pressure plumbing systems. These systems are connected with flexible hoses and rigid metal tubing. Damage sustained in battle can cause leaks which must be repaired to maintain These four systems are flyability. engine oil, transmission oil, fuel, and bleed air. The fluids and compressed air that flow through these systems must be contained and, in a case of leaks, repaired as soon as possible. The expedient repair in this section is for small holes or cracks in low pressure fluid/gas lines and is not intended to be used to repair a ruptured high pressure line exceeding 100 psi.

3-18. LOW PRESSURE HOSES AND METAL TUBING, LEAKING.

LIMITATIONS: Inspect the repaired line before and after each flight. Constant monitoring of system instruments for overheating or low pressure.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 15 Minutes
- 60 Minutes (full adhesive cure time)

MATERIALS/TOOLS REQUIRED:

- Acetone or Equivalent Solvent Cleaner (item 1, App C)
- Adhesive Repair Kit (Zip-Patch kit) (item 5, App C)

PROCEDURAL STEPS:

CAUTION

Zip-Patch and adhesive activator are flammable. Keep away from heat and flames. Use in a well-ventilated area. Avoid contact with skin and eyes. Use protective gloves and glasses.

1. Remove pressure from the line to be repaired. Drain fluids and make sure there are no fluids flowing from the damage area.

♦ U.S. GOVERNMENT PRINTING OFFICE: 1994- 655-028/00448

PIN: 049233-001

- 2. Locate the damaged area and clean off dirt and oil film with clean cloths soaked in solvent. Repair area must be absolutely clean for the patch to adhere properly.
- 3. The Zip-Patch kit contains five patches In sealed foil packages, activator spray can, gloves, and an applicator plastic tool.
- 4. Spray one side of patch lightly with activator. Proper activation will be indicated by the patch becoming darker in color. Spray the damaged area lightly with activator.
- 5. Place the activated side of the patch over the damaged area and extending two to four inches beyond the

- damage. Wrap the patch around the hose or tube until the repair area is covered. Smooth the patch with the plastic spreader tool to remove any entrapped air.
- 6. Spray the exposed area of the patch lightly with the activator.
- 7. Wait five minutes for Zip-Patch to set. Full cure is reached in one hour.
- 8. Refill system with fluid that was lost or was drained prior to repair.
- 9. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

CHAPTER 4

AI RFRAME

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

4-1. SCOPE.

- a. The purpose of this chapter is to provide BDAR to the damaged UH-1 helicopter airframe structure. The repairs are intended to repair damage which has degraded or will degrade In a short period of time the flight capabilities of the helicopter.
- b. The helicopter airframe structure can be classified as follows:
- (1) Primary load carrying structure. Longerons, caps, stringers, firewalls, and bulkheads are examples of primary structures. See Figure 4-1 for a view of the primary structures of the UH-1 helicopter.
- (2) Secondary diffused Load carrying and transferring structure. Skins, Laminated panels, and doors are examples of secondary structure. See Figure 4-2 for a complete view and Listing of the helicopters outside skin.
- c. Battle damage to the airframe structure is not always evident from the flight characteristics of the aircraft. If damage occurred in flight, landing may be necessary. The only way to assess battle damage to the airframe is through visual inspection of the aircraft.
- d. During the initial assessment, the following should be recognized:

- (1) Some primary damage/repair may be deferred.
- (2) Most secondary damage/repair can be deferred.
 - (3) All BDARs will be temporary.
- (4) Repairs must contribute to and improve some "lost function" of helicopter to as close to 100 percent of its intended function as possible under BDAR conditions.
- (5) Repairs must work without regards to weight, appearance, or aero-dynamic appeal.
- (6) Repair must be simple and quick in application.
- (7) Repair must improve the damaged helicopters flight or mission capability or at minimum, repair must allow for helicopter's self-recovery.
- e. This chapter will be arranged by sections, with each section of the helicopter being assessed by a section in this chapter. BDAR fixes are listed in the repair procedure index, paragraph 4-3. Figures 4-1 and 4-2 are to be used to locate and identify damage to the helicopter.





Figure 4-1. Fuselage Structure, Station, Water, and Butt Lines (Sheet 1 of 15)






Figure 4-1. Fuselage Structure, Station, Water and Butt Lines (Sheet 2 of 15)




Figure 4-1. Fuselage Structure, Station, Water, and Butt Lines (Sheet 3 of 15)





Figure 4-1. Fuselage Structure, Station, Water and Butt lines (Sheet 4 of 15)



CABIN FLOOR (WL 22.00) AND SUB-STRUCTURE REFERENCE LINES

Figure 4-1. Fuselage Structure, Station, Water, and Butt Lines (Sheet 5 of 15)




Figure 4-1. Fuselage Structure, Station, Water and Butt Lines (Sheet 6 of 15)




Figure 4-1. Fuselage Structure, Station, Hater, and Butt Lines (Sheet 7 of 15)




Figure 4-1. Fuselage Structure, Station, Water and Butt Lines (Sheet 8 of 15)




Figure 4-1. Fuselage Structure, Station, Water, and Butt Lines (Sheet 9 of 15)




Figure 4-1. Fuselage Structure, Station, Water and Butt Lines (Sheet 10 of 15)




Figure 4-1. Fuselage Structure, Station, Water, and Butt Lines (Sheet 11 of 15)




Figure 4-1. Fuselage Structure, Station, Water and Butt Lines (Sheet 12 of 15)






Figure 4-1. Fuselage Structure, Station, Water, and Butt Lines (Sheet 13 of 15)



STRINGER LOCATION

VIEW LOOKING FORWARD

Figure 4-1. Fuselage Structure, Station, Water and Butt Lines (Sheet 14 of 15)



TAIL BOOM

Figure 4-1. Fuselage Structure, Station, Water, and Butt Lines (Sheet 15 of 15)




Figure 4-2. Forward Fuselage Skin (Sheet 1 of 6)

Item	Name	Materi al	Speci fi cati on	Condi ti on	Thi ckness
1 2 3 4 5 6 7 8	Nose door Nose, Iwr fwd Side, fwd LH Side, fwd LH Side, upper LH Side, upper RH Center, upper Door, Iwr LH Door, Iwr RH Door, upper LH Door, upper RH Post, center RH Post, center RH Post, inner RH Post, inner LH Post, inner LH Post, inner LH	Fiberglass Al Honeycomb Al Aly Al Honeycomb Al Aly Al Aly Al Aly Al Aly	Type C MI L-C-7438 00-A-250/5 00-A-250/6 00-A-250/6 00-A-250/5 00-A-250/5 00-A-250/5 00-A-250/5 00-A-250/5 00-A-250/5 00-A-250/5 01-C-7438 01-C-7438 Type "E" 00-A-250/5	T42 T42 T42 T42 T42 T42 T42 T4 T4 T4 T4 T4 T3 T4 T3 T4 T3	0. 250 0. 020 0. 032 0. 032 0. 020 0. 020 0. 025 0. 025 0. 025 0. 025 0. 025 0. 020 0. 020 0. 020 0. 020
9 10 11 12 13	Post, pan LH Post, outer RH Post, cntr RH Post, inner RH Post, inner RH Post, pan RH Roof, center fwd Roof, side LH Roof, side RH Roof, cntr outer Roof, cntr inner Roof, side aft LH Roof, side aft RH Roof, side aft RH Roof, cntr outer LH Roof, cntr outer LH Roof, cntr outer LH Roof, cntr inner LH Roof, cntr inner LH Roof, cntr inner RH Hinged, panel Outer skin	AI AI Y AI Honeycomb Fiberglass AI AI Y AI AI Y AI AI Y AI AI Y AI Honeycomb AI AI Y AI Honeycomb AI AI Y AI Honeycomb AI AI Y	MIL-C-7438 Type "E" QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 MIL-C-7438 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 MIL-C-7438 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5	T4 T3 - T4 T42 T42 T42 T3 - T3 T4 T4 T3 - T3 T3 T4	0. 025 0. 020 0. 375 0. 025 0. 020 0. 020 0. 012 0. 750 0. 008 0. 020 0. 012 0. 500 0. 012 0. 500 0. 012 0. 500
16	Pan Door, outbd LH Door, outbd RH Door, outbd RH Door, outbd RH Door, inbd LH Door, inbd RH Door, inbd LH Door, inbd RH Door, inbd RH Door, inbd RH Door, inbd RH Fusel age LH	AI AI y	QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5 QQ-A-250/5	T4 T42 T42 T42 T42 T3 T3 T3 T3 T3 T42 T42 T42 T44 T6 T6 T6	0. 025 0. 020 0. 020 0. 020 0. 020 0. 012 0. 012 0. 020 0. 020 0. 020 0. 020 0. 020 0. 020 0. 020 0. 025 0. 025 0. 032

Figure 4-2. Forward Fuselage Skin (Sheet 2 of 6)

Item	Name	Materi al	Speci fi cati on	Condi ti on	Thi ckness
	Fusel age LH Fusel age LH Fusel age LH Fusel age LH Fusel age RH Fusel age Contr	AI AI Y	Q-A-250/5 QQ-A-250/6 Q	T6 T6 T4 T6 T6 T6 T6 T6 T6 T6 T7 T3 T3 T4 T4	0. 032 0. 032 0. 025 0. 025 0. 025 0. 025 0. 032 0. 025
17	Fuselage, cntr Door, outer LH Door, cntr LH Door, cntr LH Door, inner LH	Fi berglass Al Honeycomb Al Honeycomb Fi berglass	QQ-A. 25075 Type "E" MI L-C-7438 MI L-C-7438 Type "E"	- - - -	0. 025 0. 500 0. 250
18	Door, outer RH Door, cntr RH Door, cntr RH Door, inner RH Door, outer LH Door, cntr LH Door, inner LH Door, outer RH	Fi bergl ass Al Honeycomb Al Honeycomb Fi bergl ass Fi bergl ass Al Honeycomb Al Honeycomb Fi bergl ass	M1 L-C-7438 M1 L-C-7438	 	0. 500 0. 250 — 0. 500 0. 250
19	Door. center RH Door. center RH Door, inner RH Door, outer LH Door, center LH Door, inner LH	Fi bergl ass Al Honeycomb Al Honeycomb Fi bergl ass Fi bergl ass Al Honeycomb Fi bergl ass	Type "E" Type "E" ML-C-7438 MIL-C-7438 Type "E" Type "E" MIL-C-7438 Type "E" Type "E" MIL-C-7438 Type "E" Type "E" MIL-C-7438 Type "E" MIL-C-7438 Type "E" MIL-C-7438 Type "E" MIL-C-7438	- - - - - -	0. 500 0. 250 — 0. 500
20	Door, outer RH Door, center RH Door, inner RH Service deck outer skin Service deck core Service deck inner skin	Fi berğl ass Al Honeycomb Fi bergl ass Ti tani um Al Honeycomb Fi bergl ass	Type "E" MIL-C-7438 Type "E" MIL-T-9046 MIL-C-7438 BHT299-947-059 Type II	- - - -	0. 500 0. 016

Figure 4-2. Forward Fuselage Skin (Sheet 3 of 6)





Figure 4-2. Forward Fuselage Skin (Sheet 4 of 6)



Item	Name	Material	Specification	Condition	Thickness
1	Fairing Outer Skin	Glass Fabric	BHT299-947-037. Type E		0.500
	Core Inner Skin	Al Aly Honeycomb Al Aly	BHT299-947-037. Type E		0.500
2	Lower Cowl Inner Skin Outer Skin	Al Aly Al Aly	QQ-A-362 QQ-A-362	T4 T4	0.025 0.020
3	Upper Cowl: Louvers Bulkheads Skins: Upper Inner	Al Aly Al Aly Al Aly Al Aly	BHT299-947-012. Ty QQ-A-250/5 QQ-A-250/5 QQ-A-250/5	/pe VIII T42 T42 T42	0.025 0.025 0.025
	Lower Inner Outer Perforated Inner Tailpipe Fairing	Al Aly Al Aly	QQ-A-250/5 QQ-A-250/8	T42 H34	0.020 0.032
4	Upper Fairing	Al Aly	QQ-A-250/5	T42	0.025
5	Upper Fairing	Al Aly	QQ-A-250/8		0.025
6	Lower Fairing	Al Aly	QQ-A-250/5	Т4	0.020

Figure 4-2. Forward Fuselage Skin (Sheet 5 of 6)





Figure 4-2. Forward Fuselage Skin (Sheet 6 of 6)

4-2. ASSESSMENT PROCEDURES.


- a. Use fault isolation flow diagram, paragraph 4-2.c, and Tables 4-1 thru 4-10 to determine allowable damage limits for specific areas of the helicopter's structure. Tables 4-1 thru 4-5 list the damage which is deferrable. Damage limits in Tables 4-6 thru 4-10 are repairable by BDAR or standard repairs if time and material are available. Damage exceeding limits of Tables 4-6 thru 4-10 is cause for grounding the helicopter.
- b. For assessment purpose, the helicopter is broken down into five general sections as shown in Figure 4-1, sheet 3. These sections are nose, cabin roof, fwd fuselage, midsection fuselage, aft fuselage, and tail boom section. Further, some areas of critical structural importance are also listed in special sections. To repair damage to the helicopter, find the area of damage by the use of damage assessment flow chart, paragraph 4-2.c, and by use of the index in paragraph 4-3.

c. Visually Inspect Damage.

I TEM/ACTION <u>FAULT I SOLATION</u> <u>BDAR REF.</u>



d. Detail Assessment Inspection.



(2) To continue assessment, Insert one of the following sections listed below in paragraph 4-3 in diagram above, replacing the shown <u>airframe</u>. Continue this assessment until all areas are covered.

4-3. REPAIR PROCEDURE INDEX.

	PARA.
Cabin Roof	
Fusel age Midsection	Sec II, Tables 4-3, 4-8
	Sec II, Tables 4-4, 4-9 Sec II, Tables 4-5, 4-10
Nose Section.	Sec III

Section II. AIRFRAMES

4-4. GENERAL.

- a. There is no easy way to identify all possible types of airframe structure damage that can occur. The location and the severity of airframe structure damage can vary a great deal. Tables 4-1 thru 4-10 and Figure 4-3 will assist with identifying damage and determining what is to be acceptable or to be repaired.
- b. Except with the limits of damage allowed, Tables 4-1 thru 4-10 are identical.
- (1) Tables 4-1 thru 4-5 list condition I limits. Damage less than these limits are acceptable without any rework, and repairs are deferrable.
- (2) Tables 4-6 thru 4-10 list condition II limits. They identify damage limits exceeding condition I. Condition II helicopters will have flight restrictions imposed and will only be flown for self-recovery capable mission. Helicopters with condition II can be upgraded to condition I by repairing all damage exceeding condition I.
- (3) Helicopters with battle damage which exceed Tables 4-6 thru 4-10 should be grounded.

4-5. GENERAL SKIN AND STRUCTURAL DAMAGE.

LIMITATIONS: Listed in Tables 4-1 thru 4-10 and Figure 4-3.


PERSONNEL/TIME REQUIRED: See individual repairs listed in Chapter 3.

MATERIALS/TOOLS REQUIRED:

• Standard Sheet Metal/Mechanics Tools (See App B & C)

PROCEDURAL STEPS:

- 1. Inspect obvious skin damage. Even though skin damage is secondary structure and damage may not appear to be critical, the underlying or adjacent primary structure may have hidden critical! damage. Inspect primary structure under the skin damage for:
 - a. Visual cracks in structure.
- b. Metal deformation in both primary and secondary structure.
- c. Embedded projectiles or fragmentations.
- d. Fire damage for fire weakened metals.
 - e. Broken or missing fasteners.
- 2. Measure the damage as instructed in Tables 4-1 thru 4-10 and Figure 4-3.
- a. If damage is within limits of Tables 4-1 thru 4-5, then it is deferrable.
- b. If damage exceeds the limits of Tables 4-1 thru 4-5 but is less than Tables 4-6 thru 4-10, then this damage can be upgraded to condition I by repairing condition II damage.
- c. If damage exceeds Tables 4-6 thru 4-10, then aircraft cannot be flown and will have to be evacuated otherwise.
- 3. Repair all damage using BDAR fixes in Chapter 3, General Repairs.
- 4. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.



TYPICAL SKIN, WEB, AND PANEL DAMAGE

Figure 4-3. Damage Limits Measurement for Tables 4-1 thru 4-10

	····	<u></u> '	abie 4-1.	Damage Limits Ca	DIII KOC				
	ļ]			GE LI		FIGURE 4-1
COMPONENT/		LOCATION				/FLANG		SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD'	CL'	N	WL' N	NOTES
		FROM			(D'=N	xCL)		(D'=NXWL)	
j		22.00 TO		POST					
DOOR POST	74.25	78.00		R/H & L/H	.01	.02	10		
		FROM							
	İ	22.00 TO		POST	ł			ļ	
	63.38	-69.00		R/H & L/H	.43	.86	10	į	
		FROM		W. V. G. GV W.	1			L	
		69.00 TO		SPLICE					SHEET 3 OF 15
ł	63.38	-71.00		R/H & L/H	1	NO RIV	FT DA	MAGE	511221 5 51 15
 	03.30	FROM		K/11 & C/11	+	110 1121		T	
Į	ļ	69.00 TO		POST	1			i	
ļ	63.38	-71.00		R/H & L/H	.43	.86	10	İ	
	03.30	FROM		K/H & L/H	1.43	•00	10		
1	62.20		24 10	LIED	Ì				
	63.38		34.10	WEB	ì				a Henc Ceneber
	-74.25	-78.00	OUTBD	R/H & L/H				L	2 WEBS SEVERED
Í		FROM							
İ	63.38	22.00 TO				LIMIT			
<u></u>	-74.25	-78.00		SKIN	D/A	MAGE T	0 ELE	MENI	
1			15.25L			_			
BULKHEAD	112.8	80.00	-15.25R	UPPER FLANGE	1.1	.2	10		
		FROM						1	
		75.60 TO	15.25L						
	112.8	80.00	-15.25R	WEB	1.57	3.14	10		
		FROM							
	81.00	75.00 TO	30.00L&R		1			1	
[83.00	80.00	-OUTBD	FRAME	1.02	2.04	10		
		FROM							
1	1	75.60 TO	31.25L						
f	63.38	80.00	-31.25R	FRAME	.04	.08	10	J	
	00.00	FROM	31.20K		+				
l		75.60 TO	31.25L&R						
}	63.38	80.00	-OUTBD	FRAME	1 03	2.06	10		
}	03.30	00.00	עפוטטי	INAME	1.03	2.00	10	[
1	ŀ	1	l	[1			ł	l .

			age chares eabin		DAMA	GE LI	FIGURE 4-1		
COMPONENT/		LOCATION	 		CAP	/FLANG		SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD	CL	N	Mr, N	NOTES
FICHOLIX				ECCION	(D'=N			(D'=NXWL)	
			,					(
BULKHEAD	74.25	80.00	16.00L&R	UPPER FLANGE	.05	.10	10]	
		FROM							
		75.60 TO			!				
	74.25	-80.00	16.00L&R	WEB	.38	.76	10		
			10.001.00						
	92.00	80.00	16.00L&R	UPPER FLANGE	.08	.16	10	ļ	
		FROM 75.60 TO	'					[
	92.00	-80.00	16.00L&R	WEB	93	1.86	10		
	32.00	FROM	10.00Lak	WLD	•33	1.00	10		
		75.60 TO	30.00L&R					1	
	74.25	-80.00	OUTBD	CAP	1.02	2.04	10	1	
		FROM							
}		75.60 TO	30.00L&R						
	92.00	-80.00	OUTBD	FRAME	1.02	2.04	10		
		FROM							
ĺ		75.60 TO	16.00						
L	74.25	-80.00	-30.00L&R	FRAME	.73	1.46	10		
		FROM	16.00	İ	ĺ				
1	92.00	75.60 TO -80.00	16.00 -30.00L&R	FRAME	87	1.74	10	1	
 	32.00	FROM	-JU-UULAK	INAME	•0/	1./4	10	 	
	157.50	75.00 TO	30.00L&R]	
		-80.00	-OUTBD	FRAME	1.18	2.36	10		
		FROM							
	130.01	75.00 TO	30.00L&R					!	
	-132.01	-80.00	-OUTBD	FRAME	1.12	2.24	10	1	
								1	

				age Limits Cabin		DAMAGE	LIMITS	FIGURE 4-1
COMPONENT/		LOCATION				/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD'	CL' N	WL' N	NOTES
		FROM			(D'=N	xCL)	(D'=NXWL)	
	104.00	75.00 TO	30.00L&R					
BULKHEAD	-106.00	-80.00	-OUTBD	FRAME	1.06	2.12 10	•	
		FROM						
		75.00 TO	30.00L&R				ļ	
	114.71	-80.00	-OUTBD	FRAME	1.00	2.00 10	į	
		FROM						
		75.00 TO	30.00L&R					
	142.00	-80.00	-OUTBD	FRAME	1.00	2.00 10		
		FROM		***			1	
		75.00 TO	30.00L&R				1	
	148.00	-80.00	-OUTBD	FRAME	1.00	2.00 10		
		FROM						
	63.38	75.60 TO						
LONGERON		-80.00	15.25L&R	FRAME	.02	.04 10		
		FROM						
	74.25	75.60 TO					Ì	
	-114.71	-80.00	30.00L&R	FRAME	.08	.16 10	ļ	
		FROM						
	114.71	75.60 TO						
		-80.00	30.00L&R	FRAME	.34	.68 10		
		FROM						
	131.80	75.60 TO						
	-166.00		30.00L&R	FRAME	.08	.16 10		
		FROM						
	63.38	75.60 TO						
	-74.25	· ·	30.00L&R	FRAME	.34	.68 10		
		FROM						
	126.97	75.60 TO						
		-80.00	15.25L&R	FRAME	.02	.04 10		
		FROM						
	157.50	75.00 TO	37.00-					
DOOR POST		80.00	39.00L&R	SUPPORT BRACKET	.02	.04		ONE DAMAGED
· · · · · ·							İ	

					1	DAMA	GE L	IMITS	FIGURE 4-1
COMPONENT/		LOCATION			CAP	/FLANG	E	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD'	CL'	N	WL' N	NOTES
		FROM			(D'=N	xCL)		(D'=NxWL)	
	81.00	75.00 TO	34.10-						
DOOR POST	-83.00	-80.00	36.10L&R	SUPPORT BRACKET	.02	.04			
		FROM							
		75.00 TO	38.50-		l				ONE DAMAGED
	-132.01	-80.00	40.50L&R	SUPPORT BRACKET	.11	.22			
		FROM			ł				
	_	75.00 TO	34.10-					1	
	-106.00	-80.00	36.10L&R	SUPPORT BRACKET	.11	.22			
	62.22]				
20020	63.38	70.60		04000 0000 047	1				
DOORS	-166.00	72.60		CARGO DOOR RAIL	Ì				
	ł				Ì	NO 1 TM	7 T O		
	166.00			CARGO DOOR		NO LIM			
	100.00	FROM		CARGO DOOR	ł	UAMAGE	10 1	LEMENT	
	İ	22.00 TO		HINGED					
	74.25	-78.00		PANEL DOOR					
	74.23	-70.00		TANLE DOOK	-				
ROOF PANEL/	63.38		12.25-		}				
RIVETS	-126.97	80.00	16.00L&R	PANEL EDGE	.42	.84	5	1	
	80.00	i	9.00-		[
	-84.00	80.00	13.00L&R	STN RIVETS	Í			}	FOUR RIVETS DAMAGE
	63.38	80.00	16.00L&R	CP RIVETS					TEN RIVETS DAMAGE
1									
	63.38		40.051.55				_	}	
	-66.38	80.00	12.25L&R	PANEL EDGE	.12	.24	5	ļ	
	80.00			ļ	{			-	
	-84.00	80.00	12 251 10	CENTED DANEL	1 76	2 52	5	}	
l	1-04.00	1 00.00	I IK. COLAK	CENTER PANEL	1.40	3.52	J		

		ומטו	<u>e 4-1. Dam</u>	age Limits Cabin	KUUI -				116/	
						DAMA	GE L	IMITS		FIGURE 4-1
COMPONENT/		LOCATION			CAP	/FLANG	ìΕ	SKIN	/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD'	CL'	N	WL'	N	NOTES
					(D'=N	xCL)		(D'=	NxWL)	
ROOF PANEL	98.00									1
RIVETS	-102.00	80.00	12.25L&R	CENTER PANEL	2.79	5.58	5	<u> </u>		
										}
	66.38		į		}				_	
	-80.00	80.00	12.25L&R	CENTER PANEL				3.1	5	
								1		
	84.00		Į		1			1	_	ļ
	-98.00	80.00	12.25L&R	CENTER PANEL				3.1	5	
	102.00				Í			١.,	_	ĺ
	-126.97	80.00	12.25L&R	CENTER PANEL				3.1	5	
ļ	63.38		30.00L&R			O LIMI				1
	-166.00	80.00	-OUTBD	ROOF PANEL	D	AMAGE	TO EL	<u>EMENT</u>		
								}		ļ
	63.38		16.00-					1		
	-166.00	80.00	30.00L&R	ROOF PANEL	<u> </u>			6.00	5	

Table 4-2. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition I

	Ιαι	DIC 4-2.	Danage Limit	LS Fuselage, Forw	414 (15	DAMAG	C 1 T	MITS		FIGURE 4-1
								SKIN/	JED	AND
COMPONENT/		LOCATION				LANGE		Mr,		NOTES
MEMBER	FS	WL	BL	ELEMENT			N		N	NUIES
FORWARD					(D'=NxC	,L)		(D'=N:	KWL)	ODITION LITTU
SECTION	102.00		34.70L&R						_	CRITICAL WITH
BOTTOM	-129.00	-22.00	-OUTBD	SKIN				2.50	5_	EXTERNAL STORES
	23.00	BOTTOM	c - L&R							
	-102.00	-22.00	OUTBD	SKIN	_					SKIN NOT CRITICAL
	102.00		ļ							
	-129.00		34.70L&R	SKIN						
-		5011011			DO N	NOT US	E FI	TTINGS		
	63.33		c - L&R	CARGO TIEDOWN	WITH	H DAMA	GE W	ITHIN		
DECKS	-129.00	22.00	OUTBD	FITTINGS	6 IN	NCHES	OF F	ITTING	S	
DECKS	123.00	22.00	00100	721721100						
	74.25			DOOR ASSEMBLY						NO DAMAGE WITHIN
	-123.00	22.00	14.00L&R					8.00	5	1.5 INCH OF EDGE
	-123.00	22.00	14.00Lak	HONE POOR TANKE				0.00		
	74 25			EDGE HONEYCOMB						
	74.25	22.00	14 001 00	PANEL	1.00	1 25	10			
	-123.00	22.00	14.00L&R	PANEL	1.00	1.23	10	-		
	00.00									NO DAMAGE WITHIN
	23.00		c - L&R	HONEYCOMB BANELS				8.00	_	1.5 INCH OF EDGE
	-74.22	22.00	OUTBD	HONEYCOMB PANELS				0.00	<u> </u>	1.5 INCH OF EDGE
	23.00		c - L&R	EDGE HONEYCOMB				ļ		
	-74.00	22.00	OUTBD	PANELS	1.00	1.25	10			
										NO DAMACE LITTUE!
	74.00	İ	14.00L&R		1				_	NO DAMAGE WITHIN
1	-129.00	22.00	-OUTBD	HONEYCOMB PANELS	ł			8.00	5	1.5 INCH OF EDGE
	123.06	1		ENDS HONEYCOMB						
1	-128.75		14.00L&R	PANEL	1.00	1.50	10			
	1									
,	123.06			1				1		NO DAMAGE WITHIN
	-128.75	1	14.00L&R	HONEYCOMB PANEL				2.00	5	1.5 INCH OF EDGE
	120.73									
I	1	1	ı	ı	1			'		•

1 0

2 27 2

Table 4-2. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition I (Cont)

	Idule	4-Z. Dalli	age Lillics	ruselage, rolwalu	(13 2	DAMA	GE LI	MITS	FIGURE 4-1
COMPONENT/		LOCATION			CAD	/FLANG		SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD	CL	N	WL' N	NOTES
MEMBER	<u> </u>	WL	DL	ELEMENT	(D'=N:			(D'=NXWL)	HOILS
				UPPER CAP SPLICE		XCL)		(D -NAME)	
MAIN BEAM	112.50	22.00	14 00120	INSIDE & OUTSIDE		1 40	10		
MAIN DEAM	112.50	22.00	14.00Lax	INSIDE & COISIDE	0.70	1.40	10		
	23.00								
	-41.70	22.00	14 001 20	UPPER CAP	0.65	1.30	10		
	-41./0	22.00	14.00EdK	OITER ON	0.00	1100			
	41.70								
	-69.00	22.00	14.00L&R	UPPER CAP	0.75	1.50	10		
	00000		21000000	<u> </u>					
	69.00								
	-83.80	22.00	14.00L&R	UPPER CAP	0.75	1.50	10		
	83.80							[
	-95.50	22.00	14.00L&R	UPPER CAP	0.90	1.80	10		
	95.50								
	-129.00	22.00	14.00L&R	UPPER CAP	0.25	0.50	10		
	23.00	BOTTOM					4.0	1	
	-34.00	CONTOUR	14.00L&R	LOWER CAP	0.00	0.00	10	<u></u>	
		1.01150							
	34.00	LOWER	14 001 00	LOUED CAD	0 00	0.00	10	1	
	-60.00	CONTOUR	14.UUL&R	LOWER CAP	0.00	0.00	10	 	
	60.00	LOWER	İ						
	-69.80	CONTOUR	14.00L&R	LOWER CAP	0.35	0.70	10		
	-03.00	CONTOOR	14.00Lak	LOWER OVE	0.33	3.70	10		
	73.50	LOWER			}				
	73.30	CONTOUR	14,001 %	LOWER CAP	0.15	0.30	10		
	-/0.0/	CONTOOK	17.00Lak	LONEIL O/II		3,00			
	78.07	LOWER	}		[
	-117.00		14.00L&R	LOWER CAP	0.55	1.10	10		
	117.00		2.0002an						
	-129.00		14.00L&R	LOWER CAP	0.00	0.00	10		
			1						•

Table 4-2. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition I (Cont)

					DAMAGE L		FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
				00000	(D'=NxCL)	(D'=NxWL)	
	69.00	LOWER	44 001 00	CROSS	NO DAMAGE		
MAIN BEAM	-74.30	CONTOUR	14.00L&R	TUBE FITTING	NO DAMAGE	ALLOWED	
		FROM					
	47.60	12.00 TO -22.00	14 001 90	STIFFENER	0.50 1.00 10	i	
<u></u>	4/.00	FROM	14.UULAK	SITFLENEK	0.50 1.00 10		
		9.90 TO		:		İ	
	63.33		14 001 20	STIFFENER	2.30 4.60 10	1	
	03.33	FROM	14.00LGK	SITILITER	2.30 4.00 10		
		9.90 TO				1	
	69.00	-22.00	14.00L&R	STIFFENER	2.05 4.10 10		
		FROM					
		9.90 TO					
	74.00	-22.00	14.00L&R	STIFFENER	2.10 4.20 10		
		FROM					
		9.90 TO					
	90.50		14.00L&R	STIFFENER	0.55 1.10 10		
		FROM				}	
	102.00					1	
	-129.00	-22.00	14.00L&R	HONEYCOMB		7.50 5	
	00.00	FROM					
	23.00		14 001 80	l urb		0.75 5	
	-37.00	-22.00 FROM	14.00L&R	WEB	-	8.75 5	
	37.00	10.00 TO					
	-47.60	-22.00	14.00L	WEB		5.50 5	INCLUDES ACCESS HOLE
	-47.00	FROM	14.00L	I MED		3.30 3	INCLUDES ACCESS HOLE
	37.00	10.00 TO					
	-47.60	-22.00	14.00R	WEB		2.45 5	
	.,,,,,,,	FROM				1	
	47.00	9.00 TO					
	-69.00	-22.00	14.00L	WEB		4.25 5	

	Table	4-2. Dan	nage Limits	Fuselage, Forwar	d (FS 23 to 129)	- Condition	ı I (Cont)
	Ī				DAMAGE L	IMITS	FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
					(D'=NxCL)	(D'=NxWL)	
		FROM		j			
	47.00	9.00 TO					
MAIN BEAM	-69.00	-22.00	14.00R	WEB			
		FROM					
	69.00	8.00 TO					
	-74.30	-22.00	14.00L&R	WEB			INCLUDES ACCESS HOLES
		FROM					
	74.30	7.44 TO					
	-78.10	-22.00	14.00L&R	WEB		7.10 5	
	70.10	FROM					
	78.10	7.44 TO	44 00.00			_	
	-102.00	-22.00	14.00L&R	WEB		2.75 5	
DIII VIITAD	62.22	22 00	C - L&R	UDDED CAD	0.50 1.00 10		
BULKHEAD	63.33	22.00	OUTBD	UPPER CAP	0.50 1.00 10	<u> </u>	
		LOVED	a 19D				
	63.33	LOWER CONTOUR	C - L&R	LOUED CAD	0 15 0 20 10	ļ	
	03.33	CONTOUR	OUTBD	LOWER CAP	0.15 0.30 10]	
		LOWER		LOWER CAP	JACK ONLY TE CA	ND.	
	63.33	CONTOUR	30.00L&R		JACK ONLY IF CA		
	03.33	CONTOOR	JU-UULAR	DACKING POINT	WILL SUPPORT HE	LICOPIER	
		LOWER					
	63.33	CONTOUR	14.00L&R	SPLICE PLATE	0.50 1.00 10		
	03.33	FROM	14.00LGK	SILIOL FLAIL	0.30 1.00 10		
		7.44 TO	c - L&R				
:	63.33	-22.00	OUTBD	WEB		4.00 5	THE UDES ACCESS HOLES
	00.00		00100	7120		7.00 3	INCLUDES ACCESS HOLES
		LOWER	c - L&R				
	74.30	CONTOUR	OUTBD	LOWER CAP	0.40 0.80 10		
	, ,,,,,	33.113311	00.00		0.40 0.00 10		
		LOWER			i		
	74.30	CONTOUR	14.00L&R	SPLICE	2.45 4.90 10		
				-·	1 - 3 - 3 - 3 - 3 - 3 - 3 - 3 - 3 - 3 -	1	

Table 4-2. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition I (Cont)

				DAMAGE LIMITS					FIGURE 4-1	
COMPONENT/		LOCATION				P/FLANG		SKIN/		AND
MEMBER	FS	WL	BL	ELEMENT	CD'	CL'	N	WL'	N	NOTES
BULKHEAD	74.30	FROM 7.44 TO -22.00	c – L&R OUTBD	WEB	(D'=1	NXCL)		(D'=N 5.70	xWL) 5	INCLUDES ACCESS HOLES
	74.30	22.00	c – L&R OUTBD	UPPER CAP	0.50	1.00	10			
	23.00 37.00	BOTTOM CONTOUR & 22.00	c - L&R OUTBD	UPPER AND LOWER CAPS	* 2	2XCD	10			*25% OF CROSS- SECTIONAL AREA
	52.00 69.00									
	84.50 102.00	DOTTOM								
	23.00 37.00	BOTTOM CONTOUR -22.00	c – L&R OUTBD	WEBS				*	5	*50% OF ANY SECTION
	52.00 69.00					-				
	84.50 102.00									
SEAT RAILS	41.00 -51.00	22.00	14.00L&R 30.00L&R	SEAT TRACK (FWD)	0.75	1.50	10			
	55.70 -63.33	22.00	14.00L&R 30.00L&R	SEAT TRACK (AFT)	0.25	0.50	10			
SEAT SUPPORT BEAM	37.00 -63.33		30.00L&R	SEAT TRACK SUPPORT (CAP)	0.75	1.50	10			

	Table	4-2. Dam	age Limits	Fuselage, Forward	(FS 23 to 129) -	Condition	I (Cont)
			Ĭ		DAMAGE LI	MITS	FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
					(D'=NxCL)	(D'=NXWL)	
SEAT							
SUPPORT	37.00	LOWER					
BEAM	-63.00	CONTOUR	30.00L&R	LOWER CAP	0.65 1.30 10		
	37.00	LOWER		VERTICAL STIFFE-			
	63.33	CONTOUR	30.00L&R	NERS (CHANNELS)	1.10 2.20 10		
					DO NOT JACK IF		
1		LOWER		JACK FITTING &	DAMAGED AREA W		
SEAT RAILS	63.33	CONTOUR	30.00L&R	BACKUP STRUCTURE	NOT SUPPORT HE	LICOPTER	
PEDAL	23.00						
SUPPORT	-29.08	14.75	19.16L&R	STIFFENERS	0.06 0.12 10		
		10.00		DEDAL ADJUCTED			
	34.75	12.00	40 40 40	PEDAL ADJUSTER	0 45 0 00 10		
	-37.00	-22.00	19.16L&R	SUPPORT	0.45 0.90 10		
	22.00						
	23.00	22 00	10 161 90	CAP	0.45 0.90 10		
JACKING &	-37.00	22.00	19.16L&R	UAF	0.43 0.30 10	L	
MOORING		LOWER			DO NOT USE IF	FURTHER	
FITTINGS	62.78	CONTOUR	30.00L&R	FITTING	DAMAGE WILL OC		
LILITUGS	02.70	CONTOOR	JO. OULAN	1 4 1 1 4 1 1 4 1 4 1	DININGE MILE OF		
LANDING							
GEAR	71.60	9.90	14.00L&R	FITTING	0.00 0.00 10		
QE/II\	,		2.73024.1	<u> </u>			

					DAMAGE LI		FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	
					(D'=NxCL)	(D'=NxWL)	
MIDSECTION, BOTTOM	129.00 -155.00		34.7-OUTBD L&R	SKIN		2.50 5	WITH EXTERNAL STORES
	155.00 -178.0	LOWER CONTOUR	c-OUTBD L&R	SKIN		5.00 5	
	102.00	LOWER CONTOUR	14.00- 34.7L&R	HONEYCOMB PANEL		8.00 5	NO DAMAGE WITHIN
	129.00 -155.06		14.00L -14.00R	HONEYCOMB PANEL		8.00 5	1.5 INCH OF EDGE
HOIST MAINTENANCE SUPPORT		22.00	26.00L	UPPER SKIN	IF FLOOR SUPP		
	157.70	22.00	26.00L	DOUBLER	IS DAMAGED, U WHEN USING HO		
MIDSECTION FLOOR	166.00 -178.00	22.00 -25.58	14.00- OUTBD L&R	HONEYCOMB PANEL		6.50 5	
	155.00 -178.00		14.00L -14.00R	HONEYCOMB PANEL		3.90 5	NO DAMAGE WITHIN 1.5 INCH OF EDGE
	129.00 -166.00		14.00- OUTBD L&R	HONEYCOMB PANEL		8.00 5	
	129.00 -178.00			HONEYCOMB PANEL EDGES	1.00 5.00 10		
MIDSECTION	166.00	22 . 00 -54 . 89	14.00L&R	FRAME CHANNEL AND ANGLE	0.20 0.40 10		

	Table 4	-3. Damag	e Limits Fu	selage, Midsectio			
					DAMAGE LI	MITS	FIGURE 4-1
COMPONENT/	l	LOCATION	ľ		CAP/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
		FROM			(D'=NxCL)	(D'=NxWL)	
	155,160	22.00 TO	ł]	
MIDSECTION	166,178	-54.89	14.00L&R	VERTICAL ANGLES	0.50 1.00 10		EACH ANGLE
		FROM					
	152.75	54.68 TO		AFT, LOWER DOOR]	
BULKHEAD	-166.00	-68.64	14.00L&R	HONEYCOMB		8.50 5	
	}			LITTER	DO NOT USE I	F	
	158.00	61.00	14.00L&R	SUPPORT PLATE	DAMAGE IS EX	CESSIVE	
		FROM					
	129.00	39.60 TO					NO DAMAGE WITHIN
	-136.90	-54.90	14.00L&R	HONEYCOMB PANEL		1.00 5	1.0 INCH OF EDGE
		FROM					
		22.00 TO	14.00L				
	129.00	-39.60	-14.00R	DOOR SKIN		7.70 5	
		FROM					
		39.60 TO	14.00L	SKIN BEYOND			
	129.00	-54.00	-14.00R	DOOR DOUBLER	0.35 0.70 10		
		FROM					
		41.60 TO	c-10.00L	DOOR DOUBLER		ł	
	129.00	-50.60		AND SKIN	0.75 1.50 10		
		FROM					
		54.02 TO	14.00L				
	129.00	-65.86	-14.00R	WEB, CANTED		5.00 5	
		FROM				İ	
		22.00 TO	14.00L				
	155.00	-54.89	-14.00R	CENTER PANEL		12.00 5	
-							
	155.00		14.00L&R	TENSION FITTINGS	NO DAMAGE AL	LOWED	
		22.00-					
		LOWER	30.00-	l		1	DOES NOT INCLUDE
1	166.00	CONTOUR	OUTBD L&R	WEB, OUTER		0 5	LIGHTENING HOLES
•	i					}	

	14516 4			Hidsectio			GE LI			FIGURE 4-1
COMPONENT/		LOCATION				/FLANG	Ε	SKIN	WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD'		N	WL'	N	
				TENCION CIDAD	(D'=N	IxCL)		(D'=N	IXWL)	
BULKHEAD	166.00	22.00	14.00L&R	TENSION STRAP, VERTICAL	0.20	0.40	10			
DOCKITCAD	100.00		140000	TENSION STRAP	0.20	0.10		f		
				ACROSS BULKHEAD,						
	166.00	22.00	14.00L&R		0.02	0.04	10			
				COMPRESSION						* 4.
		LOWER		STRAP ACROSS				1		
	166.00		14.00L&R	BULKHEAD, LOWER	0.12	0.24	10			
		FROM								
		22.00 TO							_	
	-155.00	-39.60	14.00L&R	HONEYCOMB PANEL				7.50	5	
	155 00	FROM								
		22.00 TO	14 001 00	HONEVCOMP BANEI					_	NO DAMAGE WITHIN
	-1/8.00	-54.00 FROM	14.00L&R	HONEYCOMB PANEL				6.00	_5_	1.5 INCH OF EDGE
		22.00 TO	14.00-							
	166,00	-54.00	OUTBD L&R	HONEYCOMB PANEL				7.50	5	
	100.00	FROM	COTED EUR	HONETOOND TAILE				7.30		
	129.00	22.00 TO	c-OUTBD	EDGE,						
		-65.86	L&R	HONEYCOMB PANEL	1.00	5.00	10			
		FROM								
		39.60 TO								NO DAMAGE WITHIN
	-155.06	-54.00	14.00L&R	HONEYCOMB PANEL				2.50	5	1.5 INCH OF EDGE
DEAM 10:155	100.00	1.01/50	Ī							
BEAM, LOWER			14 001 00	LOWED DEAM CAD	0.05	0 50	10			
MIDSECTION	-136.00	CONTOUR	14.UUL&R	LOWER BEAM CAP	0.25	0.50	IU			
	136.00	LOWER			i					
	-172.30		14.00L&R	LOWER BEAM CAP	0.90	1.80	10			
	1, 2, 50	30171001	17.00Lan	LONEIL DEATH OAT	3.30					
	172.30	LOWER	ŀ							
	-178.00		14.00L&R	LOWER BEAM CAP	0.25	0.50	10			
					·	_				

	Table 4	-3. Dailiay	E LIMITES FU	Selage, Midsectio	11 (13 12	DAMACI		MITC	u i c i	FIGURE 4-1
			DAMAGE LIMITS CAP/FLANGE SKIN/WEB				AND			
COMPONENT/	= -	LOCATION		EL EMENT				Mr.		NOTES
MEMBER	FS	WL	BL	ELEMENT			<u> </u>		N	NUTES
					(D'=NxC	,L)		(D'=N	XWL)	
BEAM, LOWER		LOWER		CROSS TUBE STRAP		. =0		1		
MIDSECTION	166.00	CONTOUR	14.00L&R	LOWER CAP	0.25 0).50 :	10			
								ł		
	129.00							į		
	-178.00	22.00	14.00L&R	UPPER BEAM CAP	0.35 0).70 :	10			
		22.00-								
	102.00	LOWER			İ					NO DAMAGE WITHIN
	-155.00	CONTOUR	14.00L&R	HONEYCOMB PANEL				7.50	5	1.5 INCH OF EDGE
		22.00								
	102.00			EDGE						
	-155.00		14.00L&R		0.35 0	.70	10			
	20000	22.00	<u> </u>							
	155.00									DOES NOT
	-178.00		14.00L&R	WEB	1			3.00	5	INCLUDE HOLES
	-170.00	CONTOOK	27700Ean	1120		-				
	102.00	LOWER								
BEAM, LOWER			36.00L&R	INTERCOASTAL	0.25 0	.50	10	İ		
DEAM, LOWER	-133.00	22.00-	JO: OUL GR	INTERCONSTAL	0020					
	102.00			1						DOES NOT
			36.00L&R	HONEYCOMB PANEL	ļ			6.90	5	INCLUDE HOLES
	-155.06	CONTOUR	30.UULAK	HONETCOMD PANEL	 			0.30		THOUGHT HOLES
	100.00			ĺ	İ					
	102.00		36.00L&R	UPPER CAP	1.20 2	2 40	10	l		
	-155.00	22.00	30.UULAK	UPPER CAP	1.20 2	2.40	10	-		
İ	400 00		Ì		1					
	136.90		44 60: 45	DEAM CAR	0 60 1	20	1 0			
MIDSECTION	-178.00		14.00L&R	BEAM CAP	0.60 1	1.20	10	<u> </u>		
		22.00-								+25% OF CDOCC
	129.00		c-OUTBD	UPPER AND						*25% OF CROSS-
BULKHEADS	134.00	CONTOUR	L&R	LOWER CAPS	* 2XC	על	10	ļ		SECTIONAL AREA
	155.00							Ī		
	160.00		1		1			1		
								1		
	•	•	•	•	-					

					DAMAGE LIMITS			FIGURE 4-1	
COMPONENT/		LOCATION			CAP/FLANGE		SKIN		AND
MEMBER	FS	WL	BL	ELEMENT		N	WL'	N	NOTES
BULKHEADS	129.00 134.00	22.00- LOWER CONTOUR	c-OUTBD L&R	WEBS	(D'=NxCL)		(D'=1	5 5	*50% OT ANY SECTION
PYLON	160.00 129.00 -155.00	54.89	14.00L&R	ZEE	0.50 1.00	10			
SUPPORT		FROM 66.00 TO	10.25- 14.00L&R	ZEE		10			DOES NOT INCLUDE LIGHTENING HOLES
	127.47 -153.45	FROM 65.92 TO -68.14	14.44L&R	ANGLE	0.05 0.10	10			
	149.25		10.25 -14.44	TEE EXTRUSION	0.55 1.10	10_			
	153.45	FROM 68.19 TO -67.59 FROM	9.80 -14.00	WEB (THRU RIVETS)	2.30 4.60	10			
	153.45	68.19 TO -54.89	14.00R -14.00L	WEB			3.00	5	EACH SIDE
	153.45	FROM 68.19 TO -54.89	14.00L&R	STIFFENER	0.55 1.10	10			
PYLON MOUNT			12.37L&R	BOX FITTING	NO DAMA	GE AL	LOWED		
LIFT LINK BEAM		FROM 54.89 TO -40.41	3.78 -8.75	WEB			2.75	5	

					DAMAGE LIMITS			FIGURE 4-1	
COMPONENT/		LOCATION				FLANG		SKIN/WEB	
MEMBER	FS	WL	BL	ELEMENT		CL'	N	WL' N	
					(D'=N)	(CL)		(D'=NxWL	
LIFT	136.13		14.00L	CAPS, UPPER					
LINK BEAM	-138.73		-14.00R	WITH DOUBLER	0.55	1.10	10		
	-	FROM	_						
		54.89 TO	14.00L	CAPS, UPPER					
	&138.23		-14.00R	WITHOUT DOUBLER	0.55	1.10	10		
		FROM							
		54.89 TO							1
	&138.73		8.55L&R	STIFFENERS	0.0	0.0	10	<u> </u>	
		FROM	4						
		54.89 TO	14.00L						
	&138.73	-40.41	-14.00R	WEB AND DOUBLER				0.55 5	
	400 40		44 001	1 0450 040 117711					
	136.18		14.00L	LOWER CAP WITH	0.50	1 00	••		
	&138.73	40.41	-14.00R	CARGO SLING	0.50	1.00	10		_
	126 10		14 001		ŀ				
	136.18 -138.73		14.00L -14.00R	LOWER CAP COVER	1 25	2 70	10		
	-130./3	FROM	-14.00K	LOWER CAP COVER	1.33	2.70	10		
	126 19	54.89 TO		END SUPPORTS.	İ				
	-138.73		14.00L&R		0.25	0.50	10	•	
	-130./3	-40.41	14.00LGK	ZEE SECTION	0.23	0.30_	10	L	
!				LIFT LINK AND	l NC	DAMA C	GF AI	LOWED	
	137.56	55.30	0.00	ATTACHMENT	''`	<i>D/W/D/</i>	- /\L	LOWED	
	107.00				N(DAMA	GE AL	LOWED	
				CARGO		FITT			1
	137.56	39.00	0.00	SLING FITTING		SED FO			
		FROM			1				
		67.50 TO	14.00L						
5TH MOUNT	153.45	-63.87	-14.00R	FITTING	l no	DAMA	GE AL	LOWED	1 1
									1
CLIPS	178.00	22.00	14.00L&R	TENSION TIE	l NC	DAMA	GE TO	CLIPS	
					İ				

					DAMAGE L	IMITS	FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
		FROM			(D'=NxCL)	(D'=NxWL)	
		26.00 TO					
FITTING	129.00	-14.00	14.00L&R	SPLICE	0.40 0.80 10		
FITTING, EXTERNAL		44 00					
STORES	155.00	11.00	35.54L&R	LOWER FITTING			
	129.00	9.60	36.97L&R	LOWER FITTING	NO DAMAGE AL IF FITTING L FOR EXTERNAL		
	129.00 155.00		45.95L&R	UPPER FITTINGS			
LANDING GEAR	163.00	12.00	14.00L&R	AFT FITTING	NO DAMAGE AL	LOWED	

Table 4-4. Damage Limits Fuselage, Aft (FS 178 to 243) - Condition I

		WDIC T-TE	- Danage Ei	mics i usciage, Ai	c (10 2/0 co 270	, contact	OII I
					DAMAGE L		FIGURE 4-1
COMPONENT/		LOCATION		1	CAP/FLANGE	SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
					(D'=NxCL)	(D'=NxWL)	
AFT	178.00		c-OUTBD				
FUSELAGE	-211.06		L&R	SKIN		2.50 5	
	211.06		c-OUTBD				
	-243.89		L&R	SKIN		5.00 5	
	178.00 202.00		14.00L&R	ACCESS DOOR		5.00 5	NO DAMAGE WITHIN
DECKS	178.00 239.00	54.89	14.00L&R	HONEYCOMB PANEL		6.00 5	1.5 INCH OF EDGE

Table 4-4. Damage Limits Fuselage, Aft (FS 178 to 243) - Condition I (Cont)

	Table 4-4. Danage Elinite			, 400,430, 0	DAMAGE LIMITS			MITS	FIGURE 4-1
COMPONENT/		LOCATION			CAP	/FLANG		SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD'	CL'	N	WL' N	
MEMBER	-13	NL.	DL	CCENCITY	(D'=N			(D'=NxWL)	
DECKS	200.00	54.89	C SHIP	ENGINE MOUNT ATTACHMENT					
	214.00	54.89	9.70	ANTI-TORQUE SUPPORT	NO DAMAGE ALLOWED				
	178.00 239.00		14.00L&R	EDGE HONEYCOMB PANEL	1.00	5.00	10		
MAIN BEAMS	192.00	22.00	14.00L&R	BEAM CAP	.30	.60	10		
	178.00	22.00	14.00L&R	CONTOUR BEAM CAP	.14	.28	10		
	211.06	54.89	14.00L&R	BEAM CAP	.45	.90	10		
	211.06 243.89		14.00L&R	LOWER CAP	.10	.20	10		
	178.00 211.06	22.00	14.00L&R	LOWER CAP	.10	.20	10		
	178.00 211.06			WEB				1.75 5	
	211.06		14.00L&R	OUTBOARD ANGLE	.30	.60	10		
		FROM 54.89 TO 22.00		TENSION ROD	N	IO DAMA	GE AL	LOWED	

Table 4-4. Damage Limits Fuselage, Aft (FS 178 to 243) - Condition I (Cont) DAMAGE LIMITS FIGURE 4-1 COMPONENT/ CAP/FLANGE SKIN/WEB LOCATION AND NOTES CL' **MEMBER** BL **ELEMENT** WL N FS WL (D'=NxCL) (D'=NxWL) FROM 211.06 54.89 TO 243.89 22.00 WEB MAIN BEAMS NO DAMAGE ALLOWED FROM 211.06 54.89 TO 243.89 22.00 STIFFENER FROM DOES NOT 22.00 TO c - 14.00178.00 12.40 INCLUDE HOLES LOWER WEB **BULKHEADS** L&R .9 5 .3 .6 178.00 22.00 14.00L&R | HOR STIFFENER 10 FROM 54.89 TO 211.06 19.40 14.00L&R | STIFFENER FROM 9.70L OIL COVER 27.30 TO NO DAMAGE ALLOWED 211.06 19.40 4.80R **SUPPORT** FROM ANTI-TOROUE 6.30 **BOOST CYL** 36.72 TO 211.06 29.84 14.00 **SUPPORT** SKIN AND 211.06 36.72 EDGE DOUBLER **BOLT HOLE** 243.85 FITTINGS NO DAMAGE ALLOWED TAIL BOOM UPPER RIGHT-ATTACHMENT 243.85 59.78 11.31 HAND FITTING CAP SPLICE 211.06 54.89 14.00 **FITTINGS**

Table 4-4. Damage Limits Fuselage, Aft (FS 178 to 243) - Condition I (Cont)

COMPONENT/		LOCATION	J		DAMAGE LIMITS CAP/FLANGE SKIN/WEB	FIGURE 4-1 AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N WL' N	NOTES
JACKING FITTINGS	211.06		14.00L&R	FITTINGS	(D'=NxCL) (D'=NxWL) DO NOT JACK IF DAMAGED AREA WILL NOT SUPPORT HELICOPTER	
TIE DOWN	211.06		14.00L&R	FITTINGS	DO NOT USE IF DAMAGED	
AFT ENGINE MOUNT	200.00	54.89	14.00	FITTINGS	NO DAMAGE ALLOWED	
	178.00	54.89	14.00	SUPPORT		

					ı	Dama	GE L	[MITS	FIGURE 4-1	
COMPONENT/		LOCATION		}	CAP	/FLANG	Ε	SKIN/WEB	AND	
MEMBER	FS	WL	BL	ELEMENT	CD'	CL'	N	WL' N	NOTES	
	FROM				(D'=N	xCL)		(D'=NxWL)		
	17.37 TO			UPPER RIGHT					ITEM 1, FIG 4-1	
TAIL BOOM	-194.30			ANGLE	.50	1.00	5		SHEET 13 OF	
	FROM							1		
	17.37 TO			UPPER RIGHT			_			
	-194.30			LONGERON	1.75	3.50	<u>5</u>			
	FROM									
	17.37 TO			UPPER RIGHT		00	_	1		
	-194.30			STRINGER	.44	.88	5			
	FROM			LOUIS DIGUT	ļ			1		
	17.37 TO			LOWER RIGHT	ا م	F2	_			
	-194.30			STRINGER	.26	.52	<u> </u>			
1	FROM			LOUED DICUT						
	17.37 TO			LOWER RIGHT	1 27	2.54	E			
	-194.30			LONGERON	1.2/	2.54	IJ	1		
1			Į		1			I	1	

						AGE L		FIGURE 4-1
COMPONENT/		OCATION			CAP/FLAN		SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL'	N	WL' N	NOTES
	FROM				(D'=NxCL)		(D'=NXWL)	
	17.37 TO			BOTTOM MIDDLE		_		
TAIL BOOM	-194.30			STRINGER	.49 .98	5	l	
	FROM			1 00150 1 557				
	17.37 TO			LOWER LEFT	NO DAM	ACE A1	LOUED	
	-59.05			LONGERON	NO DAM	AGE AL	LUWED	
	FROM			LOUED LEET			ł	
	59.05 TO			LOWER LEFT LONGERON	2.90 5.80	10		
	-194.30			LUNGERUN	2.90 5.00	10		
	FROM 17.37 TO			LOWER LEFT				
	-194.30			STRINGER	.52 1.04	5		
	FROM			STRINGER	132 1104			
	17.37 TO			UPPER LEFT				
	-194.30			STRINGER	1.20 2.40	5		
	FROM							
	17.37 TO			UPPER LEFT				
	-194.30			LONGERON	2.77 5.54	10		
	FROM	******** i						
	17.37 TO			UPPER LEFT				
İ	-194.30			ANGLE	.58 1.16	5	l	
	FROM							
	17.37 TO			TOP RIGHT				
	-38.43			STRINGER	1.13 2.26	5		
	FROM		_					
	17.37 TO	1		MIDDLE UPPER		_		
	-38.43			RIGHT STRINGER	.86 1.72	5	ļ	
	FROM	İ		WTDD1 E 27217				
	17.37 TO			MIDDLE RIGHT	60 100	_		
	-38.43			STRINGER	.60 1.20	5	1	
	FROM			MIDDLE LOUED				
1	17.37 TO			MIDDLE LOWER	47 04	E		
1	-38.43	Ì		RIGHT STRINGER	.47 .94	5	1	

		Tabi	е 4-5. Дап	age Limits lail bu	00111	DAMA	GF I I	MITS	FIGURE 4-1	
COMPONENT /		LOCATION			CAP	/FLANG		SKIN/WEB		
COMPONENT/ MEMBER	FS	WL	BL	ELEMENT	CD'	CL'	<u> </u>	WL' N	NOTES	
MEMBER		πL	DL	CCCIACIAI	(D'=N:			(D'=NxWL)		
	FROM									
	17.37 TO			LOWER RIGHT				1		
TAIL BOOM	-38.43			ANGLE	.48	.96	5			
TAIL BOOM	FROM			7111022						
	17.37 TO			BOTTOM RIGHT						
	-38.43			STRINGER	.49	.98	5			
	FROM									
	80.44 TO			BOTTOM RIGHT						
	-101.38			ANGLE	.78	1.56	5			
· · · · · · · · · · · · · · · · · · ·	FROM	·								
	17.37 TO			BOTTOM LEFT				1		
	-38.43			INBOARD ANGLE	.50	1.00	5			
	FROM									
	80.44 TO			BOTTOM LEFT						
	-101.38			INBOARD ANGLE	.92	1.84	5	L		
	FROM									
	17.37 TO			BOTTOM LEFT	_		_			
	-38.43			INBOARD ANGLE	.50	1.00	5			
	FROM									
	80.44 TO			BOTTOM LEFT			_			
	-101.38			OUTBD STRINGER	.98	1.96	_5			
	FROM									
	38.43 TO	1		BOTTOM LEFT			_	1		
	-59.50			INBOARD STRINGER	•/1	1.42	_5			
	FROM]		DOTTON LEET	1					
	101.38T0	1		BOTTOM LEFT	00	1 00	E			
	-122.33			INBOARD STRINGER	•90	1.80	<u> </u>	 		
	FROM	j		DOTTON LECT						
	17.38 TC	1		BOTTOM LEFT	E0	1.00	Ę.			
	-59.50		ļ	OUTBD STRINGER	1 .50	1.00	<u>.</u>			
	FROM	J	1	DOTTON LEET						
	101.38TC	1		BOTTOM LEFT OUTBD STRINGER	00	1.96	5			
	-122.33			OUIDD SIKINGER	• 30	1.30	5	ſ		

COMPONENT/ MEMBER	LOCATION				CAP	DAMA FLANG	IGE L	/WEB	FIGURE 4-1 B AND	
	FS	WL	BL	ELEMENT	CD'	CL'	N	WL'	N	NOTES
					(D'=N	xCL)		(D'=	NxWL)	
BULKHEAD				INNER FLANGE	.42	.84	5			
				WEB				.23	10	
	80.44			OUTER FLANGE	.56	1.12	5			
				INNER FLANGE	.50	1.00	5			
				WEB		· • • • • • • • • • • • • • • • • • • •		.43	10	
	101.33			OUTER FLANGE	1.00	2.00	5			
	101.33			INNER FLANGE	.60	1.20	5			
				WEB				.63	10	
	122.33			OUTER FLANGE	1.00	2.00	5			· · · · · · · · · · · · · · · · · · ·
			282	INNER FLANGE	.63	1.26	5			
				WEB				.83	10	

		Tabl	<u>e 4-5. </u>	Damage Limits lail b	Boom - Condition I (Conc)	FIGURE 4-1
	-				DAMAGE LIMITS	AND
COMPONENT/		LOCATION			CAP/FLANGE SKIN/WEB	NOTES
MEMBER	FS	WL	BL	ELEMENT	00 02	
					(D'=NxCL) (D'=NxWL)	4
	FROM					
	17.37 TO			MIDDLE LOWER	50 104 5	
TAIL BOOM	-38.43			LEFT STRINGER	.52 1.04 5	
	FROM				Ì	
	17.37 TQ			MIDDLE LEFT	1 22 5	
	-38.43			STRINGER	.93 1.86 5	
	FROM	1				
	17.37 TO			MIDDLE UPPER	1 75 2 50 5	
	-38.43			LEFT STRINGER	1.75 3.50 5	
	FROM					
	17.37 TO		Ì	TOP LEFT	2.60 5.20 5	
	-38.43			STRINGER	2.60 5.20 5	
		! !	•			
				OUTED ELANCE	NO DAMAGE ALLOWED	
BULKHEAD	17.37			OUTER FLANGE	NO DAMAGE ACCORD	
	1		İ			
		İ		INNER FLANGE	.3 .6 5	
			<u> </u>	INNER FLANGE	1.5 .0 0	
	1			WEB		
	17.37	!	<u> </u>	WED	NO DAMAGE ALLOWED	İ
		1	1		140 Diange Victoria	
	20.42		1	OUTER FLANGE	1	
	38.43		 	OUTER PEARGE		
			1			
			1	INNER FLANGE	.35 .7 5	
	 	 	 	THIER I LINE		
1				WEB	NO DAMAGE ALLOWED	
		-	+	, neb		
	59.50	1		OUTER FLANGE	.33 .66 5	
	33.30	1	1	00,500		1

COMPONENT/		LOCATION			DAMAGE L CAP/FLANGE	IMITS SKIN/WEB	FIGURE 4-1 AND
MEMBER	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
					(D'=NxCL)	(D'=NxWL)	
BULKHEAD	143.28			OUTER FLANGE	1.25 2.50 5		
				INNER FLANGE	.70 1.40 5		
				WEB		1.00 10	
	164.23			OUTER FLANGE	1.50 3.00 5		
				INNER FLANGE	.92 1.84 5		
				WEB		1.00 10	
	185.18			OUTER FLANGE	1.75 3.50 5		
				INNER FLANGE	1.14 2.28 5		
				WEB		1.00 10	,
	194.30			OUTER FLANGE	2.00 4.00 5		
				INNER FLANGE	1.40 2.80 5		

		Tabl	<u>e 4-5. Dai</u>	nage Limits lail Bo	DAM	ACC II	WITC I	FIGURE 4-1
						AGE LI	SKIN/WEB	AND
COMPONENT/		LOCATION			CAP/FLAN		Mr. N	NOTES
MEMBER	BS	WL	BL	ELEMENT	CD' CL'	N	(D'=NxWL)	NOTES
					(D'=NxCL)		(D. = NXML)	
		Ì						
BULKHEAD		ļ		WEB			1.00 10	
	FS							
VERTICAL	5.08]			4.0		
FIN	-99.05			FORWARD SPAR	.44 .88	10		
	FS							
I	5.08		}			4.0		
	-59.05			AFT SPAR	4.05 8.10		<u> </u>	
					MAY BE SE			
					ONE LOCAT	ION, B	EIWEEN	
	FS		Ì		RIBS, & 5			
	10.03				CRACKED A			
	-59.05			STRINGER	LOCATIONS	ALONG	STRINGER	
	BE ⁻	TWEEN FORM	V ARD					
	ANI	AFT SPAF	RS	SKIN			3.1 1.5	
							1	
							10015	
	AFT SPAI	R TO TRAIL	_ING EDGE	SKIN			6.2 1.5	
	FS							
	5.08			TAIL ROTOR DRIVE			NOTE (2)	
	-59.05			SHAFT COVER			NOTE (2)	
	AFT OF			 	,		3.1 1.5	
	194.03		1	SKIN	DIDC MAY	HAVE		
							JP TO 50%	
		TWEEN FOR					CED, UP TO	1 .
	AND AFT SPARS			RIBS	TWO NON-A			
					MAY BE SE			
					TO 50% X-			
	AFT SPA	R TRAILIN	G EDGE	RIBS	CRACKED C			
	1							I

COMPONENT/		LOCATION			DAMAGE LI CAP/FLANGE	MITS SKIN/WEB	FIGURE 4-1 AND		
MEMBER	BS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES		
VEDITOAL					(D'=NxCL)	(D'=NxWL)			
VERTICAL FIN	227.00			BULKHEAD	.50 1.00 10				
1 2 11	227.00			DOLKIILAD	.30 1.00 10				
	194.30					İ			
	-227.00			ANGLE	.51 1.02 10				
	194.30			STRINCERS					
	-227.00			STRINGERS, CHANNELS	.25 .50 10				
	227.00			CHARACES	•23 •30 10				
				42° GEARBOX					
				MOUNT	_				
1		1		000 054000	NO DAMAGE AL	LOWED			
				90° GEARBOX MOUNT					
				MOUNT	-				
				TRAILING EDGE	NO LIMIT ON				
	101 00				DAMAGE TO EL	EMENT			
	194.30	İ		42° GEARBOX					
	-227.00 194.30		 	COVER					
1	-FWD			UPPER LEFT					
	SPAR			LONGERON	2.77 5.54 10				
	194.30								
	-FWD	l		LOWER LEFT					
	SPAR			LONGERON	3.74 7.48 10				
	194.30	1							
	-FWD			UPPER RIGHT	2 00 6 16 10				
	SPAR 194.30			LONGERON	3.08 6.16 10				
	-FWD	į		LOWER RIGHT		ļ			
	SPAR	ļ		LONGERON	2.63 5.26 10	į			

	Tat	ole 4-6. Da	<u>image Limits Cabi</u>	n Roof	- Con	11110	N II	FIGURE 4-1
							S ALLUWED	AND
	LOCATION							NOTES
FS	WL	BL	ELEMENT			N		NOTES
	FROM			(D'=N	XCL)		(D.=NXML)	
	22.00 TO					_		
74.25	78.00		POST R/H & L/H	•50	1.00	5		
	FROM							
	22.00 TO			_		_		
63.38			POST R/H & L/H	.83	1.66	5		
								A DEVICE DAMAGED
63,38			SPLICE R/H & L/H					1 RIVET DAMAGED
00.00								1
				}				1
63.38			POST R/H & L/H	.83	1.66	5		
03.30								
63 38		34.10-						
			WEB R/H & L/H					2 WEBS SEVERED
-/4.23								
63 38]
			SKIN		DAMAGE	TO E	LEMENT	
-/4.23	70.00							į.
				1				
112 80	80.00	15,251 &R	UPPER FLANGE	.40	.80	5		
112.00		10.2024.						
ļ		1						
112 00		15.251 &R	WFR	2.80	5.60	5		
112.00		10.20241						
01 00	1	30.00188						
			FRAME	2.22	4.44	5		
03.00		00100	, , , , , , ,					
				1				
62 20		31.251 AP	FRAME	.40	.80	5	Ì	
03.30	FROM	JIOLULAN	11/1/16	1				
	i rkum	1	1	1			1	
ŀ		1 21 251 RD	i .	1				
63.38	75.60 TO	31.25L&R OUTBD	FRAME	1.30	2.60	5		
	74.25 63.38 63.38 63.38 -74.25 63.38 -74.25 112.80 81.00 83.00	LOCATION FS WL FROM 22.00 TO 74.25 78.00 FROM 22.00 TO 63.38 -69.00 FROM 69.00 TO 63.38 -71.00 FROM 71.00 TO -78.00 FROM 22.00 TO 63.38 -78.00 FROM 71.00 TO -78.00 FROM 63.38 22.00 TO -74.25 78.00 FROM 63.38 22.00 TO -74.25 78.00 FROM 75.60 TO 83.00 FROM 75.60 TO 83.00 FROM 75.60 TO 83.00 FROM 75.60 TO 83.00 FROM 75.60 TO 83.00 FROM 75.60 TO 83.00 FROM	LOCATION BL BL FROM 22.00 TO 74.25 78.00 FROM 22.00 TO 63.38 -69.00 FROM 71.00 TO 63.38 -71.00 FROM 71.00 TO 63.38 -78.00 FROM 63.38 22.00 TO -74.25 -78.00 FROM 63.38 22.00 TO -74.25 -78.00 FROM 75.60 TO 112.80 80.00 15.25L&R FROM 75.00 TO 83.00 80.00 G3.38 80.00 31.25L&R FROM 75.60 TO 83.00 80.00 31.25L&R FROM 75.60 TO 83.00 80.00 31.25L&R ROM 75.60 TO 83.00 80.00 31.25L&R ROM 75.60 TO 83.38 83.00 31.25L&R ROM 75.60 TO 83.38 83.00 31.25L&R ROM 75.60 TO 83.38 83.00 83.25L&R ROM 75.60 TO 83.38 83.00 83.25L&R ROM 75.60 TO 83.38 83.00 83.25L&R ROM 75.60 TO 83.38 83.00 83.25L&R ROM 75.60 TO 83.38 83	LOCATION BL ELEMENT	NAX D. CAP CD' C	LOCATION BL ELEMENT CAP/FLANG CD' CL' (D'=NxCL)	NAX DAMAGE LIMIT	FS WL BL ELEMENT CD' CL' N WL' N (D'=NxWL) 74.25 78.00 FROM 22.00 TO 78.00 63.38 -69.00 63.38 -71.00 FROM 71.00 TO 63.38 -78.00 FROM 71.00 TO 63.38 22.00 TO 70.00 FROM 71.00 TO 63.38 22.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 71.00 TO 70.00 FROM 70.00 TO 70.00 FROM 70.00 TO 70.00

	Ţ		, oo bank	J Commercial Commercia	FIGURE 4-1			
COMPONENT/		LOCATION	I		CAP/F		S ALLOWED SKIN/WEB	AND
MEMBER	FS	WL	BL	ELEMENT		L' N	WL' N	NOTES
					(D'=NxC		(D'=NxWL)	7,0123
BULKHEAD	74.25		16.00L&R	UPPER FLANGE	.40	.80 5		
		FROM	1					
	74.25	75.60 TO -80.00	16 001 00	Luco				
	74.23	-00.00	16.00L&R	WEB	.90 1	.80 5		
	92.00	80.00	16.00L&R	UPPER FLANGE	.40	.80 5		
		FROM						
		75.60 TO		i				
	92.00	-80.00	16.00L&R	WEB	1.80 3	.60 5		
		FROM 75.60 TO	20 001 00					
	74.25		30.00L&R OUTBD	CAP	2.22 4.	44 E		
	74.23	FROM	00100	CAF	2.22 4.	.44 5		
		75.60 TO	30.00L&R					
	92.00		OUTBD	FRAME	2.22 4.	.44 5		
		FROM						
	74.05	75.60 TO	16.00					
	74.25	-80.00 FROM	-30.00L&R	FRAME	1.75 3.	50 5		
		75.60 TO	16.00					
	92.00		-30.00L&R	FRAME	1.95 3.	.90 5		
<u> </u>		FROM	COLOCLAR		1.55 5.	. JU J		
		75.00 TO	30.00L&R		ł			
	-159.50		OUTBD	FRAME	2.30 4.	60 5		
	120 01	FROM	20 001 25					
	-130.01 -132.01	75.00 TO	30.00L&R	FDAME				
	-125.01	FROM	OUTBD	FRAME	2.30 4.	60 5		
	104.00	75.00 TO	30.00L&R		1			
	-106.00		OUTBD	FRAME	2.25 4.	50 5		
					1			

		Table	4-6. Dania	ge Limits Cabin Ro	MAX D	AMAGE L	TMIT	S ALLOWED	FIGURE 4-1
ACUPOUENT (LOCATION		}		/FLANGE		SKIN/WEB	AND
COMPONENT/	FS	WL	BL	ELEMENT	CD'		N	WL' N	NOTES
MEMBER	- 13	FROM	- 00	<u> </u>	(D'=N:			(D'=NxWL)	
		75.00 TO	30.00L&R						
BULKHEAD	114.71		OUTBD	FRAME	2.00	4.00	5		
DULKIILAU	114.71	FROM	00.25						
		75.00 TO	30.00L&R						
	142.00	-80.00	OUTBD	FRAME	2.00	4.00	_5		
		FROM							
		75.00 TO	30.00L&R				_		
	148.00	-50.00	OUTBD	FRAME	2.00	4.00	5		
		FROM							
	63.38	75.60 TO				4 00	_		
LONGERON	-126.97		15.25L&R	FRAME	.90	1.80	_5_		
		FROM						ŀ	
		75.60 TO			1 00	3.80	5		
	-114.71		30.00L&R	FRAME	1.90	3.00	<u> </u>		
		FROM			٠.				
		75.60 TO	20 001 80	FDAME	1 15	2.30	5		
	-131.80		30.00L&R	FRAME	1.13	2.00			
	121 00	FROM							
		75.60 TO	30.00L&R	FRAME	1.92	3.84	5		
	-100.00	-80.00 FROM	JO. OULAN	TRANC					
	62 38	75.60 TO							
	-74.25	I.	30.00L&R	FRAME	1.15	2.30	5		
	-/4.23	FROM	301002411						
	126.97	75.60 TO		<u> </u>	1			Ì	
		-80.00	15.25L&R	FRAME	.94	1.88	5		
	100.00	FROM						1	
	157.50	75.00 TO	37.00L					1	ONE DAMACE
DOOR POST		-80.00	39.00R	SUPPORT BRACKET	.66	1.32			ONE DAMAGE
		FROM			ļ				
]	81.00	75.00 TO	34.10L		00	1 22		1	ONE DAMAGE
	-83.00	-80.00	36.10R	SUPPORT BRACKET	.66	1.32			UNE DAMAGE
	1	l			i			1	1

COMPONENT/	LOCATION			MAX DAMAGE LIMITS ALLOWED CAP/FLANGE SKIN/WEB					FIGURE 4-1 AND
MEMBER	FS	WL	l BL	ELEMENT	CD'	CL	N	WL' N	NOTES
DOOR POST		FROM 75.00 TO -80.00	38.50	SUPPORT BRACKET	(D'=N	•48		(D'=NxWL)	
	104.00 -106.00	FROM 75.00 TO -80.00	34.10 -36.10L&R	SUPPORT BRACKET	.24	.48			ONE DAMAGE
DOORS	63.38 -166.00			CARGO DOOR RAIL		NO 1 TM	TT (N		
	166.00	FROM		CARGO DOOR	NO LIMIT ON DAMAGE TO ELEMENT				
	74.25	22.00 TO -78.00		HINGED PANEL DOOR					
ROOF PANEL RIVETS	63.38 -126.97	80.00	12.25 -16.00L&R	PANEL EDGE	.94	1.88	5		
	80.00 -84.00	80.00	9.00 -13.L&R	STN RIVETS					5 RIVETS DAMAGED
	63.38	80.00	-16.00L&R	CP RIVETS					12 RIVETS DAMAGED
	63.38 -66.38	80.00	-12.25L&R	PANEL EDGE	.44	.88	5		
	80.00 -84.00	80.00	-12.25L&R	CENTER PANEL	4.00	8.00	5		
	98.00 -102.00	80.00	-12.25L&R	CENTER PANEL	4.60	9.20	5		

		Table	4-0. Dalla	ge Limits cabin	MAX DAMAGE LIMIT	SALLOWED	FIGURE 4-1
COMPONENT/		LOCATION		FI EMENT	CAP/FLANGE CD' CL' N	SKIN/WEB	AND NOTES
MEMBER	FS	WL	BL	ELEMENT	(D'=NxCL)	(D'=NXWL)	110120
ROOF PANEL/ RIVETS	66.38 -80.00	80.00	-12.25L&R	CENTER PANEL	(D'=NXCL)	15.2 5	
	84.00 -98.00	80.00	-12.25L&R	CENTER PANEL		15.2 5	
	102.00 -126.97		-12.25L&R	CENTER PANEL		15.2 5	
	63.38 -166.00		-30.00L&R	ROOF PANEL	NO LIMIT ON		
	63.38 -166.00		16.00 -30.00L&R	ROOF PANEL	DAMAGE TO E	LEMENI	

Table 4-7. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition II

	Tal	ole 4-7.	Damage Limi	ts ruselage, roin	alu (13 23 to 123	7 - Condition	
					MAX DAMAGE LIMIT	S ALLOWED	FIGURE 4-1
COURCUEUT /		LOCATION			CAP/FLANGE	SKIN/WEB	AND
COMPONENT/				ELEMENT	CD' CL' N	WL' N	NOTES
MEMBER	BS	WL	BL	ELEMENT	(D'=NxCL)	(D'=NxWL)	
FORWARD					(D'=NXCL)	(D -NVAC)	CRITICAL WITH
SECTION,	102.00	BOTTOM	34.70L&R		j.		
	-129.00		-OUTBD	SKIN	1	4.00 5	EXTERNAL STORES
BOTTOM	-129.00	-22.00	00.55				
			- OUTDD		ļ.		
		BOTTOM	c - OUTBD	l	İ		SKIN NOT
	-102.00	-22.00	L&R	SKIN			CRITICAL
							CRITICAL
Ì	102.00				1		
			34.70L&R	SKIN	İ		
	1 -129.00	BOTTOM	34./ULAK	JAIN	DO NOT USE FI	TTINGS	
ļ	63.33	;	c - OUTBD	CARGO TIEDOWN	WITH DAMAGE V		i
DECKS	-129.00		L&R	FITTINGS	INCHES OF FIT	TTINGS	}
DECKS	-129.00	1 22.00			1		
		ļ	1	1	I		•

Table 4-7. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition II (Cont)

	,	. ,	age Emiles	ascrage, forward	112 6	<u> </u>	. 	II (CONE)	
COMPONENT/		LOCATION	NI		MAX	DAMAGE	LIMI	TS ALLOWED	FIGURE 4-1
MEMBER	BS	WL	N BL	CI CMENT		P/FLANG		SKIN/WEB	AND
MLMDER	63	WL	DL.	ELEMENT	CD'	CL'	N	WL' N	NOTES
DECKS	74.25 -123.00	î .	14.00L&R	DOOR ASSEMBLY, HONEYCOMB	(D'=1	VXCL)		(D'=NxWL)	NO DAMAGE WITHIN 1.5 INCH OF EDGE
	74.25 -123.00		14.00L&R	EDGE, HONEYCOMB PANEL	1.00	5.00	5		
	23.00 -74.00	22.00	c - OUTBD L&R	HONEYCOMB PANEL				12.00 5	NO DAMAGE WITHIN 1.5 INCH OF EDGE
	23.00 -74.00	22.00	c – OUTBD L&R	EDGE, HONEYCOMB PANEL	1.00	5.00	5		
	74.22 -129.00	22.00	14.00L&R -OUTBDR	HONEYCOMB PANEL				12.00 5	NO DAMAGE WITHIN 1.5 INCH OF EDGE
	123.06 -128.75		14.00L&R	ENDS, HONEYCOMB PANEL	1.00	3.00	5		
	123.00 -128.75	22.00	14.00L&R	HONEYCOMB PANEL				3.00 5	NO DAMAGE WITHIN 1.5 INCH OF EDGE
MAIN BEAM	112.50	22.00	14.00L 14.00R	UPPER CAP SPLICE INSIDE & OUTSIDE		2.20	5		
	23.00 -41.70	22.00	14.00L 14.00R	UPPER CAP	1.40	2.80	_5		
	41.70 -69.00	22.00	14.00L 14.00R	UPPER CAP	1.50	3.00	5		
	69.00 -83.80	22.00	14.00L 14.00R	UPPER CAP	1.00	2.00	5		

	lable 4	4-/. Dama	ge Limits F	uselage, Forward	MAX DAMAGE LIMI	FIGURE 4-1		
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND	
MEMBER	BS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES	
***					(D'=NxCL)	(D'=NxWL)		
MAIN BEAM	83.80 -95.50	22.00	14.00L&R	UPPER CAP	1.80 3.60 5			
	95.50				,			
	-129.00	22.00	14.00L&R	UPPER CAP	1.10 2.20 5		w	
	23.00	воттом						
	-34.00	CONTOUR	14.00L&R	LOWER CAP	0.70 1.40 5			
	34.00	LOWER						
	-60.00	CONTOUR	14.00L&R	LOWER CAP	0.70 1.40 5			
	60.00	LOWER	i		_			
	-69.80	CONTOUR	14.00L&R	LOWER CAP	0.75 1.50 5			
	73.50	LOWER			0.75 4.50 5			
	-78.07	CONTOUR	14.00L&R	LOWER CAP	0.75 1.50 5			
		LOWER CONTOUR	14.00L&R	LOWER CAP	1.50 3.00 5			
	-117.00	CONTOOR	14.00Lan	LOWER OAI	1.50 5.00 5	1		
	117.00	LOWER CONTOUR	14.00L&R	LOWER CAP	1.55 3.10 5			
	69.00 -74.30	LOWER CONTOUR	14.00L&R	CROSS TUBE FITTING	NO DAMAGE	ALLOWED		
<u></u>		FROM						
	47.60	12.00 TO -22.00	14.00L&R	STIFFENER	0.85 1.70 5			
4		FROM 9.90 TO						
	63.33	-22.00	14.00L&R	STIFFENER	2.60 5.20 5			

	Table	4-7. Dama	ge Limits F	uselage, Forward					
004004547								S ALLOWED	FIGURE 4-1
COMPONENT/	<u> </u>	LOCATION				/FLANG		SKIN/WEB	AND
MEMBER	BS	WL	BL	ELEMENT	CD'	CL'	N	WL' N	NOTES
		FROM			(D'=N	XCL)		(D'=NxWL)	
LUATU DEAM	CO 00	9.90 TO	14 001 40	ATTEECUED		4 00	_		
MAIN BEAM	69.00		14.00L&R	STIFFENER	2.40	4.80	5		
		FROM							
	74 20	9.90 TO	14 001 40	CTIFFFNED	2 45	4 00	_		
	74.30	-22.00 FROM	14.UULAK	STIFFENER	2.45	4.90	5		
		9.90 TO							
	90.00		14.00R	STIFFENER	0.05	1.70	5		
	30.00	FROM	14.00K	SITFFENER	0.03	1.70	<u> </u>		
	102.00				1				
		-22.00	14.00L&R	HONEYCOMB PANEL				10.00 5	
	123.00	FROM	14.00LGK	HONE TOOPID TANKE				10.00 5	
	23.00	1							
	-37.00		14.00L&R	WEB	ŀ			11.00 5	
		FROM							
	37.00	10.00 TO							
	-47.60	-22.00	14.00L	WEB				7.75 5	
		FROM							
	37.00	10.00 TO			İ				
	-47.60		14.00R	WEB				3.70 5	
		FROM							
	47.00	9.00 TO							INCLUDES ACCESS HOLES
	-69.00		14.00L	WEB	<u> </u>			5.25 5	
		FROM							
	47.00	9.00 TO							
	-69.00		14.00R	WEB				3.80 5	
•		FROM							
	69.00	8.00 TO	44 001 00						
	-74.30	-22.00	14.00L&R	WEB				3.50 5	
	74.00	FROM						[
	74.30	7.44 TO	14 00: 95	LIED				0 55 5	
	-78.10	-22.00	14.00L&R	WEB				9.55 5	
I		i i			l			1	

Table 4-7. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition II (Cont)

	lable 4	4-/. Vama	ge Limits r	userage, rorward	MAX DAMAGE LIMITS ALLOWED		TI (COIIC)					
					MAX D	AMAGE I	LIMIT	S ALLO	WED	FIGU	JRE 4-1	
COMPONENT/		LOCATION				/FLANG		SKIN/			ND	
MEMBER	BS	WL	BL	ELEMENT	CD'		N	WL'	N		TES	
					(D'=N	xCL)		(D'=N	XWL)			
		FROM			ł							
	78.10				İ				_	THE UDEC	ACCECC	שחו בי
MAIN BEAM	-102.00	-22.00	14.00L&R	WEB				4.00	<u> </u>	INCLUDES	ACCESS	HULE.
		00.00	c - L&R	HDDED CAD	1 25	2.50	5					
BULKHEAD	63.33	22.00	OUTBD	UPPER CAP	1.23	2.50						
		LOUED	c - L&R		1			1				
	63.33	LOWER CONTOUR	OUTBD	LOWER CAP	0.75	1.50	5	•				
	63.33	CONTOUR	00100	LOWER CAL	0.75	1.00		L			-	
		LOWER			JACK	ONLY	IF CA	·P		1		
	63.33		30.00L&R	LOWER CAP		SUPPO!			ER			
	03.33	CONTOCK	000000									
		LOWER			1			İ				
	63.33	CONTOUR	14.00L&R	SPLICE PLATE	1.10	2.20	5					
		FROM										
İ		7.44 TO	c - L&R		1			- 25	_	THELLIPES	ACCECC	שחו ב
	63.33	-22.00	OUTBD	WEB				5.35	5	INCLUDES	ACCE33	HULE
										İ		
	74.00	LOWER	c - L&R	LOUED CAD	1 20	2.40	5					
	74.30	CONTOUR	OUTBD	LOWER CAP	1.20	2.40		}				
		LOWER	1					ļ		1		
	74.30		14.00L&R	SPLICE	2.65	5.30	5					
	/4.30	FROM	1-7-OOLGIN	0, 2102								
		7.44 TO	c - L&R					l				
	74.30		OUTBD	WEB				6.60	5	INCLUDES	ACCESS	HOLE
			c - L&R		1		_					
	74.30	22.00	OUTBD	UPPER CAP	1.00	2.00	5			ļ		
		BOTTOM								*50% O	F CROSS	_
	23.00		c - L&R	UPPER & LOWER	*	2700	5				NAL ARE	
BULKHEADS	37.00	22.00	OUTBD	CAPS	~	2XCD	5			350110	MAL AKE	^
	1			1				1		1		

Table 4-7. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition II (Cont)

MAX DAMAGE LIMITS ALLOWED FIGURE

					MAX DAMAGE LIMI		FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	BS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
					(D'=NxCL)	(D'=NxWL)	
DUL VUEADO	52.00		:				
BULKHEADS	69.00						
	84.50						
	102.00						
		BOTTOM					
	23.00	CONTOUR	c – L&R				*70% OF ANY
	37.00	-22.00	OUTBD	WEBS	* 5		SECTION
	E2 00						
	52.00 69.00						
	03.00					- 	
	84.50						
	102.00						
				CEAT TRACK			
CEAT DATIC	41.00	22.00	14.00L&R 30.00L&R	SEAT TRACK (FORWARD)	1.00 2.00 5		
SEAT RAILS	-51.00	22.00	30.00Lak	(FURWARD)	1.00 2.00 5		
	55.70		14.00L&R	SEAT TRACK			
	-63.33	22.00	30.00L&R	(AFT)	0.75 1.50 5		
SEAT				•			
SUPPORT	37.00		14.00L&R	SEAT TRACK			
BEAM	-63.33	22.00	30.00L&R	SUPPORT (CAP)	1.40 2.80 5		
	27.00	LOWER			٠,		
	37.00 -63.00	CONTOUR	30.00L&R	LOWER CAP	1.05 2.10 5		
	-03.00	CONTOOK	30.00Lak	LOWER OWN	2.00 2.10 0		
	37.00	LOWER		VERTICAL STIFF-		* *	
	-63.00	CONTOUR	30.00L&R	ENERS (CHANNELS)			
				1404 5755	DO NOT JACK I		
	62.22	LOWER	20 001 20	JACK FITTING &	DAMAGED AREA		
1	63.33	CONTOUR	30.00L&R	BACKUP STRUCTURE	SUPPORT HELIC	UPIEK	
		1	1		i		l

Table 4-7. Damage Limits Fuselage, Forward (FS 23 to 129) - Condition II (Cont)

					MAX DAMAGE LIMIT	S ALLOWED	FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	BS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
					(D'=NxCL)	(D'=NxWL)	
PEDAL SUPPORT	23.00 -29.08	14.75	19.16L&R	STIFFENERS	0.55 1.10 5		
	34.75 -37.00	FROM 12.00 TO -22.00	19.16L&R	PEDAL ADJUSTER SUPPORT	0.80 1.60 5		
	23.00 -37.00	22.00	19.16L&R	CAP	0.75 1.50 5		
JACKING & MOORING FITTINGS	62.78	LOWER CONTOUR	30.00L&R	FITTING	DO NOT USE IF FU		
LANDING GEAR	71.60	9.90	14.00L&R	FITTING	0.55 1.10 5		

Table 4-8. Damage Limits Fuselage, Midsection (FS 129 to 178) - Condition II

	Idbi	6 4-0. Du	mage Ellines	Tusciage, Miasee	•••••					
							E LIMIT	<u>S ALLO</u>	WED	FIGURE 4-1
COMPONENT/		LOCATION			CAP	7FLA	NGE	SKIN/	WEB	AND
MEMBER	BS	WL	BL	ELEMENT	CD'	CL'	N	WL'	N	NOTES
772772					(D'=N	IxCL)		(D'=N	xWL)	
MIDSECTION, BOTTOM		LOWER CONTOUR	34.70L&R -OUTBD	SKIN				4.00	5_	WITH EXTERNAL STORES
		LOWER CONTOUR	c - L&R -OUTBD	SKIN				7.00	5	
		LOWER CONTOUR	14.00L -34.70R	HONEYCOMB PANEL		-		12.00	5_	NO DAMAGE WITHIN
		LOWER CONTOUR	14.00L&R	HONEYCOMB PANEL				12.00	5	1.5 INCH OF EDGE

Table 4-8. Damage Limits Fuselage, Midsection (FS 129 to 178) - Condition II (Cont)

	Table 4-	D. Damage	Limites ras	Grage, massacram	MAX DAMAGE LIMIT	S ALLOWED	FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLANGE	SKIN/WEB	AND
MEMBER	BS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES
HOIST MAINTENANCE					(D'=NxCL)	(D'=NxWL)	
SUPPORT	157.70	22.00	26.00L	UPPER SKIN	IF FLOOR SUPP DAMAGED, USE		
					WHEN USING HO		
	157.70	22.00	26.00L	DOUBLER		_	
MIDSECTION FLOOR	166.00 -178.00	FROM 22.00 TO	14.00L&R -OUTBD	HONEYCOMB PANEL		9.00 5	
FLOOR	155.00 -178.00		14.00L&R			12.00 5	NO DAMAGE WITHIN 1.5 INCH OF EDGE
	129.00 -166.00		14.00L&R -OUTBD	HONEYCOMB PANEL		12.00 5	
	129.00 -166.00	22.00		HONEYCOMB PANEL EDGES	1.00 7.00 5		
MIDSECTION	166.00	FROM 22.00 TO -54.89	14.00L&R	FRAME CHANNEL AND ANGLE	2.00 4.00 5		
	155.00 160.00 166.00 178.00	FROM 22.00 TO -54.89	14.00L&R	VERTICAL ANGLES	0.75 1.50 5		EACH ANGLE
	152.75	FROM 54.68 TO -68.64	14.00L&R	AFT, LOWER DOOR		10.60 5	
	158.00		14.00L&R	LITTER SUPPORT PLATE	DO NOT USE IF		
		FROM 39.60 TO -54.90	14.00L&R	HONEYCOMB PANEL		3.70 5	

Table 4-8. Damage Limits Fuselage, Midsection (FS 129 to 178) - Condition II (Cont)

						4114		0 11 1 0		n II (cont)
						AMAGE				FIGURE 4-1
COMPONENT/		LOCATION		EL EMENT		/FLANG		SKIN/		AND NOTES
MEMBER	BS	WL	BL	ELEMENT	CD' (D'=N		N	(D'=N	N	NOTES
		22.00			(D = N	XCL)		(U = N	XWL)	
	100 00	22.00	14 001 80	DOOD CKIN				12.00	F	
MIDSECTION	129.00	-39.60	14.00L&R	DOOR SKIN				12.00		
		20.60		SKIN BEYOND						
	120 00	39.60	14.00L&R		0.85	1.70	5			
	129.00	-54.00	14.UULAK	DOOK DOODLEK	0.03	1./0				
		41.60		DOOR DOUBLER						
1	120 00		c -10.00L	& SKIN	1 10	2.20	5			
	129.00	-50.60	-10.00L	d 2kIN	1.10	2.20		1		
1		54.02						ł		
BULKHEAD	129.00		14.00L&R	WEB, CANTED				10.00	5	
BOLKHEAU	123.00	-03.00	14.00Lan	MLD, CANTED				10.00	<u> </u>	
i		22.00						ł		
1	155.00		14.00L&R	CENTER PANEL				15.00	5	
	100.00	01100	21000000							
			,							
	155.00	22.00	14.00L&R	TENSION FITTINGS		NO DAM	AGE A	LLOWED		
		22.00						1		
1		LOWER	30.00L&R					1		
	166.00	CONTOUR	-OUTBD	WEB, OUTER				1.5	5	DOES NOT INCLUDE
		22.00								LIGHTENING HOLES
		LOWER	С					ŀ		
1	166.00	CONTOUR	30.00L&R	WEB				3.50	5	
		······································								
				TENSION STRAP,						
	166.00	22.00	14.00L&R		0.40	0.80	5			
				TENSION STRAP,						
				ACROSS BULKHEAD,						
	166.00	22.00	14.00L&R		0.25	0.50	5			
				COMPRESSION						
		LOWER		STRAP, ACROSS						l
	166.00	CONTOUR	14.00L&R	BULKHEAD, LOWER	0.50	1.00	5	1		

Table 4-8. Damage Limits Fuselage. Midsection (FS 129 to 178) - Condition II (Cont) FIGURE 4-1 MAX DAMAGE LIMITS ALLOWED CAP/FLANGE AND SKIN/WEB COMPONENT/ LOCATION **NOTES** WL' **MEMBER** BL **ELEMENT** CL' N BS WL (D'=NxCL) (D'=NxWL) FROM 129.00 22.00 TO 10.00 5 -155.00 -39.60 14.00L&R | HONEYCOMB PANEL **BULKHEAD** FROM NO DAMAGE WITHIN 155.00 22.00 TO 9.00 5 1.5 INCH OF EDGE 14.00L&R | HONEYCOMB PANEL -178.00 -54.00 FROM 22.00 TO 14.00L&R 10.00 5 166.00 54.00 HONEYCOMB PANEL OUTBD FROM 129.00 22.00 TO c - L&R EDGE, HONEYCOMB 1.00 7.00 5 -178.00 -65.86 **PANELS** OUTBD FROM NO DAMAGE WITHIN 136.90 39.60 TO 5.00 5 1.5 INCH OF EDGE 14.00L&R | HONEYCOMB PANEL -155.06 -54.00 MIDSECTION 129.00 LOWER BEAM, 1.55 3.10 5 -136.00 CONTOUR 14.00L&R | LOWER BEAM CAP LOWER 136.00 LOWER -172.30 CONTOUR 14.00L&R LOWER BEAM CAP 0.95 1.90 5 172.30 LOWER 0.65 1.30 5 LOWER BEAM CAP -178.00 CONTOUR 14.00L&R LOWER CROSS TUBE STRAP 0.70 1.40 LOWER CAP 166.00 CONTOUR 14.00L&R 129.00 UPPER BEAM CAP 1.50 3.00 5 -178.00 22.00 14.00L&R 22.00 NO DAMAGE WITHIN 102.00 LOWER 10.00 5 1.5 INCH OF EDGE -155.00 CONTOUR 14.00L&R HONEYCOMB PANEL

•	Table 4-	B. Damage	Limits Fus	elage, Midsection	(FS 1	29 to 1	78)	- Cond	itio	n II (Cont)
					MAX D	AMAGE L	<u>IMIT</u>	S ALLO	WED	FIGURE 4-1
COMPONENT/		LOCATION				/FLANGE		SKIN/		AND
MEMBER	BS	WL	BL	ELEMENT	CD'		N	WL'	N	NOTES
		22.00			(D'=N	XCL)		(U = N	<u> </u>	
MIDSECTION	102.00			EDGE, HONEYCOMB				!		
BEAM, LOWER			14.00L&R	PANEL	0.40	0.80	5			
DEAM, LUNER	-133.00	22.00	14.00LGK	IANLL	0.40	0.00	_ <u>_</u>			
	155.00								1	DOES NOT
		CONTOUR	14.00L&R	WEB				6.00	5	INCLUDE HOLES
						· · · · · · · · · · · · · · · · · · ·				
	102.00									
BEAM, LOWER	-155.06	CONTOUR	36.00L&R	INTERCOASTAL	0.70	1.40	5_			
		22.00								DOES NOT
	102.00							0 00	_	DOES NOT
	-155.06	CONTOUR	36.00L&R	HONEYCOMB PANEL				8.90	<u> </u>	INCLUDE HOLE
	102.00									
	102.00 -155.00		36.00L&R	UPPER CAP	1.65	3 30	5	İ		
	-155.00	22.00	JO. OULAR	UFFER CAF	1.03	3.30		 		
	136.90							1		
MIDSECTION	-178.00		14.00L&R	BEAM CAP	1.60	3.20	5			
111100011011	2.000	22.00								
	129.00	LOWER	c - L&R	UPPER & LOWER						*50% OF CROSS-
BULKHEADS	-134.00	CONTOUR	OUTBD	CAPS	*	2XCD	5			SECTIONAL AREA
	155.00									
	-160.00				ļ			<u> </u>		
DVI 011	120 00							}		
PYLON	129.00 -155.00		14.00L&R	ZEE	1 75	3.50	5			
SUPPORT	-133.00	FROM	14.00Lak	LLL	1./3	3.30		1		
	131.82	66.00 TO	10.25							DOES NOT INCLUDE
		-67.57	-14.00L&R	ZEE	1.85	3.70	5			LIGHTENING HOLES
		FROM						1		
	127.47	65.92 TO								
		-68.14	14.00L&R	ANGLE	0.65	1.30	5			Į
					1					

Table 4-8. Damage Limits Fuselage, Midsection (FS 129 to 178) - Condition II (Cont) MAX DAMAGE LIMITS ALLOWED FIGURE 4-1 CAP/FLANGE SKIN/WEB AND LOCATION COMPONENT/ NOTES BL BS WL **ELEMENT** CD' CL' N WL' N **MEMBER** (D'=NxCL) (D'=NxWL) PYLON 10.25 1.10 2.20 5 149.25 54.89 -14.44TEE EXTRUTION SUPPORT FROM 68.19 TO 9.80 WEB 5 153.45 -67.59 -14.00(THRU RIVETS) 3.10 6.20 FROM 68.19 TO 153.45 -54.89 14.00L&R WEB 4.00 5 EACH SIDE FROM 68.19 TO 5 153.45 -54.89 14.00L&R STIFFENER 1.25 2.50 FROM 129.55 66.25 TO **PYLON** NO DAMAGE ALLOWED -151.32 -65.92 12.37L&R **BOX FITTING** MOUNT FROM 3.78 136.13 54.89 TO LIFT -8.75 WEB 3.70 5 -138.93 - 40.41LINK BEAM 136.13 CAPS, UPPER 14.00L&R WITH DOUBLER 0.75 1.50 5 -138.7354.89 FROM 136.13 54.89 TO CAPS, UPPER, 5 WITHOUT DOUBLER | 0.75 1.50 3.70 5 138.73 -40.41 14.00L&R FROM 136.18 54.89 TO 5 8.55L&R | STIFFENERS 0.70 1.40 138.74 -40.41 FROM 136.18 54.89 TO 1.75 5 14.00L&R WEB & DOUBLER 138.73 -40.41

LOWER CAP WITH

CARGO SLING

1.20 2.40

5

14.00L&R

136.18

138.73

40.41

Table 4-8. Damage Limits Fuselage, Midsection (FS 129 to 178) - Condition II (Cont)

	Table 4-	o. Dallage	Limitsius	elage, Midsection	MAX DAMAGE LIMIT	C ALLOWED	FIGURE 4-1
001100115117	ł	LOCATION			CAP/FLANGE	SKIN/WEB	AND
COMPONENT/		LOCATION		EI EMENT		Mr. N	NOTES
MEMBER	BS	WL	BL	ELEMENT		(D'=NxWL)	NOTES
					(D'=NxCL)	(D'=NXWL)	
LIFT	136.18		44 001 45	LOUED OAD COVED	0 00 4 00 F		
LINK BEAM	-138.73		14.00L&R	LOWER CAP COVER	2.00 4.00 5		
		FROM		F115 011550570			
		54.89 TO	4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4	END SUPPORTS	4 70 0 40 5		
	-138.73	-40.41	14.00L&R	ZEE SECTION	1.70 3.40 5		
				LIFT LINK &			
	137.56	55.30	0.00	ATTACHMENT	NO DAMAGE A	LLOWED	
1			_				
				CARGO SLING	NO DAMAGE ALLOWE		
	137.56		0.00	FITTING	FITTING IS USED	FOR CARGO	
		FROM					
		67.50 TO					
5TH MOUNT	153.45	-63.87	14.00L&R	FITTING	NO DAMAGE A	LLOWED	
CLIP	178.00		14.00L&R	TENSION TIE	NO DAMAGE T	O CLIPS	
		FROM					
		26.00 TO					
FITTING	129.00	-14.00	14.00L&R	SPLICE	0.90 1.80 5		
FITTING,							
EXTERNAL							
STORES	155.00	11.00	35.54L&R	LOWER FITTING]		
					NO DAMAGE ALLO		
	129.00	9.60	36.97L&R	LOWER FITTING	FITTING IS USE		
					EXTERNAL STORE	S	
	129.00						(
	155.00	20.24	45.95L&R	UPPER FITTINGS			
		I					
LANDING							ļ
GEAR	163.00	12.00	14.00L&R	AFT FITTING	NO DAMAGE A	LLOWED	<u> </u>

243.89

22.00

14.00L&R

LOWER CAP

.15

.3

5

Table 4-9. Damage Limits Fuselage, Aft (FS 178 to 243) - Condition II MAX DAMAGE LIMITS ALLOWED FIGURE 4-1 COMPONENT/ LOCATION CAP/FLANGE SKIN/WEB AND BS BL CD' CL' MEMBER WL **ELEMENT** WL' NOTES (D'=NxCL) (D'=NxWL) AFT 178,00 c - L&R -211.06 **FUSELAGE** SKIN OUTBD 3.25 5 211.06 c - L&R -243.89 **OUTBD** SKIN 7.00 5 178.00 202.00 **ACCESS DOOR** 14.00L&R 7.00 5 NO DAMAGE WITHIN 1.5 INCH OF EDGE 178.00 **DECKS** HONEYCOMB PANEL 239.00 54.89 14.00L&R 8.00 5 ENGINE MOUNT C 200.00 54.89 SHIP **ATTACHMENT** NO DAMAGE ALLOWED ANTI-TORQUE 214.00 54.89 9.70 **SUPPORT** EDGE, HONEYCOMB 178.00 239.00 54.89 6.00 14.00L&R PANEL 1.5 5 MAIN BEAMS 192.00 22.00 14.00L&R **BEAM CAP** 5 .45 .90 CONTOUR 178.00 22.00 14.00L&R **BEAM CAP** .20 .40 5 211.06 54.89 14.00L&R **BEAM CAP** 5 .7 1.4 211.06

Table 4-9. Damage Limits Fuselage, Aft (FS 178 to 243) - Condition II (Cont)

	<u>labi</u>	e 4-9. Dai	mage Limits	Fuselage, ATT (F	3 1/0	10 24	<u> </u>	Ollulu	1011 1	1 (COIIC)
								S ALLO		FIGURE 4-1
COMPONENT/		LOCATION				/FLAN		SKIN		AND
MEMBER	BS	WL.	BL	ELEMENT	CD'	CL'	N	WL'	N	NOTES
					(D'=N	xCL)		(D'=1	NXWL)	
	178.00									
MAIN BEAMS	211.06	22.00	14.00L&R	LOWER CAP	.15	.3	5			
		22.00								
	178.00	TO LOWER						l		
		CONTOUR		WEB				2.25	5	
								İ		
	211.06		14.00L&R	OUTBOARD ANGLE	.40	.80	5	1		
		FROM								
	214.23	54.89 TO								
		22.00		TENSION ROD						
		FROM			1					
	211.06	54.89 TO								
	243.89			WEB		NO DA	MAGE A	ALLOWE	D	
	243.03	FROM			1					
	211.06	54.89 TO			İ					
		22.00		STIFFENER						
	243.03	FROM			 			1		
	'	22.00 TO	l c		1					DOES NOT
BULKHEADS	178.00			LOWER WEB	1			1.3	5	INCLUDE HOLES
DOLKIILADO	170.00	12.40	2.100020		† — — — — — — — — — — — — — — — — — — —					
				HORIZONTAL	l			1		l
	178.00	22.00	14.00L&R	•	.4	.75	5			1
	1,0.00	FROM								
1		54.89 TO	1							
	211.06	19.40	14,001 &R	STIFFENER						
	211.00	FROM	2400cak	0.2	1					
]	27.30 TO	9.70L	OIL COOLER	1					1
	211 06	19.40	4.80R	SUPPORT		NO DA	MAGE A	ALLOWE	D	
	211.00	FROM	7.001	ANTI-TORQUE	1		•		-	
		36.72 TO	6.30	BOOST CYL						
	211 06		14.00	SUPPORT						
	211.06	29.04	14.00	3011 011						
1	1	1	1	1	1					1

Table 4-9. Damage Limits Fuselage, Aft (FS 178 to 243) - Condition II (Cont) MAX DAMAGE LIMITS ALLOWED FIGURE 4-1 COMPONENT/ CAP/FLANGE LOCATION SKIN/WEB AND MEMBER BS BL CD' CL' WL' NOTES WL **ELEMENT** N N (D'=NxCL) (D'=NxWL) SKIN & EDGE **BULKHEADS** 211.06 36.72 **DOUBLER BOLT HOLE** 243.85 **FITTINGS** NO DAMAGE ALLOWED TAIL BOOM UPPER R/H **ATTACHMENT** 243.85 59.78 11.39 FITTINGS CAP SPLICE 211.06 54.86 14.00 FITTINGS DO NOT JACK IF **JACKING** DAMAGED AREA WILL NOT FITTING 211.06 14.00L&R | FITTINGS SUPPORT HELICOPTER TIEDOWN 211.06 14.00L&R | FITTINGS DO NOT USE IF DAMAGED AFT ENGINE 200.00 54.89 FITTINGS 14.00 NO DAMAGE ALLOWED

SUPPORT

14.00

178.00

54.89

	-	· · · · · · · · · · · · · · · · · · ·	able 4-10.							
					MAX DAMAGE LIMIT		FIGURE 4-1			
COMPONENT/	<u> </u>	LOCATION			CAP/FLANGE	SKIN/WEB	AND			
MEMBER	BS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES			
					(D'=NxCL)	(D'=NxWL)				
	17.37			UPPER						
TAIL BOOM	-194.30			RIGHT ANGLE	.90 1.80 5		SEE FIGURE			
	17.37		:	UPPER RIGHT						
1	-194.30			LONGERON	3.34 6.68 10					
	17.37			UPPER RIGHT						
	-194.30			STRINGER	.95 1.9 5					
	17.37			LOWER RIGHT	ĺ					
	-194.30			STRINGER	.78 1.56 5					
	17.37			LOWER RIGHT						
	-194.30			LONGERON	3.50 7.00 10					
	17.37			BOTTOM MIDDLE						
	-194.30			STRINGER	1.15 2.30 5					
			·							
	17.37			LOWER LEFT						
	-59.05			LONGERON	NO DAMAGE A	LLOWED				
1	59.05			LOWER LEFT						
	-194.30			LONGERON	3.80 7.60 10	.				
			,							
	17.37			LOWER LEFT						
	-194.30			STRINGER	.95 1.90 5					
	17.37			UPPER LEFT						
	-194.30			STRINGER	1.35 2.70 5					
	17.37			UPPER LEFT						
	-194.30			LONGERON	3.5 7.0 10					
						}				

Table 4-10. Damage Limits Tail Boom - Condition II (Cont) MAX DAMAGE LIMITS ALLOWED FIGURE 4-1 COMPONENT/ LOCATION CAP/FLANGE SKIN/WEB AND **MEMBER** BS WL BL **ELEMENT** CD' CL' NOTES N WL' N (D'=NxCL) (D'=NxWL) 17.37 **UPPER** TAIL BOOM -194.30 LEFT ANGLE .72 1.44 5 17.37 TOP RIGHT -38.43 STRINGER 1.13 2.26 5 SEE FIGURE 17.37 MIDDLE UPPER -38.43 RIGHT STRINGER .90 1.80 5 17.37 MIDDLE RIGHT -38.43 STRINGER .96 1.92 5 17.37 MIDDLE LOWER -38.43 RIGHT STRINGER 1.00 2.00 5 17.37 LOWER -38.43 RIGHT ANGLE 1.10 2.20 5 17.37 **BOTTOM RIGHT** -38.43 **STRINGER** 1.12 2.24 5 80.44 **BOTTOM RIGHT** -101.38 ANGLE 1.20 2.40 5 17.37 **BOTTOM LEFT** -38.43 INBOARD ANGLE 1.20 2.20 5 80.44 **BOTTOM LEFT** -101.38 INBOARD ANGLE 1.30 2.60 5 17.37 **BOTTOM LEFT** -38.43 OUTBOARD ANGLE 1.20 2.40 5

		Table	4-10. D	amage Limits Tail B	MAY D	AMAGE	TMIT	S ALLOWED	FIGURE 4-1
COMPONENT /		LOCATION				/FLANG		SKIN/WEB	AND
COMPONENT/ MEMBER	B\$ I	WL	BL	ELEMENT	CD'	CL'	N	Mr. N	NOTES
ILI ID LIX					(D'=N	xCL)		(D'=NxWL)	
	80.44			BOTTOM LEFT	1.30	2 60	5		
TAIL BOOM	-101.38			OUTBOARD ANGLE	1.30	2.00	3		
:	38.43			BOTTOM LEFT IN-					
	-59.50			BOARD STRINGER	1.50	3.00	5		SEE FIGURE
				DOTTON LEFT IN	, ;				
	101.38			BOTTOM LEFT IN- BOARD STRINGER	1.20	2,40	5		
	-122.33			DOARD STRINGER	1020				
	17.38			BOTTOM LEFT OUT-			_		
	-59.50			BOARD STRINGER	1.30	2.60	5		
	101 20			BOTTOM LEFT OUT-	J				
	101.38			BOARD STRINGER	1.30	2.60	5		
	12200								
	17.37			MIDDLE LOWER	1 20	2.60	5		
	-38.43			LEFT STRINGER	1.30	2.00		 	
	17.37			MIDDLE LEFT	ļ				
	-38.43			STRINGER	1.20	2.40	5		
				MIDDLE UPPER	ł				
	17.37 -38.43			LEFT STRINGER	1.80	3.60	5		
	-30.43								
	17.37			TOP		- 00	_		
	-38.43			LEFT STRINGER	2.50	5.00	5		
BULKHEAD	17.37			OUTER FLANGE	.98	1.96	5_		
DOLINIE IS	1								
				INNER FLANGE	55	1.1	5		
	1			INNEK FLANGE	.33	1.1	•		

COMPONENT/ LOCATION					MAX DAMAGE	LIMIT		FIGURE 4-1	
MEMBER	BS T	WL	BL	ELEMENT	CAP/FLANG	N N	SKIN/WEB	AND Notes	
HEHDER				EEEIGII	(D'=NxCL)		(D'=NxWL)	110723	
BULKHEAD				WEB			.40 10		
	38.43			OUTER FLANGE	1.00 2.00	5			
				INNER FLANGE	.60 1.20	5			
				WEB			.50 10		
	59.50			OUTER FLANGE	1.10 2.20	5			
				INNER FLANGE	.60 1.20	5			
				WEB			.64 10	400	
	80.44			OUTER FLANGE	1.16 2.32	5		•	
				INNER FLANGE	.65 1.30	5_			
				WEB			.75 10		
	101.33			OUTER FLANGE	1.2 2.4	5			

	I	14510	1 200 00	aye Lillics lair i	MAX DAMAG	E LIMIT	S ALLO	WEDT	FIGURE 4-1
COMPONENT/		LOCATION			CAP/FLA		SKIN/		AND
MEMBER	BS T	WL	BL	ELEMENT	CD' CL'		WL'	N	NOTES
1.27.02.1					(D'=NxCL)		(D'=N:	xWL)	
j									
BULKHEAD	101.33			INNER FLANGE	.68 1.3	6 5	.40	10	
				LIED			.88	10	
				WEB			•00	10	
								1	
	122.33			OUTER FLANGE	1.30 2.6	50 5			
	122.55				1				
					ļ				
				INNER FLANGE	.70 1.4	10 5			
				WEB			1.00	10	
	-			WED			1.00		
							ļ		
	143.28			OUTER FLANGE	1.30 2.6	50 5	1		
	110020								
					1				
				INNER FLANGE	.75 1.5	50 5			
				WEB	1		1.12	10	
				MED	+		1		
					Ì				
1	164.23			OUTER FLANGE	1.50 3.0	00 5			
	1								
		<u> </u>		INNER FLANGE	1.00 2.0	00 5	ļ		
				WEB			1.2	10	
		1		MCD			1.2	10	
1	1		i	I	I		Ī	l l	I

004504545				MAX DAMAGE LIMIT	FIGURE 4-1		
COMPONENT/ MEMBER	BS WL)N BL	ELEMENT	CAP/FLANGE CD' CL' N	SKIN/WEB	AND	
MEMDER	D3 WL	DL	ELEMENT	(D'=NxCL)	(D'=NxWL)	NOTES	
				(D -INOL)	(B -NANE)		
BULKHEAD	185.18		OUTER FLANGE	1.75 3.50 5	.40 10		
		 	INNER FLANGE	1.20 2.60 5	.88 10		
			WEB		1.2 10		
	194.30		OUTER FLANGE	2.00 4.00 5			
			INNER FLANGE	1.40 2.80 5			
			WEB		1.20 10		
VERTICAL	5.08						
FIN	-99.05		FORWARD SPAR	1.10 2.20 5			
	5.08						
	-59.05		AFT SPAR	4.40 8.80 5	} !		
				UP TO TWO MAN-AD			
	10.03			RIBS MAY BE SEVE			
	-59.05	1	STRINGER	LOCATIONS ALONG			
	BETWEEN FORWARD						
	& AFT SPARS		SKIN		3.3 1.5		
	AFT SPAR TO TRAILING EDGE		SKIN		6.6 1.5		
	aband bydb						

		able 4-10. Dai	nage Limits lait b	MAX DAMAGE LIMI	TS ALLOWED T	FIGURE 4-1
				CAP/FLANGE	AND	
COMPONENT/		ATION	EL PAPAT	CD' CL' N	SKIN/WEB	NOTES
MEMBER	FS WI	. BL	ELEMENT		(D'=NxWL)	HOTES
				(D'=NxCL)	I (D =NXML)	į
Ì			TAIL ROTOR	NO 1 THE T		
VERTICAL	5.08		DRIVESHAFT	NO LIMIT O		
FIN	-59.05	İ	COVER	DAMAGE TO	ELEMENI	
	AFT					
ļ	OF BS					
	194.03		SKIN		3.3 1.5	
				ONE RIB MAY BE	SEVERED,	
				ADDITIONALLY AN	Y RIB MAY	
	BETWEEN FORW	ARD		HAVE UP TO 50%	X-SECTION	
	AND AFT SPAR		RIBS	CRACKED		
	MIND ALL STAR			UP TO TWO RIBS		
				SEVERED, ADDITI	ONALLY, UP	
	AFT SPAR TO			TO 50% X-SECTIO	N MAY BE I	
	TRAILING EDGE		RIBS	CRACKED ON ANY		
	IKAILING EDG	<u> </u>	KIDS	On the contract of the contrac		
į	BS				1 1	
ļ			BULKHEAD	1.00 2.00 5		
	227.00		DULKIILAU	1.00 2.00 0		
Ì	BS				1	
	194.30		ANGLE	.90 1.80 5		
	-227.00		ANGLE	.30 1.00 3	-	
	BS	İ	CTDINCEDC		1	
	194.30		STRINGERS,	.50 1.00 5	1	
	-227.00		CHANNELS	.50 1.00 5		
					·	
	i l	j	42° GEARBOX			
			MOUNT	- NO DAMAGE	AL L OUED	
-				NO DAMAGE	ALLUWED	
			90° GEARBOX			
ļ						
			TRAILING EDGE	NO LIMIT ON		
	+			DAMAGE TO E	LEMENT	
		1	42° GEARBOX			
			COVER			
			3012.11		:	
1	1 I	1	1	l		l e e e e e e e e e e e e e e e e e e e

COMPONENT/ MEMBER	LOCATION				MAX DAMAGE LIMI CAP/FLANGE		FIGURE 4-1 AND	
	FS	WL	BL	ELEMENT	CD' CL' N	WL' N	NOTES	
VERTICAL	194.30 -FWD			UPPER	(D'=NxCL)	(D'=NxWL)		
FIN	SPUR			LEFT LONGERON	3.50 7.00 10			
	194.30 -FWD SPUR			LOWER LEFT LONGERON	4.00 8.00 10			
	194.30 -FWD SPUR			UPPER RIGHT LONGERON	4.25 8.50 10			
	194.30 -FWD SPUR			LOWER RIGHT LONGERON	4.00 8.00 10			

Section III. NOSE SECTION

4-4. **GENERAL.**

- a. This section applies to the primary structure and external skin of the helicopter's nose section from fuselage station (FS) 7.50 to 23.00 inches. No part of the nose section is a critical load carrying primary structural, and therefore, most repairs to extensive battle damage will be deferred. The repair actions listed In this section are only intended for safety of the crew and to prevent further damage to helicopter.
- b. The nose section houses the cockpit instrument panel, battery compartment, radio receiver/transmitter, and other instruments. Any damage to this equipment will be covered in other chapters.
- c. The former bulkhead at FS 23.00 also serves as attachment area for the tail rotor control (foot pedals) support bracket.
- 4-5. **NOSE SECTION, DAMAGE TO EXTERNAL STRUCTURES OR SKIN.** External damage to skins and nose doors is all secondary structure and can be deferred and repaired later per TM 55-1500-204-25/1 or TM 55-1520-210-23. Loose skin or external structure which can cause serious problems in flight will be removed by the following procedures.

LIMITATIONS: Reduced flight velocity may be required.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •15 Minutes

MATERIALS/TOOLS REQUIRED:

•Cleaning Solvent (item 76, App C) ŽAdhesive Tape (items 153, 156, App C)

PROCEDURAL STEPS:

- 1. Inspect damage area and determine if it could cause such problems as the following:
- a. External skin blowing off and causing injury to the pilot, crew members, or being injested into engine air intake.
- b. Affecting the aerodynamics of flight.
- c. Reduce or restrict any of the pilots functions such as visibility.
- 2. Remove any loose skin, doors, window, or panels as is necessary to continue flight or mission.
- 3. If time permits, perform the following steps.
- a. Stop drill all cracks or trim out cracks when removing damaged skin.
- b. Clean area with naphtha and apply any aluminum backed pressure sensitive adhesive tape to bridge and cover the hole damage area.

NOTE

- •Some solvents will dissolve plexiglass. Use naphtha or clean with a detergent and water to remove grease and dirt.
- ŽNaphtha Is highly flammable. Use only in well-ventilated areas. Avoid Inhalation of vapor and skin contact. Do not use near open flame or in areas where very high temperatures prevail.
- 4. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

TM 55-1520-210-BD AI RFRAME

4-6. NOSE SECTION, BOTTOM WINDOW CRACKS AND HOLES. External damage to window plexiglass is secondary structure and can be deferred and repaired later per TM 55-1500-204-25/1 or TM 55-1520-210-23. Loose window plexiglass which can cause serious problems in flight will be removed and area repaired by the following procedures.

LIMITATIONS: Reduced flight velocity may be required.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- •1 Hour

MATERIALS/TOOLS REQUIRED:

- Cleaning Solvent (item 76, App C)
 ŽAdhesive Tape (items 153, 156, App C)
 Adhesive, 30 Minute Epoxy (item 3,
- App C)
 •Cloth, Fiberglass (item 63, App C)

PROCEDURAL STEPS:

- 1. If damage is in the form of cracks, repair as follows:
- a. Stop drill cracks and clean the area with naphtha (item 76, App C).

- b. Apply adhesive tape to both sides of the cracked window.
- 2. For hole damage, repair as follows:
- a. Cut out and trim to remove cracks. Clean the area with naphtha.
- b. Bridge the hole by overlapping with strips of 2 inch wide tape. Tape one side first and then the other.
- c. Cover the outside tape with a thin layer of 30 minute epoxy, brushing adhesive 2 inches onto the undamaged plexiglass window all the way around the patch.
- d. While epoxy is still uncured or wet, cover the area with fiberglass cloth patch. Brush the patch from center to edges to remove air and smoothen the patch.
- e. Wait 30 minutes for epoxy patch to dry. The size of hole to be repaired is only limited by the time and materials available.
- 3. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

CHAPTER 5

ALIGHTING GEAR

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

5-1. SCOPE.


- a. The alighting gear assembly consists of two skid tubes (1, Figure 5-1) attached to ends of two arched crosstubes (2 & 3). These in turn are attached to the fuselage. This gear supports the UH-1 helicopter's weight of approximately 9500 pounds upon landing.
- b. The alighting gear will normally sustain two types of battle damage. Impact damage by foreign objects, projectiles, or other pieces of aircraft debris, and the deforming of alighting gear by hard landings. Battle damage to the gear assembly could weaken or deform the structure. In turn, this weakened alighting gear assembly could result in collapsed gear and main rotor blade strike to the ground. Similarity, a deformed alighting gear could cause the helicopter to alight at an abnormal angle and cause a rotor blade ground strike.
- c. Battlefield damage to the alighting gear sustained in flight could result in an abnormal landing procedure.

Therefore, an in-flight or low hover assessment will be required to determine if a normal landing procedure will be necessary. Emergency landing procedures are covered in TM 55-1520-210-10.

- d. The purpose of this chapter is to provide BDAR temporary fixes which are not authorized or listed in other maintenance manuals. The BDAR fixes will allow a temporary fix which will return the aircraft to a flight status to complete the assigned mission and/or to self-recover.
- e. Fixes by this BDAR may require jacking up of helicopter per TM 55-1520-210-23, or any other equivalent means.
- **5-2. ASSESSMENT PROCEDURES.** Refer to Table 5-1.

5-3. REPAIR PROCEDURE INDEX.

							PARA	
Ski d	Tubes						5-4	




- Skid Tube Assy
 Aft Crosstube Assy

- 3. Forward Crosstube Assy
 4. Ski d Saddle Assy
 5. Structural Support (Cap)
 6. Structural Support (Cap)

- 7. Landing Gear Support 8. Landing Gear Support

Figure 5-1. Landing Gear and Support Installation

Table 5-1. Assessment Procedures



Section II. SKID TUBE

- 5-4. GENERAL. The skid tubes can suffer damage by either impact of projectiles, explosions, or by hard landings. Damage to the ends of the skid tubes is not critical and can be deferred. However, bent skid tubes which will interfere with normal landing procedures can be remedied by removing the ends that are bent. This fix only applies to the ends of the skid tubes past the crosstubes and not the center joining section.
- 5-5. SKID TUBES, DAMAGE TO AREA A AND E OF FIGURE 5-2.

LIMITATIONS: No run on landings permitted. All landings shall be from a low hover with no forward speed as specified in emergency landing procedures in TM 55-1520-210-10.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

• Hacksaw (item 94, Sec II, App B) with 18 to 24 Tooth High Speed Steel Blade

PROCEDURAL STEPS:

- 1. Deferrable damage to A and E of Figure 5-2 may include up to complete rupture and loss of section A and E in both skids.
- 2. Severely deformed (bent) skid tubes In area A and E, which will interfere with normal landing, will be fixed by removing the section with a hacksaw. Cut the skid tube right next to the skid saddle, but do not cut the saddle.
- 3. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

TM 55-1520-210-BD ALIGHTING GEAR

5-6. SKID TUBES, DAMAGE TO AREA C AND D OF FIGURE 5-2.

LIMITATIONS: No run on landings permitted. All landings shall be from a low hover with no forward speed as specified in emergency landing procedures in TM 55-1520-210-10. This repair is limited and will only be applied when one skid tube is still fully functional and has no major damage.

PERSONNEL/TIME REQUIRED:

- 2 Sol di ers
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

ŽAngle Extrusion (item 53, App C) •Cherrymax Rivets 3/16 inch

(CR 3213-6-7) (item 112, App C)

PROCEDURAL STEPS:

- 1. See Figure 5-3 for splint repair of skid tubes.
- 2. The following repair is to be used to repair one skid tube. The other skid tube must be functional. Any damage which affects 1/2 of the cross section of the skid tube and up to a complete separation of area C or D can be expediently repaired by applying a temporary splint.
- 3. Cut an aluminum or steel angle extrusion to bridge the damaged area of the skid tube. The splint piece length should extend onto 14 inches of undamaged skid tube on both sides of damage. Remove any damaged part of skid tube. Trim rough edges which will interfere with the fitting of splint.
- 4. With splint clamped in place, drill holes for 3/16 diameter blind rivets. See Figure 5-3. Rivet hole pattern will be a straight line of rivets on the side and on the bottom of angle extrusion with rivet spacing at 9/16 inch (3 rivet)

- diameters). Install a minimum of 88 blind rivets per splint. A second splint may be installed on top, opposite first splint, if needed.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 5-7. SKID TUBES, DAMAGE TO AREA B OF FIGURE 5-2.

LIMITATIONS: No run on landings permitted. All landings shall be from a slow hover with no forward speed as specified in emergency landing procedures in TM 55-1520-210-10. This repair is limited to skid tube damage. It is not to be used for repairs of the skid tube saddle (4, Figure 5-1).

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

- •Hose Clamps (4 or more) (item 37, App C)
- •Skid Tube Shoes or Steel Sheet 1025 (0.062 in thick) formed to fit

PROCEDURAL STEPS:

- 1. Deferrable damage in area B, Figure 5-2, may include up to 2.00 diameter (3.14 sq. in.) holes.
- 2. Damage between 2.0 diameter and 3.1 diameter holes may be repaired by this BDAR fix (see Fig 5-4 for this repair). Damage exceeding 3.1 diameter holes will require replacement of skid tube.
- 3. Use a piece of skid shoe approximately 24 inches long, or a piece of steel sheet metal to bridge the damage. cut the repair piece from a new or used skid shoe. The skid shoe off the damaged skid tube itself can be used for repair if time is available to remove it.




Figure 5-2. Skid Tube Damage Inspection





Figure 5-3. Skid Tube Splint Repair

- 4. Remove existing skid shoe from the damaged area only if it interferes with the splint repair piece. Remove burrs and sharp metal edges by cutting, filing, and hammering down edges.
- 5. Place a repair piece of skid shoe over the damage area. If available, place another piece of skid shoe on top of the skid tube right over the damage. Clamp the repair splint skid shoes in
- place with a minimum of four hose clamps. If hose clamps are not available, manufacture some clamps as shown in Figure 5-4. Use sheet metal (item 133, App C).
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.






Figure 5-4. Skid Tube - Splint and Clamp Repair

CHAPTER 6

POWER PLANT INSTALLATION

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

6-1. SCOPE. This chapter will provide BDAR actions to the power plant and related systems such as fuel, oil, electrical, instruments, and engine control. Normally, any serious problem with these systems will first be indicated by the caution lights in the caution panel. This panel is located on the pedestal mount instrument panel In the helicopter's cockpit. Refer to TM 55-1520-210-10. These BDAR actions are provided for quick non-standard repair to the power plant system.

6-2. ASSESSMENT PROCEDURES. Refer to Table 6-1.

6-3 REPAIR PROCEDURE INDEX.

	PARA.
Oil Tank, Leaking	6-5
Accessory Gearbox and Fuel Control Assy, Minor Leaks.	6-7

Section II. OIL TANK

6-4. **GENERAL**. The engine oil tank is located in the upper pylon fairing, Figure 6-1. The engine oil pressure gage in cockpit will indicate engine oil pressure, and the caution light in warning panel will light up when oil pressure drops below 25 psi. The oil sight glass next to the filler cap will indicate the oil level in the tank and indicate any oil lost or consumed by system. This section lists repair method to stop oil leaks through holes or cracks in the oil tank caused by battle damage. After a BDAR action, inspect the repaired area periodically, and closely monitor engine oil temperature, engine oil pressure and engine low pressure warning light.

6-5. OIL TANK, LEAKING.

GENERAL INFORMATION: Oil leaks may first be detected by pilot's observation of instrument in cockpit. Generally speaking, if the engine oil warning light comes on, an immediate landing will be required. After landing, visually inspect oil tank for leaks. From the oil tank's top sight glass marked "oil ferry level" down to "minimum oil level" mark in the bottom The oil capacity between sight glass. the two levels is approximately one This capacity is a safety gal I on. reserve in case of emergency flight If the oil leaks are very requirements. minor, consideration should be given to deferring this BDAR until later.

Table 6-1. Assessment Procedures

I TEM/ACTI ON FAULT ISOLATION BDAR REF. VI SUALLY INSPECT Major damage found a. Engine Minor damage Determine if damage is.... Continue visual inspection not repairable repairable recover Damage found to Fuel System b. -fuel filter ... Chpt 12 Determine if damage is... Continue visual inspection repa'i rable not repairable recover System_Damage found to CODetermine if damage is Continue visual inspection repairable not reparable recover conti nue next page

Table 6-1. Assessment Procedures (Cont)




Figure 6-1. Oil Tank

TM 55-1520-210-BD POWER PLANT

OPTION 1: Screw, Washer, and Gasket for Small Holes, Figure 6-2

LIMITATIONS: Constant monitoring of engine oil pressure, oil temperature, and warning lights during the next flight.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 20 Minutes

MATERIALS/TOOLS REQUIRED:

- Metal Washer to Fit Screw (item 175, App C)
- Rubber or Gasket (items 115-117, App C)
- Sheet Metal Screws
 (size to fit hole)
 (item 142 or 143, App C)

- 1. Cut a piece of gasket material that will overlap the hole by about 1 Inch from the center of the hole.
- 2* Select a sheet metal screw that will screw in hole, and a washer to fit screw. Screw through the gasket material through the pierced hole and through the small hole in the oil tank to stop the oil leak.

- 3. Replenish oil supply.
- 4. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 6-2. Screw, Washer and Gasket

OPTION 2: Riveted Sheet Metal Patch for Large Damage Holes, Figure 6-3.

LIMITATIONS: Constant monitoring of engine oil pressure, oil temperature, and warning lights during the next flight.

PERSONNEL/TIME REQUIRED:

- •2 Soldier
- •2 Hours

MATERIALS/TOOLS REQUIRED:


- . Blind Rivets or Sheet Metal (items 142, 143, App C)
- Gasket Rubber (items 115-117, App C)
- Sheet Metal (items 129-141, App C)
- Solvent Cleaner (items 1, 76, 150, App C)
- •5-Minute Epoxy Sealant or Equiv (item 4 or 5, App C)

PROCEDURAL STEPS:


1. Cut a piece of sheet metal that will overlap the hole by 1-1/2 inches all the

way around. Drill holes for the rivets or screws approximately 1 inch apart around the patch perimeter as shown in Figure 6-6. Use caution when drilling to keep metal shavings out of the oil tank.

- 20 **If** sealant is to be used, clean area around hole with solvent so sealant will adhere.
- 3. Put sealant or gasket material over hole. Put sheet metal plate over hole and secure with pop rivets or with self-tapping sheet metal screws.
- 4. If 5-minute epoxy sealant was used, let assembly cure for five minutes.
- 5. Replenish the oil supply.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.



SHEET METAL PLATE WITH EPOXY



SHEET METAL PLATE WITH BLIND RIVETS

Figure 6-3. Sheet Metal with Sealant or Blind Rivets

Section III. ACCESSORY GEARBOX AND FUEL CONTROL ASSEMBLY

6-6. GENERAL.

- **a.** The engine accessory gearbox and the fuel control assemblies are attached to the engine as shown in Figure 6-4.
- b. Accessory gearbox with battlefield damage can result in oil leaking which will eventually result in sufficient 011 loss to cause an engine failure. Small oil leaks through small holes, cracks, and through loose jointed surfaces may be temporarily repaired by use of adhesive or sealant.
- c. Similarly, the fuel control assembly which has sustained battle damage and has small fuel leaks must be repaired by adhesive or sealant. Fuel leaks must be stopped, otherwise they will cause engine failure and fires.
- do The following procedure gives an expedient repair to seal small holes, cracks, and loose joints which have not caused internal or major damage to gear-box or housings.

6-7. ACCESSORY GEARBOX AND FUEL CONTROL ASSEMBLY, MINOR LEAKS.

LIMITATIONS: These repairs are limited to expedient field repairs of battle-field damage. Once helicopter is flown back to home base and if time allows, the damaged gearbox or housing will be repaired/replaced by TM 55-1520-210-23.

PERSONNEL/TIME REQUIRED:

- 2 Sol di ers
- 2 Hours

MATERIALS/TOOLS REQUIRED:

- Silicone Sealant (item 10, App C)
- Solvent (items 1, 76, 150, App C)
- 5-Minute Adhesive & Fiber Glass Patch or Zip-Patch Repair Kit (items 4, 5, & 63, App C)

- 1. Visually locate cracks wherever there is an oil leak on the fuel control housing or the accessory gearbox housing, Figure 6-4. If cracks are minor and no loose metal particles are suspected internally, then continue repair.
- 2. Check for internal damage or internal obstruction by manually turning the entire engine assembly which includes the turbines, compressor, the accessory gearbox, and the fuel control assembly. To do this, follow these steps:
- a. Remove the tachometer generator, Figure 6-5.
- b. Insert a 1/4 inch ratchet into the square slot which engaged with the tachometer shaft.
- c. Turn the ratchet which in turn will rotate the entire engine assembly including the accessory gearbox and fuel control.
- d. Listen and feel for any rubbing or scrapping noises in the accessory gearbox or fuel control assemblies. **If** no interference is suspected, then continue with fix. Reinstall the tachometer generator.
- e. If Interference, rubbing, and scrapping are felt, consider replacement of the component.
- 3. Clean area of crack thoroughly with solvent.
- 4. Apply sealant material or apply a fiberglass/epoxy patch over the crack.
- 5. Allow sealant or adhesive five minutes to cure.
- 6. Replenish any oil lost in system.
- 7 Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 6-4. Fuel Control and Accessory Gearbox Assemblies




Figure 6-5. Tach Generator Removal

CHAPTER 7

ROTORS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

7-1. SCOPE. This chapter contains BDAR fixes pertaining to the main rotor and tail rotor systems. Both main and tail rotor systems consist of two blades attached to the hub through grips. The rotating controls actuate the pitch (lift) of the blades. Because of the dynamic loads imposed on the rotor heads system, the only BDAR fixes authorized are on the blades of the main rotor and tail rotor. Any other damage to critical parts will require replacement per TM 55-1520-210-23.

7-2. ASSESSMENT PROCEDURES. Refer to Table 7-1.

7-30 REPAIR PROCEDURE INDEX.

PARA.

Main Rotor Blades. 7-5

Section II. MAIN ROTOR BLADES

7-40 GENERAL. Each main rotor blade is a semi-rigid all metal bonded assembly. Battle damage in noncritical areas of the blades may be repaired by the BDAR fixes in this section. The only areas authorized for repairs is the honeycomb area, one inch away from solid aluminum extruded pieces such as the doublers, spar, trailing edge, and the blade tip. Dents and bends in the skin of blade where there are no cracks or breaks are deferrable damage. Refer to TM 55-1520-210-23.

7-5. MAIN ROTOR BLADE, DAMAGE HOLES OF 1 INCH DIAMETER OF LESS. See Figure 7-1.

LIMITATIONS: Repairs to one or both of the damaged blades may cause an unbalanced rotor system. A very badly unbalanced rotor head could cause undue stress on the helicopter's structure by excessive vibrations. Limits of flight duration should be considered in such cases. Limit repair to one time flight.

PERSONNEL/TIME REQUIRED:

- •2 Sol di ers
- 15 Minutes


MATERIALS/TOOLS REQUIRED:

• Tape (items 153, 156, App C)

Table 7-1. Assessment Procedures


<u>ITEM/ACTION</u> <u>FAULT ISOLATION</u> <u>BDAR REF.</u>

VISUALLY INSPECT



- Position blades for access to damaged area. Support blades to prevent movement and drooping.
- 2. Smooth the damaged area, removing all rough edges with an abrasive grit cloth.
- 3. Clean area around damage and completely around blade where tape is to be applied with cleaning solvent.
- 4. Cover the damaged area (hole) with a 7. Record BDAR action taken. When chord wise layer of green cloth or aluminum duct tape. Cover top and bottom of blade If damage Is through both skins. Extend ends of tape 2 Inches beyond area of damage.

- Wrap a second layer of tape chord wise over the first layer and around the entire blade, Figure 7-1. Overlap ends by 3 Inches with outside edge of top toward trailing edge.
- 6. Adjust blade balance by adding approximately the same amount of tape wraps to the opposite blade at approximately the same distance away from the hub. Balance procedures for rotor head are specified In TM 55-1520-210-23.
- mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.






Figure 7-1. Blade Repair by Application of Tape

CHAPTER 8

DRIVE TRAIN SYSTEMS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

8-1. SCOPE.

- a. The purpose of this chapter is to provide BDAR Instructions for the drive train system.
- b. The drive train system does not lend itself well to BDAR type repairs. This is due to its designed function and its importance to the basic airworthiness of the helicopter.
- c. In most instances, the only recommended repair option is to replace or repair the damage by standard maintenance listed in TM 55-1520-210-23 or TM 55-1500-204-25/1.
- d. There are several limited repairs that have been approved for evacuation purposes only and are listed in this chapter.

8-2. ASSESSMENT PROCEDURES. Refer to Table 8-1.

8-3. REPAIR PROCEDURE INDEX.

PARA . Main Transmission Cases, Leak Through Small Holes and Cracks in Case Walls . 8-5 Transmission Oil Pressure Switch Leak. 8-6 Transmission Oil Pressure Transmitter Leak 8-7 **Ext**ernal Oil Filter Leak Tail Rotor Driveshaft Sections, Minor Damage . . . 8-10 Tail Rotor Driveshaft Sections, Moderate Damage. . Gearboxes, Small Leaks Through Case Holes and Cracks. . . 8-13

Section II. MAIN TRANSMISSION ASSEMBLY

8-4. GENERAL. Battlefield damage to the transmission can cause external damage (e.g., to the case, oil lines, filter assy and oil cooler). Severe external case damage will probably be accompanied by internal damage to the transmission. Internal damage to the transmission is normally too severe to fix with BDAR actions. This section will only deal with minor damage to the external case walls and to small components externally mounted on or about the main transmission.

8-5. MAIN TRANSMISSION CASES, LEAK THROUGH SMALL HOLES AND CRACKS IN CASE WALLS. Mi nor external damage to case walls in items 1, 2, 3, 4, 5, and 7 of Figure 8-1 can be repaired by the following procedure. These repairs are designed to eliminate oil loss to the transmission system and not to repair or replace any lost function or structural strength of the castings. Any major damage to case will reduce the structural strength of the case and will affect safety of flight. In this case, component must be replaced.


Table 8-1. Assessment Procedures

BDAR REF. FAULT ISOLATION ITEM/ACTION VI SUALLY INSPECT Determine if damage is Continue visual inspection not repairable recover Mast Assembly____ No BDAR Fix c. Main Driveshaft_____ No BDAR Fix Continue visual

inspection

continue next page

Table 8-1. Assessment Procedures (Cork)







Figure 8-1. Drive Train System, Major Components (Sheet 1 of 2)



- 1. Mast Assy
- 2. Transmission Assy
- 3. Input Drive Quill
- 4. Clamp Set
- 5. Main Driveshaft Assy
- 6. Retaining Bolt
- 7. Engine Driveshaft Adapter
- 8. Tail Rotor Driveshaft Section
- 9. Tail Rotor Drive Quill (mates to sump case)
- 10. Support Case
- 11. Sump Case
- 12. Hyd Pump & Tachometer Drive Quill
- 13. Generator Drive Quill
- 14. SI eeve
- 15. Hanger Assy
- 16. Support
- 17. Intermediate (45°) Gearbox Assy
- 18. Tail Rotor (90°) Gearbox Assy

Figure 8-1. Drive Train System, Major Components (Sheet 2 of 2)

LIMITATIONS:

- •Major damage to transmission which indicates complete loss or failure of lubrication system will require application of emergency flight procedures in TM 55-1520-210-10. Aircraft usage should be limited to one time flight for self-recovery. Damaged component should be replaced per TM 55-1520-210-23 as soon as practical.
- •Minor case damage with evidence of no internal damage can be repaired without any aircraft restrictions. On such minor damage in which oil leak is very minor, consideration of deferring repairs should be given. Small oil leaks can be tolerated. Leakage rate should be inspected after each flight.

MATERIALS/TOOLS REQUIRED:

- •Abrasive Cloth (item 121, App C)
- •Adhesive Repair Kit, Zip-Patch (item 5, App C)
- Solvent Cleaner (items 1, 76, App C)
- •Zinc Chromate Putty (item 90, App C)


PROCEDURAL STEPS:

- 1. Inspect the damaged area for internal damage to gears, shafts, etc. Remove any loose metal or shrapnel from inside the cases if possible. If no internal or major structural damage exists, prepare to apply a quick drying patch to the damage hole or crack to stop oil leak.
- 2. Drain oil from system if necessary. Remove oil from damaged area by cleaning with solvent. If time permits, abrade the area around the holes or cracks with abrasive cloth. If necessary, remove sharp edges or protrusions from damaged hole.

- 3. Make sure that no oil is flowing from damaged area. If oil is flowing, repair cannot continue until oil flow is stopped. Stop oil flow using whatever means are available (e.g., zinc chromate putty or tape) to temporarily plug and stop small oil flows.
- 4. Clean a border at least 2 inches wide all the way around the damaged area. If zinc chromate putty was used to plug leak, do not clean the area directly over the putty.
- 5. Place an adhesive patch using repair kit (item 5, Appx C) over the damaged area. Follow the manufacturer's instructions in adhesive repair kit. Let patch cure for five minutes.
- 7. Start the aircraft engine and ground run transmission. Monitor/inspect the repair area for five minutes.
- 8. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- **8-6. TRANSMISSION OIL** PRESSURE SWITCH LEAK. If transmission oil is being lost due to damage of the oil pressure switch (1, Figure 8-2), eliminate switch from oil system.
- LIMITATIONS: The XMSN OIL PRESS warning segment at caution panel would be rendered inoperative. A low oil pressure condition would be indicated only at the transmission oil pressure indicator on instrument panel.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •15 Minutes



- Transmission Oil Pressure Switch Transmission Oil Pressure Transmitter

Figure 8-2. Pressure Switch and Transmitter

TM 55-1520-210-BD DRIVE TRAIN

MATERIALS/TOOLS REQUIRED:

- Fluid Liner Repair Kit (item 4, Sec I, App B)
- •Open End Wrenches (items 257-267, Sec II, App B)
- •Pliers (items 124-135, Sec II, App B)
- •Side Cutters (item 126, Sec II, App B)
- •Tie Wraps (itèms 165, 166, App C)

PROCEDURAL STEPS:

- 1. Cut safety wire and remove electrical conductor from pressure switch (1).
- 2. Cut safety wire and remove pressure switch and o-ring. Retain o-ring.
- 3. Install cap plug with o-ring where switch was removed.
- 4. Check for leaks and add oil to XMSN if necessary.
- 5. Secure loose electrical connector with tie wraps.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

8-7. TRANSMISSION OIL PRESSURE TRANSMITTER LEAK.

GENERAL INFORMATION: If oil is being lost due to damage at oil pressure transmitter (2, Fig 8-2), eliminate transmitter from oil system.

LIMITATIONS: The transmission oil pressure indicator on instrument panel would be rendered inoperative. The XMSN OIL PRESS warning segment at caution panel will only monitor transmission low oil pressure. There would be no early warning capability if a high oil pressure condition was present.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- •15 Minutes

MATERIALS/TOOLS REQUIRED:

•Open End Wrench (items 257-267, Sec II, App B)

ŽPliers (items 124-135, Sec II, App B)

•Fluid Line Repair Kit (item 4, Sec I, App B)

žSide Cutters (item 126, Sec II, App B)

•Tie Wraps (items 165, 166, App C)

PROCEDURAL STEPS:

- 1. Procedural steps are the same as in paragraph 8-6 except that they would be applicable to the transmitter (2, Fig 8-2).
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

8-8. EXTERNAL OIL FILTER LEAK.

GENERAL INFORMATION: If oil is being lost due to damage to the oil filter (4, Fig 8-3) assembly and there is no damage to adjacent oil hoses and lines, isolate oil filter from oil system by repositioning input oil line to bypass filter. See Figure 8-3.

LIMITATIONS. Fine suspended matter would not be filtered from oil system, and would increase the wear of gears and bearings.

PERSONNEL/TIME REQUIRED:


ž1 Soldier


•15 Minutes


MATERIALS/TOOLS REQUIRED:

- Open End Wrenches (items 257-267, Sec II, App B)
- •Tie Wraps (items 165, 166, App C)

- 1. Loosen nut (15) and valve (16) installation.
- 2. Loosen nut (18) and disconnect tube assembly (17) from elbow (1) on inlet side of filter assembly (4).







- 1. El bow

- 1. Elbow
 2. Nut
 3. O-Ring
 4. Filter Assy
 5. Hose Assy
 6. Coupling (or Nipple)
 7. Nut

- 7. Nut
 8. Nut
 9. O-Ring
 10. El bow
 11. O-Ring
 12. Nut
 13. Ni ppl e
 14. O-Ring
 15. Nut

- 16. Thermo Valve17. Tube Assy
- 18. Nut

ALTERED INSTALLATION

Figure 8-3. Transmission External Oil Filter Bypass

TM 55-1520-210-BD DRIVE TRAIN

- Disconnect hose assembly (5) from coupling (6) on outlet side of filter assembly (4).
- Loosen and disconnect items 6 thru 14 from filter assembly (4). Discard o-ring (14).
- Reassemble items 6 thru 13 in same configuration as before and tighten.
- 6. Attach but do not tighten loose end (18) of hose assembly (17) to nipple (13) Do not use o-ring (14) on tube nipple (13).

- 7. Rotate tube assembly (17) to a position above filter assembly (4) and connect hose assembly (5) to coupling (6).
- 8. While holding tube assembly (17), elbow (10), and hose assembly (5) in the best position allowed, tighten nuts (18 and 51).
- 9. Check for any chafing conditions and correct by use of tie wraps, etc.
- Check for Leaks. 10.
- 11. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section III. TAIL ROTOR DRIVESHAFT ASSEMBLY

8-9. GENERAL. The tail rotor driveshaft rotates at approximately 4300 rpm. Damage to the tail rotor driveshaft train, which results in metal loss or bending of shafts, can cause an out of balance condition. This condition can damage the bearings, bearing hangers, couplings, gearboxes and eventually lead to complete shaft failure (break and separation). Any repair should therefore include the restoration of balance. Major damage which is not covered in this section will require replacement of the damaged component.

8-10. TAIL ROTOR DRIVESHAFT SECTIONS, MINOR DAMAGE.

GENERAL INFORMATION: Small arms fire and PROCEDURAL STEPS: projectile passing through the driveshaft will cause minor damage. Entrance and exit holes (2 holes max) each not exceeding 0.625 inch diameter will be acceptable, Figure 8-4.

OPTION 1: Damage through the approximate center of driveshaft with holes approximately 180 degrees apart. No restoration of balance required.

LIMITATIONS: Emergency one time flight and/or for recovery of aircraft. Inspect damaged area prior to flight. Prior to takeoff, functionally test the driveshaft by running the helicopter's engine for three minutes minimum at normal operating speed. Some abnormal vibrations may be present. Consideration should be given to abort flight if vibrations will cause loss of flight control.

PERSONNEL/TIME REQUIRED:

•1 Soldier **ž**30 Minutes

MATERIALS/TOOLS REQUIRED:

• Tape, Green Cotton (item 156, App C)

- Impact of projectile may cause the driveshaft to bend. Check the driveshaft for runout in the center. Maximum runout should not exceed 0.070 inch total indicator reading.
- Inspect the damaged area for cracks radiating out of hole. All damage including cracks shall not exceed 0.625 inch in diameter. Two holes maximum are allowed.

- 3. Do not remove any significant amounts of metal as this will destroy the shaft's balance. Remove very small loose metal, burrs, and slivers from the exit hole.
- 4. Large exit hole petals (Fig 8-4) should be straightened by light hammer tapping. Tap the petals relatively smooth back to original surface. Leave the entrance hole petals which point Inward towards center of driveshaft alone.
- 5. Wrap tape around the shaft over the holes. Tape must be wrapped opposite direction of rotation. Wrap three layers deep. Tape will not add structural strength to the driveshaft but will keep air from whistling through the holes.
- **6.** Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- OPTION 2: Projectile damage through driveshaft off of center. Entrance and exit holes are not to be closer than two hole diameters between each other. Each hole not to exceed 0.625 inch diameter. Restoration of balance will be required by drilling extra lightening holes.

LIMITATIONS: Emergency one time flight and/or for recovery of aircraft. Inspect damaged area prior to flight. Prior to takeoff, functionally test the driveshafts by running the helicopter's engine for three minutes minimum at normal operating speed. Some abnormal vibrations may be present. Consideration should be given to abort flight if vibrations will cause loss of flight control.

PERSONNEL/TIME REQUIRED:

- 2 Sol di ers
- 1 Hour

MATERIALS/TOOLS REQUIRED:


- . Drill Bit Set (item 67, Sec II, App B)
- Drill Motor (item 69, Sec II, App B)
- . Ruler (flexible)
- . Tape, Green Cotton (item 156, App C)

PROCEDURAL STEPS:


- 1. Impact of projectile may cause the driveshaft centerline to bend. Check the driveshaft for runout in the center. Maximum runout should not exceed 0.70 inch total indicator reading.
- 2. Inspect the damaged area for cracks radiating out of hole. All damage Including cracks shall not exceed 0.625 inch in diameter after rework. Two holes maximum are allowed. Holes minimum edge to edge distance is two hole diameters, Figure 8-5.
- 3. Remove hole petals, burrs, and cracks by rounding up the holes with files and abrasive cloth. Do not exceed 0.625 inch in diameter after repair. Both holes should be approximately the same size in square inches of area in order to continue the restoration of balance by this procedure.
- 4. Restore balance in shaft as follows:
- a. Measure arc "S" as shown in Figure 8-5, view A-A.

NOTE

If the two holes in driveshaft are not in a single plane perpendicular to the driveshaft axis, the arc "S" measurement will be measured to a constructed centerline as shown in Figure 8-5. The arc "S" measurement must be a single plane perpendicular to the driveshaft axis for the following procedure to work correctly.




A. DAMAGED SHAFT



B. EXIT HOLE PETAL STRAIGHTENED TO A RELATIVELY SMOOTH SURFACE

Figure 8-4. Damage Passing Through Center of Shaft



ARC MEASUREMENT "S" IS IN A PLANE THAT IS PERPENDICULAR TO AXIS DRIVESHAFT.

VIEW A-A




Figure 8-5. Balance Restoring Repair for Damage Not Passing Through the Center of Shaft

TM 55-1520-210-BD DRIVE TRAIN

- b. Find the value of "Y," Figure 8-5, view A-A, by using the "S" value measured in step a above and using the curve on Figure 8-6. This "Y" value will be used in the following step.
- c. Estimate the amount of material loss in square inches of the entrance and exit holes (after rework). Let al equal to the material lost in entrance hole and a2 equal to material lost in exit hole. A counterbalance hole will have to be drilled to offset the loss of metal of holes a1 and a2.
- (1) To determine the area "A" of the hole to be drilled, use formula:

$$"A" = (a1 + a2) \times (Y/1.5)$$

- (2) Use value "A" to determine the diameter "D" of the hole to be drilled. Use Figure 8-7.
- (3) To determine the location of "D" hole to be drilled, use formula:

"Z" =
$$4.71 - \frac{(a2S)}{(a1 + a2)}$$

Value "Z" will be the distance in inches measured in an arc from hole a1.

- do Drill counterbalance hole "D" diameter at location "Z" as shown in Figure 8-5.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

8-11. TAIL ROTOR DRIVESHAFT SECTIONS, MODERATE DAMAGE.

GENERAL INFORMATION: For any one single damage, the total damaged area is not to exceed one-third of the total cross-sectional area of the driveshaft, and a maximum surface area of 4.7 square inches, Figure 8-8. Maximum damage will be in the form of a hole with maximum diameter of 2.44 inches.

LIMITATIONS: Emergency one time flight and/or for recovery of aircraft.
Inspect damaged area prior to flight.
Prior to takeoff, functionally test the driveshaft train by running the helicopter's engine for three minutes minimum at normal operating speed. Some abnormal vibrations may be present. Consideration should be given to abort flight if vibrations will cause loss of flight control.

PERSONNEL/TIME REQUIRED:

- 2 Sol di ers
- . 2 Hours

MATERIALS/TOOLS REQUIRED:

- .Drill Bit Set (item 67, Sec II, App B) . Drill Motor (item **69, Sec II** App B)
- •Hose Clamps (items 40, 41, App C)
- •Rivets, Blind (items 94-114, App C) Measuring Tape (item 121, App B)
- Sheet Metal (item 129, App C)

- 1. Inspect the damaged area, and measure to ensure that:
- a. Damaged area does not reduce the cross section of the driveshaft by 33 percent in anyone plane per every 12 inches of driveshaft length.
- b. The hole diameter (after clean-up) does not exceed 2.44 inches in diameter.
- c. The driveshaft centerline to be straight with maximum runout of 0.07 inch total indicator reading taken anywhere along shaft.
- 2. Inspect the damaged area for cracks radiating out of hole. All damage including cracks shall not exceed 2.44 inches in diameter after rework.
- 3. Remove hole petals, burrs, and cracks by rounding up the hole with files and abrasive cloth. Remove the least amount of metal required to remove cracks. Do not exceed 2.44 inches in diameter after repair.




Figure 8-6. Y vs. S





Figure 8-7. Area vs. Diameter






Figure 8-8. Repaired Shaft

- 4. Fabricate a sheet metal plate (item 129, App C) to wrap around over the damaged area. The length of the sheet metal plate should be approximately 9-7/16 Inches the shaft circumference. The width of the plate should extend at least 3 inches beyond each side of the damaged area.
- 5. Wrap and hold the sheet metal plate around the damaged portion of the drive-shaft using two or more hose clamps. The plate ends should come together on the opposite side, 180 degrees from the damage. Apply two rows of rivets on each end as shown in Figure 8-8. Apply two rows of rivets at the seams as shown in Figure 8-8.

NOTE

It is very important that the seam of repair plate be as precise as possible in 180 degree opposite location from damage to keep shaft as close to balance as possible.

- 6. Two rows of rivets (counterweight) are to be placed precisely 180 degrees opposite the rows which were used to secure the edge seam of the sheet metal plate.
- 7. To serve as counterweights for the missing metal in damaged area, Install a number of rivets to compensate for lost weight. See Figure 8-9 and Table 8-2 for data on number of rivets required for given shaft missing area.
- 8. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section IV. INTERMEDIATE GEARBOXES

- **8-12. GENERAL.** The 42 and 90 degree gearboxes are nonpressurized vented gearboxes with the bottom of gears immersed in oil. The oil quantity to fill both gearboxes Is approximately one pint. If oil is being lost through battle damage, repair damage and replenish oil supply.
- **8-13. GEARBOXES, SMALL LEAKS THROUGH CASE HOLES AND CRACKS.** The following repairs are designed to stop minor oil leaks and not to replace any lost function or structural strength of case.

LIMITATIONS: Mi nor case damage with evidence of no Internal damage can be repaired without any aircraft restrictions. On such minor damage in which oil leaks are very minor, consideration to deferring repairs should be given. Small oil leaks can be tolerated. Leakage rate should be Inspected at intervals.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- . 30 Minutes

Table 8-2. Shaft Area (in*) vs.

5

Based on No. 1/8 in. cherrymax rivets.

4.77 rivets equal the same weight as 1 sq in. shaft.




Figure 8-9. Shaft Area (in²) vs. Number of Rivets

MATERIALS/TOOLS REQUIRED:

- Abrasive Cloth (item 121, App C) Adhesive Repair Kit, Zip-Patch (item 5, App C)
- Solvent Cleaner (items 1, 76, App C)
- Zinc Chromate Putty (Item 90, App C)

- Inspect the damaged area for internal damage to gears, shafts, etc. Remove any loose metal or shrapnel from inside the cases If possible. If no Internal or major structural damage exists, prepare to apply a quick drying patch to the damage hole or crack to stop oil leaks.
- Drain oil from system if necessary. Remove oil from damaged area by using solvent cleaner. If time permits, abrade the area around the hoses or cracks with an abrasive cloth. If necessary, remove sharp edges or protrusions from damaged hole.
- 3. Make sure that no oil is flowing from damaged area. If oil is flowing, repair cannot continue until oil flow is Stop oil flow using whatever stopped. means are available (e.g., zinc chromate putty, or tape) to temporarily plug and stop small oil flows.

- 4. Clean a border at least 2 inches wide all the way around the damaged area. If zinc chromate putty was used to plug leak, do not clean the area directly over the putty.
- Place an adhesive patch using adhesive repair kit (Zip-Patch) over the damaged area. Follow the manufacturer's instructions in adhesive repair kit. Let patch cure for five minutes.
- Replenish any lost oil. If no oil supply is available, consider using engine oil from engine oil sump.
- Start the aircraft engine and ground run transmission. Monitor/inspect the repair area for five minutes.
- 8. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

CHAPTER 9

HYDRAULIC AND PNEUMATIC SYSTEMS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

9-10 SCOPE.


- a. This chapter consists of BDAR that is generally confined to fixing battle damaged hydraulic components, lines, and bleed air system to sufficiently keep helicopter flying.
- b. The procedures listed in this manual will help determine if:
- (1) Deferring repairs are possible.
- (2) Component or line replacement with new/used (salvaged) materials per TM 55-1520-210-23 is required.
- (3) Expedient BDAR repairs of components or lines are necessary. An expedient repair may be:
- (a) Bypassing damaged component or line if necessary.
- (b) Isolating damaged component or line if necessary.

9-2. ASSESSMENT PROCEDURES. Use assessment procedure, Table 9-1, to locate damage components or hydraulic line leaks. Use Figure 9-1 and schematic Figure 9-2 to guide you in identifying damaged areas and leaks. TM 55-1520-210-23 should be used in removal and replacement of components.

9-30 REPAIR PROCEDURE INDEX.

PARA 9-5 Reservoir (1. Fig 9-1) Leaks Hydraulic Filter, Damage & Leaking Relief Vălve Leaking Hydraulic Fluid. 9-9 Solenoid Valve Damaged to Pressure Switch Damaged & Leaking Check Val ve Leaking. 9-15 Armament Hydraulic System, 9-17 Metal Tube Leaking/Damaged . . 9-20 Bleed Air Lines Leaking. . . . 9-22 Bleed Air Fittings Damaged 9-24

Table 9-1. Assessment Procedures







Figure 9-1. Hydraulic System (Sheet 1 of 2)



- 1. Reservoi r
- 2. Pump
- 3. Test Couplings
- 4. Check Valve
- 5. Check Valve
- 6. Filter
- 7. Relief Valve
- 8. Sol enoi d Val ve
- 9. Pressure Switch
- 10. Power Cylinder

(typical 3 plcs)

- 11. Servo Control Valve
- 12. Irreversible Valve
- 13. Check Val ve
- 14. Check Valve

- 15. Tail Rotor Cylinder Valve
 16. Armament Shutoff Solenoid Valve
 17. Couplings for External Armament
 18. Armament Line Filter
- 19. Check Valve

Figure 9-1. Hydraulic System (Sheet 2 of 2)




Figure 9-2. Hydraulic System Schematic (Gravity Feed) (Sheet 1 of 2)




Figure 9-2. Hydraulic System Schematic (Gravity Feed) (Sheet 2 of 2)

Section II. HYDRAULIC RESERVOIR

9-4. GENERAL. The BDAR assessor must determine if the extent of leakage is acceptable and can be deferred or must be repaired. However, it should be noted that a leakage rate of one drop per second is approximately 0.38 pints per hour.

9-50 RESERVOIR, LEAKING HYDRAULICS FLUID.

LIMITATIONS: The repaired area, the hydraulic fluid level, and the pressure warning gages must be monitored more frequently.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 45 Minutes

MATERI ALS/TOOLS REQUIRED:


- Adhesive Repair Kit (Item 5, App C) . Cleaning Solvent (items 1, 76, App C)
 • Neoprene Rubber or Cloth (items 115,
- 117, App C)
- Tape (items 153, 156, App C)
- Wood Plug or Short Bolt
- . 5-Minute Epoxy (item 4, App C)

PROCEDURAL STEPS:

WARNI NG

Bring hydraulic system to zero pressure before making any repairs. Working pressure of 950 to 1000 psi can cause serious injury or death.

- Drain hydraulic fluid from the reservoir If necessary to stop all flow of fluid from damaged area, Figure 9-3.
- 2. Clean area around the crack or hole with solvent.
- 3. Seal opening with tape, short bolt, wooden plug or both, and clean again if necessary. Make sure all oil flow has stopped so adhesive will adhere.
- Use an adhesive repair kit and cover the entire area. Repair kit (item 5, Appx C) is a premixed and saturated fiberglass cloth ready to use and dries in five minutes. If not available, use method below.
- 5. Mix epoxy adhesive and apply over the plug. Extend the adhesive 1 inch or more over the edge of plug or tape, and layer on approximately 1/8 inch thick.
- 6. Replenish the hydraulic oil supply and bleed air from the system per TM 55-1520-210-23.
- Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.



NOTES

- 1. CLEAN AREA TO RECEIVE ADHESIVE WITH SOLVENT.
- 2. MAKE SURE BOLT OR WOOD PLUG WILL NOT GO THROUGH THE RESERVOIR WALL.

Figure 9-3. Patch Repair for Leaks

Section III. HYDRAULIC FILTER

9-6. GENERAL. The BDAR assessor must determine if the extend of leakage Is acceptable and can be deferred or must be repaired. However, it should be noted that a leakage rate of one drop per second is approximately 0.38 pints per hour.

9-70 HYDRAULIC FILTER, DAMAGE AND LEAKING.

OPTION 1: Filter (6, Fig 9-1) replacement with substitute filter (18, Fig 9-1)0

LIMITATIONS: The armament system will be downgraded.

PERSONNEL/TIME REQUIRED:

- •1 Sol di er
- •1-1/2 Hours

MATERIALS/TOOLS REQUIRED: Helicopter must have armament (hydraulic) configuration.

PROCEDURAL STEPS:

- 1. Refer to Figure 9-1.
- 2. Evaluate damage and determine if leakage can be deferred. If not deferrable, continue repair.
- 3. Remove damaged filter (6) and remove armament filter (18).
- 4. Remove armament filter (18) and connect both ends of hydraulic tubes together with a union, or to jumper the removed filter (18). The tubes in armament system may also be plugged; however, this will disable the armament system.
- 5. Install filter (18) in place of filter (6). Both of the filters have identical thread connections.

- 6. Turn off armament shutoff solenoid valve (16) if the system Is not needed. If it is needed, it will still operate if the removed filter (18) was jumpered.
- 7. If tubes were plugged, turn off armament valve (16).
- 8. Replenish any lost hydraulic fluid.
- 9. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Bypass damaged filter with hose.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 1 Hour

MATERIALS/TOOLS REQUIRED:

- Bypass Hose (App B)
- Hand Tools (App B)
- •Fluid Line Repair Kit (item, 4, Sec I, App B)

- 1. Remove damaged leaking filter (6).
- 2. Install fittings and bypass hose Inplace of filter, Figure 9-4.
- 3. Replenish hydraulic fluid lost.
- 4. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 9-4. Filter Bypass Hose Installation

Section IV. RELIEF VALVE

9-8. GENERAL. The BDAR assessor must determine if the extent of leakage is acceptable and can be deferred or must be repaired. However, it should be noted that a leakage rate of one drop per second is approximately 0.38 pints per hour.

9-9. RELIEF VALVE, LEAKING HYDRAULIC FLUID. (Figure 9-5.)

GENERAL INFORMATION: None.

LIMITATIONS: Hydraulic system pressure will still be regulated at approximately 1000 psig by the pressure control built into the pump. Surging may be felt in control sticks. System will not be 100 percent operational. Be prepared to shut off hydraulic boost system and fly under emergency procedures.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- . 1 Hour

MATERIALS/TOOLS REQUIRED:

 Common Hand Tools (App B)
 Fluid Line Repair Kit (item 4, Sec I, App B)

- 1. Remove damaged relief valve (7, Fig 9-5).
- 2. Install a female thread coupling or plugged tee In place of banjo fitting on return line tubing.

- 3. Remove nipple from tee and install an MS plug with preformed packing.
- 4. Replenish hydraulic fluid lost.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 9-5. Relief Valve Removal

Section V. SOLENOID VALVE

9-10. GENERAL.

- a. Two solenoid valves (8, 16, Fig 9-6) are used. One is located on forward side of cargo lift beam and the other (on helicopters with armament provisions) is located on aft side of cargo lift beam.
- b. The BDAR assessor must determine if the extent of leakage is acceptable and can be deferred or must be repaired. However, it should be noted that a leakage rate of one drop per second is approximately 0.38 pints per hour.

9-110 SOLENOID VALVE, DAMAGED AND LEAKING. (Figure 9-6.)

OPTION 1: Replacement of damaged solenoid valve (8) with identical solenoid valve (16) found in the armament hydraulic system.

LIMITATIONS: Removal of armament solenoid valve (16) and reconnecting the hydraulic lines will provide function to armament system, but it cannot be turned off

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 1-1/2 Hours

MATERI ALS/TOOLS REQUIRED:

- Common Hand Tools (App B)
- •Fluid Line Repair Kit (item 4, Sec I, App B)

PROCEDURAL STEPS:

j. Remove damaged main solenoid valve (8).

- 2. Remove armament solenoid valve (16).
- 3. Couple both ends of tube where solenoid (16) was removed using a nipple or a short piece of hose. This will leave armament hydraulic system "on line" available at all times, and it cannot be turned off.
- 4. To make armament system "off" all the time, plug both ends of hydraulic lines with" plugs or caps.
- 5. Install removed solenoid valve (16) in place of damaged and removed solenoid valve (8).
- 6. Replenish any lost hydraulic fluid.
- 7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Remove solenoid valve (8) and install a bypass hose (Figure 9-7).

LIMITATIONS: Hydraulic pressure cannot be turned off.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •1 Hour

MATERIALS/TOOLS REQUIRED:

- •Bypass High Pressure Hose (App B)
- Hand Tools (App B)
- •Fluid Line Repair Kit (item 4, Sec I, App B)




Figure 9-6. Solenoid Valve Replacement

- 1. Remove damaged solenoid valve (8) and all the hardware including the return line as shown in Figure 9-7.
- 2. Plug the banjo fitting with a plug and packing where the return line was removed.
- 3. Remove the locknuts from nipples in two places.
- 4. Install an 18 inch bypass hose.
- 5. Wrap and Insulate solenoid electrical connector that was removed from top of solenoid.
- 6. Check and replenish hydraulic oil supply
- 7. Record BDAR action taken. When mission Is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 9-7. Bypass of Solenoid Valve

OPTION 3: Solenoid Valve (16) Bypass. **In case** solenoid valve (16) is damaged and leaking, remove it and/or bypass it by coupling both tube ends that attach to it with a nipple or a short piece of

high pressure hose. The armament hydraulic system in this mode cannot be turned off. This fix is similar to bypass shown in Figure 9-7.

Section VI. PRESSURE SWITCH

9-12. GENERAL. Not applicable.

9-13. PRESSURE SWITCH, DAMAGED AND LEAKING.

LIMITATIONS: Low pressure of 500 psi or less will not be detected if pressure switch is removed to stop a leak.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 30 Minutes

MATERI ALS/TOOLS REQUI RED:

- . Fluid Line Repair Kit (item 4, Sec I, App B)
- Hand Tools (App B)

PROCEDURAL STEPS:

- 1. Remove damaged switch (9) from tee fitting.
- 2. Install an AN 814 plug In outlet of tee from where switch was removed.
- 3. Wrap and stow electrical connector with electrical tape.
- 4. Place adhesive tape over the hydraulic caution panel segment and mark it as disconnected.
- 5. Record BDAR action taken. When mission Is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section VII. CHECK VALVES

9-14. GENERAL. The BDAR assessor must determine if the extent of leakage is acceptable and can be deferred or must be repaired. However, It should be noted that aleakage rate of one drop per second is approximately 0.38 pints per hour.

9-150 CHECK VALVES, LEAKING. (Figure 9-1.)

LIMITATIONS: Check valves (4, 13, 14) are critical to proper operations of hydraulic controls, and they are to be replaced If damaged. Check valves (5, 9) are not critical and can be removed if leaking (damaged), or to use as a substitute for (4, 13, 14).

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- 2 Hours

MATERIALS/TOOLS REQUIRED:

Fluid Line Repair Kit (Item 4, Sec I, App B)Hand Tools (App B)

- 1. Remove the damaged check valve (4, 13, 14).
- 2. Remove a noncritical check valve. Preferably armament check valve (19). If valve (19) is not in aircraft, remove ground test coupling check valve (5).

- 3. Cap or plug, or bypass line tubes or fittings where noncritical check valve (5) or (19) was removed.
- 4. Check valves (5, 19) are MS-6 thread size. If substituting in place of check valve (13, 14), a reducing fitting will be required since these valves are MS-4 thread size, Figure 9-8.

CAUTION

Ensure that directional flow arrow is pointing in right direction prior to installation.

- 5. Line tubing will require a small amount of reshaping to accommodate substitute valve.
- 6. Replenish any lost hydraulic fluid.
- 7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 9-8. Check Valve Substitution

Section VIII. ARMAMENT HYDRAULIC SYSTEM

9-16. GENERAL.

- a. On helicopters with provisions for externally mounted armament, pressure is supplied to a normally-open solenoid valve (16) which is controlled by a switch on an armament control panel. When the valve is open, hydraulic fluid is supplied to the external couplings on each side of the helicopter. When external hydraulic equipment is connected, fluid used to operate the equipment is returned through a filter and check valve to the hydraulic reservoir.
- b. Any damage which causes hydraulic leaks in armament system can expediently be controlled by turning off the system and plugging line.
- 9-17. ARMAMENT HYDRAULIC SYSTEM, LEAKING.

LIMITATIONS: No armament hydraulic system.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

- Common Tools, MS-6 Plug (item 4, App B)
 Fluid Line Repair Kit (item 4,
 - Sec I, App B)

PROCEDURAL STEPS:

- 1. Turn off system pressure with armament shutoff solenoid valve (16, Fig 9-1)
- 2. Remove check valve (19) and plug line in both directions with MS-6 plugs and o-rings.
- 30 Replenish any lost fluid.
- 4. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section IX. HYDRAULIC HIGH PRESSURE HOSES

9-18. GENERAL. No BDAR fix. Turn off system.

Section X. HYDRAULIC HIGH PRESSURE METAL TUBING

9-19. GENERAL. The following BDAR fixes are designed to be quickly and easily applied and should be used if no standard repair/replacement part is available.

9-20. METAL TUBE LEAKING/DAMAGED.

OPTION 1: Replace metal tube.

LIMITATIONS: Temporary.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 1/2 Hour

MATERIALS/TOOLS REQUIRED:

- Wrenches
- Hose Clamps
- Fluid Line Repair Kit (item 4, Sec I, App B)

- 1. Disconnect metal tube from fitting.
- 20 Move metal tube free of fittings.
- 3. Connect together as many flex hoses to equal to the length of the damaged line.

- 4. Install flex hose In the place of the metal tube.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Repair with hose splice.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- •1 Sol di er
- •1 Hour

MATERIALS/TOOLS REQUIRED:

- Hacksaw (i tem 94, Sec II, APP B)
- Hose Clamp (items 67-72, App C)
- Rubber Hose (i tem 4, App B)
- Adhesive (items 4 or 10, App C)

PROCEDURAL STEPS:

- 1. Remove damaged hose section by cutting with hacksaw. Deburr ends of tube.
- 2. Cut a piece of high pressure hose to bridge the removed section plus extra length for clamping three hose clamps on each end.
- 3. Attach hose and clamps to tubing in similar fashion as shown in Figure 9-9.
- 4. Five minute epoxy adhesive may be used between tube and hose. Use care not to contaminate inside of hydraulic lines with adhesive
- 5. Replenish the hydraulic oil supply.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 3: Pin hole leaks for metal tubes.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- •1 Sol di er
- 30 Minutes

MATERIALS/TOOLS REQUIRED:

- Clamp, Hose (items 67-72, App C)
- Rubber Sheet 1/8 in. min. thickness (item 117, App C)

- 1. Pin hole leaks 1/8 diameter or less.
- 2. Place a piece of hard rubber sheet or a piece of rubber hose over the hole, and place hose clamp directly over the rubber. Rubber sheet should extend past both outside edges of clamp band.
- 3. Tighten hose clamp.
- 4. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 9-9. Rubber Pressure Patch

Section XI. BLEED AIR SYSTEM TUBES AND HOSES

9-21. GENERAL. The most critical component of the pneumatic bleed air system is the engine and transmission oil cooler fan. If damaged, every possible effort should be made to restore operation of this portion of the system to prevent engine and transmission oil overheating. Certain UH-IH/Vmodel helicopters may still have pneumatic fuel boost pumps installed on the lower fuel cells. If aircraft is in this configuration, effort should also be directed toward repairing pneumatic line damage routed to pumps. The BDAR fixes contained in this section apply only to repair of the bleed air line to the oil cooler fan and to the fuel pump.

9-22. BLEED AIR LINE LEAKING-PLUG OR I SOLATE.

GENERAL INFORMATION: None.

LIMITATIONS: Except for the oil cooler fan line and pneumatic boost pump lines. All bleed air lines can be plugged, removed, or isolated without downgrading helicopter flight status.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 30 Minutes

MATERI ALS/TOOLS REQUIRED:

- Common Hand Tools (App B)
- •Fluid Line Repair Kit (item 4, Sec I, App B)

PROCEDURAL STEPS:

- Determine if bleed air line or component it supplies can be isolated and removed. Remove damaged hose.
- 20 Install appropriate plug or cap on line.
- 3. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

9-23. BLEED (FLEX TUBE) AIR LINE 3/4 AND 1 INCH TO OIL COOLER FAN LEAKING.

OPTION 1: Splice repair-metal tube splice.

LIMITATIONS: All repairs made to the bleed air system must utilize materials and parts capable of withstanding the approximate 550 degree heated bleed air temperature.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- 1 Hour

MATERI ALS/TOOLS REQUIRED:

- Common Hand Tools (hacksaw, pliers, screwdriver) (App B)
 • Hose Clamps (item 67-72, App C)
 • Metal Tube 3/4 or 1 Inch OD
- Aluminum or Steel (low pressure) Tubi ng
- Epoxy Adhesive (items 3 or 4, App C)

PROCEDURAL STEPS:

- Remove damaged hose to facilitate repair if possible.
- Wrap wire braid cover with several layers of masking tape to facilitate cutting, and cut with a fine tooth blade hacksaw. Remove damaged section.

WARNING

Woven wire braid cover of hose will puncture human skin. Exercise care in handling. Wear protective gloves.

- Push the woven wire braid back from cut line approximately 2 inches, and hold in place by masking tape.
- Using a hacksaw, cut one or two slots in each end of flexible hose tube as shown. Cut slots 1-1/2 inches long. These slots may be left optional and instead slot the splice metal tube.




Figure 9-10. UH-1 Bleed Alr System

- 5. Cut a length of metal tubing with an outside diameter (3/4 or 1 in.) to fit inside diameter of the flexible metal hose. Length as needed to replace removed section plus 4 inches more.
- 6. Insert repair tube splice into both ends of metal flex hose as shown in Figure 9-11, and clamp in place with four hose clamps.
- 7. If time permits, and adhesive epoxy can be applied to joint. Clean area with solvent, cover the end joint, and the hacksaw cut slots with a five minute epoxy. Walt five minutes for adhesive to cure before operating system.
- 8. Record BDAR action taken. When mission is complete, as soon as prattical, repair the equipment/system using standard maintenance procedures.




Figure 9-11. Bleed Air Hose Repair

OPTION 2: Splice repair-sheet metal wrap, Figure 9-12.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

.2 Soldiers

•1-1/2 Hours

MATERIALS/TOOLS REQUIRED:

- Epoxy Adhesive (item 3 or 4, App C)
- Common Hand Tools (App B)
- Hose Clamps (items 37-41, App C)
- Safety Wire (lockwire) (items 73-75, App C)
- Tape (item 153, App C)

PROCEDURAL STEPS:

- 1. If damage has completely cut through tube, use a hacksaw to remove damaged section as shown in Figure 9-12.
- 2. Measure and cut a piece of sheet metal, allowing for 1-1/2 to 2 Inch overlap of tubing ends.
- 3. Apply sealant adhesive to both ends of tubing.
- 4. Wrap sheet metal tightly around and secure with safety wire as shown in Figure 9-12C.

NOTE

Sheet metal serves as a splice to conduct main airstream. Firesleeve or tape provides a (heat proof) seal to prevent excessive air leakage.

- 5. Measure and cut a piece of red firesleeve, allowing for 3 inch overlap of tubing end and sheet metal as shown in Figure 9-12D. If flresleeve material is not available, wrap splice area with aluminum tape.
- 6. Wrap firesleeve or tape tightly around sheet metal splice and tube. Hold firesleeve tight and secure with gear type hose clamps as shown in Figure 9-12D.

7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 3: Patch repair-sheet metal patch and clamps flexible metal hose, Figure 9-13.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- .1 Soldier
- . 1 Hour

MATERIALS/TOOLS REQUIRED:

- .Epoxy Adhesive (items 3-8, App C)
- Common Hand Tool's (App B)
- •Hose Clamp (items 37-41, App C)
- •Safety Wire (lockwire) (items 73-75, App C)
- . Sheet Metal 0.016 Stainless Steel or Equivalent (item 141, App C)
- . Tape, Aluminum (item 153, App C)

- 1. Cut the stainless steel braid outer cover with metal snips and move out of the damaged area. Use tape to secure the cut braid cover out of the way. Be careful not to damage the flexible hose any more.
- 2* Hammer or file damaged area to allow patch to fit flush with tube surface. Remove metal filings from tube to prevent clogging or downstream air nozzles.
- 3. Cut patch from sheet metal to cover hole or other damage. Patch should extend approximately 1 inch from the edge of the hole at all points if possible.
- 4. Clean the area with solvent and apply epoxy sealant around the hole area to be covered by the patch.
- 5. Place sheet metal patch in position. Make sure patch fits the contour of tube.




Figure 9-12. Rigid Bleed Air Tube Splice Repair

OVERLAP ENDS

(SECTION A-A)

CLAMPS

INSTALL FIRESLEEVE AND CLAMPS

- 60 Wrap aluminum tape around the patch 8. Record BDAR action taken. When repair. Tape should cover at least 2 mission is complete, as soon as inches beyond the edge of repair.
- 7. Secure metal patch in place using hose clamp. (If hose clamps are not available, secure in place with safety wire.)

practical, repair the equipment/system using standard maintenance procedures.




Figure 9-13. Rigid Bleed Air Tube Patch Repair

TM 55-1520-210-BD HYDRAULIC AND PNEUMATIC SYSTEMS

OPTION 4: Patch repair using adhesive patch kit.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

- Adhesive Repair Kit (item 5, App C)
- •Solvent (items 1, 76, App C)
- •Tape (item 153, App C)

PROCEDURAL STEPS:

1. Cut the stainless steel braid outer cover with tin snip, and move it out of

the damaged area. Use tape to secure the cut braid out of the way. Be careful not to damage the flexible hose any further

- 2. Remove burr, loose metal, and straighten metal tube as close to original contour as possible.
- 3. Wrap damaged area with three to four layers of aluminum tape.
- 4. Using adhesive repair kit, patch the area with two or three layers of patch material. Extend the edge of patch 1-1/2 inches past the edge of the aluminum tape all the way around.

Section XII. BLEED AIR FITTING

9-24. BLEED AIR FITTINGS, DAMAGED.

GENERAL INFORMATION: The bleed air fitting can be replaced (bypassed) with a TEE or ELBOW fitting, Figure 9-14.

LIMITATION: Use of a fitting (tee or elbow) to reconnect air supply to oil cooler fan will isolate and remove fuel boost pump and the heater from service function.

PERSONNEL/TIME REQUIRED:

- •1 Sol di er
- •2 Hours

MATERIALS/TOOLS REQUIRED:

- Common Hand Tools (App B)
- •Fluid Line Repair Kit (item 4, App B)
 Plug
 Reducer Fittings
 90° Elbow or Tee Fitting

- 1. Remove damaged parts.
- 2* Install reducer fitting in 90° elbow or tee as required. If a tee is used, install plug on one end.
- 3. Install 90° elbow into bleed air lines.
- **4.** Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 9-14. Bypassing Damaged Bleed Air Fittings

CHAPTER 10

INSTRUMENTS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

lo-l* SCOPE.

- a. Battle damage instrument repair is beyond the scope of this chapter. Replacement will normally be at AVUM or AVIM level.
- b. Deferred repairs will be emphasis and will allow helicopters to remain operational with varying degrees of limitations/capabilities, Table 10-2. This table contains information that will guide and help determine what instruments are necessary for minimum requirements.
- c. Driving input systems for instruments will be either electrical power circuits and pneumatic plumbing circuits. For repair of these systems, see paragraph 10-3.
- 10-2. ASSESSMENT PROCEDURES. See Table 10-1, Instruments Assessment.

10-3. REPAIR PROCEDURE INDEX.

PARA.

Oil Pressure Indicator or	
Transmitter, Damaged/Bad	
Read	10-6,
Pitot Plenum, Dama	. 10-8
Static Manifold, Damage	. 10-9
Instrument Replacement	TM 55-1520-
ı	210-23
Electrical Circuits	Chpt 11

Section II. ASSESSMENT AND REPAIR PLANNING

10-4. FUNCTIONAL LIST AND ASSIGNMENT OF FLIGHT ESSENTIAL INSTRUMENTS.

- a. Flight Essential Instruments. All instruments in the pilots panel are essential for safe flight. Under combat conditions, replacement instruments may not always be available and missions may have to be flown without the aid of operative instruments.
- b. Copilot panel can be used as source of replacement instruments for pilot's panel. When instruments are replaced, make sure the range markings are correct.

- c. Malfunctioning instruments should not be removed unless replacement instruments are available.
- d. When a good instrument is removed from the copilot's panel for installation in the pilot's panel, the malfunctioning instrument should be placed in the copilot's panel and marked "bad" on the face.
- e. When the cover glass of an instrument is broken and a replacement instrument is not available, remove all loose glass shards from the instrument and leave it in the panel.

Table 10-1. Instruments Assessment




	Table 10-2. System Evaluation				
I NSTRUMENT OUT OF COMMISSION		REQUIRED FOR EMERGENCY OR SELF-RECOVERY	CONDITIONAL REQUIREMENTS CROSS-REFERENCE TO OTHER I NSTRUMENTS/I NDI CATORS		
1.	Torquemeter Indicator	No	Must have functional indicators 2 and 4 as a backup.		
2.	Exhaust Gas Temperature Indicator	No	Must have functional indicators 1, 3, and 4 as a backup.		
3.	Dual Tachometer Indicator				
	Engi ne	No	If rotor portion of tachometer Is working, monitor rotor rpm.		
	Rotor	No	If engine portion of tachometer is working, monitor engine rpm.		
4.	Gas Producer Tachometer Indicator	No	Must have at least item 1 or 3 fully functional.		
5.	Engine Oil Temperature Indicator	No	If transmission oil temperature indicator reads normal, check function of the engine oil temperature Indicator by exchanging the leads of both Indicators.		
6.	Engine Oil Pressure Indicator	No	Caution panel "engine oil press" must be fully functional. Check and test circuit by exchanging leads with XMSN oil pressure indicator.		
7.	Fuel Pressure Indicator	No	Main engine fuel pump must be fully functional and heli-copter's celling limited to 4600 pressure altitude.		
8.	Fuel Quantity Indicator	No	Monitor caution panel "20 minutes" warning light.		
90	Transmission Oil Pressure Indicator	No	Monitor caution panel "trans- mission low oil pressure" warning light. If engine oil pressure indicator is func- tional, check indicator by exchanging lead of both indicators.		

Section III. ENGINE OIL PRESSURE INDICATOR AND TRANSMITTER

10-50 GENERAL. The following procedure explains how to check the system if a low pressure reading is being caused by a damaged oil pressure indicator, transmitter or electrical circuit. Battle damage to the system can be easily located by visual inspection and the following assessment procedure.

10-6, OIL PRESSURE INDICATOR OR TRANSMITTER, DAMAGED/BAD READING.

GENERAL: Low oil pressure on Indicator could be caused by tripping of electrical circuit breaker. The breaker in turn could be tripped by a damaged electrical circuit. Both the circuit breaker and circuit should be checked for battle damage failure.

LIMITATIONS: As long as oil pressure/circulation is present, the engine oil pressure system indicators can be non-functional.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- 1/4 Hour

MATERIALS/TOOLS REQUIRED:

• Volt-Ohm Meter (item 229, App B)

PROCEDURAL STEPS:

- 1. Visually check the oil pressure transmitter and indicator for damage, Figure 10-1. If damaged but no oil leaks are present, check for function by continuing below.
- 2. If the engine oil pressure reading is bad and the transmission oil pressure is good, then remove both the engine and

the transmission oil pressure indicators from the instrument panel. Disconnect the electrical plugs in back and switch the electrical plugs on the two indicators. The engine oil pressure will now be read on the transmission oil pressindicator.

- 3. If the engine oil pressure reading is bad on the transmission indicator, then the transmitter or the wiring coming from it is bad and will need replacement. Continue assessment to determine the loss of oil pressure.
- 4. If engine oil pressure indicates good on the transmission indicator, then engine is fully mission capable and the engine oil pressure indicator is bad. Replace the indicator at convenient time.
- 50 If low pressure warning light on warning panel does not come on, then engine oil pressure is above 25 psi. If the low pressure switch is damaged, check to see if it is functional by checking with the light test switch and the circuit breaker. This only checks the caution panel light bulb. To check system wiring, remove cannon plug from the pressure switch. Use volt-ohmmeter (VOM) between the two pins in the cannon plug. Check for 28 VDC. This will indicate wiring is continuous.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 10-1. 0il Pressure Transmitter

Section IV. PITOT/STATIC SYSTEM

10-70 PITOT/STATIC SYSTEM.
The fixes shown are relatively simple and expedient and can be used to restore lost function. In extreme emergency, repairs are to be deferred and repaired later by replacing damaged components.

10-8. PITOT PLENUM, DAMAGED. See Figure 10-2.

OPTION 1: Patch with aluminum tape.

LIMITATIONS: Temporary repair-reinspect every 100 hours.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 1 Hour

MATERI ALS/TOOLS REQUIRED:

- Common Hand Tools
- Aluminum Tape (item 153, App C)

PROCEDURAL STEPS:

- 1. Ensure enough of the plenum remains to allow an airtight seal with the tape.
- 2. Remove the plenum.
- 3. Wrap tape around plenum overlapping the edges to ensure an airtight seal.
- 4. Reinstall plenum.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Remove plenum and byPass.

LIMITATIONS: None.

NOTE

The plenum helps dampen pressure surges. Some indicator needle fluctuation may occur due to loss of dampening action when the plenum is removed or bypassed.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 1 Hour

MATERIALS/TOOLS REQUIRED:

- Comnon Hand Tools (App B)
- Fluid Line Repair Ki't (i'tem 4, Sec I, App B)

PROCEDURAL STEPS:

- Remove damaged plenum.
- 2. Install bypass hose using unions, or cut existing AN flare fittings from ends of existing aircraft tubing and install a bypass hose using hose clamps.
- 3. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

10-9. STATIC MANIFOLD, DAMAGED.

LIMITATIONS: Defer repair.




Figure 10-2. Bypassing Damaged Plenum

CHAPTER 11

ELECTRICAL AND AVIONICS SYSTEMS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.
(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

11-1. SCOPE.

- a. Wire Identification. Added and repaired wiring must be identified to aid in troubleshooting. Tape or sleeving at each end of added wiring of a material suitable for the ambient temperature range may be used. Typical wire and circuit identification schemes are shown in Figure 11-1 and Table 11-1.
- Circuit Function. The unit number and circuit designation letter Identify the type of circuits. The wire number consists of one or more digits. It is used to distinguish between wires The wire segment in the same circuit. letter is used to distinguish between conductor segments (a wire segment between two terminals or connections). The wire size number is used to identify the gage of the wire or cable. The ground, phase, or thermocouple letter(s) are used as suffixes to the wire identification code to further identify certain wires. Ground wires are identified with Phase Letters A, B, or C an N suffix. are added to identify the phase of wires that are in the three-phase wiring of alternating current (AC) systems. For thermocouple wire, the following suffixes are added to the identification code: AL (Alumel), CR (Chromel), FE (Iron), CN (Constantan), and CU (Copper).
- c. <u>Deferral</u>. Repair of systems and subsystems which have adequate redundancy or are not critical to mission accomplishment may be deferred if safety of flight is not significantly degraded.

The commander may defer combat maintenance and battle damage repair, even if doing so places operational limitation on the aircraft.

11-2. ASSESSMENT PROCEDURES. See Table 11-2 for Electrical and Avionics Systems Assessment.

WARNING

Before assessing and handling systems wiring or components, turn off power to all systems. Damaged equipment can cause severe shock to personnel and additional damage to equipment.

11-3. REPAIR PROCEDURE INDEX.

	PARA.
Splicing Unshielded Wires. Wire Repair Segments Damaged Wire Insulation Shielded Cable Shielded Cable Segments Shield Terminators	11-5 11-6 11-7 11-8 11-9 11-10
Nickle-Plated Terminators	11-11 1 11-12
Terminal Lucas	<u>11-13</u> 11-14
Component Bridging	11-18
Damaged Connector Pins Circuit Breaker	11-19 11-20 11-21"
Power Bus Bar Repair Battery Bus Bar Repair	11-22 11-23
Power Relay	11-24
Substitute Emergency Antenna .	11-26

SEE TABLE 11-1 FOR LETTER CODES 2 F 1 7 3 3 B 20 N GROUND OR PHASE CIRCUIT DESIGNATION—WIRE SIZE WIRE NUMBER—WIRE SEGMENT

Figure 11-1. Circult Identification

	Table 11-1. Function and	Designation Letters
CIRCUIT DESIGNA		CIRCUIT DESI GNATI ON
LETTER	CIRCUITS	LETTER CIRCUITS
A	ARMAMENT: Bomb suspension & release Guns Chemical Rocket Sight Turret Warning External pylons stores Jettison fuel tanks Mine dispenser	E ENGINE INSTRUMENT: Tailpipe temperature Fuel flow Fuel quantity Fuel capacity Oil temperature Oil pressure Manifold pressure Fuel pressure Engine oil quantity Tachometer
В	PHOTOGRAPHIC: Gun camera Mapping camera Reconnaissance camera Camera intervalometer Camera doors Camera heaters Warning	Warning F FLIGHT INSTRUMENT: Bank and turn Rate of climb Directional gyro Air position Ground position Compass (including flux gate
С	CONTROL SURFACE: Horizontal stabilizer Warning	and other stabilized compasses) Gyro horizon Attitude gyro
D	INSTRUMENT (other than flight or engine instruments): Ammeter Air pressure Free air temperature Hydraulic pressure Horizontal position stabilizer Voltmeter Clock Warning	Driftmeter Altimeter Airspeed Accelerometer Pitot-static tube meter Warning

	Table 11-1. Function and Desi	gnati on	Letters (Cent)
CIRCU	IT	CIRCUIT	Γ
	NATION	DESIGNA	
LETTE	R CIRCUITS	LETTER	CIRCUITS
Н	HEATING, VENTILATING, AND DE-ICING: Anti-icing (general) Battery heater Cabin heater		Running, position, navigation Passing Search Taxi Warning
	Cigarette lighter De-icing (general) Windshield defroster Windshield defogger Windshield de-leer Heater blanket Oil immersion heater Refrigeration Ventilation	M	MI SCELLANEOUS ELECTRIC: Wi ndshi eld spray Wi ndshi eld wi per Hoi st Enclosure operation Positioner; seat, pedal Special test equi pment
	Warni ng	N	UNASSI GNED
l	In order to avoid confusion with the numeral one, the letter "l" shall not be used for circuit on cable identification.	0	In order to avoid confusion with the numeral zero, the letter "0" shall not be used for circuit or cable identification.
J	IGNITION: Booster	Р	DC POWER
	Vi brator Di stri butor El ectroni c Warni ng	Q	FUEL AND OIL: Fuel valves Fuel booster-pump motor Moisture control
K	ENGINE CONTROL: Blower ratio Starter Warning		Oil dilution Engine primer Fuel-transfer-pump motor and control Fuel-loading-pump motor
L	LIGHTING: Approach Flasher-coder Cockpit Drift Cabin Formation Cargo 'Interior Instrument Section (fusel age) Landing Exterior		Oil transfer-pump motor and control Oil booster pump Oil scavenge pump Throttle control Fuel-pump motor Oil diverter Oil valves Warning

	Table 11-1. Function and Desi	gnati on	Letters (Cont)
CIRCUI		CIRCUIT	
DESIGNA		DESIGNA	
LETTER	CIRCUITS	LETTER	CIRCUITS
R	RADIO (Navigation and communication): RA-Instrument landing RC-Command RD-Radio direction finding		TR-Receivers TT-Transmitters TU-Reconnaissance TW-Weather devices TZ-Bombing devices
S	RF-VHF liaison RH-Homing RL-Liaison RM-Marker beacon RN-Navigation RP-Special systems RS-SHF command RT-Radio teletype RU-UHF command RV-VHF command RX-Recorder RZ-Interphone, headphone RADAR: SA-Altimeter	U	MISCELLANEOUS ELECTRONIC: Electronic wiring for which no "R", "S", or "T", designation has been assigned by the procuring activity shall have the circuit function letter "U" assigned. Examples of wiring for which the circuit function letter. "U" will be assigned are common leads to electronic equipments and systems interconnection wiring such as antenna or power circuits common to more than-one equipment or system.
	SF-Intercept SG-Gunlaying SM-Mapping SN-Navigation SQ-Bombing SR-Recorder SS-Search SV-Special systems SW-Warning SX-Recognition (IFF)	V	DC POWER and DC control cables for AC systems. WARNING AND EMERGENCY Enclosure release and locks Fire extinguishers Flare release Fire detector Intercrew buzzer or light
T	SPECIAL ELECTRONIC: TA-Adapter TB-Radar control TC-Radio control TD-Airborne announcing TE-Electronic countermeasure TF-Repeat back TG-GM homing TH-Infrared TK-Telemetering TL-Attitude indicator TM-Chaff dispenser TN-Navigation TP-Beacon (crash and locator)	Υ	AC POWER: Wiring in the AC power system. ARMAMENT SPECIAL SYSTEMS: Y*A-Air to air Y*B-Air to surface y*C-Multimode Y*M-Missile-guidance Y*T-Turret Armament special system number
	TQ-Transmitters and receivers	Z	UNASSI GNED

Table 11-2. Electrical and Avionics Systems Assessment





Table 11-2. Electrical and Avionics System Assessment (Cent)



Section II. WIRE AND CABLE

11-4. GENERAL.

- a. BDAR wiring repair provides for two types of aircraft electrical wiring repairs which are classified as "PERMANENT" or "TEMPORARY."
- (1) A <u>permanent</u> repair returns the electrical wiring system to full capability, with no degradation of any system operating characteristics. No periodic inspection or replacement Is required with a permanent repair.
- (2) Temporary repairs must be reinspected at 100 flight hours. At this time, a permanent repair will be performed or an extension of use for the temporary repair will be granted.
- (3) Emergency Repair Good for one-time flight only.
- 11-5. UNSHIELDED WIRES, DAMAGED.

GENERAL INFORMATION: This procedure provides for repairing damaged unshielded wires.

WARNING

Do not be misled by the term "low voltage." Potentials as low as 50 volts may cause death under adverse conditions.

CAUTION

Ensure aircraft power is OFF. Disconnect battery before touching any wires.

OPTION 1: Crimp Splice.

LIMITATIONS: Only to be used for wire sizes 12-26. No more than one splice is made per 10 feet of wire. This is a permanent repair.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 10 Minutes

MATERIALS/TOOLS REQUIRED:

- Splice (items 145-149, App C)
- Sealing Sleeve (item 66, App C)
 Wire Repair Kit (item 11, Sec I, App B)

Crimping Tool Strippers

Heat Gun

Refl ector

PROCEDURAL STEPS:

- 1. Refer to instructions in wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Terminal Lug Splice.

LIMITATIONS: Only to be used on wire size AWG No. 10 and smaller. This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 15 Minutes Per Splice

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (i tem 11, Sec I, App B)
 Terminal Lug
 Insulating Sleeve
 Crimp Tool

- 10 Select a terminal with a barrel large enough to accommodate both wires.
- 2. Cut off terminal lug tongue.
- 3. Prepare wire ends.




Figure 11-2. Splicingwith Terminal Lug Barrel

- 4. Slip an Insulating sleeve 1 Inch longer than terminal lug barrel over the end of one of the wires, and Insert wire end into the barrel as shown in Figure 11-2.
- 5. Crimp barrel in center.
- 6. Slide insulating sleeve over the terminal lug barrel splice, and secure in place by using tie wraps or heating if heat shrink tubing is used.
- 7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 3: Split Bolt Splice.

LIMITATIONS: Only to be used on wire sizes AWG No. 4 thru No. 10. Temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Solder
- :10 Minutes

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (item 11, Sec I, App B)
 Heat Gun
 Heat Shrinkable Tape
 Heat Shrinkable Tubing
 Reflector
 Split Bolt Splice Connector
 Strippers or Knife

PROCEDURAL STEPS:

- 10 Refer to instructions In wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 4: Twist Wire Splice.

LIMITATIONS: This is an emergency repair.

PERSONNEL/TIME REQUIRED:

- . 1 Sol di er
- . 10 Minutes

MATERIALS/TOOLS REQUIRED:

\ \text{Wire Repair Kit (item 11, Sec I, App B)}
 \text{Tape, Electrical Strippers or Knife}

PROCEDURAL STEPS:

- 1. Cut ties and work broken wire to the outside of the bundle.
- 2. Pull sufficient slack from the wire run toward the break so that there will be no strain on the splice.
- 30 Wipe wire clean with a clean dry rag.
- 4. Trim broken ends of the wire.
- 5* Split all the wire ends.
- 6. Split the strands of wire apart and twist the matching wires together as shown in Figure 11-3.
- 7. Cover splice area with electrical tape.
- 8. If a section of wire needs to be replaced, a double repair can be made, Figure 11-4.

90 Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 5: Casing Splice Method.

LIMITATIONS: This is an emergency repair for one time flight only.

PERSONNEL/TIME REQUIRED:

- . 1 Sol di er
- . 10 Minutes

MATERIALS/TOOLS REQUIRED:

- •Cylindrical metal casing such as ball point pen refills, expended cartridges, etc.
- . Wire Repăir Kit (item 11, Sec I, App B)
- . Crimp Tool (hammer, pliers, etcJ

PROCEDURAL STEPS:

10 Fabricate splices approximately 1 to 2 inches long from small metal casing.

NOTE

Ball point refills or expended cartridge shell casings when cut to length make splices, Figure 11-5.

- 2. Strip 1/2 to 1 inch insulation from both ends of wire to be spliced.
- 3. Insert wires into casing splice and crimp tightly with pliers or a hammer and small iron bar.
- 4. Insulate with tape or use plastic and string, tie in place.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 11-3. Twist Wire Splice






Figure 11-4. Replacement Section; Twist Wire Splice



BALL POINT PEN METAL REFILL (FOR 12 AWG SIZE OR LESS)



EXPENDED CARTRIDGE SHELL CASING

Figure 11-5. Metal Casing Splice Repair

OPTION 6: Bolted Terminal Lug Splice.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •10 Minutes

MATERIALS/TOOLS REQUIRED:

- Wire Repair Kit (item 11, Sec 1, App B)
- Terminal Lugs
- Insulating Sleeve or Tape (App C)
- Screw or Bolt (App C)
- Nut (item 77, App C)
- Washer (item 168, App C)
- Solvent (item 1, App C)

PROCEDURAL STEPS:

1. Cut ties and work broken wire to the outside of the bundle.

- 2. Pull sufficient slack from the wire run toward the break so that there will be no strain on the splice.
- 3. Wipe wire clean with a clean, dry rag or a rag dampened with solvent.
- 4. Trim broken ends of wire and install an insulating sleeve over one end of the wire, and slide back and out of the way for now.
- 5. Strip both wire ends and crimp an insulated terminal lug of the proper size to each wire end.
- 6. Bolt terminal lugs together as shown in Figure 11-6.

- 7. Slide the insulating sleeve over the splice so that the ends of the insulating sleeve extend at least 3/4 of an inch beyond the ends of each terminal lug.
- 8. Secure both ends of the insulation with tie wraps or string ties as shown in the figure.
- 9. If a section of wire needs to be replaced, a double repair can be made to bridge the ends of the original wire back together, Figure 11-7
- 10. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 7: Metal Clamp Method.

LIMITATIONS: This is an emergency repair.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 10 Minutes




Figure 11-6. Bolted Terminal Lug Repair of Large Wires




Figure 11-7. Replacement Section; Terminal Lug Repair

MATERIALS/TOOLS REQUIRED:

• Wire Repair Kit (item 11, Sec I, APP B)
Screw Clamp, Control Cable Clamp
or Safety Wire
Insulating Sleeve or Electrical Tape

Knife . Solvent Cleaner (item 1, 76, or 167,


PROCEDURAL STEPS:

App C)

- 1. Cut ties and work broken wire to the outside of the bundle.
- ?. . Pull sufficient slack from the wire run toward the break so that there will be no strain on the splice.
- 3. Wipe wire clean with a clean dry rag.
- 4. Trim broken ends of wire.
- 5* Remove 2 inches of wire insulation from each end of the damaged wire.
- 6. Ram or push the two wire ends together so that the strands interlink.
- 7. Secure with screw clamp, control cable clamp, safety wire, or other suitable means, Figure 11-8.
- 8. Insulate with tape or insulation sleeve.
- 9. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 11-60 WIRE REPAIR SEGMENTS; UNSHIELDED WIRES.

GENERAL INFORMATION: The BDAR electrical wiring kit (item 11, Sec I, App B) has wire replacement segments for replacement sections up to 9 inches in length. The replacement sections are located in compartment B-12., in wire repair kit.

WIRE RAMMED TOGETHER



SCREW CLAMP OR EQUIVALENT

Figure 11-8. Ram Wire Repair <u>CAUTION</u>

Ensure aircraft power is off. Disconnect battery before touching any wires.

LIMITATIONS: This is a permanent repair.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 20 Minutes

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (item 11, Sec I, App B)
Crimp Tool
Insulation Sleeve or Tape
Replacement Section (Table 11-4)
Splice

PROCEDURAL STEPS:

1. Refer to instructions in wire repair kit.

TM 55-1520-210-BD ELECTRICAL AND AVIONICS SYSTEMS

- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 11-7. DAMAGED WIRE INSULATION.

GENERAL INFORMATION: If the wire insulation is damaged but the wire itself is not, repair of the Insulation may be accomplished by installing heat shrinkable tape, a transparent sleeve of flexible tubing, and securing with nylon braid or some other means.

CAUTION

Ensure aircraft power is off. Disconnect battery before touching wires.

OPTION 1: Heat Shrinkable Repair Tape.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Soldler
- 10 Minutes

MATERI ALS/TOOLS REQUIRED:

 Wire Repair Kit (item 11, Sec I, App B)
 Heat Shrinkable Tape
 Reflector (2 Types Elec Wiring Kit)
 Heat Gun/Heat Source

PROCEDURAL STEPS:

- Refer to instructions in wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Insulation Sleeve.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 10 Minutes

MATERIALS/TOOLS REQUIRED:

. Wire Repair Kit (item 11, Sec I, App B) -Knife Insulation Sleeving String, Nylon Braid, or Tie-Wraps

PROCEDURAL STEPS:

- 1. Remove damaged insulation and examine to ensure center conductor is not damaged.
- 20 Prepare a transparent sleeve of flexible tubing 1-1/2 times the outside diameter of the wire and 2 inches longer than the damaged portion of the insulation.
- 3. Split lengthwise and wrap 1-1/2 times around the wire at the damaged section.
- 4. Tie with string or other suitable material at each end and at 1 inch Intervals over the entire length, Figure 11-9.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 3: Tape Insulation.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- . 5 Minutes Per Wire

MATERI ALS/TOOLS REQUIRED:

. Wire Repair Kit (item **11,** Sec I, App B) Knife Tape, Electrical

PROCEDURAL STEPS:

1. Remove damaged Insulation and examine to ensure center conductor is not damaged.

INSULATING SLEEVING SPLIT LENGTHWISE AND TIED IN PLACE




Figure 11-9. Insulation Repair with Sleeving

- 2. Wrap tape over exposed center conductor of wire. Tape should extend 2 inches over the wire insulation at each end of the area to be covered.
- 3. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-80 SHIELDED CABLE REPAIR.

GENERAL INFORMATION: The following procedures may be used to repair severed shielded cables.

OPTION 1: Shielded Cable Splice.

LIMITATIONS: This is a permanent repair.

PERSONNEL/TIME REQUIRED:

1 Soldier 15 Minutes

MATERIALS/TOOLS REQUIRED:

•Wire Repair Kit (item 11, Sec I,
 App B)
 Crimping Tool
 Heat Gun
 Reflectors
 Sealing Sleeve (appropriate size)
 Splice (appropriate size)

PROCEDURAL STEPS:

Stri ppers

1. Refer to instructions in wiring repair kit.

2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Sheath Connector and Grounding Sheath.

LIMITATIONS: This is a temporary repair until heat shrink is installed, then it is a permanent repair.

PERSONNEL/TIME REQUIRED:

. 1 Soldier

•30 Minutes Per Wire

MATERIALS/TOOLS REQUIRED:

. Wire Repair Kit (item 11, Sec I, App B)
Insulating Sleeving, Heat Shrink or
Tape
Knife
Strung, Nylon Braid, or Tie Wrap
(to be used if insulating sleeve
is used)
2 Sheath Connectors
Grounding Sheath
Center Conductor Splice

- 1. Select a grounding sheath.
- 2. Prepare the severed ends of the cable for application of a grounding sheath as shown in Figure 11-10.

- Position sheath connector and grounding sheath as shown in Figure 11-10, step B. (NOTE: Crimp sheath connector and grounding sheath only at one side at this time.)
- Slide insulating sleeve over uncrimped sheath connector as shown Figure 11-10, step B. (NOTE: If insulating sleeve is not available, use shrink or alternate insulating material such as electrical tape.)
- Splice center conductor using a permanent splice or by using one of the slicing procedures in paragraph 11-6.
- Push the free end of the grounding wire into the uncrimped grounding sheath connector. Crimp securely, Figure 11-10, 5. Record BDAR action taken. When step C.
- If an insulating sleeve is used, slide into place and tie both ends, Figure 11-10, step D. If heat shrink is used, slide into place and shrink into position. If tape is used, use it to cover repair.
- Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 3: Pigtailed Sheath Method.

This is a temporary LIMITATIONS: repai r.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- •30 Minutes Per Wire

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (item 11, Sec I, App B) Kni fe Insulating Sleeving or Tape String, Nylon Braid, or Tie Wrap (to be used if insulating sleeve is used) Center Conductor Splice

PROCEDURAL STEPS:

- Prepare severed ends of cable for pigtail method of shield terminations, Figure 11-11, step A.
- 2. Splice center conductor, Figure 11-11, step B, using a permanent splice or by using one of the splicing procedures in paragraph 11-6.
- Use two splice connectors to add short length of insulated wire as extension to complete shield connection, Figure 11-11, step B.
- Insulate repair, Figure 11-11, step C.
- mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 4: Substitute Shielded Braid.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 30 Minutes Per Wire

MATERI ALS/TOOLS REQUIRED:


Wire Repair Kit (item 11, Sec I, App B) Substitute Shielded Braid Kni fe Center Conductor Splice Metal Screw Clamp, Sheath Connector, or Equivalent Shield Terminator


PROCEDURAL STEPS:

Prepare severed ends of cable for application of repair splice and

shielding, Figure 11-12, step A.













Figure 11-10. Shielded Cable Repair









COVER WITH VINYL SLEEVE AND TIE AT BOTH ENDS

Figure 11-11. Pigtail Method Repair



STEP A

STEP B






Figure 11-12. Substitute Shielded Braid Repair

2. Select suitable shielding material and slide over one end of severed cable. Shielding must be long enough to overlap the shielding on both sides of the cable being repaired after the center conductor is repaired. Shielding material can be obtained from another shield cable or ground cable material.

NOTE

It is essential that the shielding, as well as the inner conductor, be repaired properly to prevent electromagnetic interference (EMI) problems.

- 3. Splice center conductor using a permanent splice or by using one of the splicing procedures in paragraph 11-5 and Figure 11-12, step B.
- 4. Slide shielding material over repaired inner conductor and clamp at shielding overlap areas, Figure 11-12, step Co
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-9. SHIELDED CABLE REPAIR SEGMENTS.

GENERAL INFORMATION: The electrical wiring kit has wire replacement segments for replacement sections up to 9 inches in length. The replacement sections are located in compartments of wire repair Kit.

CAUTION

Ensure aircraft power is off. Disconnect battery before touching any wires.

LIMITATIONS: This is a permanent repair.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •1 Hour

MATERIALS/TOOLS REQUIRED:

•Wire Repair Kit (item 11, Sec I, App B) Replacement Section
 Stripper or Knife
 Splice
 Insulation Sleeve
 Crimp Tool

PROCEDURAL STEPS:

- 1. Refer to wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-10. SHIELD TERMINATORS.

GENERAL INFORMATION: The kit (item 11, Sec I, App B) contains various types of shield terminators for shielded cable.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 15 Minutes

MATERIALS/TOOLS REQUIRED:

•Wire Repair Kit (item 11, Sec I, App B)
Shield Terminator
Reflector
Heat Gun/Heat Source
Stripper or Knife
Insulating Sleeve

- 1. Refer to wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-11. TERMINATORS FOR NICKEL-PLATED SHIELDS (INCLUDING VERMILION).

GENERAL INFORMATION: The kit contains shield terminators for nickel-plated shields, including vermilion.

LIMITATIONS: This is a permanent Repair.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •15 Minutes

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (item 11, Sec I, App B)

PROCEDURAL STEPS:

- 1. Refer to wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-12. TERMINAL BOARDS.

GENERAL INFORMATION: The terminal boards provided are all five inches in length. They are located in wiring repair kit. They can be cut to shorter lengths using a hacksaw.

LIMITATIONS: Permanent repair.

PERSONNEL/TIME REQUIRED:

- •1 Sol di er
- Time will depend on the number of wires on the terminal board in question.

MATERIALS/TOOLS REQUIRED:

- Wire Repair Kit (item 11, Sec I, App B)
- Replacement Terminal Board

PROCEDURAL STEPS:

- 1. Refer to wire repair kit.
- **2.** Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-13. TERMINAL LUGS.

GENERAL INFORMATION: Terminal lugs are provided in the wiring repair kit (item II, Sec I, App B). They are located in compartments of wire repair kit. The general procedure for installing terminal lugs is as follows:

LIMITATIONS: Permanent Repair.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 10 Minutes Per Wire

MATERIALS/TOOLS REQUIRED:

•Wire Repair Kit (item 11, Sec I, App B) Strippers or Knife Replacement Terminal Lug Crimp Tool

PROCEDURAL STEPS:

- 1. Refer to wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-14. COAX SPLICE FOR RG-136/U AND RG-179B/U.

GENERAL INFORMATION: There are various coax splices in the wiring repair kit that may be used for the different types and sizes of coax cable.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 15 Minutes

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (item 11, Sec I, App B)
 Coax Splice
 Stripper or Knife
 Crimp Tool, AD-1377
 Reflector
 Heat Gun/Heat Source

PROCEDURAL STEPS:

- 1. Refer to wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 11-15. COAX SPLICE FOR RG-180B/U, RG-124/U, RG-142B/U, RG-302/U, RG-303/U.

GENERAL INFORMATION: There are various coax splices in the wiring repair kit that may be used for the different types and sizes of coaxial cable.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- 15 Minutes

MATERIALS/TOOLS REQUIRED:

PROCEDURAL STEPS:

- 1. Refer to wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system usng standard maintenance procedures.

11-16. COAX SPLICE FOR RG-9B/U, RG-214/U, RG-225/U, RG-393/U.

GENERAL INFORMATION: There are various coax splices in the wiring repair kit that may be used for the different types and sizes of coax cable.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- 1 Sol di er
- 15 Minutes

MATERIALS/TOOLS REQUIRED:

•Wire Repair Kit (item 11, Sec I, App B) Crimp Tool, AD-1377 Coax Splice Stripper or Knife Reflector Heat Gun/Heat Source

PROCEDURAL STEPS:

- Refer to wire kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 11-17. COAX SPLICE FOR RG-58C/U, RG-233/U, RG-59B/U, AND RG-71B/U.

GENERAL INFORMATION: There are various coax splices in the wiring repair kit that may be used for the different types and sizes of coax cable.

LIMITATIONS: This is a temporary repair.

PERSONNEL/TIME REQUIRED:

- •1 Sol di er
- •15 Minutes

MATERIALS/TOOLS REQUIRED:

.Wire Repair Kit (item 11, Sec I, App B)
Coax Splice
Stripper or Knife
Reflector
Heat Gun

PROCEDURAL STEPS:

- 10 Refer to wire repair kit.
- 2. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-18. COMPONENT BRIDGING.

GENERAL INFORMATION. Inmost cases it will be quicker not to replace bulkhead connectors, junction boxes, or terminal strips. These circuits can be repaired by "bridging" the damaged area with jumper wires spliced in to eliminate the damaged area or component, Figure 11-13.

LIMITATIONS. Temporary repair.

PERSONNEL/TIME REQUIRED:

. Will be dependent on the type of splice used.

MATERIALS/TOOLS REQUIRED:

. Wire Repair Kit (item 11, Sec I, App B)

PROCEDURAL STEPS:

- 1. Identify wires to be bridged together.
- 2. Splice wires and jumper wires together using one of the splicing techniques of this chapter.
- 3. Secure jumper wires after repair is made.
- 4. Record BDAR action taken. When mission Is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 11-13. Component Bypass

Section III. CONNECTOR REPAIR

11-19* DAMAGED CONNECTOR PINS.

GENERAL INFORMATION: Deformed, crushed, missing, or otherwise damaged connectors can be replaced or repaired. If a replacement connector is not available to replace a crushed connector, clean up fragments of the connector and use

jumper wires to bridge wire ends together. If only part of the connector has been damaged and there are unused pins/sockets on the connector which are undamaged, wires on both sides of the connectors can be moved to the unused good pins/sockets. Also, any available undamaged pigtails on the connector may be used.

TM 55-1520-210-BD ELECTRICAL AND AVIONICS SYSTEMS

OPTION 1: Replace Damaged Pins or Sockets; No Damage to Connector.

LIMITATIONS: Permanent Repair.

PERSONNEL/TIME REQUIRED:

•1 Sol di er

• 10 Minutes Per Wire

MATERIALS/TOOLS REQUIRED:

- •Connector Repair Kit (item 2, Sec I, App B)
- Wire Répair Kit (item 11, Sec I, App B)
 Replacement Pins/Sockets
 Insertion/Extraction Tool
 Knife

PROCEDURAL STEPS:

- 1. Remove damaged pins or sockets from connector.
- 2. Cut damaged pins or sockets off wire.
- 3. Strip wire ends.
- 4. Crimp wires to pin/sockets, Figure 11-14.
- 5. Insert the pins/sockets into the connector.
- **6.** Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Bridge Across Damaged Connector. Refer to paragraph 11-18, component bridging and splicing.


LIMITATIONS: Temporary repair.

MATERIALS/TOOLS REQUIRED:

 Wire Repair Kit (item 11, Sec I, App B)
 Wire splice
 Wire

PROCEDURAL STEPS:

1. Locate the damaged wire ends that go into connector.



CONNECTOR SOCKET

Figure 11-14. **Connector Pin and Socket**

- 2. Splice the appropriate wires together. The splice will bypass the connector.
- 3. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 3: Cannibalize Connector from Other Aircraft.

LIMITATIONS: None.

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (item 11, Sec I, App B)
 Replacement Connector with Pigtail
 Splices or Tape
 Knife

PROCEDURAL STEPS:

1. Obtain a replacement connector with a pigtail. (Replacement may be obtained from a crash damaged aircraft.) Cut pigtail so that splices can be staggered, Figure 11-15.

- 2. Remove damaged connector; stagger the wires being cut to remove the damaged connector. The staggered wires should match the staggered pigtail of the replacement connector of step 1, Figure 11-15.
- 4. Record BDAR action taken. When mission Is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 3. Splice the appropriate wires together.




Figure 11-15. Damaged Connector and Pigtail

Section IV. CIRCUIT OVERCURRENT PROTECTION DEVICES

11-20. CIRCUIT PROTECTION DEVICE REPAIR. LIMITATIONS: None.

GENERAL INFORMATION: Attempt to maintain a fused system at all times. Circuits with damage circuit breakers can be repaired by:

- a. Circuit breakers of the same rating salvaged from other non-flyable aircraft or removed from other non-essential circuits in the aircraft.
- b. Replacing circuit breakers with a specified number of solid wire strands (0.0039 inch diameter/No. 38 AWG). Solid wire strand can be made from a No. 26 AWG stranded wire.

OPTION 1: Salvaged Circuit Breaker Replacement.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •20 Minutes

MATERIALS/TOOLS REQUIRED:

- •Salvaged Circuit Breaker
- •Electrical Tape

- 1. Gain access to area behind circuit breaker panel by turning dzus fasteners counterclockwise.
- 2. Remove screws holding plastic face plate on circuit breaker panel.

- 3. Use pliers to remove nut and inside star lockwasher from damaged circuit breaker.
- 4. Use phillips screw driver to remove the two screws from the back of the circuit breaker.
- 5. Replace bad circult breaker with the salvaged circuit breaker.
- 6. Connect back of circuit breaker to line and bus bar by reinstalling the two phillips screws.
- 7. Place inside star washer and nut on front of circuit breaker and tighten with pliers.
- 8. Replace plastic face plate on front of circuit breaker panel with screws previously removed.
- 90 Clean and remove any debris from inside circuit breaker panel and close panel. Secure by turning dzus fasteners clockwise.

OPTION 2: Solid Wire Strands of No. 38 AWG as Circuit Breaker BDAR Repair.

LIMITATIONS: Emergency.

PERSONNEL/TIME REQUIRED:

- . 1 Soldier
- •20 Minutes

MATERI ALS/TOOLS REQUIRED:

•Wire Repair Kit (item 11, Sec I,
 App B)
 No. 8 Terminal Lugs
 1 Ft. of No. 26 AWG Wire (item 183,
 App C)

PROCEDURAL STEPS:

- **1.** Perform steps 1 thru 4 of option 1, and remove circuit breaker.
- 2. Identify the wires hooked to each circuit breaker.

- 3. Determine amperage of damaged cir-cuit breaker(s) to be replaced.
 (Amperage is printed on the end of reset button.)
- 4. Use Table 11-3 to determine number of 'strands of No. 38 AWG wire needed to replace damaged circuit breaker.
- 5. Strip No. 26 AWG wire, select number of No. 38 AWG wire strands (6 to 8 inches long) as per Table 11-3. Save insulation and cut into 1 inch lengths (one length for each fuse 1 ink required).

Table 11-3	Fuse[Link
CIRCUIT BREAKER AMPERAGE	AWG SIZE WI RE	NO. OF STRANDS
112A 1A 2A 3A 4A 5A IOA* 15A* 20A*	NO. 38 NO. 38 NO. 38 NO. 38 NO. 38 NO. 38 NO. 38 NO. 38	1 1 1 2 2 5* 7* 1 0 *

* Signifies Extrapolated Values

6. Cut line side wire 1 inch from terminal lug; strip both ends and crimp an 8-32 terminal lug where wire was cut and stripped.

NOTE

Try to use inner strands of wire that are not cut or nicked by knife used to remove insulation.

- 7. Twist the No. 38 AWG strands of wire, from step 5, together and insert the end of line side of terminal lug, wrap and twist as shown in Figure 11-16. Slip 1 Inch piece of Insulation over No. 38 AWG strands of wire. Insert the other end of No. 38 AWG strands of wire into the other terminal lug (supply side), pull tight against the piece of insulation and twist tight, Insulate bare end of terminal lugs on both sides of 1 Inch piece of insulation with tape. Use 8-32 screw to connect other terminal lug to bus side of bus bar.
- 8. Use this procedure to replace damaged circuit breaker.
- 9. Secure fuse link to other wiring with tape to avoid pinching wire when circuit breaker panel Is closed.
- 10. Clean up damaged area behind circuit breaker panel to remove debris, and use tape to insulate any damaged parts that might cause electrical shorts.
- 11. Carefully close circuit breaker panel and secure by turning dzus fasteners clockwise.

12. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-210 BROKEN FUSES.

GENERAL INFORMATION: If a fuse is broken, It may be replaced by another fuse or a piece of solder or wire. A replacement fuse must be of the same physical size. It should be of the same current rating and type, fast blow, or slow blow. Where the same current rating fuse is not available, one as close to proper as possible should be used. A slow blow fuse could be replaced by a fast blow fuse of higher current rating while a fast blow fuse could be replaced by a slow blow fuse of lower current rating. The solder or wire should be used only when no fuse Is available.

CAUTION

If the fuse Is blown, the same procedure can be used but the cause of the fuse blowing must be fixed. Substituting for the fuse without fixing the cause of blowing can cause more damage to the fused equipment.




Figure 11-16. Construction of Fuse Link

LIMITATIONS: If too low a current rating fuse is used, it will blow from the turn on surge current. If too high a current rating fuse or if the solder or wire is used, the equipment will not be properly protected in case of a short circuit and could be destroyed. The decision to use a high current rating fuse, solder, or wire should be made by the commander.

OPTION 1: Sal vaged Fuse Replacement.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

Spare Fuse

PROCEDURAL STEPS: Replace fuse with the following steps in order.

- **a.** An identical spare fuse from other equipment.
- b. An identical fuse from the other equipment of lower priority.
 - c. A similar fuse.

OPTION 2: No. 38 AWG Strands (0.0039 in. diameter as Fuse BDAR Repair.

LIMITATIONS: Emergency.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- 1 Hour

MATERIALS/TOOLS REQUIRED:

- •Wire Strand NO. **38** AWG Wire (item 183, App C)
- •Small Dowel, Stick, or Piece of Pencil. Electrical Tape (item 154, App C)

- 10 Remove damaged fuse.
- 2. If type A fuse, break off glass of ceramic part and salvage end caps. If type B fuse, break off clear top portion.

- 3. For type A fuse, cut wire, and dowel, stick or pencil piece to proper length. Refer to Table 11-3 to determine the number of No. 38 AWG wire to use for the different site, amperage, and fuses. See Figure 11-17 for fuse assembly and assemble as follows:
 - a. Lay wire piece between caps.
- b. Trim dowel, stick or pencil piece as necessary to fit into end caps, and hold wire in place. **This** stiffens the substitute fuse.
- c. Wrap dowel, stick or pencil piece and wire with electrical tape, but do not cover end caps.
- 4. For type B fuse, connect substitute No. 38 AWG wire from point A to point B, Figure 11-18. Use Table 11-3 to determine the number of No. 38 AWG strand to use between points A and B for different size, amperage, and fuses.
- 5. Install fuse into equipment.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 11-17. Fabricated Fuse, Type A




Figure 11-18. Fabricated Fuse, Type B

Section V. BUS BARS

11-22. POWER BUS BAR REPAIR.

GENERAL INFORMATION: Rigid bus bars are used in the power distribution circuits of the aircraft. Replace damaged bus bars with aluminum or brass strips of the same or higher cross-sectional area.

OPTION: Fabricate Bus Bar.

LIMITATIONS: Repaired bus bars will have a somewhat higher resistance than the original circuit and a higher than normal voltage drop may occur. This is a temporary repair.

PERSONNEL/TIME REQUIRED:

ž2 Soldiers

• 2 Hours

MATERI ALS/TOOLS REQUI RED:

- •Drill & Bit Set (item 67, Sec II, App B)
- •Nuts, Bolts, Flat Washers, Lock Washers (App C)

žTape (item 154, App C)

- •Files (items 80-88, Séc II, App B)
- Hacksaw (item 94, Sec II, App B)

- 1. Cut a section of another bus bar or piece of aluminum scrap to use for splice.
- 2. Drill matching holes in bus bar sections and splice, Figure 11-19.
- 3. Remove insulation from bus bar only where needed. Ensure contact surfaces of cracked bus bar and splice are smooth, and clean to reduce resistance. If necessary, use file and wire brush to dress and prepare contact surfaces.
- 4. Install bolts and washers and tighten. Ensure no contact of bolts with aircraft structure.
- 5. Insulate repair with tape or slit a piece of insulating tubing. Wrap it around the repair and tie it with string.
- 6. Same repair procedure can be used to lengthen bus bars, Figure 11-20.

7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

11-23. BATTERY BUS BAR REPAIR.

GENERAL INFORMATION: Nickel-Cadmium (Ni-Cad) consists of a number of cells connected in series. Damage to a cell which does not result in destruction of the battery may be repairable. This procedure gives instructions for locating and removing bad Ni-Cad battery cells and creating a bus bar jumper around the bad cell.

WARNING

Ni-Cad batteries use potassium hydroxide, a strong caustic alkali, as the electrolyte. Do not get this electrolyte on your skin or in your eyes. Use rubber gloves, rubber apron, and protective goggles when handling the electrolyte. If accidental contact with the electrolyte is made, use ONLY clean water and immediately (seconds count) flush contaminated areas. Conti nue flushing with large quantities of clean water and get medical attention as soon as possible.




Figure 11-19. Splicing Bus Bars




Figure 11-20. Lengthening Bus Bars

WARNING

Cell temperature should never exceed 120°F - 130°F. If steam or spewing electrolyte is observed or the battery is hot to the touch, <u>DO NOT</u> attempt to remove from the aircraft.

CAUTION

Penetration of battery case by small arms fire or shrapnel may cause thermal runaway. The battery cells will overheat and rupture, melt, or explode. Exercise extreme caution when repairing damaged battery.

OPTION: Jumper Cells.

LIMITATIONS: Some loss of battery voltage (1.25 to 1.50 V dc per cell removed) and amperage.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 30 Minutes

MATERIALS/TOOLS REQUIRED:

- Multimeter with Leads (item 10, Sec I, App B)
- Rubber Gloves
- Protective Goggles
- •Rubber Apron
- •Torque Wrench (items 270-272, Sec II, App B)
- •Gauge Wire and Terminal Lugs

PROCEDURAL STEPS:

- 1. Disconnect battery and remove from aircraft if necessary.
- **2.** Release snap fasteners and remove cover.
- 3. Use a multimeter to measure voltage across each cell. Normal readings should be 1.25 to 1.5 V dc per cell.

Remove cells that are dead. For engine cranking loads, cell voltages as low as 0.6 V dc are acceptable. Also, remove any damaged, cracked, or extremely hot cells leaking or spewing electrolyte.

WARNING

Be extremely careful when removing or 'installing battery cells. Bodily injury and equipment damage may result if any metal tools or parts accidentally cause a short circuit.

- 4. Remove bad cells, loosen and remove terminal screws. Remove washers and and terminal links. To remove individual cells, screw terminal screws back into each cell terminal, grasp these screws with pliers and lift the cell straight up.
- 5. After removing bad cells, prepare jumper from 1 foot of No. 4 AWG and two terminal lugs. Remove 1/2 inch of insulation from one end of wire and crimp terminal lug on stripped end of wire. Measure and cut wire to needed length, strip 1/2 inch of insulation and crimp terminal lug to other end of wire.
- 6. Install jumper across removed cells in place of terminal links. Cells are connected in series (positive to negative, Figure 11-21.
- 7. Torque terminal screws (10-32) to 35 to 50 inch-pounds, or terminal screws (8-32) to (20 to 25) inch-pounds. If torque wrench is not available, tighten firmly with wrench or pliers.
- 8. Replace cover and install battery in aircraft.
- 9. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 11-21. Battery, Storage BB-433/A Cell Layout

Section VI. POWER RELAYS

11-24. POWER RELAY TEST AND REPAIR.

GENERAL INFORMATION: Use the following procedures to check power relays for malfunctions.

OPTION 1: Check Power Relay for Malfunction.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •5 Minutes

MATERIALS/TOOLS REQUIRED: **Ž**Multimeter (item 229, Sec II, App B)

PROCEDURAL STEPS:

- 1. Check for 28 V.DC at terminal XI, if voltage is not present, input power wire is open.
- 2. Check for 0 V.DC at terminal X2. If 0 V.DC is present, its alright. If 28 V.DC is present, the ground wire is open.

3. If 28 V.DC is present at X_2 , check for voltage ON AI & A2, B1 & B2, etc. If voltage is present on AI, but not on A2 (for example), the relay is bad and must be replaced.

OPTION 2: Salvaged Power Relay Installation.

NOTE

Identical P/N or NSN (Figure 11-22) denotes interchangeability. If damage is extensive, salvaged relays may be difficult to attach to bulkheads.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

Ž 1 Soldier

•30 Minutes

MATERIALS/TOOLS REQUIRED:

•Sal vaged Power Relay

PROCEDURAL STEPS:

- 1. Obtain salvaged power relay.
- 2. Disconnect battery.
- 3. Remove damaged power relay as follows:

NOTE

Note the position of wires/bus bar and what terminals they are connected to.

- a. Remove attaching hardware, wires, and bus bar.
- b. Remove attachment bolts, and lift relay free from compartment.
- 4. Position salvaged power relay, and install mounting hardware.
- 50 Install wires and bus bar on correct terminals and secure with hardware.

OPTION 3: Creating a Jumper for Damaged Power Relays.

LIMITATIONS: Emergency repair. No control over jumpered power relays, circuit cannot be turned on or off.

CAUTION

- •DO not jumper battery relay on any aircraft.
- •This procedure is to be used only for one time emergency evacuation and recovery of UH-1 helicopters.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- Ž 20 Minutes

MATERIALS/TOOLS REQUIRED:

Wire Repair Kit (item 11, Sec I, App B)
 Appropriate Size Aircraft Type Wire Appropriate Size Terminal Lugs

PROCEDURAL STEPS:

- 1. Disconnect battery.
- 2. Figure 11-23A and 11-23B, shows two typical power relay configurations with jumper. This may be used as an aid in performing steps 3 thru 7.

NOTE

Use wire with the same gage or larger than the one being replaced.

- 3. Prepare a jumper wire, (A 1/2 to 1 foot length of appropriate size wire with appropriate size terminal lugs crimped on each end.)
- 4. Locate terminals marked Al and A2 on power relay. Power relay terminals should be marked on case of relay. If markings are illegible, Al and A2 terminals will be the ones with the largest diameter terminal studs.
- 5. Remove hardware from terminals Al and A2.
- 6. Install jumper from terminal Al to terminal A2. Reference Figures 11-23A and 11-23B.
- 7. Install hardware on terminals Al and A2. Tighten hardware to hold jumper in place.
- 8. Remove jumper as soon as emergency evacuation flight is completed.
- 9. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Helicopters Serial No. 66-746 Through 66-17144

DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	FUNCTI ON
K1 K2 K3 K4 K5 K6 K7 K8 K9 K10 K11 K15 K22 K23 K24 K27 K35 K36 K46 K46	MD24171D1 MD24171D1 MD24172D1 MS24568D1 AN3025-300 RE200 MS25457 MI LR7611TYPEMA1 MS24171D1 MS24149D1 MS24149D1 MS24149D1 MS24166D1 AN3025-300 MS24149D1 MS24149D1 MS24166D1 MS24171D1 MS24166D1 MS24166D1 O2A3-12HC2-0030 MS24171D1 205-075-137-5	Relay, Ext. Power Relay, Non-Ess Bus Relay, Starter Relay, Bus Cont. (Gen Fail) Relay, Reverse Curr. (Main) Relay, Overvoltage Relay, Gen Field Relay, AC Failure Relay, Battery Relay, Fuel Transfer Relay, Lockout Cabin Heater Relay, Standby Gen. Field Relay, Heater Purging Relay, Standby Gen. Rev. Curr. Relay, Cargo Hook Release Relay, Inverter Relay, Hoist Power Relay, Main Invtr. Power Relay, Spare Invtr. Power Relay, Overheat Relay, Battery Aft Location Relay, Battery Feeder

Figure 11-22. UH-IH/V Relay Location




Figure 11-23. Block Diagram, Typical Power Relays

Section VII. ANTENNAS

11-25. GENERAL. This section contains expedient repair procedures to restore lost antenna.

WARNING

Avoid contact with expedient antennas. Bare wires could cause severe burns and electrocution hazard.

11-26. SUBSTITUTE EMERGENCY ANTENNA.

GENERAL INFORMATION: This procedure gives instructions for construction of a replacement antenna that can be used to transmit and receive radio messages on all FM radios on UH-IH/V helicopters.

OPTION: Fabricate Emergency Antenna.

LIMITATIONS: Some loss of antenna gain and radio transmitter power.

PERSONNEL/TIME REQUIRED:


•1 Soldier Ž 1 Hour

MATERIALS/TOOLS REQUIRED:

- . Cable, Coax RG-58U or Other Available Coax
- Tape, Elec (or equivalent)
- Resistor, Carbon, 1 Watt 51 Ω ±5%
- •Wire Repair Kit (item 11, Sec I, App B)

- 1. Determine length of wire needed for the radiating element by using Figure 11-24. Example:
- **Ž**FM radio with frequency range of 30 to 69.95 MHz.
- **ž**Center of frequency range is 50 MHz.
- **Ž**Using Figure 11-24, look under frequency column for 50 MHz on the wave length side of the Table, 6 M is shown.

- **Ž**I Jse Figure 11-24 to convert meters to feet. Six meters multiplied by 3.280 = 19.68 feet for one wave length.
- **Ž**Divide the one wave length by 8, for a 1/8 wave length antenna, $\frac{19.68}{8}$ = 2.46
- feet. Multiply the 1/8 wave length by a 0.95 correction factor: 2.46 ft. X 0.95 = 2.34 feet. This is the length of the radiating element.
- 2. Cut the coax cable to the length of the required radiating element. Remove the outer insulation and shield from the piece of coax cable and then strip a 1 inch piece of insulation from each end exposing the center conductor, Figure 11-25.
- 3. Wrap and solder the 51 Ω resistor to one end of the radiating antenna element as per Figure 11-25. This completes the fabrication of the emergency antenna.
- 4. Next, open the access panel door on the right-hand side just forward of the tail boom, Figure 11-26. The location of antenna coax lead may be found on other location of aircraft. The emergency antenna is a generic fix for FM radios ARC-54, ARC-131, and ARC-114.
- 5. At the tail boom quick disconnect, locate coax cable marked ARC 114-105A and disconnect it.
- 6. Cut the coax connector off the antenna coax and prepare a 4 inch pigtail termination on the end of the coax cable as shown in Figure 11-27.
- 7. Pass the radiating element of the antenna, from step three, with the resistor end down into the drain hole in the bottom of the tail boom where it joins the fuselage, Figure 11-26.
- 8. Twist join the center conductor from the radiating element of the antenna to the center conductor of the coax. Make a good mechanical joint and insulate with tape.






Figure 11-26. Installation of Field Expedient Antenna




Figure 11-27. Pigtail Termination for Shielded Wire

- 9. Ground the pigtail from the coax antenna by wrapping and twisting it around the plug where the coax was disconnected. A ground strap at the bottom of the bulkhead, Figure 11-26.
- 10. Secure with tape to hold the antenna and coax in place inside the tail boom. Let the antenna dangle free through bottom of helicopter.

NOTE

Antenna must be at right angle (90°) to aircraft skin to radiate R.F. energy. Do not tape antenna to skin of aircraft.

- 11. Solder a one to two ounce weight, below the 51 Ω resistor as shown in Figure 11-25 to make it hang down.
- 12. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

CHAPTER 12

FUEL SYSTEM

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

12-1. SCOPE.

- a. The fielded UH-IH/V is equipped with a crashworthy fuel system which is designed to resist fuel spillage and reduce fire hazards. It incorporates self-sealing tanks and self-sealing breakaway valves in the fuel supply and vent lines, Figure 12-1. Breakaway fittings are designed to break between self-closing valves if a crash occurs. The fuel supply consists of five interconnected cells which act as a single tank, Figure 12-1. Three cells are located below the engine deck with the filler cap on the right cell. The two forward cells are located under the cabin deck and are gravity fed from the aft cells. Both forward fuel cell sump assemblies contain electrically or pneumatic driven boost pumps.
- Fuel is delivered under pressure from the pump to a check valve manifold on the front of the engine forward firewall out through an electrically controlled shut-off valve to the main fuel filter then to the engine at the fuel control. The fuel shut-off valve and the check valves in the manifold have internal bypasses to relieve pressure produced by thermal expansion of trapped fuel when the system is inoperative. The fuel pressure transmitter is attached to the check valve manifold. Figure 12-1 shows a perspective layout of the fuel system. Figure 12-2 is a schematic flow diagram.

- c. Self-sealing fuel cells which have a 50 caliber ballistic protection level seal by the swelling of the sealant when exposed to fuel. When the projectile penetrates the cell wall, the fuel causes the sealant to swell closing the damage hole.
- d. Because the fuel cells are interconnected if one of the fuel cells, drain valves, or interconnect lines is damaged and cannot self-seal, all the fuel in both the forward and aft cells may eventually leak out. BDAR fixes to this area are generally confined to component replacement, expedient line repairs, or isolating damaged subsystems. Damage to fuel systems may require refueling to replace fuel lost by leaks and/or defueling.
- e. If a fuel system component such as a fuel cell, pump, module, valve, etc. is damaged and component still operates satisfactorily and does not leak, repair may be deferred. The component, however, should be inspected after every flight to assure that operation has not been degraded or that a leak has not developed.
- f. Fuel system hoses and tubes. If leaks develop as a result of such damage and time and resources are not available for standard repair procedures, use the BDAR fixes in this TM.




Figure 12-1. Fuel Cell Installation - Crashworthy




Figure 12-2. Fuel System Schematic

12-2. **ASSESSMENT PROCEDURES.** No specific assessment procedure Is needed to locate damage fuel cells, components, or leaking fuel lines. Use Figures 12-1, 12-2 and 12-3 to guide you In locating and identifying damaged areas and leaks. The replacement of damage components should be per TM 55-1520-210-23.

12-3. REPAIR PROCEDURE INDEX.

	PARA.
Fuel Line Replacement Metal Tube Replacement	12-4 12-4
Hose Replacement	12-4
Metal Tube Repairs	12-5 12-6
Fuel Cell Replacement Bypass.	
Fuel Cell Repairs	12-9 12-10

Table 12-1. Assessment Procedures

ITEM/ACTION FAULT ISOLATION BDAR REF. VISUALLY INSPECT Damage found to Fuel System -fuel cells......Para 12-7 -hoses and tubes......Para 12-4 Determine if damage is.... Continue visual repairable by deferrable inspection -BDAR repair..... Para 12-3 -bypas's & isolation Para 12-3

Section II. FUEL LINES

12-4. GENERAL.

a. Fuel Lines.

- (1) Replacement fuel lines need not be routed along the path of the original installation. They may be routed along any convenient path as long as they do not interfere with personnel or with operating equipment. Long lines and hoses should be clamped or fastened with tape to hard supports at convenient intervals not exceeding two feet.
- (2) Fuel system metal tubes and rubber hoses.
- (a) All the fuel system tubes and hoses on the UH-1, their sizes, and lengths are identified by item number in Figure 12-3.
- (b) Damaged tubes will normally be replaced with hose assemblies from BDAR kit or with a salvaged/cannibalized tube of same ID. The length can be longer.
- (c) If hose assemblies from BDAR kits are not available, damage may be cut out and replaced with a small section as shown by BDAR repairs (refer to repair procedures), or a replacement hose may be manufactured if a long enough hose section and MS fittings are available (refer to repair procedures in TM 55-1520-210-23).
- (d) Never discard MS fittings, they are reusable. The MS21922 sleeve is not reusable.

12-5. METAL TUBING, DAMAGED.

OPTION 1: Rubber Hose Coupling and Hose Clamps Repair, Figure 12-4.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

. 1 Soldier


Ž 1 Hour

MATERIALS/TOOLS REQUIRED:

- •Safety Wire or Equivalent (items 73-75, App C)
- •4 Hose Clamps AN737 (items 37-42, App C)
- •5-Minute Epoxy Sealant (item 4, App C)
- Fluid Line Repair Kit (item 4, Sec I, App B) Hose

PROCEDURAL STEPS:


- 1. Cut and remove damaged area of metal tube.
- 2. This step is optional. If time permits, make an improvised bead as shown in Figure 12-4 by wrapping wire around the metal tube four to eight turns. Coat the wire with epoxy and let cure 5 to 10 minutes. Make the epoxy bead as smooth as possible.
- 3. Select a piece of rubber hose that will fit snug to tight over the tubing ends. Cut to length so that it will extend 1-1/2 to 2 inches over tubing ends.
- 4. Apply 5-minute epoxy adhesive on the tube ends being careful not to contaminate the inside of fuel line, Figure 12-4. Quickly push rubber hose on ends of tube and secure with four (each) hose clamps. Let joints cure 10 minutes.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.



INDEX	PIN	NOMENCLATUR	NOM E OD	WALL THI CKNESS	MIN LENGTH	
17 20 14 20 8 20 10 M 11 20 9 M 4 20 5 20 1 M 3 M 2 20 12 M 7 20 16 M 13 20	05-060-690-1 05-062-662-1 05-062-663-1 05-062-650-9 S87028H280C 05-061-655-1 S87028K146A 05-062-650-13 05-062-650-11 S87028K214A S87028K292A 05-060-695-1 S87028E216A 05-060-697-1 S8000G180C 05-060-696-1 05-060-696-1	Tube Assy¹ Tube Assy¹ Tube Assy¹ Hose Assy³ Hose Assy² Hose Assy³ Hose Assy³ Hose Assy³ Hose Assy³ Hose Assy² Tube Assy² Tube Assy Tube Assy Tube Assy Tube Assy Tube Assy Tube Assy Tube Assy	3/8 3/8 3/8 1070 1/2 3/8 3/4 1.70 1.70 3/4 3/4 1/4 3/8 3/8	0.035 0.035 0.035 0.062 0.035 0.067 0.067 0.067 0.035 0.031 0.035 0.040 0.035 0.035	46. 0 9.0 30.0 33.7 28.0 28.0 14.7 15.3 14.1 21.5 29.2 38.0 21.7 49.0 18.0 35.5 35.5	

- Tube = AL alloy 5052-0
 Hose = Rubber MIL-H-83797
 Hose = Self-sealing (crashworthy) coated hose


Fugure 12-3. Fuel System Hose/Tube Installation (Sheet 1 of 4)



INDEX	PIN	NOMENCLATURE	NOM OD	MIN LENGTH
24 21 18 19 23 25 22 20	205-062-698-1 70-010L000G056 205-062-698-3 205-062-650-1 205-062-650-5 205-062-650-3 205-062-697-3	Hose Assy ³ Hose Assy ³ Hose Assy ³ Hose Assy ³ Hose Assy ³ Hose Assy ³ Hose Assy ³	3/4 3/4 1/4 1.70 1070 3/4 1.85 3/4	14. 3 5. 7 12. 6 22. 2 16. 5 12. 1 11. 5 9. 0


- Tube = AL alloy 5052-0
 Hose = Rubber MIL-H-83797
 Hose = Self-sealing (crashworthy) coated hose

Figure 12-3. Fuel System Hose/Tube Installation (Sheet 2 of 4)



INDEX	PIN	NOMENCLATURE	NOM OD	WALL THI CKNESS	MIN LENGTH
31 32 27 30 29 28 26 33*	MS87028H090A 205-062-666-1 MS87028J336C 646121-6D0280 MS8000G070C MS8000G130A MS87028H110C 205-061-668-1	Hose Assy Hose Assy Hose Assy Hose Assy Hose Assy Hose Assy Tube Assy	1/2 1/2 5/8 . 55 3/8 3/8 1/2 1/2	0. 062 0. 063 0. 210 0. 040 00040 0. 062 0. 035	9. 0 20. 7 33. 7 28. 0 7. 0 13. 0 11. 0 12. 0

Figure 12-3. Fuel System Hose/Tube Installation (Sheet 3 of 4)



INDEX	PIN	NOMENCLATURE	NOM OD T	WALL HICKNESS	MIN LENGTH
40 38 36 39 37 34 35	MS87028H175A 205-062-666-1 MS87028J336C 646121-6D0280 MS8000G090C MS8000G130A MS87028H110C	Hose Assy Hose Assy Hose Assy Hose Assy Hose Assy Hose Assy	1/2 1/2 5/8 3/8 3/8 3/8 1/2	0. 062 - 0. 063 0. 040 0. 040 0. 062	17 5/8 20. 7 33. 7 28. 0 9. 0 13. 0 11. 0

Figure 12-3. Fuel System Hose/Tube Installation (Sheet 4 of 4)




Figure 12-4. Hose and Clamp Fuel Tubing Repair

OPTION 2: Metal tubing; long damaged sections can be replaced with a metal tube spliced in place at both ends by two rubber hose external couplings. Use the procedural steps in option 1 to install these two couplings. Also, see Figure 12-4.

OPTION 3: Metal tubing; small hole damage can be repaired as follows:

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- 30 Minutes


MATERIALS/TOOLS REQUIRED:

- . Adhesive (item 4, App C)
- Hose Clamps (item 37-42, App C)
 Hose Piece or Other Rubber Patch Material (items 115-117, App C)
- •Sheet Metal , 1/32 Aluminum (item 131, App C)

PROCEDURAL STEPS:

1. Use a piece of rubber hose or other hard rubber material, and cut a patch to fit over the hole. The patch should be as large as possible. If a piece of hose is used, cut it lengthwise.

- 2. Place the patch centered over the hole. If a piece of hose is used, install the hose over the hole with the split opposite the hole.
- 3. Place a hose clamp over the patch, center it and secure in place tightly. The hose clamp band width should be twice as wide as the hole. If hole is very large, apply a piece of 1/32 aluminum sheet metal over the rubber patch. Use either one or two hose clamps to secure tightly in place.
- 4. Five minute adhesive epoxy can be used to adhere rubber patch and sheet metal backup. Clean area to be joined with solvent cleaner.
- 5. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.
- 12-6. RUBBER HOSE, DAMAGED. All high pressure hose repairs will be repaired by replacing per TM 55-1520-210-23. Fluid line repair kit (item 4, Sec I, App B) will be used to make up repair lines.






Figure 12-5. Damaged Hose Repair

Section III. FUEL CELLS

12-7. GENERAL.

- a. The BDAR helicopter repairs listed in this section are for repairing leaks that go beyond the self-sealing capability of crashworthy fuel cells and/or to isolate and bypass damaged fuel cells. The repairs are given in time to accomplish the repair, but not the time required to gain access to the damaged area.
- b. Because of the size, location, plumbing connections and the specific fuel cell affected, the time to gain access to the damaged area can vary considerably. The trained assessor will determine if the conditions warrant deferring the repair, bypassing the damage fuel cell, or repairing. It is not the intent of this section to detail the steps in gaining access to the fuel cell repair area. Information on skin, panels and structure removal can be found in TM 55-1520-210-23 and TM 55-1500-204-25/1.
- c. The BDAR repairs may limit or restrict the operational capability of the helicopter to a one-time flight, mission completion flight, or self-recovery flight. Further, the repairs specified will not necessarily return the tanks to their original self-sealing and crash resistant level.
- d. The UH-1 crashworthy fuel cells are designed to resist catastrophic fuel loss in case of a crash. They are also self-sealing to penetration damage of a normal (nontumbling) 0.50 caliber API or smaller projectile.
- e. Damage caused by a fully tumbled 0.50 caliber projectile or any other cause which will leave a damaged area 1 X 3 inches in rectangular area (or exceeds this area) is not allowed.

12-8. FUEL CELL, DAMAGED BEYOND REPAIR. If a fuel cell is severely battle damaged and there is no replacement for it, then alterations should be made to the system to isolate and bypass the damaged cell. For other repairs to fuel cells, see paragraph 12-3, repair procedure index.

LIMITATIONS:

- 1. The helicopter's center of gravity may be changed after the removal/isolation of any one or more of the fuel cells due to non-semetry and unbalanced fuel load. See Table 12-2 and Figure 12-6. Also, consult TM 55-1520-210-10, UH-IH/V Helicopter Operator's Manual.
- 2. The fuel supply will be reduced, Table 12-2.
- 3. The pilot must adjust mission configuration equipment according to existing mission needs and overall helicopter flight degradation.

PERSONNEL/TIME REQUIRED:

- •2 Soldiers
- •3 Hours

MATERIALS/TOOLS REOUIRED:

- •Bolt (item 14, App C) & Nut (item 77, App C)
- •Bolt (item 15, App C) & Self-Lock Nut (item 84, App C)
- •Cap Fitting (item 4, Sec I, App B)
- •Drill Motor & Drill Bit Set (item 67, 69, Sec II, App B)
- Knife and Scissors (item 118, 161, Sec II, App B)
- •Rubber Gasket Material (item 117, App C)
- •Sealant (item 10, App C)
- •Washer, Flat (item 168, App C)

PROCEDURAL STEPS:

1. Defuel the helicopter's fuel system per paragraph 12-9, procedural step No. 1.

	Table 12-2.	Weight & Bala	ance Compu	utation Dat	a for Fuel Cel	ls APPROX
FUEL CELL	APPROX QTY US GAI	APPROX AREA TANK BOTTOM SQ IN	APPROX WT JP4 LBS	APPROX STA CTR OF CELL	LONGI TUDI NAL MOMENT 1100	LATERAL MOMENT 1100
R/H Fwd L/H Fwd R/H Aft L/H Aft Ctr Aft TOTAL	38.5 38.5 32.5 32.5 64 206.0	1242 1242 304 304 588	250 250 211 211 416 1338	130 130 177 177 168	325 325 373 373 699	63 63 57 57 0
90 ————————————————————————————————————	FUEL TANK	FUS STA 117.50 LEVELING PLATE				£ SHIP
8	NOSE PILOT-	100 150 21	241 GINE		AILBOOM	500 55
150 —	STA 0.0	FUS STA 133.5	₩ L 134.5 HUB &	INTERSECTION MAST	W L 137.5	
50 22 W L 0 7.6 IN.		FWD JACK PADS (ST.	AFT	a 243.89 DACK PADS (STA 23 DEL CELLS HI	11.58) GHLIGHTED BY C	ROSS HATCHIN

Figure 12-6. Fuel Cell Location and Approximate Arm as Compared with Center of Gravity

TM 55-1520-210-BD

FUEL SYSTEM

- 2. Remove access panels as necessary to gain access to the crossover lines, and the top or the cells.
- 3. Isolate fuel cell A or C of Figure 12-7 as follows. Procedures are listed for cell A and are the same for cell C.
 - a. Blocking Off Hose (3), Flange (2).
- (1) Remove four screws (1) from hose adapter flange (2) of the gravity feed hose (3) which is connected to check valve (4).
- (2) Fabricate cover (5) from a piece of sheet metal or other plate material to fit over the face of adapter flange (2), Figure 12-7.
- (3) Drill four holes 1/4 inch diameter to match holes in adapter flange (2). See detail C.
- (4) Make a gasket (6) from rubber material or from the isolated cell to the same size as the flange (2) and Cover (5). Punch, drill, or cut holes for the bolts.
- (5) If avallable, apply fuel resistant adhesive sealant between rubber gasket (6) and facing adapter flange (2)₀
- (6) Position bolts of sufficient length to reach through flange (2) and (5) Place rubber gasket (6) on bolts (7). Place cover on bolts (7).
- (7) Secure with four flat washers (8), four lockwashers (9), and four nuts (10). A locknut may be used. Torque to 20-30 inch-pounds. Secure the hose with adhesive tape to a fixed object so as to prevent it from bouncing around.
 - b. Blocking Off Crossover Port (11).
- (1) Gain access to the crossfeed port (11) through the center cell (cell B) aft access cover (17) by removing 24 bolts and washers (18, 19), and removing access cover (17).

- (2) Remove four bolts (16) from crossfeed port (11).
- (3) Make a cover (12) for the crossfeed port (11) in accordance with Figure 12-7, detail B.
- (4) Make a gasket (13) from rubber material or from the isolated cell to the same size as the cover (12) as per Figure 12-7, detail B.
- (5) If available, apply fuel resistant adhesive sealant to both sides of rubber gasket (13).
- (6) Position Lockwashers (15), then flat washers (14) on the bolts (16) of sufficient Length to ensure a minimum of three full threads of contact in nuts or threads.
- (7) Place bolts through holes in cover (12). Place rubber gasket (12) on bolts (16).
- (8) Position over crossfeed port (11) and tighten bolts to 20-30 inchpounds.
- (9) Replace access cover (17) with 16 bolts and washers (18, 19).
 - (10) Refuel aircraft.

NOTE

Refueling must be accomplished slowly to allow cell C to fill through the gravity feed lines.

- c. Blocking and Isolating Cell B. See Figure 12-8 for index numbers.
- (1) Disconnect the No. 12 B-nut hose fitting (1) from both gravity feed lines (2). See detail A, Figure 12-8.
- (2) Plug hose fitting with a 12 AN plug fitting.
- (3) Blocking of both crossover ports will be accomplished by paragraph 12-8, procedural step 3 (b).




Figure 12-7. Isolation of Cell A




Figure 12-8. Isolation of Cell **B**

NOTE

When center cell B (Figure 12-8) is isolated, fuel quantity indicator will not be accurate until total fuel load is contained in forward cells.

- 5. Isolation of cell D or E. See Figure 12-9.
- a. Procedures given are for cell E, but cell D uses same procedures.
- b. Disconnect fuel pressure line (23) from fuel manifold (Z). Plug end of hose with No. 10 AN plug and MS29512 packing.
- c. Disconnect gravity feed hose (2) at crashworthy breakaway valve (W). Remove crashworthy breakaway valve (W) from fuel manifold (Z).
- do Disconnect crossfeed hose (25) from fuel manifold (Z).
- e. Remove manifold from tank by removing 12 bolts and washers and disconnecting pump line (Y) from inside of manifold.

NOTE

If breakaway valve (W) is good, it may be reused to help couple gravity feed and crossfeed lines together.

- f. Use adapters to reduce feed hose (2) (No. 20 fitting-female) to hose (25) (No. 12 fitting-female). Use proper size M29512 packing in each connection.
- **9.** Disconnect boost pump electrical connection, and pull circuit breaker for that pump-tag circuit breaker "DO NOT RESET THIS BREAKER."
 - h. Refuel helicopter.

6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

12-9. FUEL CELL, LEAKING, DAMAGE UP TO 3 X 1 INCH AREA.

OPTION 1: Mechanical Clamp, Figure 12-11.

LIMITATIONS: Emergency one time flight repair. Repair limited to a flat area of cell.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

Mechanical Clamps (items 43, 44, App C)Fluid Line Repair Kit (item 4, Sec I, App B)

PROCEDURAL STEPS:

CAUTION

Ground aircraft during defueling and fueling procedures.

- 1. Defuel aircraft using one or more of the following procedures as necessary to evaluate the cell/cells being worked.
- a. Defueling may be accomplished by disconnecting inlet to fuel control (Figure 12-10) and using fuel boost pumps to pump out fuel or
- b. opening gravity defuel valves located on sumps adjacent to pump drain valves (1, Figure 12-1). The defuel valve is activated by using a fitting such as AN815-12 union, AN832-12 union, AN9190-12 reducer, and MS33656E12 end fitting after removing protection cover, and
- c. drain trapped fuel at drain valves (1 and 9, Figure 12-1).




Figure 12-9. Isolation of Cell D or E




Figure 12-10. Inlet Line to Fuel Control

FUEL SYSTEM

NOTE

- .Each forward cell has two drain valves, one forward and one aft of internal baffle.
- .When cover is jnstalled after defueling, use only enough torque to slightly compress seal.
- d. Each electric boost pump (1) has a drain valve.
- e. To drain main fuel filter (3, Figure 12-1), use valve in drain line from filter sump. Access is by opening lower left engine cowl. Drain line discharges just forward of aft landing gear cross tube.
- 2. Locate the damage (i.e., hole or tear) on the cell.

NOTE

For holes less than 2 inches across, use the 3 inch clamp. For holes greater than 2 inches across but less than 3 inches across, use the 5 inch clamp. Holes larger than 3 X 1 inches in area are nonrepairable; isolate the damaged cell per paragraph 12-8.

- 3. Use knife to clean up hole up to 2 inches maximum for a 3 inch clamp and a 3 inch maximum for the 5 inch clamp, Figure 12-11.
- 4. Using Figure 12-11 as a guide, insert the bottom plate of the clamp through the hole and pull up using the cord. Position the plate so the hole is entirely within the gasket area. Slip the top plate over the threaded stud and hand tighten the wing nut.

CAUTION

Excessive mechanical tightening of the wing nut can result in failure of the clamp. The wing nut shall be finger tightened and the maximum torque on the wing nut shall not exceed 10 to 12 inch-pounds.

- 5. Refuel the aircraft.
- Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

OPTION 2: Adhesive Patch Repair.

GENERAL INFORMATION: Generally, emergency adhesive repairs can be accomplished within 2 inches of exposed metal of fuel cell fittings and to damage in any other fuel cell area for which a onetime flight capability is required, Figure 12-12.

NOTE

Emergency adhesive repair provides temporary fuel leakage protection only. It does not stop fuel activation of self-sealing construction which will eventually cause cell degradation.


LIMITATIONS: One time emergency flight inspection before any second flight.


PERSONNEL/TIME REQUIRED:


- 1 Soldier
- I 3 Hours

MATERIALS/TOOLS REQUIRED:

- Abrasive Cloth, 320 Grit (item 119, App C)
- Cement Repair Kit (item 35, App C)
- Knife and Scissors (items 118, 161, Sec II, App B)
- Ž Repair Fabric Patch (item 91, App C)
- Solvent (items 1, 76, App C)







POSITION TOP PLATE OF REPAIR CLAMP AND HAND TIGHTEN WING NUT

NOTES

- 1. MECHANICAL TIGHTENING OF WING NUT CAN RESULT IN CLAMP FAILURE. TIGHTEN WITH FINGER PRESSURE.
- 2. MECHANICAL CLAMPS, ITEM 42 & 43 APPENDIX C.

Figure 12-11. Emergency Mechanical Clamp Repair




Figure 12-12. Fuel Cell Patch Repair

PROCEDURAL STEPS:

1. Defuel the aircraft. Refer to option 1, step 1.

NOTE

Repairs can be accomplished from either the exterior or Interior of the fuel cell, whichever is the fastest way to gain access to damaged area. Patch can be applied either Internal or externally.

- 2. Trim the outer exposed damaged area to provide a reasonably smooth exterior surface. DO NOT ENLARGE HOLE beyond 1 X 3 inches.
- 3. Abrade and solvent wash the area surrounding the damage using solvent at least 4 inches beyond the damage.
- 4. Cut a fabric patch to overlap the damaged area by a minimum of 1 inch all the way around. Soak the patch in solvent. (NOTE: No hole is required In the center of the patch.)
- 5. Prepare the adhesive per instructions on the package of adhesive cement.

- 6. Apply adhesive to the wound opening for at least 1-1/2 Inches around the damaged area or enough to accept the patch cut In step 4 (above).
- 7. Position the solvent soaked fabric patch on the applied adhesive and smooth it out.
- 8. Apply additional adhesive If required to seal the patch to the tank and smooth out the surface.

CAUTI ON

The patch will tend to slip when applying additional adhesive and smoothing. Be sure to recenter the patch.

- 9. Maintain the patch position for 30 minutes until the adhesive sufficiently sets. Then allow the adhesive to cure 2 hours before refueling.
- 10. Refuel the aircraft.
- 11. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

12-10. FUEL FILTER ASSEMBLY, DAMAGED AND LEAKING.

LIMITATIONS: Bypassing of fuel filter assembly can result In contaminated fuel with sediment or foreign particles entering the engine fuel system and causing damage.

PERSONNEL/TIME REQUIRED:

- . 1 Soldier
- •30 Minutes

MATERIALS/TOOLS REQUIRED:

. Comnon Hand Tools (App B)

PROCEDURAL STEPS:

- 1. Open left engine access panel to gain access to external fuel filter.
- 2. Disconnect hose fitting (1, Figure 12-13) from breakaway fitting (2).
- 3. Disconnect elbow (3) from filler (4) outlet port.
- 4* Bypass the filter assembly by connecting hose fitting (1) to elbow fitting (3).
- 5. Test repair by starting engine. Inspect for leaks.
- 6. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 12-13. Filter Bypass Detail

CHAPTER 13

FLIGHT CONTROLS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER. (AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.) IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

13-1. SCOPE.

- a. The purpose of this chapter is to provide BDAR repairs to flight control system which consists of the cyclic controls, collective controls, power controls, elevator controls, and tail rotor controls. See Figures 13-1 thru 13-5.
- b. The majority of repairs listed will deal with BDAR on connecting links and bellcranks.
- (1) Connecting links are rigid solid rods or tubes. They consist of a middle link with attaching fittings on each end.
- (2) Bellcranks, horns, and levers are all typical mechanical parts. They are used to increase/decrease output force and travel distance, and to change direction of input/output force.

13-2. ASSESSMENT PROCEDURES. See Tabl e 13-1.

13-3. REPAIR PROCEDURE INDEX.

	PARA.
Connecting Links Damaged to Center of Link	
(ends undamaged)	13-5
Link End Fitting, Fabrication of	13-5
Link, Fabrication of Complete	13-5 13-5
Levers and Bell cranks Levers, Fabrication of	13-7
Bellcrank, Fabrication of Elevator Horn Damage Repair .	13-9 13-11
Control Cables Repair	13-12

Section II. CONNECTING LINKS

13-40 **GENERAL**.

- a. Most of the long connecting links are hollow aluminum tubes with attachment fittings riveted on the ends. Some short links are solid metal. BDAR fixes described in this section are to be used for fixing complete break or separation of links.
- b. If connecting link is cut by damage or if it must be cut for repair, refer to Table 13-2 for the correct length of center to center attachment holes.
- c. Not all the hardware of nuts, bolts, washers, locknuts, and other hardware used is listed in this chapter. Refer to TM 55-1520-204-25/1 for hardware specifications. Some hardware listed will reference to Appendix C.
- d. TM 55-1520-210-23 provides installation and removal instructions for the connecting links.

FLIGHT CONTROLS




Figure 13-1. Cyclic Control System




Figure 13-2. Collective Control System




Figure 13-3. Elevator Control System




Figure 13-4. Power Control System




Figure 13-5. Tall Rotor Control System

Table 13-1. Assessment Procedures

ITEM/ACTION FAULT ISOLATION BDAR REF.

VISUALLY INSPECT




Table 13-1. Assessment Procedures (Cont)

ITEM/ACTION

FAULT ISOLATION

BDAR REF.

VI SUALLY INSPECT





Table 13-1. Assessment Procedures (Cent)


I TEM/ACTI ON

FAULT ISOLATION

BDAR REF.

VI SUALLY INSPECT





							DESIRE SPLICE	D TUBE O.D.
					WALL	NOMINAL	(INCH	
				AL LINK	THICK-	C.TO C.	INSIDE	OUTSIDE
FIGURE	ITEM NO.	PART NO. & NSN	0.D.	INCHES)	NESS INCHES	LENGTH INCHES	TYPE SPLICE	TYPE SPLICE
FIGURE	NO.	PART NO. & NON	0.0.	1.0.	INCHES	INCHES	SPLICE	SPLICE
		204-001-027-23	j					
13-2	1	3040-00-886-5994	1 3/4	1 41/64	.049	50.34	1 5/8	1 7/8
	_	205-001-011-17						
13-2	3	3040-00-995-1333 _	1 3/4	1 41/64	.049	53.93	1 5/8	1 7/8
13-2	6	205-001-013-1 3040-00-963-0945	7/8	49/64	.049	27.87	3/4	1
13-2	5	205-060-702-1 3040-00-792-1494	3/4	11/16	.028		5/8	
13-2		205-060-712-1	3/4	11/10	•028	37.68	5/8	7/8
13-2	7	3040-00-967-7679	1/2	27/64	.035	20.47	3/8	5/8
13-1	1	204-001-011-13 3040-00-624-5139	3/4	41/64	.049	15.55	5/8	7/8
		204-001-016-13						
13-1	2	3040-00-624-5122	3/4	41/64	.049	16.12	5/8	7/8
13-1	3	204-001-012-31 3040-00-624-5146	3/4	41/64	.049	26.67	5/8	7/8
		204-001-012-13						,,,
13-1	4	3040-00-624-5143	3/4	41/64	.049	15.55	5/8	7/8
13-1	5	204-001-027-5 3040-00-624-5109	1 1/2	1 25/64	.049	56.32	1 3/8	1 5/8
13-1	6	205-001-014-1 3040-00-964-5072	1 3/8	1 17/64	040	40.70	1 1/4	1 1/2
13-1	-	205-001-011-13	1 3/6	1 1//04	•043	40.70	1 1/4	1 1/2
13-1	7	3040-00-964-5068	1 1/8	1 1/64	.049	40.44	1	1 1/4
13-1	9	204-001-018-27 3040-00-775-7739	7/8	49/64	.049	25.55	3/4	1
		204-001-957-1						
13-3	1	3040-00-731-8093	3/4	43/64	.035	10.21	5/8	7/8
13-3	3	205-001-017-1 3040-00-052-6312	1 1/8	1 1/64	.049	30.05	1	1 1/4
13-3	5	205-011-017-7 3040-00-964-5073	1 1/4	1 9/64	.049	42.95	1 1/8	1 1/2
Í								

Table 13-2. Connecting Link Dimensions (Cont)

		(Refer to	, Figure	s 13-1 tl	nru 13-5))		
			ORIGIN	AL LINK	WALL THICK-	NOMINAL C.TO C.	DESIRE SPLICE (INCH INSIDE	
	ITEM			INCHES)	NESS	LENGTH	TYPE	TYPE
FIGURE	NO.	PART NO. & NSN	0.D.	I.D.	INCHES	INCHES	SPLICE	SPLICE
13-3	7	205-001-018-5 3040-00-246-4554	1 1/2	1 25/64	.049	56.10	1 3/8	1 5/8
13-3	8	205-001-019-1 3040-00-952-7145	1	57/64	.049	31.45	7/8	1 1/8
13-3	9	205-001-011-33 3040-00-051-3648	1 3/4	1 41/64	.049	71.38	1 5/8	1 7/8
13-3	10	205-001-012-25 3040-00-877-2954	1 3/8	1 17/64	.049	40.05	1 1/4	1 1/2
13-5	1	204-001-014-7 3040-00-736-3999	3/4	41/64	.049	22.12	5/8	7/8
13-5	2	204-001-012-1 3040-00-624-5142	1 1/4	1 9/64	.049	44.00	1 1/8	1 3/8
13-5	3	205-001-011-9 3040-00-952-8835	1 1/2	1 25/64	.049	58.03	1 3/8	1 5/8
13-5	5	205-001-011-5 3040-00-964-5066	1 3/4	1 41/64	.049	53.93	1 5/8	1 7/8
13-5	6	205-001-011-1 3040-00-964-5064	1 3/4	1 41/64	.049	62.89	1 5/8	1 7/8
13-5	9	205-001-012-19 3040-00-051-3647	1 3/4	1 41/64	.049	61.32	1 5/8	1 7/8
13-4	2	204-001-602-1 3040-00-859-2742	3/4	43/64	.035	43.00	5/8	7/8
13-4	1	204-061-716-7 3040-00-939-7531	1/2	27/64	.035	21.41	3/8	5/8
<u>13-4</u>	3	205-060-734-9 3040-00-952-9754	1/2	27/64	.035	13.95	3/8	5/8
13-4	5	205-060-729-19 3040-00-952-7152	5/8	35/64	.035	37.90	1/2	3/4
13-4	6	205-060-729-21 3040-00-952-7153	5/8	35/64	.035	23.91	1/2	3/4
13-4	8	205-060-729-23 3040-00-952-7149	5/8	35/64	.035	24.01	1/2	3/4
13-4	9	205-060-729-25 3040-00-952-7150	5/8	35/64	.035	33.57	1/2	3/4
13-4	10	205-060-734-11 3040-00-952-9755	1/2	27/64	.035	21.31	3/8	5/8
13-4	11	205-060-733-9 3040-00-952-7147	3/8	19/64	.035	11.17	1/4	1/2

TM 55-1520-210-BD

FLIGHT CONTROLS

13-5. CONNECTING LINKS, DAMAGED IN CENTER (both attaching ends acceptable).

OPTION 1: Splice Repair. See Figure 13-6.

LIMITATIONS: One flight and inspection of area before and after flight.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •2 Hours

MATERI ALS/TOOLS REQUIRED:

- •Extrusion Angle (items 47-60, App C)
- Tube Stock
- •NAS-1304 Bolt (item 19, 21, 23, App C)
- •Rivets (items 94-114, App C)

PROCEDURAL STEPS:

- 1. Remove damaged connecting link from helicopter.
- 2. Trim damaged area. Do not cut unless necessary.

WARNI NG

Do not use soft aluminum rivets to join splices. Use steel rivets, tempered aluminum rivets, monel rivets, or steel bolts.

- 3. Select a metal splice inner, outer, or angle, whichever is more suitable. See Figure 13-6.
- **4.** Splice should overlap damaged area a minimum of 3 X diameter on each side. See Figure 13-6.
- 5. Drill at least two bolt/rivet holes through tube, and splice on each side of damaged area. See Table 13-3 for bolt/hole sizes.
- 6. Holes should be in 90° cross pattern. See Figure 13-6 for spacing.
- a. Inside type splice start measurement at edge of damaged area working outward.

b. Outside type splice or angular splice start measurement at end of splice and work Inward.

NOTE

Angular splice angles should be held in place with water hose clamps, safety wire, etc. before drilling.

- 7. Make sure that original center to center length is maintained, Table 13-2.
- 8. Reinstall link after repair Is accomplished, and check for binding or interference by manually moving appropriate controls through several cycles.
- 9. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Table 13-3. Bolt/Drill Sizes


	101 SpiiceCenepalis					
-	LINK					
	NOM OD	FOR BOLT	DRI LL HOLE	FOR Bolt	DRILL Hole	
	5/8 3/4 7/8 1 1/8 1-1/4 1-3/8 1-1/2	No. 6 8 10 10 10 1/4 1/4 5/16	9/64 No. 19 9 9 LTR F LTR F LTR O	NO. 8 10 1/4 1/4 1/4 5/16 5/16 3/8	No. 19 9 LTR F LTR F LTR O LTR O LTR V	


OPTION 2: Fabrication of Connecting Link End. Link damaged at one end, Figure 13-7.

LIMITATIONS: One flight limitation.

PERSONNEL/TIME REQUIRED:

- •1 Sol di er
- . 2 Hours











Figure 13-6. Control Connecting Link Splices









R. CONSTRUCTION DETAIL OF FABRICATED TUBE END

Figure 13-7. Fabrication of Link End (Sheet 1 of 2)



E. INSTALLATION OF FABRICATED CONNECTING LINK ON A BELLCRANK OR LEVER WITH A BEARING TYPE END



F. INSTALLATION OF FABRICATED CONNECTING LINK END ON TO BELLCRANK OR LEVER WITH A CLEVIS TYPE END

Figure 13-7. Fabrication of Link End (Sheet 2 of 2)

TM 55-1520-210-BD

FLIGHT CONTROLS

MATERIALS/TOOLS REQUIRED: Tube Stock (same or larger diameter as original tube, 0.035 in. min. wall thickness).

PROCEDURAL STEPS:

- 1. Remove damaged connecting link from helicopter.
- 2. Measure accurately center to center length of damaged connecting link, Table 13-2.
- 3. Trim/remove damaged area from connecting link.
- 4. Select a length of new bulk tubing or cannibalized tubing for the replacement end. Length of replacement tubing must be a longer than damaged length to allow for fabrication process, Figure 13-7.
- 5. Form one end of replacement link flat **as** shown in Figure 13-7, sheet 1 of 2.
- 6. Slip open end of replacement link into or over original link.
- 7. Mark center to center length taken in step 2. Punch mark pivot hole.
- 8. Refer to Table 13-4 and Figure 13-7, sheet 1 of 2. Select correct radius from table and lay on tube end as shown in Figure 13-7.
- 9. Drill proper size pivot hole to match original link hole diameter.
- 10. Trim and file off excess metal from connecting link end.
- 11. Slip fabricated end into or over trimned end of original end. Overlap a minimum of 3 X OD of original link OD.
- 120 Drill at least two bolt holes through link and splice. See Table 13-3 for bolt and hole sizes.
- 13. Holes should be in 90" cross pattern. See Figure 13-7 for spacing of bolt holes.

14. Make sure original center to center length, measured in step 2, is maintained.

WARNING

Use self-locking nuts, double nuts, or cotter pins to retain all flight control pivot bolts.

15. Install repaired link In helicopter. Use flat washers to shim out excess play, but leave approximately 0.010 inch clearance to prevent binding.

NOTE

Flat washers should be large enough to completely cover pivot bearing.

16. Record BDAR action taken. When mission Is complete, as soon as practical, repair connecting link with an actual replacement connecting link.

Table 13-4. Fabricated Link Fnd Dimensions

	Liiu Diiliciisioii	3
REPAI R		MI NI MUM
TUBE	RADI US	EDGE
SI ZE	±1/32	DI STANCE
1/2	0. 279	0. 217
5/8	0. 353	0. 274
314	0. 426	0. 332
7/8	0. 500	0. 391
1	0. 575	0. 450
1-1/8	0. 632	0. 507
1-1/4	0. 706	0. 565
1-3/8	0. 780	0. 623
1-1/2	0.869	0. 682
1-3/4	1. 05	0. 798

OPTION 3: Fabrication of Control Link from Tube.

LIMITATIONS: One flight limitation.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- •3 Hours

MATERIALS/TOOLS REQUIRED:

- •Drill & Bits (item 67, 69, Sec II, App B)
- . Common Hand Tools (App B)
- . Tube Stock (same or larger dia as original tube, 0.035 ln. min. wall thickness, 0.049 preferred)

PROCEDURAL STEPS:

- 1. Remove damaged connecting link from helicopter.
- 2. Identify part number of link from location in Figures 13-1 thru 13-5. (P/N may be marked on tube by manufacturer.)
- 3. Refer to Tables 13-2 and 13-3. Select new bulk tubing or cannibalized tubing of original diameter or larger. Length of replacement link must be longer than original to allow for fabrication process. Refer to Figure 13-8.
- 4. Mark center to center length taken from Table 13-2.
- 5. Squeeze ends of replacement link flat as shown in Figure 13-8.
- 6. Measure accurately and remark center to center length.
- 7. Punch mark each pivot hole.
- 8. Refer to Table 13-4. Select correct radius from table and lay on link ends as shown in figure.
- 9. Drill proper size pivot hole to match original link end.
- 10. Trim and file off excess metal from link ends.

WARNI NG

Use self-locking nuts, double nuts, or cotter pins to retain all flight control pivot bolts.

11. Install fabricated connecting link in aircraft. Use flat washers to shim out excess play, but leave approximately 0.010 inch end clearance to prevent binds.

NOTE

Flat washers should be large enough to completely cover pivot bearing.

12. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 13-8. Fabrication of Links from Tube

TM 55-1520-210-BD FLIGHT CONTROLS

Stock.

OPTION 4: Fabrication of Short Flight Control Connecting Links Using Bar

NOTE

This repair option generally should not be used for control tubes or links in excess of 24 inches long unless angle stock or other means are incorporated to prevent bowing.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- 1 Soldier
- •3 Hours

MATERIALS/TOOLS REQUIRED:

- •Common Hand Tools (App B)
- •Bolts & Washers (items 11-29, 168, App C)
- •Drill & Bits (item 67, 69, Sec II, App B)
- •Flat Bar Stock Aluminum 2024T, 7075T, or Steel Bar Stock
- •Nuts (item 82-86, App C)

PROCEDURAL STEPS:

- 1. Remove damaged linkage from helicopter.
- 2. Refer to Figure 13-9 and select most suitable repair for fabrication of damaged part.

NOTE

Variations and adaptations of these techniques may be utilized to repair several types of parts in addition to those shown.

- 30 Cut bar stock to match length of damaged linkage. Saw, file, or grind end of bar to form radius shape.
- 40 If clevis link is fabricated from two bars as shown in Figure 13-9, detail C, drill holes for cross bolts as needed. Assemble cross bolts, washers, and bars to create fabricated link.
- 5. Mark and drill proper size holes for linkage end pivot bolts. Drilled hole for pivot bolt should be AF.

CAUTION

Overtightening of pivot bolts will cause binding of controls. Use self-locking type nuts, double nutted, or cotter pined to prevent nuts from working loose.

- 6. Install link into helicopter flight controls. Tighten pivot bolt nut leaving approximately 0.015 inch bolt axial end play.
- 7. Cycle controls through several strokes and check for binding or interference.
- 8. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.






Figure 13-9. Fabrication of Connecting Link (Sheet 1 of 3)




7

C. FABRICATING LINK WITH CLEVIS ENDS




D. FABRICATION OF TAIL ROTOR (POWER CYLINDER) CONNECTING LINK, P/N 205-001-715-1

Figure 13-9. Fabrication of Connecting Link (Sheet 2 of 3)



LEVER P/N	"A" DIME	NSION "B"
204-001-353-1	2.155	9.750
204-001-354-1	1.000	9.750






Figure 13-9. Fabrication of Connecting Link (Sheet 3 of 3)

Section III. LEVER ASSEMBLIES

13-6. GENERAL. A lever can be fabri-cated by using the actual damaged lever or another identical lever as a template. A lever from another UH-IH/V helicopter may be used if damaged part is shattered.

13-7. FABRICATION OF LEVER ASSEMBLY.

OPTION 5: Fabricate Flight Control Lever.


LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- •1 Soldier Ž 3 Hours
- MATERIALS/TOOLS REQUIRED:
- •Common Hand Tools (APP B)
- •Drill & Bits (item 67, 69, Sec II, App B)
- •1/2 in. thick (or as needed) X 2 in. wide Aluminum 2024T, 7057T, or Steel Bar Stock

PROCEDURAL STEPS:

- 1. Remove damaged lever and use as a template to punch mark pivot hole centers, Figure 13-10.
- 2. Saw off excess stock and round corners.
- 3. Install lever using flat washers to shim out side play as needed.
- 4. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.



FABRICATED LEVER

Figure 13-10. Fabrication of Lever from Flat Bar Stock

0.500

Section IV. BELLCRANKS

- 13-8. GENERAL. A bellcrank assembly can be fabricated by using the actual bearing as a template if it is still intact. An identical bellcrank from another UH-IH/V helicopter may be temporarily used as a template if damaged part is not intact.
- 13-9. FABRICATION OF BELLCRANKS AND LEVERS.

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

- •1 Soldier
- . 4 Hours

MATERIALS/TOOLS REQUIRED:

- Ž Common Hand Tools (App B)
- •Cutting Torch (if steel plate Is used)
- Drill & Bits (item 67, 69, Sec II, App B)
- •Flat Washers (Items 168-176, App C)
- 3/8 or 1/2 in. Aluminum or Steel Plate Stock

PROCEDURAL STEPS:

- 1. Remove damaged bellcrank or lever from helicopter.
- 2. Refer to Figure 13-11A and B. Use old bellcrank or lever as a template. Mark outline and center punch bearing hole locations, or drill holes using bearing holes as guide.

- 3. Saw or flame cut plate along outline marks. File or grind edges smooth. Round off corners.
- 4. Refer to Figure 13-IIC. Drill same size pivot holes as per original part.
- 5. Refer to Figure 13-IID. Install fabricated bellcrank or lever into flight control system. Use flat washers as needed to shim out side to side play.

CAUTION

Overtightening of pivot bolts will cause binding of controls. Use self-locking type nuts, double nutted, or cotter pinned to prevent nuts from working loose.

- 6. Cycle flight controls to check for interference or binds.
- 7. Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.

Section V. ELEVATOR


13-10. GENERAL. The elevator is connected and operated by input from the swashplate through a series of control tubes, levers, and bellcranks, Figure 13-3. Any damage to the flight control tubes, levers, and bellcranks which renders the elevator inoperable and which cannot be fixed, will require that the elevator be disconnected completely and locked out to keep in from flapping and affecting flight. This is the only BDAR fix allowed for elevator if it is malfunctioning.

13-110 ELEVATOR, INOPERABLE.

LIMITATIONS: Inspect after every flight for no elevator rotation. Do not exceed 40 knots airspeed.


NOTE

This option to be used only if elevator system cannot be made operative.




3/8 or 1/2 INCH FLAT PLATESTOCK BLANK

A. LAYOUT PLATE STOCK




B. PUNCH MARKING PIVOT HOLE CENTERS

Figure 13-11. Fabrication of Bellcranks and Levers (Sheet 1 of 2)



C. FINISHED FABRICATION



D. FABRICATED BELLCRANK OR LEVER INSTALLATION

Figure 13-11. Fabrication of Bellcranks and Levers (Sheet 2 of 2)

PERSONNEL/TIME REQUIRED:

11 Soldier

•3 Hours

MATERIALS/TOOLS REQUIRED:

Common Hand Tools (App B)2-Rubber Strips 3/4 in. wide X 6 in. long (item 116, App C)

PROCEDURAL STEPS:

- Remove at least one control link tube in the elevator control system, preferably all those with damage, Figure 13-3.
- 2. Ensure that fore and aft movement of cyclic stick and resulting movement of swashplate is not restricted in any way.
- Remove middle tail boom access cover plate to gain access to elevator horn area.
- Refer to Figure 13-12. Remove four bolts holding left and right upper support assembly caps.
- Remove support assembly caps and spacer washers.
- Cut two pieces of rubber or leather approximately 3/4 X 6 inches. Any material approximately 1/16 to 1/8 inch thick can be used such as rubber hose or shoe leather strips.
- 7. Clean all lubricants from elevator horn grooves and support assembly caps.
- 8. Lay rubber or leather strips in horn grooves and install caps. Do not install spacer washers.

NOTE

Rubber or leather strips act as friction brake pads to prevent elevator rotation.

- 9. Install four bolts removed from each support assembly cap with cyclic control stick set neutral. Set elevator trialing edge to top (neutral rig) rivet 'P.' Tighten the four bolts sufficiently to prevent rotation of elevators.
- 10. Install tail boom access cover plate.
- 11. Record BDAR action taken. When mission Is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.




Figure 13-12. Elevator Lock Out

Section VI. CONTROL CABLES

13-12. GENERAL.

- a. The UH-1 helicopter has a tail rotor control cable, 1/8 Inch in diameter, which connects a control quadrant (pulley wheel) mounted in front of the tail boom to the other end; a chain/sprocket wheel. This sprocket wheel is attached to and drives the tall rotor pitch control. This cable Is part of the mechanical link in the yaw controls of helicopter. It ties the yaw foot pedal controls to the tail rotor pitch control.
- b. Damage to the cables can be from minor damage such as a few strands of cable broken to complete separation of cable. Any damage which will prevent free movement of the tall rotor pitch controls must be repaired. The following BDAR repairs are for a complete separated cable.
- 13-13. CONTROL CABLE, DAMAGED (SPLICE REPAIR)

LIMITATIONS: None.

PERSONNEL/TIME REQUIRED:

•1 Soldier . 2 Hours

MATERIALS/TOOLS REQUIRED:

• Common Hand Tools (App B)

•Stranded Steel Control Cable
Nicopress Sleeves or Cable Clamps
Nicopress Crimping Tool

PROCEDURAL STEPS:

1. Remove broken cable preferable at speed rig points. Refer to Figure 13-13A.

WARNING

In all cases, it is preferable to replace the flight control cable rather than repair. Repairs should be made as a last resort for one time flight only. Take care in positioning the joints and clamps. Avoid interference between clamps, structure, and fairleads or pulleys through the required range of movement.


- 2. Trim the frayed portion of cable back to a point where the cable diameter can be maintained consistently. Select an area where steps in splice (Figure 13-13C&D) will not travel past holes in structure or other structure that would restrict cable travel.
- 3. Install rig pins at supporting cranks at both ends of cables.
- 4. Relax opposing cables by adjusting turn buckle five full turns.
- 5. Cut a piece of the same or larger size cable long enough to overlap both ends of damaged cable. The cable should also be long enough to provide space for two nicopress sleeves or two cable clamps at each splice as shown In Figure 13-13B.
- 6. Slide two nicopress sleeves or two cable clamps over one end of damaged cable and stock cable. Place end sleeves or clamps 1/4 to 1/2 inch from end of cable as shown in Figure 13-13.
- 7. Use an Installation tool (P/N 51-P-850) for nicopress sleeves or a wrench for clamps and nuts. Crimp sleeves or tighten clamp nuts.

TM 55-1520-210-BD

FLIGHT CONTROLS

- 8. Slide two nlcopress sleeves or cable clamps onto damaged cable and stock cable at second splice. Match cable slack to undamaged opposing cable. While maintaining this cable slack, crimp sleeves or tighten clamps using an installation tool or wrench.
- 9. Insert lockwire through eyelet In speed rig, wrap lockwire around pin then back through eyelet. Twist wire to proper length and secure around locking collar at base of speed rig, cut wire to proper length, twist and fold into speed rig cavity, Figure 13-13.

- 10. Adjust cables to specified tensions.
- 11. Remove rig pins.
- 120 Operate control systems through several cycles and check to ensure there are no binds or chaffing in the splice area. Ensure that nicopress sleeves or cable clamps clear adjacent structure.
- 13* Record BDAR action taken. When mission is complete, as soon as practical, repair the equipment/system using standard maintenance procedures.



NOTE: Lockwire must go around pin, through hole in back of barrel, and around barrel groove.






Figure 13-13. Clamp Splicing Control Cable (Sheet 1 of 2)



C. LOCATING SPLICES TO CLEAR STRUCTURE



D. LOCATING SPLICES TO CLEAR PULLEYS

Figure 13-13. Clamp Splicing Control Cable (Sheet 2 of 2)

UTILITY SYSTEM

(NO BOAR REPAIRS TO SYSTEM)

ENVIRONMENTAL CONTROL SYSTEM
(NO BDAR REPAIRS TO SYSTEM)

HOIST AND WINCHES

(NO BDAR REPAIRS TO SYSTEM)

CHAPTER 17 AUXILIARY POWER PLANT (not applicable)

MISSION EQUIPMENT

(not applicable)

APPENDIX A

REFERENCES

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER. (AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.) IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

The following references of the issue in effect are required for use by repair personnel to accomplish the Instructions set forth in this TM .

PUBLICATION NUMBER	TITLE
AR 95-1 AR 385-11	Army Aviation Flight Regulations Ionizing Radiation Protection Catalog Supply and Management Data
DA Form 2028	Recommend Changes to Publications Aircraft Inspection and Maintenance Record Uncorrected Fault Record Equipment Inspection List
DA PAM 738-751	Functional User's Manual for the Army Maintenance Management System Aviation (TAMMS-A)
FM 1-202. FM 3-5 FM 10-68	Environmental Flight NBC Decontamination Aircraft Refueling Field Manual
MI L-H-83797	General Specification for Medium Pressure Lightweight Rubber Hose
MI L-S-8516	General Specification for Potting Compound Insulation Synthetic Rubber
SF 368	Quality Deficiency Report
TB 43-0108 • •	Handling, Storage, and Disposal of Army Aircraft Components Containing Radioactive Materials
TB MED 501	Occupational and Environmental Health Hearing Conservation
TM 3-261	Handling and Disposal of Unwanted Radioactive Materials

APPENDIX A (Cont)

TM 55-1500-204-25/1 . •, . •	General Aircraft Maintenance Manual
TM 55-1520-210-10 ••. •.	Operators Manual for UH-IH/V Helicopter
TM 55-1520-210-23 . • •.	Aviation Unit and Intermediate Maintenance Instructions: Army Model UH-ID/H/EH-IH Helicopter
TM 55-1520-210-23P. •	Aviation Unit and Intermediate Maintenance Repair Parts and Special Tools List (Including Depot Maintenance Repair Parts and Special Tools), Helicopter, Utility-Tactical Transport UH-IB, UH-IC, UH-ID, UH-IH, UH-IM, EH-IH (Bell)

APPENDIX B

SPECIAL TOOLS AND REPAIR KITS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER. (AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.) IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section 1. GENERAL

B-1. SCOPE. This appendix lists special tools and test equipment. Several special tools are contained in the BDAR kits listed on the next page. The kits also contain small quantities of parts and durable supplies not listed in other appendices. Each kit contains its own inventory list and tool usage instructions. There are no fabricated tools associated with this BDAR manual.

B-2. SPECIAL TOOLS AND REPAIR KITS LISTING. The Items listed in this appendix will enhance crew members and mechanics at all levels to accomplish battlefield damage assessment and repairs.

Section I. SPECIAL TOOLS AND REPAIR KITS

ITEM NO.	NSN	DESCRI PTI ON
1	• ž ž	Composite Structures Repair Kit
2	5935-01-161-5883	Connector Repair Kit (Special Tools for Electrical Connector Repair) (11851) DMC658
3	4920-01-266-7535	Emergency Repair Kit (Special and Common Tools for Electrical Repair, Including Repair Parts) (11851) DMC895
4	4920-01-266-7534	Fluid Line Repair Kit (Special and Common Tools for Tubing and Hose Repair, Including Repair Parts) (78286) 70700-20900-041
5	• • •	Fuel Cell Repair Kit
6	5120-00-017-2849	Riveter, Blind, Hand (10054) 200
7	5120-00-224-9296	Riveter, Blind, Hand (25472) C6000-10-32
8	5120-00-979-7601	Riveter, Blind, Hand (03481) C6000-4-40
9	3540-01-117-7870	Sealing Iron, Electric (19836) 50-T
10	4920-01-266-7536	Test Equipment Repair Kit (Elec Test Equipment) (78286) 70700-20638-041
11	5935-01-254-1688	Wire Repair Kit (Special Tools Used for Electrical Wiring Repair, Including Repair Parts) (06090) MR-0015-1

Section II. TOOLS

This section lists tools recommended for support of the UH-1 helicopter in a combat environment.

ITEM NO.	NATIONAL STOCK NUMBER	DESCRI PTI ON	U/I
110.	NOMBLIN	DESCRIPTION.	0/1
1	5120-00-240-8702	Adapter, 1/2 to 3/8 inch	EA
2	5120-00-528-2891	Adapter, Apex 1/4 in.dr.,	EA
3	5120-00-528-2892	Adapter, Apex 3/8 in.dr	EA
4	5120-00-227-8095	Adapter, Socket 3/8 to 1/4 inch	EA
5	5120-00-223-8191	Awl, Saddlers Pad 4 inch	EA
6	5120-00-221-1542	Awl, Scratch	EA
7	5120-00-293-2503	Bar, Bucking Rivet, Angle Head Type 4 inch	EA
8	5120-00-293-2502	Bar, Bucking Rivet, L Head Type 4 inch	EA
9	5120-00-293-2501	Bar, Bucking Rivet, Universal Type 4 inch	EA
10	5210-00-919-2374	Bending Gage, Trim	EA
11	5210-00-844-7757	Bender, Trim Tab M/R	ĒΑ
12	5120-00-240-0152	Bender, Tube, Hand, 1/4 inch	EA
13	5120-00-240-0153	Bender, Tube, Hand, 5/16 inch	EA
14	5120-00-240-0154	Bender, Tube, Hand, 3/8 inch	EA
15	5120-00-240-0155	Bender, Tube, Hand, 1/2 inch	EA
16	5120-00-240-0156	Bender, Tube, Hand, 5/8 inch	EA
17	5120-00-240-0157	Bender, Tube, Hand, 3/4 inch	EA
18	5120-00-240-0158	Bender, Tube, Hand, 7/8 inch	EA
19	5110-00-927-1063	Blade, Hand, Flat (Tungsten)	EA
20	5110-00-277-4591	Blade, Hand Hacksaw	EA
21	5140-00-289-8910	Box, Tool, Steel Mechanic Type 10X1-2X22X13	EA
22	5210-00-263-0376	Caliper, 8 inch	EA
23	5110-00-242-3457	Chisel, Cold Hand 3/8 inch	EA
24	5110-00-234-1927	Chisel, Cold Hand Steel 1/4 in. Cut 4 in. long	EA
25	5110-00-186-7107	Chisel, Cold Hand Type 1/2 in. Cut 5 3/4 in. iong.	EA
26	5120-00-061-1273	Clamp, "C" 1 inch	EA
27	5120-00-203-6439	Clamp, "C'' 2 1/2 inch	EA
28	5120-00-180-0905	Clamp, "C'' 2 3/4 inch	EA
29	5120-00-180-0908	Clamp, "C'' 4 inch	EA
30	5120-00-203-6431	Clamp, "C'' 6 inch	EA
31	7910-00-857-1042	Cleaner, Vacuum	
32	5120-00-242-3789	CLECO, 3/32 inch	
33	5120-00-222-3336	CLECO, 5/32 i nch	
34	5120-00-242-3791	CLECO, 3/16 inch	
35	5120-00-541-1808	CLECO, 1/8 inch	
36	5120-00-253-3882	CLECO, 1/4 inch	12EA
37	• • • 5100 00 000 1000	CLECO, Clamps, P/N 00784EL-1/2-1	EA
38	5133-00-293-1902	Countersink 3/8 in. Body 1/4 in. Shank	EA
39	5133-00-243-2298	Countersink 7/16 in. Body 1/8 in. Pilot	EA
40	5133-00-243-2300	Countersink 7/16 in. Body 3/16 in. Pilot	EA
41	5133-00-243-2299	Countersink 7/16 in. Body 5/32 in. Pilot	EA
42	5120-00-278-2423	Crimping, Tool Large	EA
43	5120-01-120-8721	Crimping, Tool, AD-1377	EA
44	5120-00-170-7938	Crimping, Tool Hand.,	EA

TTEM NO.	NATIONAL STOCK NUMBER	DESCRIPTION	U/I
45 46 47 48 49 50 51 52 53 54 55 56 61 62 63 64 65 66 67 71 72 73 74 75 77 78 81 82 83 84 85 88 88	5120-00-184-8410 5120-00-184-8414 5120-00-184-8409 5120-00-184-8409 5120-00-184-8403 5120-00-184-8401 5120-00-184-8398 5120-00-184-8398 5120-00-184-8397 5120-00-184-8397 5120-00-184-8397 5120-00-184-8397 5120-00-236-2261 5120-00-236-2261 5120-00-239-8253 • • • • • • • • • • • • • • • • • • •	Crow Foot, 3/8 dr. X 1 3/8 flat. Crow Foot, 3/8 dr. X 1 5/8 flat. Crow Foot, 3/8 dr. X 1 1/2 flat. Crow Foot, 3/8 dr. X 1 1/2 flat. Crow Foot, 3/8 dr. X 1 1/8 flat. Crow Foot, 3/8 dr. X 1 1/8 flat. Crow Foot, 3/8 dr. X 1 1/8 flat. Crow Foot, 3/8 dr. X 1 3/16 flat Crow Foot, 3/8 dr. X 1 3/16 flat Crow Foot, 3/8 dr. X 5/8 flat. Crow Foot, 3/8 dr. X 1/2 flat. Crow Foot, 3/8 dr. X 3/4 flat. Crow Foot, 3/8 dr. X 3/4 flat. Crow Foot, 3/8 dr. X 1/16 flat Crow Foot, 3/8 dr. X 1/16 flat Crow Foot, 3/8 dr. X 1 1/16 flat Crow Foot, 3/8 dr. X 1 1/4 flat. Crow Foot, 3/8 dr. X 1 1/4 flat. Cutter, Diagonal, 6 in. Cutter, Diagonal, 7 in. Heavy Duty, P/N 93389209 Cutter, Rivet Squeeze Type Cutter, Tubing. Die, Round 1/4-28, 2 in. 0. D. Digital Multimeter, Simpson MOD 407. Disk, Holding 1 inch, P/N 00179741C1 Dividers, Mechanics 8 inch. Drill, Bit Set Twist No. 1 thru No. 60 with Case Drill, Hand, Type I. Drill, Stop 1/8 inch, P/N 00784AT570-28. Drill, Stop 1/8 inch, P/N 09784AT570-21 Drill, Stop 3/32 inch Drill, Stop 3/32 inch Drill, Stop 3/32 inch Drill, Stop 3/32 inch Drill, Stop 3/32 inch Drill, Stop 3/32 inch Drill, Stop 3/32 inch Drill, Stop 3/36 inch Extension, 3/8 dr. 9 inch. Extension, 3/8 dr. 9 inch. Extension, Socket 1/4 in. dr. 2 inch Extractor Set, Screw Sz. 1 thru 6. Extractor, Cotter Pin. File, Half Round Bastard Cut 8 inch File, Hand Flat Bastard 10 inch. File, Hand Flat Bastard 10 inch. File, Hand Round Bastard Cut 8 inch File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Hand Round Bastard Cut 8 inches. File, Rot. Hss. No. 1, Coarse Cut File, Rod. Reg. Cut 6 inches.	EAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAA

ITEM NO.	NATIONAL STOCK NUMBER	DESCRI PTI ON	U/I
NO. 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126	NUMBER 5120-00-180-2951 3643-00-517-1043 3463-00-251-2267 6320-00-299-3035 5110-00-289-9657 5210-00-221-1902 5210-00-221-1893 5210-00-221-2448 5210-00-221-2451 5130-00-293-2797 5120-00-494-1910 4930-00-25-2478 4940-00-785-1162 5120-00-061-8542 5120-00-240-1396 5120-00-240-5396 5120-00-240-1418 5120-00-240-1418 5120-00-240-1418 5120-00-241-7957 5120-00-241-7957 5120-00-241-7957 5120-00-243-1686 5110-00-595-9244 5110-00-240-5943 5120-00-243-1686 5110-00-240-5943 5120-00-278-0352 5120-00-278-0352 5110-00-222-2708	Finger, Mech. Flexible 24 inches Fixture, Locating & Drill 3/16 dia Fixture, Locating & Drill 1/8 dia Fixture, Locating & Drill 1/8 dia Fiaring Tool Flashlight, Explosion Proof, 3 Cell Frame, Hacksaw Adjustable 10 to 12 Inch. Gage, Depth. Gage, Depth. Gage, Rnd. Sheetmetal Thickness. Gage, Thickness. Gage, Wire 0-36. Grinder, Pneu. Horizontal Grips, Vice Curved Jaw 7 inch. Gun, Grease Gun, Heat Electric Portable. Hammer, Ball Peen 12 oz. Hammer, Ball Peen 16 oz. Hammer, Ball Peen 20 oz Handle, Hinged 1/4 in. dr. Handle, Rachet 3/8 in. dr. Handle, Spin 1/4 in. dr. Handle, Socket Rachet 1/4 in. dr. Holder, Aprx. 3/8 dr. 5/16 in. Sz. Bit Holder, Countersink Adj Holder, Hole Spring Type Tension Cleco 3/16. Holder, Sheet Metal Cleco Edge Clamp Installation Tool, Hand Operated Jo-Bolt Joint Univ. Socket 1/4 dr. Key Set Ilpc sz. 0 to 53 3/8 in. sizes Knife, Pocket Electricians with Screwdriver Blade. Knife, Putty Flex. 1 1/4 in. Blade Mallet, Rawhide 1 1/2 in. dia. Measuring Tape 16 ft. Mirror, Round Large. Nut Driver Set, Xcelite 3/16 to 9/16 Pliers, Cannon Plug 8 in. Pliers, Channel Locks 10 In. Pliers, Diagonal Cut Reg. Nose 7 1/2 in. size.	EA EA EA EA EA EA EA EA EA EA EA EA EA E
126 127 128 129 130 131 132 133 134	5110-00-222-2708 5120-00-595-9519 5120-00-239-8250 5120-00-184-9403 5120-00-221-1597 5120-00-494-1889 5120-00-624-8065 5120-00-170-7983 5120-00-494-1911	Pliers, Diagonal Cut Reg. Nose / 1/2 in. size Pliers, Duck Bill	EA EA EA EA EA EA

TTEM NO.	NATI ONAL STOCK NUMBER	DESCRI PTI ON	U/I
135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 170 171 172 173 174 175 176 177 178 179 180	5120-00-223-7396 5140-00-329-4306 5120-00-102-6847 5120-00-293-3509 5120-00-293-3509 5120-00-240-6083 5120-00-240-6106 5120-00-240-6104 5120-00-240-5364 4931-01-119-7103 5120-00-017-2849 5120-00-017-2849 5120-00-979-7601 5120-00-224-9296 5130-01-044-7207 • • • • • • • • • • • • • • • • • • •	Pliers, Wrench Straight Jaw 8 in. Pouch, Tool Mech Canvas. Puller, Riv-Nut size 1/4-28. Puller, Riv-Nut size 6/32. Punch, Center Solid Stock 5/32 in dia tip. Punch, Drive Pin 1/4 in. Point. Punch, Drive Pin 1/8 in. Point. Punch, Drive Pin 3/16 in. Point. Punch, Drive Pin 3/32 in. Point. Punch, Drive Pin 5/32 in. Point. Punch, Drive Pin 5/32 in. Point. Punch, Drive Pin 5/32 in. Point. Rachet, 3/8 in.dr Repair Kit, Electrical Connector, P/N 12205360 Riveter, Blind Hand Riveter, Blind Hand Riveter, Blind Hand Riveter, Blind Hand Riveter, Blind Hand Riveter, Pneu. Cherry Rivet. Riveter, Pneu. Portable 3/16 In, 119764X Riveter, Pneu. 3/32 in Rivet Gun Rivet, Set 8110782 Router Bit, 3/16 in, P/N 89684310005 Router Bit, No 1. Rule, Mach. Steel Safety Wire pliers Saw Hole. Scissors, Electricians Screwdriver, Common I/4 X 4 in Screwdriver, Common 8 in Screwdriver, Ommon Bin Screwdriver, Phillips No. 1. Screwdriver, Jewelers. Screwdriver, 3/8 dr., 3/8 Tip, 12 in. long Screwdriver, 3/8 dr., 3/8 Tip, 12 in. long Screwdriver, 6 in. Phillips No. 2. Screwdriver, 6 in. Phillips No. 3. Scribe, Mach Dbl. Point 8 to 9 in. long. Screwdriver, 6 in. Phillips No. 3. Scribe, Mach Dbl. Point 8 to 9 in. long. Screwdriver, 6 in. Phillips No. 3. Scribe, Mach Dbl. Point 8 to 9 in. long. Screwdriver, 6 in. Phillips No. 3. Scribe, Mach Dbl. Point 8 to 9 in. long. Screwdriver, 6 in. Phillips No. 1. Shears, Metal Cutting R/H 10 1/2 inch. Shears, Metal Cutting R/H 10 1/2 inch. Shears, Str. Cut Light Duty 10 inch. Shears, Str. Cut Light Duty 10 inch. Shears, Str. Cut Light Duty 12 inch. Socket, 12 pt. 1/4 dr. 1/2 in. deep.	AAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAAA

TTEM NO.	NATIONAL STOCK NUMBER	DESCRI PTI ON	u/l
181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206	5120-00-775-6983 5120-00-888-6120 5120-00-242-3351 5120-00-242-3352 5120-00-235-5878 5120-00-235-5822 5120-00-775-6980 5120-00-235-5869 5120-00-189-8610 5120-00-189-8610 5120-00-236-2264 5120-00-236-2262 5120-00-189-7922 5120-00-236-2263 5120-00-242-3345 5120-00-242-3345 5120-00-293-0163 5120-00-203-6446 5120-00-880-9970 5120-00-165-4097	Socket, 12 pt. 1/4 dr. 1/4 in. deep. Socket, 12 pt. 1/4 dr. 11/32 in. deep. Socket, 12 pt. 1/4 dr. 11/32 in. sh. Socket, 12 pt. 1/4 dr. 3/16 in. deep. Socket, 12 pt. 1/4 dr. 3/16 in. deep. Socket, 12 pt. 1/4 dr. 5/16 in. sh. Socket, 12 pt. 1/4 dr. 5/16 in. sh. Socket, 12 pt. 1/4 dr. 7/16 in. deep. Socket, 12 pt. 1/4 dr. 7/16 in. deep. Socket, 12 pt. 1/4 dr. 7/16 in. sh. Socket, 12 pt. 1/4 dr. 1/2 in. sh. Socket, 6 pt. 1/4 dr. 3/8 in. deep. Socket, 6 pt. 1/4 dr. 3/8 in. deep. Socket, 6 pt. 1/4 dr. 3/8 in. deep. Socket, 6 pt. 1/4 dr. 9/32 in. sh. Socket, 6 pt. 3/8 dr. 3/8 in. deep. Socket, 6 pt. 3/8 dr. 3/8 in. sh. Socket, 6 pt. 3/8 dr. 1/2 in. deep. Socket, 6 pt. 3/8 dr. 7/16 in. sh. Socket, 6 pt. 3/8 dr. 7/16 in. sh. Socket, 6 pt. 3/8 dr. 7/16 in. sh. Socket, 6 pt. 3/8 dr. 7/16 in. sh. Socket, 6 pt. 3/8 dr. 9/16 in. sh. Socket, 6 pt. 3/8 dr. 9/16 in. sh. Socket, 6 pt. 3/8 dr. 9/16 in. sh. Socket, 6 pt. 3/8 dr. 11/16 in. sh. Socket, 6 pt. 3/8 dr. 11/16 in. sh. Socket, 6 pt. 3/8 dr. 11/16 in. sh. Socket, 6 pt. 3/8 dr. 11/16 in. sh. Socket, 6 pt. 3/8 dr. 11/16 in. sh. Socket, 6 pt. 3/8 dr. 11/16 in. sh. Socket, 6 pt. 3/8 dr. 11/16 in. deep, P/N 557195SFS221	
207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226	5120-01-091-0690 5120-00-227-6705 5120-00-242-3330 5120-00-720-1350 5120-01-119-3205 5120-00-116-9466 5120-00-227-6696 5120-00-178-0806 5120-00-177-7068 3439-00-264-9573 5110-00-803-6339 6625-01-102-6878 5136-00-729-5700 5136-00-729-5695 5136-00-729-5695 5136-00-729-5694 5120-00-781-7981 5140-00-498-8772 5120-01-128-5511	Socket, 6 pt. 3/8 dr. 3/4 in. deep Socket, 12 pt. 3/8 dr. 3/4 in. sh. Socket, 12 pt. 3/8 dr. 7/8 in. sh. Socket, 6 pt. 3/8 dr. 7/8 in. sh. Socket, 6 pt. 3/8 dr. 13/16 in. deep Socket, 6 pt. 1/2 dr. 15/16 in. sh. Socket, 6 pt. 1/2 dr. 1 in sh. Socket, 6 pt. 1/2 dr. 1 1/8 in. sh, P/N 09669743414 Socket, 6 pt. 1/2 dr. 1 1/4 in. sh. Socket, 6 pt. 3/4 dr. 7/8 in. deep Soldering Iron Bat. Operated Splitting Tool, Nut 7/8 in. cap. TA-1 Continuity and Test Probe Kit, P/N 123036622. Tap, Hand Thread 10/32 Tap, Hand Thread 6/32 Tap, Hand Thread 8/32 Tie Wrap Gun. Tool Box, Portable, Steel with Removable Tray. Tool Set, Supplement, Organizational	EA EA EA EA EA EA

APPENDIX C

EXPENDABLE/DURABLE SUPPLIES AND MATERIALS LIST

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING
AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD
PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

C-1. SCOPE. This appendix lists expendable supplies and materials needed to make BDAR fixes on the UH-IH/V helicopter. Items are listed alphabetically by the item shown in the description column. These Items are authorized to you by CTA 50-970, Expendable Items (Except Medical, Class V, Repair Parts, and Heraldic Items) or CTA 8-100.

C-2. EXPLANATION OF COLUMNS.

a. Item Number. This number Is assigned to the entry in the listing and is referenced in the narrative instructions to identify the material (e.g., "Use cleaning compound, item 5, Appendix C").

- b. <u>National Stock Number</u>. This is the National stock number assigned to the Item; use it to request or requisition the Item.
- c. <u>Description</u>. Indicates the Federal item name and, if required, a description to Identify the item. The last line for each Item indicates the Commercial and Government Entity Code (CAGEC) In parentheses followed by the part number.
- d. <u>Unit of Issue (U/I)</u>. Is the abbreviation of the types of units under which material is issued.

APPENDIX C
Section II. EXPENDABLE SUPPLIES AND MATERIALS LIST

ITEM NUMBER	NSN	DESCRI PTI ON	UNIT OF ISSUE
1	6810-00-223-2739	Acetone, Techni cal (81348) 0-A-51	PT
2	6810-00-184-4796	Acetone, 0-A-51, (81348)	CN
3	8040-00-162-9704	Adhesi ve, Epoxy (16059)´ Z-T014 (30 Min Cure)	KT
4	8040-00-264-6816	Adhesive, 5-Minute Epoxy (16059) P/N 14210	KT
5	8040-01-293-2686	Adhesive Repair Kit (16059) 72250 (Zip-Patch)	KT
6	8040-01-089-9073	Adhesi ve, Epoxy (Bl ade Repair) (33564) EA9330	CN
7	8040-01-102-2098	Adhesi ve, Epoxy (Bl ade Repair) (33564) EA934NA	CN
8	8040-00-944-7292	Adhesi ve, Epoxy Metal Set A4 (33564) EA9340	CN
9	8040-00-165-8614	Adhesive, General Purpose (81348) MMM-A-121	TU
10	8040-00-941-9984	Adhesive, Silicone Rubber (80244) MIL-A-46106, Type I	TU
11	5306-00-141-4511	Bol t (88044) AN173H20A	ВХ
12	5306-00-150-9083	Bol t (88044) AN173H10	BX
13	5306-00-156-2533	Bol t (88044) AN173H6A	BX
14	5306-00-180-2756	Bol t (88044) AN5H17, 5/16-24 X 1-1/2	HD
15	5306-00-182-1529	Bolt (88044) AN4H11, 1/4-28 X 1-1/8	HD
16	5306-00-206-4911	Bol t (88044) AN173H15A	ВХ
17	5306-00-292-8284	Bol t (88044) AN173H4A	BX
18	5306-00-582-5723	Bol t (80205) NAS1305-8	BX
19	5306-00-616-6471	Bol t (80205) NAS1304-10	BX
20	5306-00-619-2178	Bol t (80205) NAS1303-8	EA
21	5306-00-655-7443	Bol t (80205) NAS1304-8	BX
22	5306-00-680-5285	Bol t (80205) NAS1303-6	EA
23	5306-00-722-1788	Bol t (80205) NAS1304-6	HD
24	5306-00-774-8915	Bol t (80205) NAS1305-6	BX
25	5306-00-806-7697	Bol t (80205) NAS1305-4	BX
26	5306-00-807-2958	Bol t (80205) NAS1304-4H	EA
27	5306-00-816-0948	Bol t (80205) NAS1305-10	BX
28	5306-01-074-2075	Bol t (80205) NAS1303-10	HD
29	5306-01-107-1224	Bol t (80205) NAS1303-4	HD
30	7920-00-514-2417	Brush, Stiff Fiber Bristle (80244) H-B-643	EA
31	5975-00-156-3253	Cabl e, Ti e, El ec (81349) MI L-S-23190	EA
32	5975-00-984-6582	(81349) MIL-3-23190 Cable Tie, Elec (81349) MIL-S-23190	EA

APPENDIX C
Section II. EXPENDABLE SUPPLIES AND MATERIALS LIST (Cont)

ITEM Number	NSN	DESCRI PTI ON	UNIT OF ISSUE
33	5940-00-280-3499	Cap, Elec Crimp (96906) MS25274-2	EA
34	5979-00-729-1628	Cap, Elec Crimp 14/16 AWG (Blue) (81349) MIL-T-7928	PG
35	• • •	Cement, Repair Kit (25500) (3 part cartridge kit) Semkit-GAC P/N 324-3-47178	KT
36	8030-00-057-2354	Chemical Conversion Coating (Alodine) (80244) MIL-C-81706	GL
37	4730-00-087-0831	Clamp, Hose (9/16 to 15/16) (88044) AN737TW24-30	EA
38	4730-00-203-3132	Clamp, Hose (13/16 to 1-1/16) (88044) AN737TW34-38	EA
39	4730-01-048-3532	Clamp, Hose (61/64 to 1-1/2) (08484) AN737TW44-48	EA
40	4730-00-289-5909	Clamp, Hose, (1-21/64 to 2-1/16) (08484) AN737TW56-66	EA
41	4730-00-908-3193	Clamp, Hose, (1-7/7 to 2-27/32) (08484) AN737TW74-91	EA
42	4730-00-203-3132	Clamp, Hose (2-5/8 to 3-9/16) (31610) AN 737 TW98-114	EA
43	5340-00-720-8863	Clamp, Mechanical (22337) (Patch) CFD212E, Size 5	EA
44	5340-00-720-8864	Clamp, Mechanical (22337) (Patch) CFD212E, Size 3	EA
45	8030-00-231-2345	Corrosion Preventive Compound (80244) MIL-C-16173	CN
46	5310-00-297-3751	Cotter Pin Assortment (81348)	KT
47	9540-00-140-2401	Extrusi on Angle 2X1X0. 125 (81348) 00-A-200/9	FT
48	9540-00-140-2417	Extrusion Angle I-1/2XI-I/2 X 0.125 (81348) 00-A-200/11	FT
49	9540-00-145-4524	Extrusion Angle I-1/4X3/4 X 0.063 (81348) QQ-A-200/3	FT
50	9540-00-145-5716	Extrusion Angle I-3/4XI-I/2 X 0.156 (81348) QQ-A-200/11	FT
51	9540-00-145-7542	Extrusion Angle 2X1X0.156 (81348) QQ-A-200/11	FT
52	9540-00-145-7543	Extrusion Angle 2X1-1/2 X 0.125 (81348) QQ-A-200/3	FT
53	9540-00-288-3740	Extrusion Angle 3 X 3 X 0.250 (81348) QQ-A-200/II(T6)	FT
54	9540-00-230-2338	Extrusion Angle I-1/2XI-1/2 X 0.188 (81348) QQ-A-200/11	FT
55	9540-00-236-5240	Extrusion Angle 3X1-1/2 X 0.250 (81348) QQ-A-200/11	FT

APPENDIX C
Section II. EXPENDABLE SUPPLIES AND MATERIALS LIST (Cont)

ITEM Number	NSN	DESCRI PTI ON	UNIT OF ISSUE
56	9540-00-596-3006	Extrusion Angle 1-1/2 X 1/4 X 0.094 (81348) QQ-A-200/11	FT
57	9540-00-854-6554	Extrusion Angle 2X2 X 0.250 (81348) QQ-A-200/	FT
58	9540-00-931-7261	Extrusion Angle 2X2 X 0.188 (81348) QQ-A-200/3	FT
59	9540-00-933-9650	Extrusi on Angle I - 1/2XI - I/2 X 0.094 (81348) QQ-A-200/3	FT
60	9540-00-596-3016	Extrusion, L Angle 2024T-4 0.063 (81348) QQ-A-267	FT
61	9540-00-555-1172	Extrusion, T Angle 2024T-4 0.063 (81348) QQ-A-200/3	FT
62	5940-00-296-5326	Ferrul, Electrical, 22-14 Wire Gage size (10 ea) (59730)	EA
63	8305-00-530-0109	Fi bergl ass Cloth (81349) MI L-C-9084	RO
64	8305-00-530-0111	Fi bergl ass Resin (81349) MI L-C-9084	CN
65	5330-00-467-3615	Gasket, Paper Filer 1/32 In. (81348) HH-P-96	SH
66	5970-00-032-0291	Heat Shrink SI eeve Assortment (61521) DI-295-MS-1	KT
67	4730-00-203-3131	Hose Clamp (66295) AN737TW57-66	EA
68	4730-00-278-9200	Hose Clamp (66295) AN737TW22	EA
69	4730-00-279-0065	Hose Clamp (08484) QS200M1200	EA
70	4730-00-541-7747	Hose Clamp (66295) AN737TW74-91	EA
71	4730-00-720-0167	Hose Clamp (88044) AN737TW30	EA
72	4730-00-908-6292	Hose Clamp (88044) AN737RM98	EA
73	9505-00-596-5101	Lockwire, Steel 0.020 (81348) 00-W-423	RO
74	9505-00-293-4208	Lockwlre, Steel 0.032 (81348) QQ-W-423	RO
75	9505-00-331-3275	Lockwire, Steel 0.041 (81348) QQ-W-423	RO
76	6810-00-238-8119	Naptha, Aliphatic (81348) TTN95	GL
77	5310-00-297-3751	Nut Assortment (81348) FFN836	PG
78	5310-00-807-1467	Nut (80205) NAS1291X3	BX
76 79		, ,	
	5310-00-807-1469	,	BX
80	5310-00-807-1474	Nut (80205) NAS679A3	BX
81	5310-00-807-1475	Nut (96906) MS21042L4	ВХ
82	5310-00-680-7105	Nut, Self-Lock Steel 5/16 (80205) NAS 679C5M	EA

APPENDIX C
Section II. EXPENDABLE SUPPLIES AND MATERIALS LIST (Cont)

ITEM Number	NSN	DESCRI PTI ON	UNIT OF ISSUE
83	5310-00-807-1474	Nut, Self-Lock Steel 3/16 in	HD
84	5310-00-844-4872	(80205) NAS679A3 Nut, Self-Lock Steel 1/4 in (80205) NAS67904	HD
85	5310-00-071-8390	Nut, Self-Locking (96906) MS17825-4, 1/4-28	EA
86	5310-00-900-9421	Nut, Self-Locking (96906) MS17825-5, 5/16-24	EA
87	5330-00-966-8657	Packing, Preformed Assortment (51808) MAOK311	PG
88	9150-00-250-0926	Petrolatum, Technical (81349) VV-P-236	CN
89	8030-00-616-7696	Potting Compound, Electrical (81349) MIL-S-8516	KT
90	8030-00-664-4968	Putty, Chromate (81349) MIL-P-8116	RO
91	• • •	Repair Fabric (25500) GAC CODE 290 N, 12 oz. Nylon, EA as one sq. yd.	EA
92 93	6810-00-995-4804 5905-00-901-9520	Resin Activator (22527) 4573T Resistor, Fixed Composition	KT EA
93 94	5320-00-006-4912	51 ohm (81349) 63A5A68-510 Rivet, Blind (92215) RV1100-4-3	ВХ
95	5320-00-117-6826	(.139/.143 Shank Dia) Rivet, Blind (96906) MS2040AD4-4	ВХ
96	5320-01-033-8177	(1/8 Nominal) Rivet, Blind, Cherry Max 5-2	EA
97	5320-01-033-8178	(81349) MI L-R-788516 (.173/.176 Shank Dia) Rivet, Blind, Cherry Max 5-6 (81349) MI L-R-7885/6	EA
98 99	5320-01-033-8179 5320-01-033-8642	(.173/.176 Shank Dia) Rivet, Blind (81349) MIL-R-7885/6 Rivet, Blind, CR3243-4-3 (11815), 1/8 Nominal	BX HD
100	5320-01-033-9127	Rivet, Blind, CR3243-4-2 (11815), 1/8 Nominal	HD
101	5320-01-033-9128	Rivet Blind, CR3243-4-4 (11815), 1/8 Nominal	HD
102	5320-01-033-9663	Ri vet Blind, CR3243-4-5 (11815) , 1/8 Nomi nal	HD
103	5320-01-041-6454	Rivet, Blind (11815) CR3553-5-2	EA
104	5320-01-041-6458	(.172/.176 Shank Dia) Rivet, Blind, CR3553-6-6 (96906) MS7885/8-6-6 (.201/.205 Shank Dia)	EA

APPENDIX C
Section II. EXPENDABLE SUPPLIES AND MATERIALS LIST (Cont)

I TEM NUMBER	NSN	DESCRI PTI ON	UNIT OF LSSUF
105	5320-01-042-2891	Rivet, Blind (7652) CR3553-5-6	EA
106	5320-01-042-8250	(.172/.176 Shank Dia) Rivet, Blind (F7652) CR3553-6-4	EA
107	5320-01-042-8893	(.201/.205 Shank Dia) Rivet, Blind (F7652) CR3553-6-2	EA
108	5320-01-043-6694	(.201/.205 Shank Dia) Rivet, Blind (F7652) CR35553-5-4	EA
109	5320-01-084-9234	(.172/.176 Shank Dia) Rivet, Blind, Cherrymax 6-6 (81349) MIL-R-7885/2	EA
110	5320-01-084-9235	(.188/.192 Shank Dia) Rivet, Blind (81349) MIL-R-7885/2-6-05	EA
111	5320-01-084-9236	(.188/.192 Shank Dia) Rivet, Blind (11815) CR3213-6-11	EA
112	5320-01-085-9995	(.188/.192 Shank Dia) Rivet, Blind, Cherrymax (11815) CR3213-6-7	EA
113	5320-01-135-7319	(.188/.192 Shank Dia) Rivet, Blind, Cherrymax 6-3 (81349) MIL-R-7885/2	EA
114	5320-01-136-1782	(.188/.192 Shank Dia) Rivet, Blind, Cherrymax 6-4	EA
115	9320-00-241-9747	(81349) MIL-R-7885/2 Rubber Sheet (81349) MIL-R-6855	SH
116	9320-00-291-8468	3/16 in. thick Rubber Sheet (22337)	SH
117	9320-01-117-1964	PF10056, 1/32 in. thick Rubber Sheet (81349) MIL-R-6855,	SH
118	5330-00-224-7201	1/8 in. thick Abrasive Paper 400 Grit (81348)	SH
119	5350-00-224-7203	P-P-101 Abrasive Paper 320 Grit (81348)	SH
120	5350-00-619-9167	P-P-101 Abrasive Paper 80 Grit (81348)	SH
121	5350-00-721-8117	P-P-101 Abrasive Paper 180 Grit (81348)	SH
122	5330-01-060-8212	P-P-101 Abrasive Paper 600 Grit (98747)	SH
123	5305-00-206-2036	7530179-50 Screws, Wood (81348) FF-S-85	BX
		(2.0.0)	DΛ

 $\label{eq:appendix} \mbox{Section II. EXPENDABLE SUPPLIES AND MATERIALS} \ \mbox{LIST (Cont)}$

ITEM NUMBER	— NSN	DESCRI PTI ON	UNIT OF ISSUE
124	8030-00-881-5238	Sealant and Puttying Compound (81349) MIL-S-8516	KT
125	8030-00-935-1083	Seal ant, Asphal t Base (81349)	CN
126	8030-00-965-2004	Seal ant, Synthetic Rubber (81349) MIL-S-8802	KT
127	8030-00-656-1426	Sealing Compound, Gasket Non- Hardening (81349) MIL-S-45180	PT
128	8030-00-723-2746	Sealing Compound, Pro-Seal 890 (81349) MIL-S-7502	QT
129	9535-00-167-2280	Sheet Metal, 0.040 2024-T3 (81348) QQ-A-250/5	SH
130	9535-00-224-7032	Sheet Metal, .020 in, 2024-T3	SH
131	9515-00-231-8601	Sheet Metal, 0.032 Stainless (81349) MIL-S-5059	SH
132	9535-00-232-0383	Sheet Metal, 0.071 2024-T3 (81348) QQ-A-250/5	SH
133	9535-00-232-0405	Sheet Metal, 0.090 2024-T3 (81348) QQ-A-250/5	SH
134	9535-00-232-0529	Sheet Metal, 0.063 2024-T3 (81348) QQ-A-250/5	SH
135	9535-00-232-0569	Sheet Metal, 0.050 2024-T3 (81348) QQ-A-250/5	SH
136	9535-00-232-7540	Sheet Metal, 0.063 7075-T6 (81348) QQ-A-250/13	SH
137	9535-00-236-7075	Sheet Metal, 0.125 7075-T6 (81348) QQ-A-250/13	SH
138	9535-00-249-5808	Sheet Metal, 0.040 7075-T6 (81348) QQ-A-250/13	SH
139	9535-00-249-5809	Sheet Metal, 0.050 7075-T6 (81348) 00-A-250/13	SH
140	9515-00-596-1728	Sheet Metal, 0.040 Stainless (81349) MIL-S-5059	SH
141	9515-00-995-0731	Sheet Metal, 0.016 Stainless (81349) MIL-S-5059	SH
142	5305-00-854-6689	Sheet Metal Screws (96906) MS24617-33	ВХ
143	5305-00-883-0628	Sheet Metal Screws (96906) MS24617-21	ВХ
144	8040-00-828-7385	Silicon Sealant	TU
145	5940-01-079-1375	Splice, 14/16 AWG Blue (81349) MIL-T-7928/3	EA
146	5940-01-079-1646	Splice, 24/26 AWG Yellow (81349) MIL-T-7928/3	EA
147	5940-01-079-1647	Splice, 18/20 AWG Red (81349) MIL-T-7928/5	EA

 $\label{eq:appendix} \textbf{APPENDIX} \ \textbf{C}$ $\textbf{Section} \quad \textbf{II.} \quad \textbf{EXPENDABLE} \ \textbf{SUPPLIES} \ \textbf{AND} \ \textbf{MATERIALS} \ \textbf{LIST}(\textbf{Cont})$

I TEM NUMBER	NSN	DESCRI PTI ON	UNIT OF LSSUF
148	5940-01-079-1936	Splice, 12/10 AWG Yellow (81349) MIL-T-7928/3	EA
149	5940-00-500-8723	Splice, Conductor, Crimp Style, Wire Gage 10 (96906) MS25181-3	EA
150	6850-00-264-9038	Solvent, Cleaning, P-D-680 (81348)	GL
151	4020-00-753-6555	String (81349) MIL-T-43435	RO
152	7510-00-473-9855	Tape, Opaque Mat, Cotton (81349) MI L-T-23397	RO
153	7510-00-754-2522	Tape, Aluminum Adhesive (16059) P/N 14210	KT
154	5970-00-419-4291	Tape, Electrical (81349) MIL-I-24391	RO
155	7510-00-680-2450	Tape, Maski ng (80244) MI L-T-21595	RO
156	7510-00-074-5124	Tape, Green (58536) A-A-1586	DO
157	5940-00-143-4777	Termi nal , Lug (81349) MIL-T-7928	RO
158	5940-00-115-0776	Terminal, Lug, 2 AWG 3/8 in. Hole (96906) MS20659-114	BX EA
159	5940-00-115-4992	Terminal, Lug, 6 AWG 3/8 in. Hole (96906) MS20659-110	EA
160	5940-00-143-4771	Terminal, Lug, 10 AWG 18/20 (96906) MS25036-103	EA
161	5940-00-143-4780	Terminal, Lug, Crimp Style Stud, Size 10, Wire Gage 16-14	ВХ
162	5940-00-804-9184	(81349) MIL-T-7928 Terminal, Quick Disconnect, Wire Size 14-16 (96906) MS27429-2	PG
163	5940-00-804-9185	Terminal, Quick Disconnect, Wire Size 18 (96906) MS27429-1	PG
164	1670-00-725-1437	Ti edown Strap, Cargo (240 in) (81349) MIL-T-27260, Type CGUB1	EA
165	5975-00-156-3253	Tiedown Strap, Elec (96906) MS3367-2-9	HD
166	5975-00-984-6582	Ti edown Strap, Elec (96906) MS3367-1-0	HD
167	8305-00-753-2967	Towel, Wiping (81348) CCCC46	ВХ
168	5310-00-275-4290	Washer Assortment (81349) MIL-W-1085	PG
169	5310-00-167-0765	Washer, Flat (88044) AN970-3	DV
170	5310-00-167-0766	Washer, Flat (88044) AN970-4	BX
171	5310-00-167-0801	Washer, Flat Steel, 3/16	BX
		(88044) AN960C10	EA

 $\label{eq:appendix} \textbf{APPENDIX} \ \textbf{C}$ Section II. EXPENDABLE SUPPLIES AND MATERIALS LIST (Cont)

I TEM NUMBER	NSN	DESCRI PTI ON	UNIT OF ISSUE
172	5310-00-167-0812	Washer, Flat (88044) AN960C10L	EA
173	5310-00-205-8924	Washer, Flat (88044) AN960C416L	EA
174	5310-00-209-0027	Washer, Flat Steel, 1/4 (80205) NAS143-4	EA
175	5310-00-268-2735	Washer, Flat Assortment (81349) MIL-W-1085	HD
176	5310-00-883-3049	Washer, Flat Steel 5/16 (80205) NAS1587-5L	EA
177	6145-00-144-0231	Wire, Elec, 22 AWG (81349) MIL-W-81044/11	FT
178	6145-00-192-0680	Wire, Elec, 14 AWG (81349) MIL-W-81044/2	FT
179	6145-00-578-6595	Wire, Elec, 4 AWG (81349) MIL-W-5086/2	FT
180	6145-00-917-6378	Wire, Elec, 20 Gage (81349) MIL-W-22759/5	FT
181	6145-00-989-3723	Wire, Elec, 12 Gage (81349) MIL-W-22759/5	RO
182	6145-00-993-5490	(81349) MIL-W-22759/5 Wire, Elec, 18 Gage (81349) MIL-W-22759/5	FT
183	6145-00-023-6777	Wire, Elec, 26 Gage (81349) MIL-W-16878/17	FT
184	6145-01-081-1073	Wire, Elec, 10 Gage (92607) M22759/5-10-9	FT
185	6145-01-122-3317	(92007) M2273973-10-9 Wire, Elec, 2 Gage (81349) MIL-W-22759/3	FT
186	6145-01-203-5399	(81349) MIL-W-22759/3 Wire, Elec, 16 Gage (81349) MIL-W-22759/3	FT

APPENDIX D

SUBSTITUTE MATERIALS/PARTS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

D-1. GENERAL. This appendix lists substitute/alternate materials and parts. Section II contains prime National stock number (NSN) interchangeability cross-references for spare and repair parts from other models of helicopters.

Section III contains o-ring, packing, and gasket substitute information. Section IV contains petroleum, oil, lubricant (POL) substitute, and blending information. Section V contains a substitute table for structural metal alloys.

Section II. INTERCHANGEABLE PARTS

D-2. SCOPE. This section lists and cross-references UH-IH/V helicopter spare and repair parts to other systems having these same parts.

D-3. GENERAL.

- a. Parts pertaining to the helicopter's mechanical and electrical functions are listed on Table D-1.
- b. All parts which have the same NSN can be used on the UH-IH and UH-IV without making any modification prior to installation.

- c. All subcomponents of the major components may be substituted; however, the level of disassembly must be consistent with field tools and skill levels available.
- d. These table listings may be used to cross-reference parts and components provided from cannibalized aircraft.

Table D-1. Spare and Repair Parts U H 6 Н Н H Н Н Н Н Н Н Н H H H H H Н H H 5 1 H 1 E 1 1 6 0 1 1 F 1 P 1 T 1 F 1 1 6 1 H H Ñ NOUN/NSN **BLADE MAIN ROTOR** 1615-00-756-9140 HUB ASSEMBLY X X X MAIN ROTOR 1615-00-886-1778 HUB ASSEMBLY X X X X MAIN ROTOR 1615-00-056-4550 X X TRANSMISSION ASSY 1615-00-919-1351 X X X ENGINE 2840-00-134-4803 X SKID TUBE 1620-00-795-0678 X X X CROSS TUBE 1620-00-076-9036 X X CROSS TUBE 1620-00-967-7624 X X X SHAFT T/R DR 1615-01-008-2798 X X X Х Х X X X SHAFT T/R DR 1615-01-008-2797 X X X BEARING, HANGER 1615-01-056-5365 ELEVATOR, LH 1560-00-996-3906 X X X ELEVATOR, RH 1560-00-996-3905 X SERVO CYLINDER, T/R X 1650-00-014-2038 SERVO CYLINDER, F/C 1650-00-148-9077 Х X TANK, HYD FLUID 1650-00-923-0629 X Χ X TURBINE FAN, OIL COOL 2935-00-916-2528 Χ X Х

				Tab1	e D-	·1.	Spar	e ar	id Re	pair	Par	ts (Cont	.)							
NOUN/NSN	UHIH	H 1 V	H H H	H H M	H H 1 H	UH1E	U 7:1 K	H 1	H 1 F	H 1 P	H	U H 6 0	A H 1 E	H 1 S	A H 1 F	A H 1 P	A H 1 T	A H 6	C H 4 7	0 H 5 8	0 H 6 A
TURBINE FAN, OIL COOL 2935-00-066-0300	X	X	x	X		-					IN			-		-		-	/	-	^
TURBINE FAN, OIL COOL 2935-00-939-8428	X	x	x	^																	
COOLER, LUBRICATING 2935-00-410-5884		x	x																		
PUMP, SUBM FUEL 2915-00-921-5660	х	x	x																		
PUMP, SUBM FUEL 2915-00-012-8684	X	x	x																		
MAST 1615-00-255-2896	x	x	x																		
BLADE, T/R 1615-00-472-7308	X	x	x													_					
STARTER-GENERATOR 205-060-401-3	X	X	x								ļ										
90° GEARBOX 1615-00-918-2677	X	x	x																		
42° GEARBOX 1615-00-918-2676	X	x	х	x																	
VALVE, HYDRAULIC 4810-01-022-3699	X	<u>x</u>	x																		
PUMP, HYDRAULIC 4320-00-134-0980	X	x	x																		
IGNITER-EXCITER 2925-00-064-9435	X	x	x	x	x_	x	x	x	х	x	x		х	x	x	x	x		х		
LINEAR ACTUATOR 2995-00-990-3163	X	x	x	x	X	X	x	x					X	X	x	x					
TANK LUBE OIL 1560-00-070-7837	X	x	X																		
FILTER, XMSN OIL 1615-00-796-5004	χ	x	χ	X		х			х				Х	X	χ	x					
COOLER, XMSN OIL 1615-00-133-6226	X	x	х																		L

					e D-		Spar	e an			Par		Cont	:)							
NOUN/NSN	H 1 H	H 1 V	H 1 H	U H 1 M	H H 1	U H 1 E	H 1 K	H 1 L	U H 1 F	U H 1 P	U H 1 N	U H 6 0	A H 1 E	H 1 S	A H 1 F	A H 1 P	A H 1 T	A H 6 4	C H 4 7	0 H 5 8	0 H 6 A
MANIFOLD, FUEL 2915-00-003-5903	x	x	x										х	x	х	х					
VALVE, FUEL SHUTOFF 2915-00-991-3255	х	х	x																		
FILTER, FUEL 2915-00-003-5904	x	x	x	x_	x	x	x	ļ					x	<u>x</u>	х	x					
FORCE GRADIENT 1560-00-888-7348	x	x	x	x	x_	x			x	x			x	x	x_	x	_				
CONNECTING LINK 3040-00-736-3999	x	<u>x</u> _	x	X_																	
CONNECTING LINK 3040-00-624-5142	x	х	х	х										ļ							
CONNECTING LINK 3040-00-952-8835	x	х	x																		
CONNECTING LINK 3040-00-967-8758	х	х	x								ļ										
CONNECTING LINK 3040-00-964-5066	x	x	х								ļ 										
CONNECTING LINK 3040-00-964-8758	x	x	x																		
CONNECTING LINK 3040-00-055-9023	x	х	x																		
CONNECTING LINK 3040-00-051-3647	х	х	x																		
CONNECTING LINK 3040-00-731-8098	х	x	x																		
CONNECTING LINK 3040-00-052-6312	x	x	x																		
CONNECTING LINK 3040-00-964-5073	x	х	x																		
CONNECTING LINK 3040-00-246-4554	х	х	x																		
CONNECTING LINK 3040-00-952-7145	х	х	x																		

				Tabl	e D-	1.	Spar	e an	d Re		Par	ts (Cont								~
NOUN/NSN	U H 1 H	U H 1 V	E H 1 H	UHIM	H H - H	UH1E	UH1K	DHIL	U H 1 F	U H 1 P	UHIN	ODEO	A H 1 E	A H I S	A H 1 F	A H 1 P	H 1 T	A H 6 4	C H 4 7	0 H 5 8	0 H 6 A
CONNECTING LINK 3040-00-051-3648	X_	х	X																		
CONNECTING LINK 3040-00-877-2954	x	x	x																		
CONNECTING LINK 3040-00-964-5068	x	x	x																		
CONNECTING LINK 3040-00-775-7739	x	x	x			_															<u> </u>
CONNECTING LINK 3040-00-624-6741	x	x	x	x_							ļ 							_			ļ
CONNECTING LINK 3040-00-624-5109	x	x_	x	x			_														
CONNECTING LINK 3040-00-964-5072	x	x	x					_	ļ												<u> </u>
CONNECTING LINK 3040-00-624-5122	x	x	x_	x				_		_		<u> </u>						_	<u> </u>		<u> </u>
CONNECTING LINK 3040-00-624-5146	x	x	x	x_			_					ļ	<u> </u>						<u> </u>		
CONNECTING LINK 3040-00-624-6739	x_	x	x	x			ļ		ļ		-		<u> </u>					-		ļ 	_
CONNECTING LINK 3040-00-624-5139	x	x	x	x	_		<u> </u>	ļ			_		_								<u> </u>
CONNECTING LINK 3040-00-624-5143	x	x	x	x_	ļ	_	_	_			<u> </u>	_	<u> </u>	ļ			_		-		-
MAGNETIC BRAKE 1680-00-909-8098	x	x	X.	x	x	x		-		_	x	_	x	x	x	х	_		ļ	X_	_
MAGNETIC BRAKE 1680-00-921-5992	x	x	x	x	_	_					_			_			_	ļ		_	igg
MAGNETIC BRAKE 1680-00-909-8716	x	_x	X_	x	x	X	x_	x	X.	x	x	_	x	<u>x</u>	x	x	х		-	x	_
GRADIENT, FORCE 1680-00-767-4219	x_	x	x	x	_	_		_	_	_	-	_		_	ļ		_		-	ļ	_
GRADIENT, FORCE 1560-00-888-7348	x	x	x	x																	

								e an					Cont	.)(:)							
NOUN/NSN	H 1 H	H 1 V	H 1 H	HIM	H H 1	H 1 E	H 1 K	H 1 L	U H 1 F	U H 1 P	U H 1 N	H 6 0	A H 1 E	H 1 S	H 1 F	A H 1 P	A H 1 T	H 6	C H 4 7	0 H 5 8	0 H 6 A
TUBE, CYCLIC	<u> </u>	<u>`</u>	 ''-	 	 	<u> </u>	<u> ``</u>	-	†	<u> </u>	<u>"</u>	<u> </u>	-	<u> </u>	 	 	† <u>'</u>	1	 	۳	_
CONT RH 1560-00-624-5127	х	x	x	х											Ì						
TUBE, CYCLIC	<u> </u>	 ^-	 ^-	<u> </u>								 					 	1	<u> </u>	 	
CONT LH 1560-00-652-3262	x	x	x	X	1				ļ								1				
IND, INDICATED		<u> </u>	l .	<u> </u>	1			1				<u> </u>			<u> </u>		 	 -	†		
SPEED 6610-00-526-4397	х	x	X	x																	
																					·
INDICATOR, ATTITUDE 6610-00-731-7969	х	х	x	x					l							l	l				
					Î																
ALTIMETER, ENCODER 6610-00-115-2405	х	х	x	x																	
ALTIMETER, ENCODER																					
6610-00-134-5625	X	X	X	x					ļ.,.												
ALTIMETER, ENCODER																					
6610-01-055-0468	Х	х		Х																	
INDICATOR, COURSE																					
5826-00-505-3094	Х	X	Х	Х					Х				х	Х	х	Х				х	ļ.,
INDICATOR, VERT VEL				1																	
6610-00-952-8832	Х	Х	X	X													<u> </u>	<u> </u>			
INDICATOR, VERT VEL				1														l			
6610-01-125-0726	Х	X	X	X	ļ		<u> </u>					ļ	ļ		ļ	<u> </u>	ļ				
INDICATOR, VERT VEL																					
6610-00-012-4624	Х	Х	X	X	 	ļ								ļ		ļ		ļ			
INDICATOR, VERT VEL																		1			
6610-00-903-0714	X	X	X	X		├						ļ		ļ			<u> </u>	 	<u> </u>		
INDICATOR, LIQ QTY			١													i					
6680-00-181-1955	Х	X	X	_	_	<u> </u>										<u> </u>					
INDICATOR, LIQ QTY	L.																				
6680-00-104-6704	X	X	X		 		\vdash	_									<u> </u>				
INDICATOR, PRESS			,										.,			.					
6620-00-514-5334	X	X	X	Х	-		ļ	ļ					X	X	X	Х	<u> </u>				
INDICATOR, OIL TEMP	J			J												_					
6685-00-557-0370	X	<u> </u>	X	X	 		ļ						X	X	X	X			X		
INDICATOR, OIL PRES	v																				
6620-00-179-1886	X	X	X	X	<u></u>		<u>X</u>										l	l	L		i

				Tabl	e D-	1	Spar	e ar	d Re	pair		ts (Cont	.)							
NOUN/NSN	U H 1 H	U H 1 V	H 1 H	H 1 M	H 1 H	HIE	U H 1 K	H	DIAF	UHIP	DHAN) H 60	A H 1 E	AHIS	A H 1 F	A H 1 P	A H 1 T	A H 6 4	C H 4 7	01158	0 H 6 A
VOLTMETER, DC 6625-00-235-4782	х	X_	x	x																	
VOLTMETER 6625-00-538-9683	x	x	х	x								i									
METER, SPEC SCALE 6625-00-544-5899	x	x	х	x																	
ALTIMETER, PRESS 6610-00-110-3368 TNDICATOR RADIO-MAG	x	х	x	x									x	x	x	x		<u></u>	x	x	
5826-00-897-4889	X	X	X	X	<u> </u>	_			_	_		<u> </u>	-		<u> </u>		ļ				
INDICATOR, IAS 6610-00-526-4397	х	х	х	х																	
INDICATOR, TACH 6680-00-907-8380	х	х	х	х																	
INDICATOR, TACH 6680-00-841-0302	X_	х	х	x									х	Х	х	х					
IND, TURN & SLIP 6610-00-169-1489	х	х	х	х							х		x	Х	x	x					
IND, TURN & SLIP 6610-00-339-1254	х	х	х								х		х	X	х	х					
INDICATOR, TACH 5620-00-557-3023	x	х	х	х																	
INDICATOR, TEMP 6685-00-557-5910	х	х	х	х									x	х	х	x					
INDICATOR, ATTITUDE 6610-00-781-8537	х	х	х	х																	
INDICATOR, ATTITUDE 6610-00-179-9035	Х	х	х	х																	
INDICATOR, ATTITUDE 6610-00-758-2385	X	х	х	х																	
INDICATOR, ATTITUDE 6610-00-905-0210	Х	х	х	х																	
INDICATOR, ATTITUDE 6610-00-912-3613	Х	х	X	x																	

TM 55-1520-210-BD

APPENDIX D

Table D-1. Spare and Repair Parts (Cont)

	H	H	H	H	H	H	H	H	H	H	H	H	H	A H	A H	H	A H	A H	D H 4) I	H
NOUN/NSN	Ĥ	٧_	Ħ_	M	Ħ_	Ę	Ķ	Ĺ	F	P_	Ň	ő	Ė	Š	F	P	Ť	4	7	8	Ā
CLOCK 6645-00-084-1424	х	x	x	x							x		x	x	x	х			X	X.	
BATTERY 6140-00-578-7525	X	x	x																		
BATTERY 6140-01-046-1116	x	x	х																		

Section III. O-RING, PACKINGS, AND GASKETS

D-4. SCOPE. This section lists and cross-references packings and o-rings in the military part number series to commercial or other military series, Table D-2.

D-5. GENERAL. Use of substitute or alternate packings may limit the operational life of the packing when exposed

to higher temperatures or fluids not in its range. The degradation process will not occur rapidly enough to affect the helicopter mission except in instances where low temperature packings or seals are used in high temperature applications on the engine or bleed air system.

Table D-2. Packings Reference and Temperature Guides Chart

	IGDIC D	_		and competators as		
PRIMARY PART NO. SERIES	MILITARY SPECIFICATION	PARKER COMPOUND	BASE POLYMER	TEMP GUIDE CONT SERV	DURO- METER	SERVICE
AN6227B AN67230B	MIL-P-5516 Class B	PS-01-30-5	NITRILE (BUNA N)	-65°F to +180°F	70	Air Force and Navy hydraulic fluid MIL-H-5606, MIL-H-83282
MS28775	MIL-P-25732	N304-7	NITRILE (BUNA N)	-65°F to +250°F	70	
MS29512 MS29513 2-, 3-	MIL-P-5315	N602-7	NITRILE (BUNA N)	-65°F to +180°F	60	Air Force & Navy aircraft fuel JP-4, JP-5
MS29561 NAS617	MIL-R-7362 Comp.A, Type 1	47-071	NITRILE (BUNA N)	-65°F to +250°F	70	Synthetic lubricants MIL-L-7808
AN6290 MS28778 2-, 3-	MIL-P-5510	N507-9	NITRILE (BUNA N)	-65°F to +180°F	90	Hydrualic oil, MIL-H-5606 MIL-H-83282
NAS1593 NAS1595	MIL-R-25897 CL 1	77-545	Fluoro-1 Elastomer	-20°F to +400°F	70	High temperature, fluid resistant.
NAS1594 NAS1596	MIL-R-25897 CL 2	V-377-9	Fluoro-1 Elastomer	-20°F to +400°F	90	High temperature, fluid resistant.

ALTERNATE, SUBSTITUTE PART NO.		PARKER COMPOUND	BASE POLYMER	TEMP GUIDE CONT SERV	DURO- METER	SERVICE AND SPECIFICATIONS
2-, 3-	SC720BCE1 E3 F2	C147-7	NEOPRENE	-65°F to +300°F	70	Freon 12, weather & salt water resistant. AMS3209
2-, 3-	SC712BE1 E3 F2	C526-7	NEOPRENE	-65°F to +300°F	70	General purpose industrial Neoprene. AMS3209
2-, 3-	R810 B F2	F515-8	ETHYLENE PROPYLENE	-65°F to +300°F	80	Skydrol, Cellulube, & other phosphate esters, steam, water, air, dilute acids & alkalis.

Table D-2. Packings Reference and Temperature Guides Chart (Cont)

	lable D-2.	<u>Packings</u> ke	rerence and	Temperature Guide	5 Cliai L	(conc)
ALTERNATE,	COMMERCIAL	_				
SUBSTITUTE	DESIGNATION	PARKER	BASE	TEMP GUIDE	DURO-	SERVICE AND
PART NO.	ASTMID735-58T	COMPOUND	POLYMER	CONT SERV	METER	SPECIFICATIONS
						Mineral oil & hy-
						draulic fluid, water,
	SB620B E1		NITRILE			steam, coolants,
2-, 3-	E3 F1	N525-6	(BUNA N)	-40°F to +250°F	60	pneumatic service.
						Petroleum base
MS9021						fuel & low tempera-
MS9020			NITRILE			ture resistance.
2-, 3-	SB712B E1 F2	N506-7	(BUNA N)	-65°F to +225°F	65	AMS7271
						Commercial gasoline,
						mineral oils &
	SB715B E1		NITRILE			hydraulic fluids,
2-, 3-	E3 F2	N103-7	(BUNA N)	-65°F to +225°F	70	pneumatic service.
						Mineral oil &
						hydraulic fluids,
]			alkalies, gasolines,
	SB715B E1		NITRILE			diesel oils,
2-, 3-	E3 F1	N109-7	(BUNA N)	-30°F to +250°F	70	pneumatics.
AN1239XX						Petroleum base
AN1240XX	SB715B E1		NITRILE			fuel resistant.
2-, 3-	E3 F2	N179-7	(BUNA N)	-40°F to +250°F	70	AMS7270
AN1238XX						Petroleum base
AN1239XX			NITRILE			lubricating oil
2-, 3-	SB720B E1 F2	N180-7	(BUNA N)	-20°F to +250°F	70	resistant. AMS7274
						Listed by Underwriter
						Laboratories for
	SB715B E1		NITRILE			fuels, oils, and
2-, 3-	E3 F1	N214-7	(BUNA N)	-40°F to +250°F	70	gasolines.
						Mineral oils &
						hydraulic fluids,
						gasolines, pneu-
1	SB715B E1		NITRILE		ĺ	matics, SAE 120R
2-, 3-	E3 F1	N219-7	(BUNA N)	-40°F to +250°F	70	Class 1, UL Listed.

Table D-2. Packings Reference and Temperature Guides Chart (Cont)

					·	
SUBSTITUTE	COMMERCIAL DESIGNATION	PARKER	BASE	TEMP GUIDE	DURO-	SERVICE AND
PART NO.	ASTMID735-58T	COMPOUND	POLYMER	CONT SERV	METER	SPECIFICATIONS
1						Water service. Low
						swell, extremely
	SB710B E1		NITRILE			stable. Oil
2-, 3-	E3 F1	N398-7	(BUNA N)	-40°F to +250°F	70	resistance.
						For rotary seals.
	SB820B E1		NITRILE			Do not use with
2-, 3-	E3 F1	N256-8	(BUNA N)	-20°F to +225°F	80	stainless steel.
						Mineral oils &
	SB715B E1		NITRILE			hydraulic fluids,
2-, 3-	E3 F1	N532-8	(BUNA N)	-20°F to +250°F	80	gasoline, pneumatics.
						Mineral oil &
1						hydraulics fluid,
			NITRILE			pneumatics. High
2-, 3-	SB915B E1 E3	N183-9	(BUNA N)	-30°F to +250°F	90	extrusion resistance.
			1			Mineral oil &
			NITRILE			hydraulic fluids
2-, 3-	SB915B E1 E3	N552-9	(BUNA N)	-30°F to +250°F	90	pneumatics.
						Air & gases.
	TA-605B E1	ļ				Static seal
2-, 3-	E3 F2	S418-6	SILICONE	-80°F to +450°F	60	only. AMS3303
						Air & gases.
	TA705B E1					Static seal
2-, 3-	E3 LF2	S417-7	SILICONE	-80°F to +450°F	70	only.
						Air & gases.
MS9068	TA-705BE1					Static seal
2-, 3-	E3 F2	S604-7	SILICONE	-80°F to +450°F	70	only. AMS3304
	20 . 2		00000000			High temperature
		}				oils, aromatic
1			Fluoro-1			solvents, chemical
2-, 3-	None	77-545	Elastomer	-20°F to +400°F	70	service. AMS7278
						High temperature
						oils, aromatic
			Fluoro-1			solvents, chemical
2-, 3-	None	V377-9	Elastomer	-20°F to +400°F	90	service. AMS7278
						/ / / L/ C

Section IV. PETROLEUM, OIL, AND LUBRICANTS (POL)

D-6. SCOPE. This section lists various types of substitute fuels, lubricants, and hydraulic fluids which can be used on the UH-IH/V helicopter. Contained in this section Is general Information concerning types, uses, and effects of such POL substitutes and methods of purging and flushing systems after use.

D-7. **GENERAL.**

- a. Some products are made up of chemical ingredients which are not compatible with products used on a UH-IH/V aircraft. Some fuels, oils, and hydraulic fluids can have an adverse effect on systems and components compatible with the UH-IH/V systems; therefore, it is advisable to properly identify the product by specification number and name for cross-reference with primary and expedient products available.
- b. National stock numbers are used in conjunction with specification numbers to distinguish them from foreign products. The identification of (NATO) product numbers relate directly to U.S. Military Specification Numbers and thus are considered direct replacements.
- c. In some situations, POL substitute products of friendly or enemy nations can be used; however, CAUTION should be exercised due to the possibility of sabotage. If there is no other alternative but to use enemy products, check for signs of contamination, discoloration, smell, and thickness.
- d. Once a product under consideration is identified, as described above, it will fall in one of three categories. These categories are defined as follows:
- (1) Primary Products. These are basic products for which the system was designed. The system will function without limitation.

(2) Alternate Product. These are products that closely match the primary product and may result in some reduced performance with no effect on system durability. There are no limitations on duration of use.

CAUTION

The helicopter shall not be flown when emergency fuel has been used for a total cumulative time of 50 hours unless **a** hot section inspection is performed.

- (3) Emergency/Expedient Products. These are products that can be used for only short periods of time. These products are to be used as a last resort. These products will cause poor performance and system damage after prolonged use.
- e. Table D-3 lists some possible U.S. military and commercial fuels, in proper priority, that may be used. Table D-4 lists primary and alternate fuel sources for various countries. Table D-5 lists some commercial fuel sources that may be substituted for the primary or standard JP-4 fuel and also some alternate fuel sources which are similar to JP-5 and JP-8.
- f. Some substitute fuels, which alone cannot be used on UH-IH/V, can be blended with a primary fuel and can then be utilized for engine operation.
- (1) When using fuel blends, it is preferable to premix the fuels in a container before pouring into tank. This method of mixing the primary fuel with a substitute fuel ensures that the fuels mix completely. The best expedient fueling method is to add both fuels at the same time from two separate fuel lines.

TM 55-1520-210-BD

APPENDIX D

Table D-3. Substitute U.S. Fuels

	Table D-3.	Substitute U.S. F		
PRIMARY FUEL	ALTERNATE FUEL	EMERGENCY FUEL	MILITARY SPECIFI- CATION	COMMERCIAL SPECIFI- CATION
Aviation Turbine Fuel (JP-4)			MI L-T-5624 (JP-4) NATO CODE F-40	ASTM-D-1655-70 (Jet B JP-4 Type)
	Aviation Turbine Fuel (JP-5)		MI L-T-5624 (JP-5) NATO CODE F-44	ASTM-D-1655-70 (Jet A JP-5 Type)
	Aviation Turbine Fuel (JP-8)		MI L-T-83133 (JP-8) NATO-CODE F-34	ASTM-D-1655-70 (Jet A-1 JP-8 Type)
		AVGAS (any)	MI L-G-5572 NATO CODES F-12, F-18, F-22	

Table D-4. Approved Alternate Foreign Commercial Fuels for the UH-IH/V Helicopter

USSR	GOST 1842-52 GOST 10227-62 T-1. TS-1		
UNITED STATES	MIL-T-5624 Grade JP-4	MIL-T-5624 Grade JP-5	
UNITED KINGDOM	D. Eng. RD. 2454	D. Eng. RD. 2498	
TURKEY	MIL-T-5624 Grade JP-4		
PORTUGAL	MIL-T-5624 Grade JP-4		_
NORWAY	MIL-T-5624 Grade JP-4		
NETHERLANDS	MIL-T-5624 Grade JP-4	D. Eng. RD. 2493	
<u>I TALY</u>	AA-M-C-1421	AMC-143	_
GREECE	MIL-T-5624 Grade JP-4		
FEDERAL REPUBLIC OF GERMANY	TL 9130-006	UTL 9130-007/ UTL 9130-010	
FRANCE	AIR 3407/A		_
DENMARK	MIL-T-5624 Grade JP-4		
CANADA	3-GP-22F	3-6P-24. e	_
BELGI UM	BA-PF-2B	BA-PF-6	
PRODUCT DESCRIPTION	TURBINE FUEL, AVIATION TYPE: WIDE CUT TYPE	TURBI NE FUEL, AVI ATI ON: HI GH FLASH KEROSENE TYPE	TURBI NE FUEL, AVI ATI ON: KEROSENE TYPE
NATO CODE NO.	F-40	F-44	F-34
U.S. MILITARY FUEL	JP-4(MIL-T-5624)	JP-5(MIL-T-5624)	JP-8-(MIL-T-83133)
	Fuels for the UH-IH/V Helicopter PRIMARY FUEL ALTERNATE FUELS		

Table D-5. Commercial Fuels for the UH-1H/V Helicopter

SOURCE	PRIMARY OR STANDARD FUEL	ALTERNATE FUELS	
U.S. MILITARY FUEL	JP-4(MIL-T-5624)	JP-5(MIL-T-2624)	JP-8(MIL-T-83133)
NATO CODE NO.	F-40	F-44	F-34
COMMERCIAL FUEL (ASTM-D-1655)	JET B	JET A	JET A-1
American Oil Co.	American JP-4	American Type A	
Atlantic Richfield Richfield Div	Arcojet B	Arcojet A Richfield A	Arcojet A-1 Richfield A-1
B. P. Trading	B. P. A. T. G		B. P. A. T. K.
Caltex Petroleum Corp.	Caltex Jet B		Caltex Jet A-I
City Service Co.		CITCO A	
Continental Oil Co.	Conoco JP-4	Conoco Jet-50	Conoco Jet-60
Exxon Co. U.S.A.	Exxon Turbo Fuel B	Exxon A	Exxon A-1
Gulf Oil	Gulf Jet B	Gulf Jet A	Gulf Jet A-1
Mobil Oil	Mobil Jet B	Mobil Jet A	Mobil Jet A-1
Phillips Petroleum	Philjet JP-4	Philjet A-50	
Shell Oil	Aeroshell JP-4	Aeroshell 640	Aeroshell 650
Sinclair		Superjet A	Superjet A-1
Standard Oil Co.		Jet A Kerosene	Jet A-1 Kerosene
Chevron	Chevron B	Chevron A-50	Chevron A-1
Texaco	Texaco Avjet B	Avjet A	Avjet A-1
Uni on Oil	Uni on JP-4	76 Turbine Fuel	

NOTE:

Anti-icing and Biocidal Additive for Commercial Turbine Engine Fuel. The additive provides anti-icing protection and functions as a biocide to kill microbial growths in aircraft fuel systems. Icing inhibitor conforming to MIL-I-27686 shall be added to commercial fuel, not containing an icing inhibitor, during refueling operations, even though the engine or aircraft has a fuel heater and regardless of ambient temperatures. Refueling operations shall be accomplished in accordance with accepted commercial procedures. This additive (Prist or eq.) is not available through the Army Supply System, but is to be locally procured when needed.

- (2) There is no special limitation on the use of Army standard fuel or alternate fuel. When using an emergency fuel, a fuel mixture which contains over 10 percent leaded gasoline is considered to be all leaded fuel. When using an emergency fuel, an entry on the faults and remarks column of DA Form 2408-13, Inspection Record, should be made. The entry should annotate the type of fuel, additives, and duration of operation.
- (3) Fuels having the same NATO code number are interchangeable, and fuels conforming to ASTM-D-1655 specification may be used when standard fuel MIL-T-5624-JP4 is not available. Refer to Table D-3.
- This section lists primary, alternate, and expedient lubricants and hydraulic fluids. The lubricants and hydraulic fluids used in UH-IH/V systems and components must have a compatible base composition, as well as good additive level. Being that the purpose of lubricants and hydraulic fluids is to reduce wear, support bearing loads, and provide cooling, their chemical composition must be com-In addition to lubricating, patible. hydraulic fluids must transmit power and motion. If two incompatible hydraulic fluids are mixed, there is a tendency of a gel substance forming within the system and ruining it.
- (1) Some Lubricants will not withstand UH-IH/V temperatures or Loads for extended periods of time. These types of Lubricants do not contain the necessary base properties for withstanding Long term performance; therefore, they are recommended only as a last resort.

- (2) Expedient Lubricants can cause one of three problems.
- (a) They may not allow proper efficient operations because of improper viscosity.
- (b) They may allow an increase in wear because of improper viscosity.
- (c) They may cause seals to swell or create deposits because of improper composition.
- h. Table D-6 lists the primary lubricants and hydraulic fluids which are used as primary, alternate, or emergency uses on the UH-IH/V helicopter.

CAUTI ON

Lubricating oil MIL-L-23699 shall not be used in ambient temperatures below -25°F/-32°C

NOTE

It is not advisable to mix MIL-L-7808 and MIL-L-23699 oils, except during an emergency. If oils are mixed, the system should be flushed within six hours. An entry on DA Form 2408-13 is required when the oils are mixed. Hydraulic oils MIL-L-83282 and MIL-L-5606 should not be mixed except during an emergency. When these oils are mixed with each other or any other oil, a DA Form 2408-13 is required.

Table	D~6. Substitute Lub	ricants and	Hydraullc Fluids	
UH-1H/V EQUIPMENT	PRIMARY		ALTERNATE	
	MI L-SPEC	NATO CODE		
Engi ne Transmi ssi on	MIL-L-23699 (use in ambient	0-156	0-149	
42° Gearbox 90° Gearbox	temp above -25°F/-32°C)		CAUTION NATO O 140 i a NOT com	
Pillow Block	NOTE		NATO 0-149 is NOT compatible with MIL-23699. DO NOT MIX. Drain flush and fill when conversion required.	
	Do not use MIL-L-23699 below -25°F (-32°C)			
	MIL-L-7808 (use in ambient	0-148	0-149	
	temp above -25°F/-32°C)		**Mixture of MIL-L-23699 and MIL-L-7808 is accept- able in an emergency.	
Main Rotor Hub P/N 204-012-101-31 (typ UH-IH/V)	MIL-L-2104, Grade 40 (use In ambient temp 41°F/5°C and above)	0-230	Mix oils only in an emergency.	
	MIL-L-2104, Grade 30 MIL-L-46152, Grade 30 (use In ambient temp 0°F/-I8°C to 41°F/5°C)	0-230	Make DA Form 2408-13 entry when mixing occurs.	
			MUST be flushed within 6-hours.	
	MIL-L-2104, Grade 10 MIL-L-46152, Grade 10W30 (use in ambient temp -20°F/-29°C to o°F/-18°c)	0-230		
	MIL-L-46167, DEXTON II ATF (use in ambient temp -65°F/-54°C to -4°F/-20°C)			

Table D-6	Substitute Lubr	icants and b	<u> Tydraulic Fluids (Cont)</u>
UH-I H/V EQUI PMENT	PRI MARY		ALTERNATE
	MI L-SPEC	NATO CODE	
Hydraulic System	MIL-H-5606 (use In ambient temp below -30°F/-35°C)	H-515	Mix hydraulic fluid only in an emergency.
	MIL-H-83282 (use in ambient temp above -30°F/-35°C)		Make DA Form 2408-13 entry when mixing occurs.

Table D-7. Substitute Commercial Oils and Hydraulic Fluids

For MIL-L-7808 - Lubricating Oil, Acft Turbine Engine, Synthetic Base Substitute:

PQ Turbi ne 011 8365
Exxon Turbo 0i I 2389
Esso Turbo 011 2389
RM-184A
RM-201A
E-6825
Royco 807HR
Royco 808HR
PL-10568

Ameri can 011 & Suppl y Co.
Exxon Co. USA

Mobi I 0i I Corp.
Stauffer Chemi cal Co.
Royal Lubri cants Co.
Rohm & Haas Co.

STO-6530

For MIL-L-23699 - Lubricating Oil, Acft Turbine Engines, Synthetic Base Substitute:

American 011 & Supply Co. PQ Turbine Lubricant 6423 PQ Turbine Lubricant 5247 PQ Turbine Lubricant 6700 PQ Turbine Lubricant 7731 PQ Turbine Lubricant 8878 PQ Turbine Lubricant 9595 PQ Turbine Lubricant 9596 PQ Turbine Lubricant 9597 Bray 011 Co. Brayco 899 Brayco 899-G Brayco 899-S Brayco 899-D Castrol Oil Inc. Castrol 205 Chevron International Oil Co., Inc. Chevron Jet Engine Oil 5 Drew Chemical Corp. STO-21919 STO-21919A

Table D-7. Substitute Commercial Oils and Hydraulic Fluids (Cont)

HATCOL 3211 W. R. Grace & Co., Hatco Chemical Div. HATCOL 3611 Esso Turbo Oil 2380 Humble Oil & Refining Co. Esso Turbo Oil 2380 2395 Turbo Oil (WS-6459) 2392 Turbo Oil 2393 Turbo 0il Gulflight 20 Mobil Jet II/RM-139A Gulf Oil Co. Mobil Oil Corp. Avrex S Turbo 260 Avrex S Turbo 265 ROYCO 899 (C-915) Royal Lubricants Co. Stauffer Jet II Royco 899SC Aeroshell Turbine Oil 500 Shell Oil Co. Shell Aircraft Turbine 551 AeroShell Turbine Oil 550 Shell International Petroleum Co. Ltd. Chevron Jet Engine Oil 5 Standard Oil Co. of California Stauffer Jet II Stauffer Chemical Co. Stauffer 6924 SATO 7377 Texaco, Inc. SATO 7730 Starjet 5

For MIL-H-5606 - Hydraulic Fluid, Petroleum Base, Acft and Ordnance Substitute:

"PO" Hydraulic Fluid 4226 American Oil & Supply Co. Brayco 757B Bray Oil Co. Brayco 756C Brayco 756D Brayco 756E Castrol Hyspin A Castrol Oils, Inc. Univis J41 Humble Oil & Refining Co. Univis J41 Exxon Co. Mobil Aero HFB Mobil Oil Corp. Pennsyl vani a Refining Co. Petrofluid 5606B Petrofluid 4607 ROyCO 756C Royal Lubricants Co. ROyCO 756D DS-437 PED 3565 Standard Oil Co. of California PED 3337 TL-5874 Stauffer Aero Hydaroi I 500 Texaco, Inc. Stauffer Chemical Co. 25606 MZF Associates FP-221 Union Carbide Corp.

Table D-7. Substitute Commercial Oils and Hydraulic Fluids (Cont)

For MII-H-83282:

The following commercial oils may be purchased locally under the following manufacturer's designation:

Brayco Micornic 882 XRM-230A XRM-231A Royco 782 Hanover R-2 HF-832 Brayco Oil Co.
Mobil O11 Corp.
Mobil O11 Crop.
Royal Lubricants Co.
Hanover Chemical Industries, Inc.
Hanover Processing Co.

Section V. STRUCTURAL METAL ALLOYS

- D-8. **SCOPE**. This section lists and cross-references substitute structural metal alloys.
- D-9. GENERAL. Due to the short term of use, weight and dissimilar metal corrosion, considerations can be overlooked during BDAR structural repairs. Metal selection should be based only on strength requirements. Refer to Table D-8 and use the following steps to locate substitute metal alloy types:
- a. Locate the material to be replaced on the line in the left-hand column.

- b. Locate the substitute material In the vertical columns.
- c. To obtain the minimum thickness of the substitute material, multiply the thickness of the material to be replaced by the factor shown at the Intersection of the line and column found in step a & b, substitute standard gage equal to this thickness or nearest standard gage.

Table D-8. Metal Substitution Chart

			2024		1025)75 [6	8	130 630 EEL		TITA	MUIM			STAINLES STEEL	5
MATERIAL TO BE REPLACED	ULTIMATE TENSILE STRENGTH PSI	T3&4 CLAD	T4 EXTRUDED	T6 BARE	STEEL	CLAD	EXTRUDED	90 KSI	125 KSI	99%	8 Mn	6AL -4V	6A1- 6V- 2Sn	1/4 301	1/2 302	321 347
6061-T6 EXTRUDED	38,000	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
AZZIA-H MAGNESIUM	39,000	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
6061-T6 CLAD	42,000	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
2024 T4 EXTRUDED	57,000	1.0	1.0	1.0	1.04	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
2024 T4 CLAD	58,000	1.0	1.02	1.0	1.05	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
2024-T3 CLAD	60,000	1.04	1.05	1.0	1.09	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
2024 16 BARE	62,000	1.07	1.09	1.0	1.13	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
2024 T81 CLAD	64,000	1.1	1.12	1.03	1.16	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
2024 T88 CLAD	70,000	1.21	1.23	1.13	1.25	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
7075 T6 CLAD	72,000	1.24	1.27	1.16	1.31	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
7075-16 BARE	78,000	1.35	1.37	1.26	1.42	1.09	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
7075-16 EXTRUDED	78,000	1.35	1.37	1.26	1.42	1.09	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
7178 T6 BARE	84,000	1.45	1.48	1.36	1.53	1.17	1.08	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
7178 TO EXTRUDED	84,000	1.45	1.48	1.36	1.53	1.17	1.08	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
TITANIUM 99Z	80,000	1.38	1.40	1.29	1.45	1.11	1.02	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
TYPE 321 & 347 CRES	100,000	1.72	1.75	1.61	1.82	1.38	1.28	1.11	1.0	1.25	1.0	1.0	1.0	1.0	1.0	1.0
TITANIUM BMn	120,000	2.06	2.1	1.93	2.18	1.66	1.53	1.33	1.0	1.50	1.0	1.0	1.0	1.0	1.0	1.20
TYPE 301 STAINLESS	125,000	2.15	2.19	2.09	2.27	1.73	1.60	1.38	1.0	1.56	1.04	1.0	1.0	1.0	1.0	1.25
TITANIUM 6AL-4V	134,000	2.31	2.35	2.16	2.43	1.86	1.71	1.48	1.07	1.67	1.12	1.0	1.0	1.07	1.0	1.34
TITANIUM 4AL-4Mn	140,000	2.41	2.45	2.25	2.55	1.94	1.79	1.55	1.12	1.75	1.16	1.04	1.00	1.12	1.0	1.40
TYPE 301 STAINLESS	150,000	2.58	2.63	2.42	2.73	2.08	1.92	1.66	1.20	1.88	1.25	1.11	1.0	1.2	1.0	1.50
TITANIUM 6A1-6V-2Sn	155,000	2.67	2.71	2.5	2.81	2.15	1.98	1.72	1.24	1.93	1.29	1.15	1.0	1.24	1.03	1.55

APPENDIX E

BDAR FIXES AUTHORIZED FOR TRAINING

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

NOTE

.The repair procedures listed below are authorized for sustainment training. They do not permanently alter aircraft or components. These procedures duplicate those highlighted in each system's chapter, Repair Procedure Index, surrounded by a box.

. All other BDAR fixes contained in this manual can be used to train soldiers if scrap parts or beyond economical repair (BER) components are available for practice repair. Such training must be approved by the unit commander. Most of the other procedures not listed in this appendix will permanently alter or damage the equipment.

REPAIR PROCEDURE	<u>Para no</u> .
DRIVE TRAIN	
Transmission Oil Pressure Switch Leak	8-6 8-7 8-8
HYDRAULIC AND PNEUMATIC	
Hydraulic Filter Damage and Leaking Relief Valve Leaking Hydraulic Fluid Solenoid Valve, Damaged and Leaking Pressure Switch Damaged and Leaking	9-7 9-9 9-11 9-13 9-15 9-17 9-20 9-22 9-23 9-24
INSTRUMENTS	
Instrument Replacement	10-6

BDAR FIXES AUTHORIZED FOR TRAINING (Cont)

REPAIR PROCEDURE	<u>PARA NO</u> .
ELECTRICAL AND AVIONICS SYSTEM	
Unshielded Wire, Damaged Wire Repair Segments, Unshielded Wires Damaged Wire Insulation Shielded Cable Repairs Shielded Cable Repair Segments Shield Terminators Terminator for Nickle-Plated Shields Coax Cable Component Bridging (Bypassing) Damaged Fuse Emergency Fabrication Broken Fuses. Substitute Antenna	11-6 11-7 11-8 11-9 11-10 11-11 11-14 11-18 11-20 11-21
FUEL SYSTEM	
Fuel Cell Isolation	12-8 12-10

APPENDIX F

AVIONICS CONFIGURATIONS

BDAR FIXES SHALL BE USED ONLY IN COMBAT OR FOR TRAINING AT THE DISCRETION OF THE COMMANDER.

(AUTHORIZED TRAINING FIXES ARE LISTED IN APPENDIX E.)
IN EITHER CASE, DAMAGES SHALL BE REPAIRED BY STANDARD PROCEDURES AS SOON AS PRACTICABLE.

Section I. INTRODUCTION

F-1. SCOPE. This appendix lists and depicts the major components, cable routes, and wiring terminations pertaining to the UH-lH/V helicopter. This information Is furnished as an aid to expedient repair techniques described in Chapters 10 and 11.

F-2. GENERAL. The actual configurations may vary depending on particular requirements or changes incorporated through modification work order (MWO) action and special purpose alterations.

Figures F-1 thru F-16 show typical location of radios and their associated components in relation to the helicopter and lists the radio and component part number. Each figure also has a table associated with the avionics system which contains acomplete wire listing. This includes the wire number, type (shielded, not shielded, or pair twisted with shield), both end plugs, and the pin numbers on each end plug.





Table F-1. UHF/AM Radio System AN/ARC-51BX					
WLŖĘŊIJMB <u>E</u> .Ŗ	TYPE 2	END 1	P.I.N.1	END 2	I PIN 1
RU1264A22	NO/S	P1401	Е	P3801	J
RU1231A22	NO/S	P1401	u	P3801	V
RU1232A22	NO/S	P1401	Τ	P3801	W
RU1233A22	NO/S	P1401	L	P3801	<u>a</u> <u>b</u>
RU1234A22	NO/S	P1401	M	P3801	<u>b</u>
RU1235A22	NO/S	P1401	K	P3801	Z
RU1236A22	NO/S	P1401	N	P3801	а
RU1237A22	NO/S	P1401	J	P3801	T
RU1238A22	NO/S	P1401	Υ	P3801	<u>f</u> 9
RU1239A22	NO/S	P1401	F	P3801	9
RU1240A22	NO/S	P1401	Z	P3801	ĥ
RU1241A22	NO/S	P1401	Н	P3801	1 Y
RU1242A22	NO/S	P1401	g P	P3801	
RU1243A22	NO/S	P1401	P	P3801	K
RU1244A22	NO/S	P1401	Χ	P3801	M
RU1245A22	NO/S	P1401	g	P3801	Х
RU1246A22	NO/S	P1401	g b	P3801	Z
RU1247A22	NO/S	P1401	5	P3801	S
RU1248A22	NO/S	P1401	R	P3801	R
RU1230A22	NO/S	P1401	V	P3801	V
RU1249A22	NO/S	P1403	С	P3801	D
RU1257A22	NO/S	P1403	Z	P3801	В
RU1251A22	NO/S	P1403	Τ	P3801	Α
RU1252A22	SHI ELD	P1403	R	P3801	Е
RU1272A22	NO/S	P1403	a P	P3801	Н
RU1250A22	NO/S	P1403	P	P3304	F
RU1274A22	NO/S	P1403	U	TB26	3
RU1267A22	NO/S	P1403	Α	CB29(UHF)	-
RU1267B22	NO/S	P1403	В	CB29(UHF)	
RU1266A18N	NO/S	P1403	Υ	TB66	i
RU1266B18N	NO/S	P1403	Χ	TB66	9
RU1266C22	NO/S	P1403	D	(SHI ELD	Pins V*
				GND)	and E*
RU1258A22	PR/S	P1403	٧*	P3303	Α
			(Red)		
RU1259A22	PR/S	P1403	E*	P3303	u
			(Blk)		
RU1256A22	SHI ELD	P3801	F	J600	24
RU1273A	COAX	P1405	-	P1407	(AT 1108])
RU1254A18N	NO/S	P3801	N	TB26	6
L122A20	NO/S	P3801	Р	TB12	1

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield

PR/S--PairTwisted, W/Shield

DRAWING DESIGNATION	PART <u>NUMBER</u>	DESCRIPTION
1	AT-1108/ARC	Antenna, VHF/UHF
2	AN/ARC-115()	Radio, VHF/AM
3	205-075-382	Filter, Band Pass, VHF




Tabl e	F-2. VHF	// AM Radio	_AN/ARC	<u>′ 115</u>	
WIRE NUMBER	TYPE 2	END 1	TPIN 1	END 2	TPIN 1
ARC1I 5-101A	COAX	P3200	1	P3202 (FL6)	1
ARC115-102A	COAX	P3203 (FL6)	-	P1906 (AT-1108)	-
ARC115-27A22 ARC115-28A22N ARC115-2A22 ARC115-31A22 ARC115-14A20N ARC115-5A20N ARC115-4A20 ARC115-3A22 ARC115-3B22 ARC115-3B22 ARC115-11A22(BLK] ARC115-10A22(RED] ARC115-60A22N	SHI ELD SHI ELD NO/S NO/S NO/S NO/S NO/S NO/S NO/S NO/S	P3201 P3201 P3201 P3201 P3201 P3201 P3201 P3201 SPLI CE SPLI CE P3201 P3201 P3201	dieib rip e d c l k shi eld on	J600 TB66 P3201 P3304 TB26 TB26 CB32(VHF) SPLI CE TB12 P3302 P3303 P3303 TB66	e 7 V G 4 4 3 C Z G 7
ARC115-11B22N ARC115-10B22 ARC115-61B22	SHI ELD SHI ELD NO/S	P3303 P3303 P3303	L & K W C D	TB66 TB20 SHI ELD ON w & c	7 5

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/--No Shield

PR/S--Palr Twisted, W/Shield



DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	<u>DESCRIPTION</u>
1	MT-1535/ARC-54	Mount Dinast Dankagement
2	MT-3664/ARC-131 RT-348/ARC-54	Mount, Direct Replacement Receiver-Transmitter
	RT-823/ARC-131	Receiver-Transmitter, Direct Replacement
3	ID-1347()/ARN-82	Course Indicator
4	C-8157/ARC	Control -Indicator
5	C-3835/ARC-54	Control
	C-7088/ARC-131	Control, Direct Replacement
6	206-075-543-3	Antenna .
7	AS-1922/ARC	Antenna, FM Homing
8	MT-3802/ARC	Mount
9	TSEC/KY-28	Speech Security (KY-58 and
	or TSEC/KY-58	KY-28 uses same wiring)

Figure F-3. VHF/FM RadloAN/ARC-54/131 (Sheet 2 of 2)

Table F-3. VHF/FM Radio AN/ARC-54/131

6		DIE ID.		UTO ANTARCE		
	WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
	RF400A20N RF400B20N RF400C20N RF401B22 RF401C22 RF401A22 RF403A22 RF404D22 RF404D22 RF405A22 RF405A22 RF407A22 RF407C22 RF407C22 RF408A22 RF409A22 RF410A22 RF410A22 RF410A22 RF411A22 RF415A22 RF415A22 RF415A22 RF417A22 RF417A22 RF417A22 RF417A22 RF417A22 RF417A22 RF417A22 RF418A22	TYPE 2 NO/S NO/S NO/S NO/S NO/S NO/S NO/S NO/	P2106 P2106 P2106 P2106 P2106 P2106 P2106 P2106 P2106 P2201A P2106 P2201A P2106	PIN 1 1 2 3 42 41 (RF401B22) (RF401C22) 11 10 G 13 6 14 - 6 5 - 26 31 25 30 24 29 23 32 37 8 9	GND GND GND SPLI CE SPLI CE P2107 P2107 SPLI CE SPLI CE SPLI CE SPLI CE SPLI CE SPLI CE P421 P422 SPLI CE P421 P2107	(RF40I A22) (RF40IA22) V y (RF404C22) (RF404C22) (RF405C22) H V (RF407C22) K k m BB LL cc J G h i W x
ı		I				

Table F-3 VHF/FMRadio AN/ARC-54/L31 (Cont)					
WIRE NUMBER	TYPE 2	END 1	PIN 1		PIN 1
RF419A22 RF420A22 RF421A22 RF423A22 RF423A22 RF425A22 RF425A22 RF426A22 RF426B22 RF426B22 RF426D22 RF427A22 RF428A20 RF429A20 RF430A20 RF430B20 RF430B20 RF431B22 RF431B22 RF433B22 RF433B22 RF444A18 RF444B20 RF444C20 RF444C20 RF444C20 RF444B20 RF445A22 RF446B22 RF446B22 RF447A22 RF446B22 RF447B22 RF447B22 RF447B22 RF447B22 RF447B22 RF447B22 RF447B22 RF447B22 RF447B22 RF447B22 RF450B22 RF450B22 RF450B22 RF450B22 RF450B22 RF450B20 RF451A22 RF451B22 RF453B20N RF453B20N	NO/S NO/S NO/S NO/S NO/S NO/S NO/S NO/S	P2106 P2106 P2106 P2106 P2106 P2106 P2107 K53 K54 TB71 P2106 P2107 P2107 P2107 P2106 P2106 K53 P2106 K53 P2106 K53 P2107 K53 P2107 P2107 P2107 P2107 P2107 P2107 P2107 P2107 P2107 P2107 F2107 P2107 K53 P2107 K54 P2107 K53 K54 P2107 K54 P2107 K53 K54 P2107 K53 K54 P2107 K53 K54 P2107 K53 K54 P2107 K53 K53 K53 K53 K53 K53 K53 K53 K53 K53	12 4 28 33 35 22 27 DD XI XI 2 17 CI 19 5 C D E S D1 NN B2 FF CI GG D3 Q KK 5 N G A A X2 WI RE SHI ELDS X2 WI RE SHI ELDS	P2107 P2107 P2107 P2107 P2107 P2107 P2107 P2107 K53 K54 TB71 P2106 P2107 FL1 FL1 FL1 FL1 FL1 FL1 FL1 FL1 FL1 FL1	v K P R s T u x l x l 16 MM Al L t i C1 5 5 D1 2 B1 C Al D1 B1 4 4 J A F 4 Y

Н

Ζ

1

7

B-2

A-2

20

P3302

P3302

TB12

TP26

K54

K54

J600

<u>и</u> НН

> <u>а</u> Б

R

S

Table, F-3. VHF /FM Radio AN/ARC-54 1131 (Cont) WIRE NUMBER TYPE 2 END 1 PIN 1 END 2 PIN 1 WI RE NO/S P2107 GND RF458A20N SHI ELDS (RF407A22) NO/S **SPLICE** RF461A22 P2202A Ε RF462A22 NO/S P2201A Ε **WIRE** SHI ELDS Ε WIRE CAP (RF603A22N] RF463A22N NO/S J2202A RF603A20N NO/S (RF463 **GND** A22N) (RF465A22N) WIRE CAP RF464A22 NO/S J2201A Ε (RF464A22) WIRE CAP RF465A22N NO/S GND PP 2 RF470A22N SHI ELD P2107 **TB26** P2107 2 RF471A22N SHI ELD **TB26** RF472A22N NO/S P2107 **WIRE TB26** 2 SHI ELDS F RF404B22 SHI ELD P2107 JJ J2202A J2202A Н RF405B22 SHI ELD P2107 В $\frac{x}{d}$ RF406B22 SHI ELD P2107 J2201A ٧ RF407B22 SHI ELD P2107 J2202A K RF434A COAX P609 P601L RF435A COAX P605 P601R RF436A COAX P2105 P3310 S NO/S P2106 KY28-10A20 3i P2201A Р NO/S KY28-11A22 P2106 7 P2201A NO/S KY28-12A20 P2106 39 P2201A W KY28-13A22 NO/S P2106 15 P2201A D KY28-14A22 NO/S P2106 44 P2201A M ARC114-21A22 SHI ELD P2107 P3302 C Χ Ă ARC114-22A22 SHI FI D P2107 Υ P3302

1 Underlined Connector Pin Letters Denote Lower Case

P2107

P2107

P2107

P2107

P1601

P1601

P2201A

SHI ELD

SHI ELD

NO/S

NO/S

NO/S

NO/S

NO/S

2 Denote: NO/S--No Shield

ARC114-8A22

L125A22


L128A20N

RF448C22

RF447C22

RF600A20

ARC114-23A22



DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1	AN/ARC-I 14A	Receiver-Transmitter
2	CU-942B/ARC	Antenna Coupler
3	AS-1703/AR	Antenna, Whip
4	212-075-328-3	FM Filter

Figure F-4. VHF/FM Radio AN/ARC-114 (Sheet 2 of 2)

Table F-4. VHF/FM Radio AN/ARC 114


Table F-4VHF/FM Radio AN/ARC 114						
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1	
			_			
ARC114-2A22	NO/S	P3302	В	P3302	V	
ARC114-3A22	NO/S	P3302	С	SPLI CE		
ARC114-4A20	NO/S	P3302	D	CB33		
ARC114-5A20N	NO/S	P3302	Е	TB26	4	
ARC114-8A22	SHI ELD	P3302	Н	P2107	<u>ū</u>	
ARC114-10A22(RED)	PR/S	P3302	K	P3303	n N	
ARC114-11A22(BLK)	PR/S	P3302	L	P3303	<u>e</u> 7	
ARC114-10B22	SHI ELD	P3303	L	TB20	7	
ARC114-11B22N	SHI ELD	P3303	<u>b</u> P	TB26	1	
ARC114-14A20N	NO/S	P3302	P	TB26	4	
ARC114-21A22	SHI ELD	P3302	Χ	P2107	<u>c</u> Ā	
ARC114-22A22	SHI ELD	P3302	Υ	P2107	Ā	
ARC114-23A22	SHI ELD	P3302	Z	P2107	HH	
ARC114-27A22	SHI ELD	P3302	d	J600	26	
ARC114-27B22	SHI ELD	J600	d d e i	TB20	12	
ARC114-28A22N	SHI ELD	P3302	e	TB26	1	
ARC114-28B22N	NO/S	TB26	i	GND	-	
ARC114-31A22	NO/S	P3302	h	P3304	h	
ARC114-60A22N	NO/S	P3302	CAP LUG	TB26	i	
ARC114-61A22	NO/S	P3303	S	CAP LUG	SHI ELD	
ARC114-61B22	NO/S	P3303	M	CAP LUG	SHI ELD	
ARC114-101A	COAX	P3300		P2112		
ARC114-105A	COAX	P2111		P2104		
ARC114-105B	COAX	J2104		P2103		

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield

PR/S--PalrTwlsted, W/Shield





DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRIPTION_
1 2	C-3940/ARc-94 CU-1658A/ARC	Control Coupler, Antenna
3	MT-3772AIA	Mount
4	PP-3702/ARC-102	Power-Inverter, Mounting
5	RT-698/ARC-102	Receiver-Transmsitter

Figure F-5. HF Radio AN/ARC-102 (Sheet 2 of 2)

	Table F-		dio AN/ARC		
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
RL2575A20 RL2576A20 RL2577A20 RL2578A20 RL2579A20 RL2580A20 RL2581A20 RL2582A20 RL2583A20 RL2584A20 RL2585A20 RL2586A20 RL2587A20 RL2589A20 RL2591A20 RL2591A20 RL2591A20 RL2593A20 RL2593A20 RL2593A20 RL2593B20 RL2593B20 RL2593B20 RL2593B20 RL2593B20 RL2594A20 RL2599A18 RL2599A18 RL2599B18 RL2600A8 RL2600B20	NO/S NO/S NO/S NO/S NO/S NO/S NO/S NO/S	P1806 P1806	36 35 34 33 32 48 47 46 45 52 51 50 49 41 40 39 38 24 u 7 7 30 25 56 E	P1808 P1804 TB44 TB44 TB44 TB44 TB44 TB44 TB44 TB	ED c B A N M L K T S R P J H G F - 7 1 9 z v E L 4 1 2 3 2 2 3 3 10 c K 9


Table F-5. HF Radio AN/ARC-102 (Cont)

	iabie F-5.	HF Radi o	AN/ARC-I 02	(Cont)	
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
-				_	
RL2602A18	NO/S	CB35	_	TB44	6
RL2602B12	NO/S	CB34	_	BUSBAR	U
			<u>-</u>		-
RL2602C18	NO/S	P1806	16	TB44	6
RL2602D18	NO/S	P1806	4	TB44	6
RL2603A16	NO/S	CB36	-	TB44	5
RL2603B18	NO/S	TB44	5	P1809	2
RL2603C18	NO/S	TB44	5	P1809	3
RL2606A20	SHI ELD	P1806	11	P1805	В
RL2606B20	SHI ELD	J1805	В	P1804	Ä
RL2607A20	SHI ELD	P1806	5	P1805	F
RL2607B20	SHI ELD	J1805	F	P1804	S
RL2609A20	SHI ELD	P1806	26	P1805	D
RL2609B20	SHI ELD	J1805	D	P1804	F
RL2611A20	NO/S	P1808	<u>k</u>	TB19	8
RL2614A20	SHI ELD	P1806	10	P1805	А
RL2614B20	SHI ELD	J1805	А	P1804	Н
RL2615A20	NO/S	P1808		TB19	8
RL2615B20	NO/S	TB19	<u>m</u> 8	P3304	E
			U		Ľ
RL2616A	COAX	P1801	-	P1802	-
RL2616B	COAX	J1802	-	P1803	-
RL2618A20	SHI ELD	P1806	27	P1809	9
RL2618B20	SHI ELD	P1806	27	P1805	G
RL2618B20	SHI ELD	J1802	G	P1804	D
RL2619A20	SHI ELD	P1806	12	P1809	5
RL2620A20N	NO/S	P1809	6	P1806	GND
RL2620B20N	NO/S	P1809	7	P1806	GND
RL2620C20N	NO/S	P1809	4	P1806	GND
RL2620D8N	NO/S	P1806	GND	F 1000	GND
			r	TD2/	
RL2620E20N	NO/S	P1808		TB26	9
RL2620F20N	NO/S	<u>-</u>	GND	SPLI CE	-
RL2620G20	NO/S	P1804	G	SPLI CE	-
RL2620H20	NO/S	J1805	Н	SPLI CE	SHI ELDS
RL2620J20	NO/S	P1805	Н	SPLI CE	SHI ELDS
RL2621A20	NO/S	P1808	<u>P</u>	P1806	31
RL2622A20N	NO/S	P1808	<u>e</u>	TB26	6
RL2623A22(BLK)	PR/S	P1806	<u>5</u> 57	J600	SPLI ČE
RL2624A22(RED)	PR/S	P1806	58	J600	
					19
RL2625A22(BLK)	PR/S	P1806	53	J600	SPLI CE
RL2626A22(RED)	PR/S	P1806	37	J600	T
RL2627A20N	NO/S	P1806	CAP LUG	SHI ELDS	GND
RL2627B20	NO/S	P1806	CAP LUG	SHI ELDS	SHI ELDS
RL2627C20N	NO/S	P1809	CAP LUG	SHI ELDS	GND
RL2700A	NO/S	P1803	ANT	P1807	-
RL2700	NO/S	J1807	ANT	TAI LBOOM	_
L126A20	NO/S	P1808	<u>d</u>	TB12	2
	1.0, 0		<u> </u>	. 5 . 2	۷

¹ Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield

PR/S--Pair Twisted, W/Shield



M

DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1	AM-3209/ASN	Servoamplifier
2	I D-9980/ASN	Radio Magnetic Indicator
3	CN-9980/ASN-43	Directional GYRO
4	R-1391/ARN-83	Radi o Recei ver
5	CN-405/ASN	Compensator
6	T-611/ASN	Compass Transmitter
7	C-6899/ARN-83	Control, Direction Finder
8	ID-250()/ARN	Radio Magnetic Indicator

Figure F-6. Gyrocompass J-2, AN/ASN-430 (Sheet 2 of 2)

Table F-6. GYRO Compass J-2, AN/ ASN-430 END 2 PIN 1 WIRE NUMBER TYPE 2 END 1 PIN 1 P403 F2A22(YEL) TWTI S 42 P410 В F2B22(YEL) TWT/S В J410 T-611 В F3A22(BLU) TWTI S P403 43 P410 С F3B22(BLU) TWTI S J410 С T611 С F4A22(GRN) TWTI S P403 44 P410 Α F4B22(GRN) TWTI S T-611 J410 Α Α F5C22 NO/S TB10 P410 D 6 F5D22 NO/S D J410 T-611 D D F5F22 NO/S T-611 T-611 F5G22 NO/S F J410 **SPLICE** SHI ELDS F5H22 NO/S T-611 **SPLICE** SHI ELDS F5J22 NO/S P410 F **SPLICE** SHI ELDS F42A22(GRN) J TWT/S P411 P403 G F43A22(YEL) TWT/S 2 P411 P403 F44A22(BLU) TWT/S P411 11 P403 1 P410 F22A22 M NO/S P411 Ε F22B22 NO/S Ε Ε J410 T-611 F24A22 SHI ELD P403 45 P411 D F50A22 NO/S P403 46 P411 В F65A22 NO/S P403 5 P415 6 F67B22 NO/S P403 **SPLICE** F67A22(BLK) PR/S **SPLICE** P415 3 F60A22 NO/S P415 10 P403 54 F61A22 NO/S P415 13 P403 8 F62A22 NO/S P415 14 P403 9

1 Underlined Connector Pin Letters Denote Lower Case

NO/S

2 Denotes: NO/S--No Shield

F70A22N


PR/S--Pair Twisted, W/Shield

TWT/S--Three Wire Twisted, W/Shield

P403

55

GND



DRAWING DESIGNATION	PART <u>NUMBER</u>	DESCRI PTI ON
1	C-6899/ARN-83	Direction Finder Control
2	AS-1863/ARN-83	Antenna, Loop
3	R-1391/ARN-83	Radi o Recei ver
4	MT-3605/ARN-83	Mount
5	205-075-325-1	ADF Sense Antenna

Figure F-7. Direction Finder Set AN/ARN-83 (Sheet 2 of 2)

Table F - 7 Direction Finder Set , AN/ARN -83


Table			nder set , A	M/AKN -83	ATM 4
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
		l I			
R N354B22	NO/S	P403	29	TB1	7
R N354C22	NO/S	TB1	7	P409	Ť
RN355B22	NO/S	P403	29	TB1	6
RN355C22	NO/S	TB1	6	P409	U
RN361A20	NO/S	P407	36	SPLI CE	-
RN361B20	NO/S	P302	M	SPLI CE	-
RN5361C20N	NO/S	SPI CE		TB26	5
RN362A22	NO/S	P407	30	P302	a
RN363A22	NO/S	P407	31	P302	l T
RN364A22	NO/S	P407	32	P302	<u>-</u> S
RN365A22	NO/S	P407	12	P302	m
RN366A22	NO/S	P407	13	P302	ה מרויופובוסא
RN367A22	NO/S	P407	14	P302	ä
RN368A22(YEL)	TWT/S	P407	9	P302	X
RN369A22(BLU)	TWT/S	P407	10	P302	Ŷ
RN370A22(GRN)	TWT/S	P407	11	P302	ż
RN371A22	NO/S	P407	, 29	P302	i
RN372A22	NO/S	P407	28	P302	i it 제작하다
RN373A22	NO/S	P407	27	P302	y k
RN374A22(GRN)	TWT/S	P407	33	P302	Ŧ
RN375A22(BLU)	TWT/S	P407	34	P302	<u> </u>
RN376A22(YEL)	TWT/S	P407	35	P302	h 7
RN377A22	NO/S	P407	15	P302	끝
RN378A22	NO/S	P407	22	P302	
RN379A20	NO/S	P302	K	CB22	<u> </u>
RN382A22	NO/S	P302	G	TB12	1
RN383A22	NO/S	P302		TB12	1
RN384A22(RED)	PR/S	P302	<u>b</u> ₩	J600	18
RN385A22(BLK)	PR/S	P302 P302	V V	J600 J600	28
RN386A22(RED)	PR/S PR/S	P302 P407	23	P302	
	PR/S PR/S	P407 P407	23 24	P302 P302	Ţ
RN387A22(BLK)					Ų
RN388A20	NO/S	P407	26	P302	L
RN389A2ON	NO/S	P302	<u>a</u> 17	TB26	5
RN389B22N	NO/S	P407		TB26	10
RN389C20N	NO/S	P407	16	TB26	10
RN390A22	NO/S	CB98		SPLI CE	-
RN390B22	NO/S	SPLI CE		SPLI CE	-
		[

Table F-7	 Direction 	Fi nder_		RN-83 (Cont	3)
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
RN5390C22 RN5390D22 RN5390E22 RN5390F22 RN5391A22N RN5392A22 RN5392B22 RN5392C22 RN5393A22 RN5393B22 RN5393B22 RN5393C22 RN5393C22 RN5395A	NO/S NO/S NO/S NO/S NO/S NO/S NO/S NO/S	SPLI CE SPLI CE SPLI CE SPLI CE P409 P407 P407 TB1 P403 P407 TB1 P403 P406	M 21 20 9 31 19 8 32 c E	P407 P407 P403 P302 P403 GND TB1 P403 P409 TB1 P403 P409 P401	8 18 27 J 53 9 22 N 8 23 P SENSE ANT
• • •	MOLDED CABLE	P404	1	P402	LOOP ANT

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes:

NO/S--No Shield PR/S--Palr Twisted, W/Shield TWTS/--Three Wire Twisted, W/Shield



DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1	MT-3600/ARN-82	Mount, Radio
2	R-1388/ARN-820	Radi o Recei ver
3	ID-13470/ARN-82	Course Indicator
4	As-1304/ARN	Antenna
5	5995-00-858-6552	Spider, Coax Assembly (05211)
6	AS-1304/ARN	Antenna
7	C-6873/ARN-82	Radio Set Control

Figure F-8. VOR/MG/GS AN/ARN-820 (Sheet 2 of 2)

	Table F-8	VOR/MG	GSAN/ARN	-82()	_
WIRE NUMBER	TYPE 2	'END 1	PIN 1	END 2	PIN 1
RN5280A RN5280B SPYDER IR N5281A22(RED)	COAX COAX COAX PR/S	P303 J1303 J801 P311	- h	P1303 P801 P1305 P1307 P304	
R N5282A22(BLK) R N5283A22 R N5284A22 R N5285A20N R N5285B20N	PR/S NO/S NO/S NO/S NO/S	P311 P311 P311 P304 TB26	<u>Б</u> С Р Z X 10	P304 P304 CB21 TB26 P311	N J 10 SPLI CE
R N5285C20 R N5286A22 R N5287A22(RED) R N5288A22(BLK) R N5288B22N	NO/S NO/S PR/S PR/S NO/S	P311 P311 P311 P311 TB19	hH diel6 A	P311 TB12 TB19 TB19 TB66	SPLI CE 3 7 6 2
R N5290A22 R N5290B22 R N5290C20 R N5291A22 R N5292A22	NO/S NO/S NO/S NO/S NO/S	P304 P304 SPLI CE P311 P311	A R - <u>a</u> Y	SPLI CE SPLI CE P311 P304 P304	M K k
R N5293A22 R N5294A22 R N5295A22 R N5296A22 R N5297A22	NO/S NO/S NO/S NO/S NO/IS	P311 P311 P311 P311 P311	L giC D F	P304 P304 P304 P304 P304	k t pf gh ijW
R N5298A22 R N5299A22 R N5300A22 R N5301A22 R N5302A22	NO/S NO/S NO/S NO/S	P311 P311 P311 P311 P311	DEfBVXG	P304 P304 P304 P304	V
R N5303A22 R N5304A22 R N5305A22 R N5305B22	NO/S NO/S NO/S NO/S NO/S	P311 P311 P304 P304	F W m B	P304 P304 P304 TB66 TB66	u T S 10 10
R N5305C22 R N5305D22	NO/S NO/S	P304 K53	P D-3	TB66 A32	10

Table F-8. VOR/MG/GS AN/ARN-820 (Cont)

Table F-8. VOR/MG/GS AN/ARN-820 (COTT)					
WI RE NUMBER	TYPE 2	'END 1	PIN 1	END 2	PIN 1
RN5305E22	SHI ELD	P1601	J	K53	D-2
RN5305F22	NO/S	A32	3	TB66	10
RN5306A22	NO/S	P304	n	K53	c-3
RN5306B22	SHI ELD	K53	C=2	P1601	K
RN5306C22	NO/S	P304	d	A32	4
RN5307A22	NO/S	P304	<u>d</u> b	K54	c-3
RN5307B22	NO/S	K54	C-2	P1601	Р
RN5308A22	NO/S	P304	а	SPLI CE	
RN5308B22	NO/S	P304	<u>a</u> <u>c</u>	SPLI CE	
RN5308C22	NO/S	SPLI CE	-	K54	D-3
RN5308D22	NO/S	K54	D-2	P1601	N
RN5309A22	NO/S	P1601	Н	P304	Н
RN5310A22	NO/S	P304	С	P1601	С
RN5311A22	NO/S	P304		P1601	D
RN5312A22	NO/S	P304	D E F	P1601	E
RN5313A22	NO/S	P304	F	P1601	E F G T
RN5314A22	NO/S	P304	G	P1601	G
RN5315A22	NO/S	P304	Z	P1601	T
RN5316A22	NO/S	P304	Υ	P1601	U
RN5352A22	NO/S	P306	G	TB1	12
RN5354A22	NO/S	P306	Н	TB1	7
RN5354B22	NO/S	TB1	7	P403	29
RN5354C22	NO/S	TB1	7	P409	T
RN5355A22	NO/S	P306	K	TB1	6
RN5355B22	NO/S	TB1	6	P403	30
RN5355C22	NO/S	TB1	6	P409	U
RN5356A20	NO/S	P306	J	СВ	
F80A22	NO/S	P306	С	P403	18
F81A22	NO/S	P306	D	P403	19
F82B22N	NO/S	P306	Е	GND	

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield

PR/S--Pair Twisted, W/Shield

DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1 2	I D-2192/ARN-124 RT-1294/ARN-124	Control - Indicator Receiver-Transmitter
3	MT-6034/ARN-124	Mount
4	RT-8590/APX-72	Recei ver-Transmi tter
5	AT-7411A	Antenna
6	C-6873B/ARN-82	Control

Figure F-9. DME ANMRN-124 (V-Only) (Sheet 2of2)

Table F-9. DME ANMRN - 1 2 4(V-Only)

	lable 1-9.	DME ANMRN	<u>- 124(V-C</u>	ו או או	
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
ARN124-1A22	NO/S	P102	37	P311	R
ARN124-2A22	NO/S	P102	39	P311	N
ARN124-3A22	NO/S	P102	41	P311	0
ARN124-4A22	NO/S	P102	42	P311	<u>t</u>
ARN124-5A22	NO/S	P102	43	P311	<u> </u>
ARN124-6A22	NO/S	P102	47	P311	<u> </u>
ARN124-7A22	NO/S	P102	49	P311	Otigiikiminifi 23
ARN124-8A22	NO/S	P102	50	P311	<u>m</u>
ARN124-9A22	NO/S	P102	46	P311	<u>n</u>
ARN124-10A22	NO/S	P102	45	P311	<u>f</u>
ARN124-11A20	TWT/S	P102	20	P201	23
(WHT/RED)					
ARN124-12A20	TWT/S	P102	4	P201	24
(WHT/BLU)					
ARN124-13A20	TWT/S	P102	7	P201	9
(WHT/YEL)					
ARN124-14A20N	NO/S	P102	13	SPLI CE	SP1
ARN124-14B20N	NO/S	SPLI CE	SP1	SPLI CE	SP4
ARN124-14C20N	NO/S	SPLI CE	SP4	P201	2
ARN124-14D20N	NO/S	SPLI CE	SP4	P201	19
ARN124-14E20N	NO/S	SPLI CE	SP1	SPLI CE	SP2
A RN124-15A22	NO/S	P201	36	P201	8
ARN124-16A22N	NO/S	P102	11	P201	32
ARN124-17A20N	NO/S	P102	23	P201	26
A RN124-18A22	NO/S	P102	38	P201	10
ARN124-19A22	PR/S	P102	34	P201	17
(WHT/RED)					
ARN124-20A22	PR/S	P102	35	P201	36
(WHT/BLU)					
ARN124-21A22N	NO/S	P102	18	SPLI CE	SHIELDS
ARN124-23A22N	NO/S	P201	35	SPLI CE	SHI ELDS
ARN124-24A22	PR/S	P102	3	P201	15
(WHT/RED)					
A RN124-25A22	PR/S	P102	1	SPLI CE	SP3
(WHT/BLU)					
ARN124-25B22	NO/S	SPLI CE	SP3	P201	34
A RN124-26A22N	NO/S	P102	31	SPLI CE	SHI ELDS
					- !

Table F-9. DME AN/ARN-124 (V-Only) (Cont)

Table F-9. DME AN/ARN-124 (V-Only) (Cont)					
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
ARN124-27A20	NO/S	CB2	-	LIGHT, DME CODE HOLD	1
ARN124-28A20 ARN124-29A20 ARN124-30A22 ARN124-31A22 ARN124-32A20	SHIELD SHIELD NO/S NO/S PR/S	P102 P102 P102 P102 P102	15 32 16 17 5	P916 P916 P201 P201 P201	12 11 22 20 33
(WHT/BLU) ARN124-33A2ON ARN124-33B2ON (WHT/RED)	NO/S PR/S	P102 SPLICE	10 SP2	SPLICE SPLICE	SP2 SP5
ARN124-33C20N ARN124-33D20N ARN124-33E20N	NO/S NO/S NO/S	SPLICE SPLICE TB26	SP5 SP5 9	P201 TB26 LIGHT, DME CODE	28 9 3
ARN124-34A20 ARN124-37A22	NO/S SHIELD	P102 RESIS- TOR BOARD	6 2	HOLD CB TB26	- 3
ARN124-37B22 ARN124-38A20N	NO/S NO/S	SPLICE LIGHT, DME CODE HOLD	SP3 2	TB26 P201	3 25
ARN124-40A22 ARN124-41A22 ARN124-42A20 ARN124-45A22	NO/S NO/S NO/S SHIELD	P201 P201 P201 RESIS- TOR	6 11 18 4	P311 P311 TB13 P201	S K 1 16
ARN124-46A22	SHIELD	BOARD RESIS- TOR BOARD	6	TB20	8
RN5285B22 ARN124-101	NO/S COAX	P311 P101	<u>h</u> -	TB26 P103	9 ANT

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield

PR/S--Pair Twisted, W/Shield

TWT/S--Three Wire Twisted, W/Shield




Figure F-10. Radar Altlmeter AN/APR-209 (V-Only) (Sheet 1 of 2)

DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1 2	AS-2595/APN-194(V) RT-1115/APN-209	Antenna Recei ver-Transmitter, Height Indicator
3 4	ID-1917/APN-209 AS-2595/APN-194(V)	Height Indicator Antenna

Figure F-10. Radar Altimeter AN/APR-209 (V-Only) (Sheet 2 of 2)

Table F-10. Radar Altimeter AN/APR-209 (V-Only)


Table F-10. Radar Altimeter AN/APR-209 (V-Only)						
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1	
					-	
APN209-1A22	NO/S	P1	7	K100	3	
APN209-1B22	NO/S	K100	1	J3	K	
APN209-1C22	NO/S	Р3	K	TB13	9	
APN209-7A22	NO/S	P1	9	СВ	-	
APN209-7B22	NO/S	СВ	_	*P1	1	
APN209-8A22N	NO/S	P1	3	GND	-	
APN209-8B22N	NO/S	GND	_	*P1	2	
APN209-13A22	NO/S	P2	8	*P1	16	
APN209-14A22	NO/S	P2	13	*P1	21	
APN209-15A22	NO/S	P2	8 13 3 2	*P1	15	
APN209-16A22	NO/S	P2	2	*P1	9	
APN209-17A22	NO/S	P2	11	*P1	9 5	
APN209-18A22(RED)	PR/S	P2	12	*P1	19	
APN209-19A22(RED)	PR/S	P2	4	*P1	11	
APN209-20A22	NO/S	*P1	6	K100	6	
APN209-20B22	NO/S	K100	8	J3	Ĺ	
APN209-20C22	NO/S	P3	Ĺ	TB13	4	
APN209-23A22	NO/S	P2	5	*P1	3	
APN209-24A22	NO/S	P2	6	*P1	4	
APN209-34A22(BLU)	PR/S	P2	10	*P1	20	
APN209-35A22(BLU)	PR/S	P2	1	*P1	10	
APN209-36A22	NO/S	СВ	-	SPLICE	SP1	
APN209-36B22	NO/S	K100	7	DIMMER	CONTROL	
APN209-36C22	NO/S	K100	4	SPLICE	SP1	
APN209-36D22	NO/S	K100	5	SPLICE	SP2	
APN209-36E22	NO/S	K100	5 2	SPLICE	SP2	
APN209-36F22	NO/S	SPLICE	SP2	SPLICE	SP1	
APN209-21A	COAX	Р3	ANT	P1501	-	
APN209-22A	COAX	P4	ANT	P1501	-	
L211D22N	NO/S	P1	5	GND	-	
L211E22N	NO/S	GND	_	*P1	18	
L212B22	NO/S	P1	10	TB100	8	
L215C22	NO/S	TB100	3	*P1	17	

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shi el d

PR/S--Palr Twisted, W/Shield

* DENOTES P1 ON HEIGHT IND, ID-1917/APN-209



DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1	RT-8590/APX-72	Recei ver-Transmi tter
2	TS-1843()/APX	Transponder Test Set
3	MT-3513/APx	Mount
4	MT-3809/APX-72	Mount
5	C-6280A(P)/APX	Transponder Control
6	AT-884/APX-44	Antenna
7	AAU-32A	Altimeter

Figure F-11. IFF System AN/APX-72 (Sheet 2 of 2)

Table F-11 IFF System AN/APX -72

WIRE NUMBER	Table F-11 TYPE 2	END 1	tem AN/APX PIN 1	END 2	PIN 1
SX45N22 SX45P22 SX45P22 SX45S22 SX45S22 SX45S22 SX45V22 SX45W22 SX45W22 SX58M22 SX58M22 SX58P22 SX58P22 SX58P22 SX705A20N SX705E20N SX705E20N SX705E20N SX705F22N SX705F22N SX705F22N SX705G22N SX705A22 SX712A22 SX714A22 SX714A22 SX714A22 SX714A22 SX717A22 SX719A22 SX719A22 SX719A22 SX720A22 SX720A22 SX736A20N SX743A22 SX747A20 SX755A22 SX755A22 SX755A22	NO/S NO/S NO/S NO/S NO/S NO/S NO/S NO/S	P916 SPLICE SPLI	31 31 31 34 8 2 8 1 4 21 20 19 18 16 15 14 53 6 1 40 39 A-2	SPLI CE TB26 TB26 TB26 SPLI CE GND GND CB17 P917 P917 P917 P917 P917 P917 P917 P9	6 7 8 24 2 11 5 6 8 9 10 8 31 26 27

Table	F-11.	IFF	System	AN/APX-72	(Cont)
14010		411	9196611		1001161


WINE NUMBER Type 2 END 1 PIN 1 END 2 PIN 1	1100 100000	Die L-II.	TEL SASE	em AN/APX-/	Z (COIIC)	B 7 1 2 1
SX757A22	WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
SX757A22			l		l	
SX758A22	SX756A22	SHIELD		38	P917	28
SX758A22 SHIELD P916 29 P917 30	SX757A22	SHIELD	P916	37	P917	29
SX761A22	SX758A22	SHIELD	P916	36	P917	
SX762A22						
SX763A22 SHIELD P916 27 P917 35 SX765A22 SHIELD P916 25 P917 36 SX765A22 SHIELD P916 25 P917 37 SX766A22 SHIELD P916 24 P917 38 SX766A20 NO/S K68 A-3 P24 DD SX76BA22 SHIELD P917 12 TB12 3 SX775B20N NO/S P918 9 P918 10 SX802A22 NO/S P916 53 P921 28 SX802B22 NO/S P916 53 P921 28 SX802B22 NO/S P921 30 K68 X1 SX80A222 SHELD P916 10 GND - SX80A222 SHELD P916 8 P8002 K SX80A223 SHELD P916 54 P8002 K SX80A223 SHELD P916						
SX76AA22 SHIELD P916 26 P917 36 SX765A22 SHIELD P916 24 P917 37 SX766A20 NO/S K68 A-3 P24 DD SX76BA22 SHIELD P917 12 TB12 3 SX774A22 NO/S P918 9 P918 10 SX777A22 NO/S K68 X2 GND - SX802A22 NO/S P916 53 P921 28 SX802A22 NO/S P916 53 P921 28 SX802A22 NO/S P916 53 P921 28 SX802A22 SHIELD P916 10 GND - SX804A22N SHIELD P916 10 GND - SX804A22N SHIELD P916 8 P8002 K SX804A22N SHIELD P916 54 P8002 K SX804A22 SHIELD P916						
SX765A22						
SX766A22						
SX766A22	SX765A22	SHIELD	P916	25	P917	37
SX766A20	SX766A22	SHIELD	P916	24	P917	38
SX768A22		NO/S				
SX774A22						
SX775B20N NO/S K68 X2 GND - SX802A22 NO/S P916 53 P921 28 SX802B22 NO/S P921 30 K68 X1 SX803A22 SHIELD P916 9 J600 22 SX804A22N SHIELD P916 10 GND - SX804B22N NO/S SPLICE - GND - SX806A22 SHIELD P916 8 P8002 K SX807A22 SHIELD P916 54 P8002 J SX804B22 SHIELD P916 55 P8002 J SX804B22 SHIELD P916 55 P8002 J SX804B22 SHIELD P916 55 P8002 J SX804B22 SHIELD P916 55 P8002 J SX810A22 SHIELD P916 30 P8002 G SX811A22 SHIELD P916 30 P8002 E SX812A22 SHIELD P916 31 P8002 D SX813A22 SHIELD P916 32 P8002 D SX813A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 42 P8002 L SX818A22 SHIELD P916 59 P917 4 SX820A22 SHIELD P916 59 P917 4 SX820A22 SHIELD P916 50 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 19 SX823A22 SHIELD P916 58 P917 20 SX825A22 SHIELD P916 58 P917 20 SX825A22 SHIELD P916 59 P917 55 SX825A22 SHIELD P916 50 P917 55 SX825A22 SHIELD P916 50 P917 55 SX825A22 SHIELD P916 50 P917 55 SX825A22 SHIELD P916 50 P917 55 SX825A22 SHIELD P916 50 P917 55 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 50 P917 50 SX825A22 SHIELD P916 5						
SX802A22						10
SX802B22						-
SX803A22 SHIELD P916 9 J600 22 SX804A22N SHIELD P916 10 GND - SX804B22N NO/S SPLICE - GND - SX806A22 SHIELD P916 8 P8002 K SX807A22 SHIELD P916 54 P8002 J SX809A22 SHIELD P916 55 P8002 H SX809A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 30 P8002 F SX81A322 SHIELD P916 31 P8002 E SX813A22 SHIELD P916 32 P8002 C SX815A22 SHIELD P916 35 P8002 B SX816A22 SHIELD P916 41 P8002 Capped SX816A22 SHIELD P916 42 P8002 L SX816A22 SHIELD </td <td> SX802A22</td> <td></td> <td>P916</td> <td>53</td> <td>P921</td> <td>28</td>	SX802A22		P916	53	P921	28
SX803A22 SHIELD P916 9 J600 22 SX804A22N SHIELD P916 10 GND - SX804B22N NO/S SPLICE - GND - SX806A22 SHIELD P916 8 P8002 K SX807A22 SHIELD P916 54 P8002 J SX809A22 SHIELD P916 55 P8002 H SX809A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 30 P8002 F SX81A322 SHIELD P916 31 P8002 E SX813A22 SHIELD P916 32 P8002 C SX815A22 SHIELD P916 35 P8002 B SX816A22 SHIELD P916 41 P8002 Capped SX816A22 SHIELD P916 42 P8002 L SX816A22 SHIELD </td <td>SX802B22</td> <td>NO/S</td> <td>P921</td> <td>30</td> <td>K68</td> <td>X1</td>	SX802B22	NO/S	P921	30	K68	X1
SX804A22N SHIELD P916 10 GND - SX804B22N NO/S SPLICE - GND - SX806A22 SHIELD P916 8 P8002 K SX807A22 SHIELD P916 54 P8002 J SX808A22 SHIELD P916 17 P8002 H SX810A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 23 P8002 F SX811A22 SHIELD P916 31 P8002 E SX812A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 32 P8002 C SX816A22 SHIELD P916 32 P8002 C SX816A22 SHIELD P916 42 P8002 C SX816A22 SHIELD P916 42 P8002 C SX816A22 SHIELD						
SX804B22N NO/S SPLICE - GND - SX806A22 SHIELD P916 8 P8002 K SX807A22 SHIELD P916 54 P8002 J SX808A22 SHIELD P916 55 P8002 H SX809A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 30 P8002 F SX811A22 SHIELD P916 31 P8002 E SX812A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 42 P8002 L SX817A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 43 P917 16 SX821A22 <t< td=""><td></td><td></td><td></td><td></td><td></td><td></td></t<>						
SX806A22 SHIELD P916 8 P8002 K SX807A22 SHIELD P916 54 P8002 J SX808A22 SHIELD P916 55 P8002 H SX809A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 30 P8002 F SX811A22 SHIELD P916 31 P8002 D SX813A22 SHIELD P916 32 P8002 D SX814A22 SHIELD P916 32 P8002 C SX815A22 SHIELD P916 41 P8002 B SX816A22 SHIELD P916 42 P8002 L SX816A22 SHIELD P916 42 P8002 L SX816A22 SHIELD P916 42 P8002 L SX818A22 SHIELD P916 59 P917 15 SX821A22 SHIELD <td></td> <td></td> <td></td> <td>1.</td> <td></td> <td>_</td>				1.		_
SX807A22 SHIELD P916 54 P8002 J SX808A22 SHIELD P916 55 P8002 H SX809A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 23 P8002 F SX811A22 SHIELD P916 30 P8002 E SX813A22 SHIELD P916 32 P8002 C SX813A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 59 P917 4 SX816A22 SHIELD P916 59 P917 15 SX819A22 SHIELD P916 43 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22						- -
SX808A22 SHIELD P916 55 P8002 H SX809A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 23 P8002 F SX811A22 SHIELD P916 30 P8002 E SX813A22 SHIELD P916 32 P8002 D SX813A22 SHIELD P916 35 P8002 B SX814A22 SHIELD P916 41 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 42 P8002 L SX816A22 SHIELD P916 43 P917 15 SX818A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 57 P917 19 SX824A22	The state of the s					
SX809A22 SHIELD P916 17 P8002 G SX810A22 SHIELD P916 23 P8002 F SX811A22 SHIELD P916 30 P8002 E SX812A22 SHIELD P916 31 P8002 D SX813A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 42 P8002 L SX817A22 SHIELD P916 43 P917 4 SX819A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 19 SX824A22						
SX810A22 SHIELD P916 23 P8002 F SX811A22 SHIELD P916 30 P8002 E SX812A22 SHIELD P916 31 P8002 D SX813A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX815A22 SHIELD P916 42 P8002 L SX818A22 SHIELD P916 59 P917 4 SX819A22 SHIELD P916 43 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX825A22	SX808A22	SHIELD	P916	55	P8002	Н
SX810A22 SHIELD P916 23 P8002 F SX811A22 SHIELD P916 30 P8002 E SX812A22 SHIELD P916 31 P8002 D SX813A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 41 P8002 Capped not used SX815A22 SHIELD P916 42 P8002 L SX817A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 59 P917 15 SX819A22 SHIELD P916 43 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX825A22	SX809A22	SHIELD	P916	17	P8002	G
SX811A22 SHIELD P916 30 P8002 E SX812A22 SHIELD P916 31 P8002 D SX813A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 34 P917 42 SX825A22	SX810A22	SHIELD	P916	23		F
SX812A22 SHIELD P916 31 P8002 D SX813A22 SHIELD P916 32 P8002 C SX814A22 SHIELD P916 35 P8002 B SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 59 P917 4 SX819A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 57 P917 20 SX824A22 SHIELD P916 58 P917 25 SX826A22 SHIELD P916 34 P917 42 SX828A <t< td=""><td></td><td></td><td></td><td></td><td></td><td>Ē</td></t<>						Ē
SX813A22						, L
SX814A22 SHIELD P916 A1						
SX815A22 SHIELD P916 41 P8002 Capped not used SX816A22 SHIELD P916 59 P917 4 SX817A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 58 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 45 P921 2 SX829A SHIELD P916 45 P921 2 SX830A SHIELD P916 47 P921 1 SX831A SHIELD						
SX816A22						
SX816A22 SHIELD P916 42 P8002 L SX817A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 34 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX831A SHIELD P916 48 P921 4 SX833A22 SHIELD P916<	SX815A22	SHIELD	P916	41	P8002	Capped
SX816A22 SHIELD P916 42 P8002 L SX817A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX831A SHIELD P916 47 P921 1 SX833A22 SHIELD P916 48 P921 4 SX834A20 SHIELD P916	į.					
SX817A22 SHIELD P916 59 P917 4 SX818A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 45 P921 2 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD P917 <td>SX816A22</td> <td>SHIELD</td> <td>P916</td> <td>42</td> <td>P8002</td> <td>1</td>	SX816A22	SHIELD	P916	42	P8002	1
SX818A22 SHIELD P916 43 P917 15 SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX831A SHIELD P916 47 P921 1 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 <td></td> <td></td> <td></td> <td></td> <td></td> <td>7</td>						7
SX819A22 SHIELD P916 44 P917 16 SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX831A SHIELD P916 47 P921 1 SX833A22 SHIELD P916 48 P921 4 SX834A20 SHIELD P916 49 GND - SX834C20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 <td></td> <td></td> <td></td> <td></td> <td></td> <td></td>						
SX820A22 SHIELD P916 50 P917 17 SX821A22 SHIELD P916 56 P917 18 SX823A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD TB19 1 J506 B						
SX821A22 SHIELD P916 56 P917 18 SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX822A22 SHIELD P916 57 P917 19 SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834C20 SHIELD TB19 1 J506 B						18
SX823A22 SHIELD P916 58 P917 20 SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B	SX822A22	SHIELD	P916			
SX824A22 SHIELD P916 22 P917 25 SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX825A22 SHIELD P916 34 P917 42 SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX826A22 SHIELD P916 51 P917 55 SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX828A SHIELD P916 45 P921 2 SX829A SHIELD P916 46 P921 3 SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						55
SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						2
SX830A SHIELD P916 47 P921 1 SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B	SX829A	SHIELD	P916	46	P921	3
SX831A SHIELD P916 48 P921 4 SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B	SX830A					1
SX832A22 NO/S P916 52 P921 17 SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX833A22 SHIELD P916 49 GND - SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						
SX834A20 SHIELD CB17 12 TB19 1 SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						1/
SX834B20 SHIELD P917 51 TB19 1 SX834C20 SHIELD TB19 1 J506 B						-
SX834C20 SHIELD TB19 1 J506 B						1
SX834C2O SHIELD TB19 1 J506 B	SX834B20	SHIELD	P917	51	TB19	1
	SX834C20					
						7
		, 5		10	5557	,
	I	•	,		'	

Table F-11. IFF System AN/APX-72 (Cont)

	716 1 -221		111 /11/// / / C		
WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
SX834E20	NO/S	DS84	3	S62	2
SX834F20	NO/S	S62	1	DS84	2
SX836A22	NO/S	P917	45	P918	3
SX837A22	NO/S	P917	40	P918	4
SX838A22	NO/S	P917	41	P918	5
SX839A22	NO/S	P917	43	P918	6
SX840A22	NO/S	P917	44	P918	7
SX841A22	NO/S	P917	46	P918	8
SX847A22	NO/S	P917	32	J506	Α
SX847B22	NO/S	P506	Α	S62	5
SX848A22	NO/S	P917	1	P921	37
SX849A22	SHIELD	P917	3	P921	19
SX851A22	NO/S	P917	22	P921	33
SX852A22	NO/S	P917	23	P921	14
SX855A22	NO/S	P921	9	P917	48
SX861A22	SHIELD	P917	50	P916	33
SX701A	COAX	P913A	_	P919	_
SX844A	COAX	P913	<u> </u>	P914	-

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield



DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1	IP-11500/APR-39	Indicator, Radar Signal
2	C-9326/APR-39(V)	Control, Detecting Signal
3	209-077-053-1	Bracket, Support
4	CM440/APR-39(v)	Comparator
5	AS-2891/APR-39(V)	Antenna, Right Spiral
6	209-077-100-5	Cable Assy, Radio
7	209-077-100-7	Cable Assy, Radio
8	AS-2892/APR-39(V)	Antenna, Left Spiral
9	R-1838()/APR-39	Recei ver, Radar
10	AS-2890/APR-39(V)	Antenna
11	AS-2891/APR-39(V)	Antenna, Right Spiral
12	209-477-100-11	Cable Assy, Radio
13	R-1838()/APR-39	Recei ver, Radar
14	209-477-100-9	Cabl e Assy, Radi o
15	AS-2892/APR-39(V)	Antenna, Left Spi ral

Figure F-12. Radar WarnIng System AN/APR-39(V) 1 (Sheet 2 of 2)

Table F-12. Radar Warning System AN/APR-39(V) 1

WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
APR39-1A	COAX	3422Z1P1	8	3422RE1P3	J3
APR39-2A	COAX	3422J1	Α	3422RE2P3	J3
APR39-2B	COAX	3422P1	Α	3422Z1P1	18
APR39-3A	COAX	3422J1	В	3422RE2P4	J4
APR39-3B	COAX	3422P1	В	3422Z1P1	19
APR39-4A	COAX	3422Z1P1	9	3422RE1P4	J4
APR39-11A22	NO/S	3422DS1P1	1	3422Z1P1	1
APR39-12A22	NO/S	3422DS1P1	1 2 3	3422Z1P1	2 3
APR39-13A22	NO/S	3422DS1P1	3	3422Z1P1	
APR39-14A22	NO/S	3422DS1P1	4	3422Z1P1	4
APR39-15A	COAX	3422DS1P1	5	3422Z1P1	5
APR39-16A22N	NO/S	3422DS1P1		3422TB1	1
APR39-17A	COAX	3422Z1P1	7	3422RE1P5	J5
APR39-18A22	NO/S	3422Z1P1	12	3422A1P1	2 3
APR39-19A22	NO/S	3422Z1P1	13	3422A1P1	
APR39-20A22	NO/S	3422Z1P1	14	3422A1P1	4
APR39-21A22	NO/S	3422Z1P1	15	3422A1P1	5
APR39-22A22N	NO/S	3422Z1P1	16	GND	-
APR39-23A	COAX	3422J1	С	3422RE2P5	J5
APR39-23B	COAX	3422P1	С	3422Z1P1	17
APR39-24A22	NO/S	3422DS1P1	7	3422A1P1	7
APR39-25A22	NO/S	3422DS1P1	8	3422A1P1	8
APR39-26A22	NO/S	3422DS1P1	9	3422A1P1	9
APR39-27A22N	NO/S	3422TB1	1	3422A1P1	10
APR39-28A22	NO/S	3422A1P1	12	CB1	-
APR39-29A22	NO/S	TB12	3 2	3422A1P1	13
APR39-30A22	COAX	3422TB1	2	3422A1P1	14

Table F-12. Radar Warning System AN/APR-39 (V) 1 (Cont)

WIRE NUMBER	TYPE 2	END 1	PIN 1	END 2	PIN 1
APR39-31A	COAX	3422Z1P1	21	P916	11
APR39-40A22	NO/S	3422Z1P1	20	GND	SHIELD
APR39-41A20	NO/S	CB1	_	BUS	-
APR39-42A22N	NO/S	3422TB1	1	GND	-
APR39-44A22	COAX	3422TB1	2	P3810	LL
APR39-45A22	COAX	3422TB1	2	P3809	LL
209-077-100-5	COAX	3422RE2	J1	3422E4J1	J1
209-077-100-7	COAX	3422RE2	J2	3422E5J1	J1
209-477-100-9	COAX	3422RE1	J1	3422E2J1	J1
209-477-100-11	COAX	3422RE1	J2	3422E3J1	J1
APR39-8A	COAX	3422Z1P2	J2	34422E1P1	J1
(If C-1611 is used		f C-6533)			
APR39-29A22	NO/S	3322A1P1	13	TB12	5
APR39-43A22	NO/S	3422TB1	3	TB20	9

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield

P4

MB/LAMP

MB VOL

HI/LO

CB

P-1601

P-1 P2 | P3 |

J-506 P-506

K-53 K-54

2 18-26

5

√ J₁ 1-P-1

P-311

DRAWI NG DESI GNATI ON	PART <u>NUMBER</u>	DESCRI PTI ON
1 2	R-1963/ARN I D-1347C/ARN-A2	Radio Receiver Course Indicator
3	AT-640A/ARN	Antenna
4	C-6873B/ARN-82	Radio Set Control
5	AS-3188/ARN	Antenna
6	MT-4835/ARN	Mount

Figure F-13. GS/MB Configuration R-1963/ARN (V) (Sheet 2 of 2)

WIRE NUMBER	TYPE 2	PLUG	PIN 1	PLUG	PIN 1
R-1963-1A R-1963-3A22 R-1963-3A22 R-1963-5A22 R-1963-6A22 R-1963-6A22 R-1963-8A22 R-1963-9A22 R-1963-10A22 R-1963-11A22 R-1963-12A22 R-1963-13A22 R-1963-15A22 R-1963-15A22 R-1963-16A22 R-1963-16A22 R-1963-16A22 R-1963-18A22 R-1963-19A22 R-1963-20B20 R-1963-20B20 R-1963-21B22 R-1963-21B22 R-1963-23B22 R-1963-23B22 R-1963-25A22 R-1963-25B22 R-1963-28B22 R-1963-28B22 R-1963-29B22	COAX COAX NO/S NO/S NO/S NO/S NO/S NO/S NO/S NO/S	P2 P3 P-1 P-1 P-1 P-1 P-1 P-1 P-1 P-1 P-1 P-1	- 11 29 12 30 13 31 14 32 15 33 28 34 16 17 35 10 4 T - 1 8 27 6 T 1 320 - 21 - M 7 P 8 C	PLOG P4 1-P-1 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 P-311 S-53 K-53 K-54 K-54 P-311 SPLICE CB P-1 J-506 HI-LO GND J-506 SW MB/LAMP SPLICE	NsitiginiykiEiriyk8570J58W-T21M2P3C5

Table F-13. GS/MB Configuration R-1963/ARN (V) (Cont)

I WD I G I	101 007 HD	Volli 1 gal av		1441 (1) 100	
WIRE NUMBER	TYPE 2	PLUG	PIN 1	PLUG	PIN 1
R-1963-30A22	PR/S	P-506	R	RESISTOR	4
R-1963-32A22	PR/S	P-506	G	RESISTOR	5
R-1963-32B22	NO/S	J-506	G	TB-26	3
R-1963-34A22	NO/S	P-1	19	GND	SHIELD
R-1963-34B22	NO/S	J-506	N	GND	SHIELD
R-1963-34C22	NO/S	P-506	N	GND	SHIELD
R-1963-34F22N	NO/S	SHIELD	GND	GND	-
RF431B22	NO/S	K-53	4	P-1601	L
RF446B22	NO/S	K-53	7	P-1601	M
RF447C22	NO/S	K-54	19	P-1601	S
RF448C22	NO/S	K-54	16	P-1601	R
RM901D20	NO/S	J-506	R	TB-20	8
RM917A20N	NO/S	HI/LO	SW	GND	-
RM919A20N	NO/S	MB/LAMP	3	GND	-
RN5293A22	NO/S	P-304	1	SPLICE	-
RN5293B22	NO/S	SPLICE		P-311	L

1 Underlined Connector Pin Letters Denote Lower Case

2 Denotes: NO/S--No Shield

PR/S--Pair Twisted, W/Shield

GLOSSARY

NOTE

•The terms and acronyms listed herein are defined in relation to BDAR, and accordingly may not be used in the same manner in other manuals.

. Additional definitions of terms, markings, and acronyms used during BDAR assessment procedures will be found under chapter 1, paragraph 1-10, Tagging and Identifying BDAR Repairs.

ABRASION Roughened surface, varying from light to severe.

ALLOWANCE A prescribed difference between the maximum condition of

mating parts. The minimum clearance or maximum inter-

ference between such parts.

API Armor piercing incendary armament round.

ASSEMBLY A group of two or more physically connected and related

parts, capable of disassembly, and when combined with

other assemblies and parts, creates a component.

ASSEMBLY CLEARANCE The actual fit between two or more mating parts with

respect to the amount of clearance or interference

between them.

ASSESSMENT A procedure to rapidly determine what is damaged,

whether it is repairable, what assets are required, who can perform the repair, and where the repair

can made.

ASSOCIATED PARTS A group of parts which could contain one or more

unrelated parts of a subassembly, one or more sub-

assemblies, and attaching hardware.

AXIAL Related to an axis. Describes the linear distance a

shaft or gear moves.

BATTLEFIELD DAMAGE Any incident such as combat damage, random failures,

operator errors, accidents, and wear-out failures which occur on the battlefield and which prevent the equipment/end item from accomplishing its mission.

BEAM A primary structural element designed to carry heavy

loads by resisting bending in one direction. Usually constructed with a channel, tee, or "I" cross section.

BEND Any change in an intended configuration.

BORE Inside measurement of the interior diameter of a hole

or tube. Also used to describe the hole itself.

TM 55-1520-210-BD

GLOSSARY

GLOSSARY (Cont)

BOWED Curved or gradual deviation from original line or plane.

BOX BEAM A primary structural element designed to carry heavy

loads by resisting bending In at least two directions characterized by a square or rectangular hollow cross

section.

BRAID Machine woven wire strands.

BREAK Separation of a part or substance from Itself.

BRIDGING Jumping or bypassing of a part or component.

BRINELLED Circular Indentations on bearing surfaces.

BULKHEAD The primary vertical structural element. Often called

frames or walls.

BUCKLE Wrinkle or crease damage to sheet metal structural

elements.

BURN Loss of metal resulting from overheating.

BURNISHING The smoothing of a metal surface by mechanical action

without loss of material. Generally found on plain bearing surfaces. Surface discoloration is sometimes

present around outer edges of a burnished area.

BURR A rough edge or sharp projection.

CANNIBALIZATION The removal of needed parts or assemblies from other

aircraft, equipment, or from non-essential systems

on the helicopter undergoing repair.

CAP A continuous structural element (angle, tee, or

channel shape) fastened to the top and bottom of

a beam or web.

CATASTROPHIC A sudden and disastrous event caused by equipment

failure which endangers human life.

CHAFED Functional wear. A rubbing action between two parts

having relative motion.

CHECK An examination for verifying.

CHIPPING Breaking away of small metallic particles.

CHORDLINE An imaginary line running perpendicular to the leading or

trailing edge of a rotor blade.

GLOSSARY (Cont)

CLOCKWISE A circular motion in the direction the hands of a clock

rotate when viewed from the front.

COATING, PROTECTIVE An external surface treatment, such as paint, anodizing,

electroplating or chemical film, used to delay the

effects of corrosive or atmospheric elements upon metals.

COMBAT CAPABLE The ability of the helicopter to perform the MINIMUM

combat mission assignments.

COMBAT EMERGENCY The ability of the helicopter to perform LIMITED

CAPABLE specific tactical mission assignments.

COMPONENT A group of physically connected assemblies or parts.

CONSUMABLE ITEMS Parts or materials which are consumed by usage or which

have a one-time usage In depot maintenance activity.

CORE The inner layer of material used to construct

honeycomb structural panels.

CORROSION Surface chemical action which results in surface

discoloration, a layer of oxide, rust, or removal of

surface metal.

COUNTER-CLOCKWISE The direction opposite to the direction the hands of a

clock rotate, when viewed from the front.

CRACK A break in some type of material.

CRIPPLE Damage to a load carrying structural member which

would cause degradation of the helicopters full

mission capability.

CRITERIA Standards or rules used to judge.

DATA A group of facts.

DECONTAMINATION To make an item safe for unprotected personnel by

removing, neutralizing, or destroying any harmful substance. A function of Nuclear, Biological, and

Chemical (NBC) Warfare.

DENT Indentation in metal surface produced by an object

striking with force.

DISASSEMBLY The operations necessary to reduce an assembly to its

separate components and parts.

TM 55-1520-210-BD GLOSSARY

GLOSSARY (Cont)

DISTORTION A change from an original shape.

EROSION Wearing away of metal.

EVACUATION A combat service support function which Involves the

movement of recovered helicopters from a main supply route, maintenance collection point, or maintenance

activity to higher categories of maintenance.

EXPEDIENT A rapid and often non-standard method of repairing

an Item (repair technique).

FAILURE MODE The specific cause of failure, relating to categories

such as cracks, corrosion, ballistic impact, etc.

FATIGUE FAILURE Sharp indentations, cracks, tool marks, or inclusions

that result in progressive yielding of one or more local

areas of material.

FIX Any rapid action that returns a damaged part or

assembly to full or an acceptably degraded operating

condition (repair technique).

FLANGE A broad ridge or pair of ridges projecting from the

edge of a structural element, providing additional

strength or a place for attachment.

FLAKING Loose particles of metal or evidence of separation of a

surface covering material.

FLUORESCENT PENETRANT A test for locating cracks and fissures in non-

magnetic material, making use of radiation properties of fluorescent particles when exposed to ultraviolet

light.

FORMER A curved structural element which gives the fuselage

its even aerodynamic shape. Normally longerons and

stringers are attached and the skin is fitted

tightly over all these elements.

FRACTURE Separation of a part or piece of material from Itself.

FRAYING Loose or raveled threads and fibers.

FULLY MISSION The ability of the helicopter to perform ALL its combat

CAPABLE (FMC) mission assignments.

FUNCTIONAL GROUP Major helicopter subsystems identified in and

corresponding to functional groups in TM 55-1520-210-23.

FUSELAGE The central main body of the helicopter.

GLOS-4

GLOSSARY (Cont)

Aggravated condition of wear, generally caused by a GALLING

rubbing action with little or no lubrication.

Clearance between faying surfaces, measurement of which GAP

Is used to determine thickness of shims.

Removal of surface metal because of mechanical contact GOUGING

with foreign material.

HEAT DISCOLORATION A change In color or appearance of a part, caused by

excessive temperature.

HEI High explosive incendiary armament round.

A frame support or cover, used to hold parts of **HOUSING**

machinery In place. Also used as a protective cover.

A cavity with smooth bottom or sides, which can occur **INDENTATION**

on rolling contact surfaces.

A critical examination of parts to determine their use-I NSPECTI ON

fulness or condition.

INTERFACE The joining point of two flat surfaces.

JURY-RIGGING A rapid non-standard method of repairing an item

(repair technique).

An established point or boundary, in time, speed, or LIMIT

space, beyond which something may not go or is not

permitted to go.

LOAD PATH The route taken by a mechanical force traveling through

an airframe structure.

A principle longitudinal (fore and aft), structural LONGERON

element (angle or tee shape) continuous across several

points of support.

LRU Line replaceable unit (electronic circuit board).

MAINTENANCE COLLECTION

POI NT

A point operated by AVIM units for the collection of

equipment for repair.

MAINTENANCE SUPPORT

TEAM (MST)

A team consisting of AVUM and AVIM mechanics and technical specialist who are trained in assessing battle damage in

addition to their routine speciality.

TM 55-1520-210-BD

GLOSSARY

GLOSSARY (Cont)

MAINTENANCE TEAM

(MT)

A team consisting of organizational mechanics who may be trained in assessing battle damage and field repair

procedures.

MISSION FUNCTION

COMBAT CAPABLE

(MFCC)

The ability of the helicopter to perform the MINIMUM

combat mission assignments.

MODIFICATION An alteration and/or integral change affecting the

configuration of equipment or its respective parts,

components, subassemblies, or assemblies.

NATIONAL STOCK NUMBER

(NSN)

The assigned identifying number for an item of supply, consisting of the four-digit Federal Supply Class (FSC), and the nine-digit National Stock

Identification Number (NIIN).

A local break or notch in the edge of material. NI CK

Performance of a practical, functional action. OPFRATION

OPTI ON A specific BDAR repair technique often non-standard

In nature.

The process of repairing or adjusting a machine to **OVERHAUL**

restore, improve, or lengthen its useful life.

PEELING A breaking away of surface finishes such as coatings

or platings, or flaking of large pieces of such material.

PI GTAI L A group of electrical wire strands twisted together.

Small holes or indentations, generally caused by rust, PI TTI NG

corrosion, high compressive stresses, or metal-to-metal

poundi ng.

PRACTI CE A repeated or customary action.

The major structural load carrying elements of an PRIMARY STRUCTURE

airframe without which helicopter flight safety would

be compromised.

PROCEDURE A particular course of action.

A series of actions conducive to an end. **PROCESS**

PYLON The box shaped structural area surrounding the helicopter

main transmission. This area carries several primary

structural Loads.

GLOSSARY (cont)

REASSEMBLY The assembling and allgning of all subassemblies and

parts into a complete assembly to affect a serviceable

Item of equipment.

RECOVERY The retrival of immobile, Inoperative, or abandoned

helicopters from the battlefield or immediate vicinity and its movement to a maintenance collection point, main supply route, or a maintenance activity for disposition,

repair, or evacuation.

REMOVE To move by lifting, pulling or pushing.

REPAIR To restore a defective part, component, subassembly, or

assembly to a usable condition in accordance with the

instructions contained in this manual.

REPLACE To supply an equivalent for.

REWORK To work over again.

RUPTUR\qE The breaking of an airframe structural element or skin

due to overstress/hostlle fire.

SCORING Very deep scratches caused by foreign particles between

surfaces that are moving, or between one moving and one stationary surface. Scores follow the travel

direction of the part.

SCRATCHING Narrow, shallow lines resulting from movement of

foreign particles across a surface.

SECONDARY STRUCTURE The non-flight safety structural elements of an airframe.

SELF-RECOVERY The ability of the helicopter to fly at reduced airspeed

and altitude from the battlefield or immediate vicinity to a maintenance collection point, the main supply route,

or maintenance activity for disposition, repair or

evacuation.

SEMIMONOC A structural design which relies on strength of the skin

to carry a large portion of the load. The skin Is normally reinforced by longerons and vertical bulkheads

(walls), but has no diagonal bracing, leaving the interior

basicly hollow.

SERVICING The lubrication, treating, cleaning, or preservation

necessary to maintain the equipment and other respective

parts in serviceable condition.

SKIN The aerodynamic exterior covering of the helicopter.

TM 55-1520-210-BD GLOSSARY

GLOSSARY (Cont)

SPALLING Chipped or flaked surface caused by the breaking away of

the hardened metal and separation of the case from the

core.

SPANWISE The location of a point or direction of movement parallel

to the leading or trailing edge of a rotor blade.

SPAR A primary structural element designed to carry weight and resist bending loads in wings and rotor blades.

Spars typically extend the full length of the wing, and taper down to a smaller cross section toward the tip

of the wing.

STIFFENER A longitudinal (fore and aft) structural element use in

semimonocoque design which stiffens the skin. Often

called a stringer.

STOP HOLE A hole intentionally drilled at the end of a crack, or saw

cut which normally will prevent further propagation

of the crack.

STRINGER A longitudinal (fore and aft) structural element used in

semi monocoque design which stiffens the skin. Often

called a stiffener.

TEST As used herein, the checking or operation of equipment

to determine that the unit functions properly within the

limits set forth in this manual.

TOLERANCE The difference between two limiting sizes as a

means of specifying the degree of accuracy.

TOXIC A poi sonous substance.

TWIST The damage of a structural element by turning or torque

forces causing permanent deformation.

VISCOSITY The property of a fluid that tends to resist the force

trying to make it flow such as gravity or applied

pressure.

WARPAGE The bending or twisting damage causing a structural

element to weaken and permanently loose its original

shape.

WEB The sheet metal membrain connecting the upper and lower

flanges of a beam or spar. Provides overall rigidity to

the airframe structure.

WHIP The tendency of a bent shaft to rotate away from its

original center as the shaft RPM is increased, thus

causing severe vibration.

INDEX

Subject	Paragraph
A	
Accessory Gearbox and Fuel Control Assembly, Minor Leaks Armament-Hydraulic System, Leaking Antenna, Substitute Emergency. Assessment Procedures Alighting Gear Airframe. Drive Train Systems Electrical and Avionics System Flight Controls Instruments Fuel System General Repairs. Helicopter Flight. Hydraulic and Pneumatic Systems Power Plant. Rotors.	6-7 9-17 11-26 5-2 4-1 8-2 11-2 13-2 10-2 12-2 3-2 2-2 9-2 6-2 7-2
Battery Bus Bar Repair	11-23 9-24 9-22 9-23 11-21 3-11 3-12
Characteristics BDAR. Operating. Check Valves, Leaking. Circuit Protection Device Repair. Coax Splice Component Bridging. Connecting Links, Damaged in Center. Connector Pins, Damaged. Control Cable, Damaged (Splice Repair)	1-5 1-7 9-15 11-20 11-14, 11-1 11-16, 11-1 11-18 13-5 11-19 13-13
Definitions.	1-4

TM 55-1520-210-BD

INDEX

INDEX (Cont)

Subj ect	Paragraph
E	
Elevator, Inoperable	13-11 8-8
F	
Fabrication of Bellcranks and Levers	13-9 13-7 12-10 12-8 12-9 10-4
G	
Gearboxes, Small Leaks through Case and Cracks	8-13
Н	
Honeycomb Panels, Damaged 2 Inch Max Dia	3-14 3-15 3-16 9-7
l	
J	
K	
L	
Longerons and Caps, Severed	3-9 3-18
M	
Main Rotor Blade, Damage Holes of 1 Inch Dia or Less	7-5
in Case Walls	8-5 9-20 12-5

INDEX (Cont)

Subject		Paragraph
	N	
Nose Section, Bottom Window Cracks and H Nose Section, Damage to External Structu		4-6 4-5
	0	
Oil Filter Leak, External Oil Tank, Leaking Oil Pressure Indicator or Transmitter,	Damaged/Bad Reading	8-8 6-5 10-6
	P	
Pitot Plenum, Damaged		10-8 10-7 11-22 11-24 9-13
	Q	
	R	
Relief Valve, Leaking Hydraulic Fluid. Reservoir, Leaking Hydraulics Fluid. Rubber Hose, Damaged		9-9 9-5 12-6
Repair Procedure Index Alighting Gear Airframe. Drive Train System. Electrical and Avionics System. Flight Controls. Instruments. Fuel System. General Repairs. Hydraulic and Pneumatic Systems. Power Plant.		5-3 4-3 8-3 11-3 13-3 10-3 12-3 3-3 9-3 6-3

TM 55-1520-210-BD | NDEX

INDEX (Cont)

Subj ect		Paragraph
S		
Shi el d Termi nators Shi el ded Cable Repair. Shi el ded Cable Repair Segments Shi el ded Cable Repair Segments Ski d Tubes, Damage to Area A and E of Figure 5-2 Ski d Tubes, Damage to Area B of Figure 5-2 Ski d Tubes, Damage to Area C and D of Figure 5-2 Ski n and Structural Damage, General Ski n Damage. Sol enoi d Val ve, Damaged and Leaking. Static Mani fol d, Damaged Stiffeners and Stringers, Damaged.		5-5 5-7 5-6 4-5
Tagging/Identifying BDAR Repairs	on) .	8-11 11-12 11-13 11-11 1-8 8-6
U U U U U U U U U U U U U U U U U U U		11.5
Unshi el ded Wi res, Damaged		11-5
·		
W		
Waiver of Precautions		1-6 11-7 11-6
XYZ		

By Order of the Secretary of the Army:

CARL E. VUONO General, United States Army Chief of Staff

Official:

THOMAS F. SIKORA
Brigadier General United States Army
The Adjutant General

DISTRIBUTION:

To be distributed in accordance with DA Form 12-31-R, AVUM and AVIM Maintenance requirements for UH-1H and UH-1V Helicopter, Utility.

*U.S. GOVERNMENT PRINTING OFFICE:1991 554-122/21093

RECOMMENDED CHANGES TO EQUIPMENT TECHNICAL PUBLICATIONS

	SOMETHING WRONG WITH PUBLICATION FROM: (PRINT YOUR UNIT'S COMPLETE ADDRESS) THENJOT DOWN THE DOPE ABOUT IT ON THIS FORM. CAREFULLY TEAR IT OUT, FOLD IT AND DROP IT IN THE MAIL. DATE SENT								
	UBLICAT	TON NUMBE	ER			PUBLICATION D	ATE	PUBLICATION TITLE	
╏┠╌	E EXAC PAGE NO.	T PIN-PC PARA- GRAPH	FIGURE NO.	TABLE NO.				AT IS WRONG DONE ABOUT IT.	
PF	RINTED I	NAME, GRA	DE OR TITL	E AND TELE	EPHONE NU	JMBER	SIGN HE	ERE	

DA 1 JUL 79 2028-2

PREVIOUS EDITIONS ARE OBSOLETE. P.S.--IF YOUR OUTFIT WANTS TO KNOW ABOUT YOUR RECOMMENDATION MAKE A CARBON COPY OF THIS AND GIVE IT TO YOUR HEADQUARTERS.

THE METRIC SYSTEM AND EQUIVALENTS

'NEAR MEASURE

Centimeter = 10 Millimeters = 0.01 Meters = 0.3937 Inches

1 Meter = 100 Centimeters = 1000 Millimeters = 39.37 Inches

1 Kilometer = 1000 Meters = 0.621 Miles

YEIGHTS

Gram = 0.001 Kilograms = 1000 Milligrams = 0.035 Ounces

1 Kilogram = 1000 Grams = 2.2 lb.

1 Metric Ton = 1000 Kilograms = 1 Megagram = 1.1 Short Tons

LIQUID MEASURE

1 Milliliter = 0.001 Liters = 0.0338 Fluid Ounces

1 Liter = 1000 Milliliters = 33.82 Fluid Ounces

SQUARE MEASURE

1 Sq. Centimeter = 100 Sq. Millimeters = 0.155 Sq. Inches

1 Sq. Meter = 10,000 Sq. Centimeters = 10.76 Sq. Feet

1 Sq. Kilometer = 1,000,000 Sq. Meters = 0.386 Sq. Miles

CUBIC MEASURE

1 Cu. Centimeter = 1000 Cu. Millimeters = 0.06 Cu. Inches 1 Cu. Meter = 1,000,000 Cu. Centimeters = 35.31 Cu. Feet

TEMPERATURE

 $5/9(^{\circ}F - 32) = ^{\circ}C$

212° Fahrenheit is evuivalent to 100° Celsius

90° Fahrenheit is equivalent to 32.2° Celsius


32° Fahrenheit is equivalent to 0° Celsius

 $9/5C^{\circ} + 32 = {\circ}F$

APPROXIMATE CONVERSION FACTORS

TO CHANGE	TO	MULTIPLY BY
Inches	Centimeters	2.540
Feet	Meters	0.305
Yards	Meters	
Miles	Kilometers	
Square Inches	Square Centimeters	
Square Feet	Square Meters	
Square Yards	Square Meters	0.836
Square Miles	Square Kilometers	2.590
Acres	Square Hectometers	
Cubic Feet	Cubic Meters	
Cubic Yards	Cubic Meters	
Fluid Ounces	Milliliters	
nts	Liters	
arts	Liters	
allons	Liters	
Ounces	Grams	
Pounds	Kilograms	
Short Tons	Metric Tons	
Pound-Feet	Newton-Meters	
Pounds per Square Inch	Kilopascals	
Miles per Gallon	Kilometers per Liter	
Miles per Hour	Kilometers per Hour	
-	•	

TO CHANGE	то	MULTIPLY BY
Centimeters	Inches	0.394
Meters	Feet	3.280
Meters	Yards	
Kilometers	Miles	
Square Centimeters	Square Inches	
Square Meters	Square Feet	
Square Meters	Square Yards	1 196
Square Kilometers	Square Miles	0.386
Square Hectometers	Acres	
Cubic Meters	Cubic Feet	
Cubic Meters	Cubic Yards	
Milliliters	Fluid Ounces	
Liters	Pints	
Liters	Quarts	
'ers	Gallons	
.ms	Ounces	
.ograms	Pounds	
Metric Tons.	Short Tons	
Newton-Meters	Pounds-Feet	
Kilopascals	Pounds per Square Inch .	
ometers per Liter	Miles per Square Inch .	9 254
meters per Hour	Miles per Gallon	
miecers per mour	Miles per Hour	U.OZI



PIN: 049233-001